

USB4 1.0 ENGINEERING CHANGE NOTICE FORM

Title: No Sideband Transaction on Sleep Entry
Applied to: USB4 Specification Version 1.0

Brief description of the functional changes:

Clarify that there are no Sideband Transaction except LT_LRoff after Sleep Ready bit is set.
--

Benefits as a result of the changes:

Complete description of the Sideband behavior during Sleep entry
--

An assessment of the impact to the existing revision and systems that currently conform to the USB specification:
--

None

An analysis of the hardware implications:
--

None

An analysis of the software implications:
--

None

An analysis of the compliance testing implications:
--

Need to check that there are no Sideband transactions after Sleep Ready bit is set, except LT_LRoff

USB4 1.0 ENGINEERING CHANGE NOTICE FORM

Actual Change

(a). Section 4.5.1 – Entry to Sleep

To Text:

After the *Enter Sleep* bit is set to 1b, the Router shall complete any pending Transactions on the Sideband Channel. When the Router is ready for the sleep event it shall set the *Sleep Ready* bit to 1b. After setting the *Sleep Ready* bit and before the Sleep event, the Router shall not initiate any Sideband transaction except LT LROff. A Router shall set the *Sleep Ready* bit to 1b within tSetSR time after the *Enter Sleep* bit is set to 1b, unless the Router is waiting for a Notification Acknowledgment Packet as described in Section 11.1.4.2. A Router shall also send the Connection Manager a Notification Packet with Event Code = ROP_CMPLT and the *Event Info* field set to 03h.