메인	27.2	27.2	27.2	32.7	32.7	32.7	38.2	38.2	38.2	43.7	43.7	43.7	49.1	49.1	49.1
총연장길이	9	9	9	9	9	9	9	9	9	9	9	9	9	9	9
어댑터1	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4
연장붐1	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5
연장붐2	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
연장붐3	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
연장붐4	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
어댑터2	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
러핑길이	56	56	56	56	56	56	56	56	56	56	56	56	56	56	56
러핑메인각도	84	76	66	84	76	66	84	76	66	84	76	66	84	76	66
무게추	204	204	204	204	204	204	204	204	204	204	204	204	204	204	204
overRear	х	х	х	х	х	х	х	х	х	х	х	х	х	х	х
optional	х	х	х	х	х	х	х	х	х	х	х	х	х	х	X
26	46.1			45.5											
28	45.9			45			43.9								
30	45.3			44.5			43.4			42			40.5		
32	44.8			44.1			43			41.7			40.2		
34	44.4			43.6			42.6			41.3			39.9		
36	44			43.3			42.3			41			39.7		
38	43.6			42.9			42			40.8			39.3		
40	43.3	40.6		42.6			41.7			40.5			38.4		
42	42.9	40.3		42.3	39.5		41.5			40.1			37.2		
44	42.2	40.1		41.7	39.3		41	38.1		39.5			36		
46	41.5	39.9		41	39.2		40.5	37.7		38.4	36.1		34.9		
48	39.6	39.6		40.1	37.8		39.6	36.1		37.3	34.6		33.9	31.8	
50	37.5	38		38.2	36.2		38.6	34.6		36.3	33.1		32.9	30.8	
52	35.5	36.4		36.2	34.8		37.1	33.2		35.4	31.8		31.9	29.7	
54	33.6	34.8	22.2	34.3	33.4		35.1	31.9		34.5	30.5		31	28.7	
56	31.9	33.3	28.2	32.5	32	25	33.3	30.6		33.6	29.4		30.3	27.7	
58	30.4	31.9	27	30.9	30.6	25	31.6	29.4	22.2	32.3	28.3		29.6	26.8	
60 62	28.8	30.6 29.3	25.8 24.8	29.4 26.7	29.3	23.9 22.9	30.1 28.7	28.1 27	22.2 21.2	31.3 30	27.1		29 28.6	25.9 25.1	
64		29.3	23.7	20.7	28.1 27	22.9	20.7	25.9	20.4	30	26 25	18.1	28.3	25.1	
66		27.1	23.7		26	21.1		25.9	19.5		23.9	17	20.3	23.1	16.4
68		26	21.9		25	20.3		23.9	18.6		23.9	16		22.2	15.3
70		20	21.3		23	19.5		23.9	17.6		22.1	15.1		21.3	14.4
72			20.3			18.7		23	16.8		21.3	14.3		20.5	13.6
74			19.5			18			16.0		21.5	13.5		20.5	12.8
76			13.3			17.3			15.3			12.8			12.2
78						5			14.7			12.3			11.5
80									14.1			11.7			11
82												11.2			10.4
84															9.9
<u> </u>	<u> </u>			<u> </u>	<u> </u>	<u> </u>	<u> </u>	<u> </u>	<u> </u>	<u> </u>		<u> </u>	+ 100	000 0000	1 00 000