메인	27.2	27.2	27.2	32.7	32.7	32.7	38.2	38.2	38.2	43.7	43.7	43.7	49.1	49.1	49.1
총연장길이	9	9	9	9	9	9	9	9	9	9	9	9	9	9	9
어댑터1	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4
연장붐1	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5
연장붐2	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
연장붐3	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
연장붐4	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
어댑터2	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
러핑길이	59.5	59.5	59.5	59.5	59.5	59.5	59.5	59.5	59.5	59.5	59.5	59.5	59.5	59.5	59.5
러핑메인각도	84	76	66	84	76	66	84	76	66	84	76	66	84	76	66
무게추	204	204	204	204	204	204	204	204	204	204	204	204	204	204	204
overRear	х	х	х	х	х	х	х	х	х	х	Х	х	х	х	х
optional	х	х	х	x	x	х	х	х	x	x	х	x	х	х	х
26	40.8														
28	41.4			41			40.1								
30	41.3			40.6			39.7			38					
32	40.9			40.2			39.4			38.1			36.7		
34	40.5			39.8			39			37.8			36.4		
36	40.1			39.4			38.7			37.5			36.2		
38	39.8			39.1			38.3			37.2			35.9		
40 42	39.5	36.7		38.8	36		38.1 37.9			36.9 36.7			35.7 35.3		
42	39.2 39	36.5		38.6 38.4	35.8		37.9 37.7	34.8		36.5			34.6		
46	38.8	36.3		38.3	35.6		37.7	34.7		36.3			33.6		
48	38.7	36.1		38.2	35.5		37.4	34.6		35.5	33.1		32.6		
50	37.9	36		38	35.4		36.6	34.4		34.6	32.7		31.7	29.7	
52	35.8	36		36.6	34.5		35.8	33		33.7	31.4		30.8	28.8	
54	34	34.7		34.7	33.1		35	31.7		32.9	30.1		29.9	27.9	
56	32.3	33.4		32.9	31.9		33.5	30.5		32.1	29		29.2	27	
58	30.7	32	27	31.3	30.7		31.9	29.4		31.4	27.9		28.5	26.1	
60	29.2	30.7	25.9	29.7	29.5	24	30.3	28.3		30.8	26.9		27.9	25.3	
62	27.9	29.4	24.8	28.4	28.3	23	28.9	27.2	21.3	29.7	25.9		27.3	24.5	
64	25.3	28.3	23.8	27.1	27.1	22.1	27.5	26.1	20.5	28.3	25		26.9	23.8	
66		27.2	22.9		26.1	21.2	25.4	25.1	19.7	27	24	18.1	26.6	23	45.0
68		26.2	22		25.1	20.3		24.1	18.9		23.1	17.2		22.1	15.8
70 72		25.2	21.1 20.3		24.1	19.5 18.8		23.2 22.3	18.1 17.4		22.2 21.3	16.2 15.3		21.2 20.4	14.8
72 74			19.6		23.2	18.8		22.3	16.7		20.5	15.3		19.7	13.9 13
74			18.9			17.4		21.5	16.1		20.5	13.8		18.9	12.3
78			18.2			16.7			15.5			13.1		10.5	11.6
80			10.2			16.1			14.9			12.4			11.0
82						13.1			14.3			11.9			10.5
84												11.4			10
86															9.5
														000 0110	1 00 000