



RG=500 equates to gain of 100









