breakyBreaky breakout board BOM 15100501-02 Revision 4.0, Revised 11/3/2016

krtkl inc. 350 Townsend Street Suite 301A San Francisco, CA 94107 +1 415 857 4857

Bill Of Materials November 3,2016 14:06:55

Item	Qty.	Reference	Description	Manufacturer	Part Number
1	1	F1	3A 24V PTC Resettable Fuse	Bourns	MF-LSMF300/24X-2
2	6	JC1, JB1, JA1, JB2, JA2, J3	Conn, Header, 40-pin, 20-posx2-row, 0.1" Vert, TH	Samtec	TSW-120-07-F-D
3	1	J1	Conn, Jack, 2-pos, 5.5mm OD x 2.5mm ID DC Power, 8A T/H RA	CUI Inc	РЈ-063ВН
4	1	J2	Conn, Header, 30-pin, 15-posx2-row, 0.1" Vert, TH	Samtec	TSW-115-07-F-D
5	1	J5	Conn, Header, 10-pin, 5-posx2-row, 0.05" Vert, Shrouded, TH	Samtec	FTSH-105-01-F-D-007-K
6	1	J6	Conn, Header, 14-pos, 2MM VERT Gold SHRD	Molex Inc.	87831-1420
7	4	M1, M2, M3, M4	Standoff, 0.25" high 0.125" dia snap-in, 0.5" square base, adhesive	Keystone	9071
8	6	PC1, PB1, PA1, PB2, PA2, P3	Conn, Header, 40-pin, 20-posx2-row, 0.05" Vert Shrouded, TH	Samtec	TFM-120-01-F-D-A
9	1	P2	Conn, Header, 30-pin, 15-posx2-row, 0.05" Vert Shrouded, TH	Samtec	TFM-115-01-F-D-A
10	1	R1	Resistor, 10.0K ohm 1% 1/8W, SMD 0805	Vishay	CRCW080510K0FKEA
11	1	R2	Resistor, 0 ohms 1/10W, SMD 0603	Vishay	CRCW06030000Z0EA
12	1	R3	Resistor, Do Not Install, 1/10W, SMD 0603	N/A	N/A
13	3	SH1, SH2, SH3	Conn, Jumper, 2pos Open Top, For 0.025" Square Pins 0.1" LS, Gold Flash	Sullins	QPC02SXGN-RC
14	2	TVS2, TVS3	Diode Array, Quint 3.3V ESD Prot., SOT363	NXP Semiconductor	PESD3V3L5UY,115
15	1	TVS4	TVS Diode, 17VWM max, 400W peak, SMA	Bourns	SMAJ17A
16	1	TVS5	TVS DIODE 3.3VWM SOD523	NXP Semiconductors	PESD3V3U1UB,115