

Project: Exit Square

Feature: Standardized Multi-Count Inventory

Version: 1.1

Initial Date: 11/02/2025

Last Update: 12/03/2025

Authors: ECO

◆ METADATA

```
{  
  "document_type": "Technical & Functional Specification",  
  "project": "Exit Square",  
  "system": "Speed WMS",  
  "version_speed": "A.8.6.F",  
  "dev_env": "Windev 28",  
  "feature": "Standardized Inventory with Multi-Count & Traceability",  
  "languages_supported": ["French", "English"],  
  "status_management": ["Validated", "Partial", "Discrepancy"],  
  "entry_points": ["PE171", "PE261", "PE915"],  
  "version": "1.1"  
}
```

◆ SECTION 1 — Context & Environment

1.1 Context

- Standardized AGL inventory to be deployed across all sites
- Based on KBL inventory principles with multiple counts
- Counting rules:
 - Blind counting
 - Radio traceability display

- New inventory proposed if discrepancies
- Inventories linked via automated index system

1.2 Environment

- Developed for **Speed A.8.6.F**
- Coded in **Windev 28**
- 80% client environments in English → translation mandatory
- Core libraries: WDLSpeedCMAAdmin.wdl, WDLSpeedCMRadio.wdl

◆ SECTION 2 — Inventory Creation & Index Management

2.1 Standard Inventory Creation

- Type: **Inventaire général**
- Inventory code: max 11 characters
- Automatic counter for indices (last 4 chars, separated by _)
- Index displayed in a dedicated IHM field

Example:

Displayed code: 20250211

IVE_DAT.IVE_CODE: 20250211_001

IVE_ALPHA1: 20250211

2.2 Business Rules

RG Code	Description
SPD023_CDI_RG_001	Inventory code ≤ 11 chars; special chars allowed except _; code = input + _ + index
SPD023_CDI_RG_002	Index init = 001 in new mode; decode code if existing; display in dedicated field
SPD023_CDI_RG_003	IVE_CODE = input + _ + index; IVE_ALPHA1 = input

◆ SECTION 3 — Counting & Radio Traceability

3.1 Radio Counting

- Standard flow: Inventory selection → F5 → flash location → flash support → flash article → traceability screen
 - **Traceability Fields:**
STK_LOT1, STK_LOT2, STK_LOT3, STK_DLUO, STK_DFAB, STK_DLC, STK_DLV, STK_POIV, STK_CFIS
 - **IHM Presentation:**
 - Table format, highlight current element
 - Navigate via arrows
 - Flash advances automatically to next element
-

◆ SECTION 4 — Discrepancy Management

4.1 Standard Cases

- **Case 1:** No discrepancies → inventory validated & closed
- **Case 2:** Discrepancies but no new count → validate or delete discrepancies → close inventory

4.2 Specific Case

- **Case 3:** Discrepancies require new count
- New partial inventory created, linked via automated index
- Inventory lines without discrepancy automatically validated
- Full location recomputation (not only items with discrepancy)
- Repeatable up to 999 recounts

Example:

General inventory: 20250211_001

Partial inventory: 20250211_002

IVE_ALPHA1 = 20250211

◆ SECTION 5 — PE171: Generate Discrepancies

- PE171 used for discrepancy processing

- Wrapped in F_Transaction for DB atomicity
 - **Business Rules:**
 - SPD023_GLE_RG_001 → check lines with discrepancies
 - SPD023_GLE_RG_002 → close current index, update stock, free locations, set IVE_STAT = '050'
 - SPD023_GLE_RG_003 → create new index, duplicate lines in discrepancy, reset quantities
 - **Controls & Actions:**
 - SPD023_GLE_CTRL_001 → lines with discrepancies exist?
 - SPD023_GLE_CTRL_003 → inventory header exists?
 - SPD023_GLE_CTRL_004 → inventory status correct?
 - SPD023_GLE_ACT_001 → confirmation dialog for new count or close
-

◆ **SECTION 6 — PE261: Traceability Windows**

- Fen_IV01200_SPE → duplicate standard Fen_IV01200 for multiple-count traceability
 - Fen_IV01300_SPE → duplicate Fen_IV01300
 - Table display of traceability with flash control
 - Highlight active row, display type & date format (MM/DD/YYYY or DD/MM/YYYY)
 - SPD023_TRA_RG_001 → load traceability table
 - SPD023_TRA_ACT_001 → flash updates table, move to next element
-

◆ **SECTION 7 — PE915: Intrus Management**

- Remove unconfirmed inventory lines from recounts (indices > 1, zero stock)
- **Business Rules:**
 - SPD023_915_RG_001 → duplicate standard code
 - SPD023_915_RG_002 → decode index, delete intrus lines with IVL_TCPT=1, IVL_QUGC=0, STK_QTE=0, IVL_TOIN=null
- **Controls:**

- SPD023_915_CTRL_001 → positive InventorieAZéro
 - SPD023_915_CTRL_002 → index decoding successful
-

◆ **SECTION 8 — Validation**

- AGL acknowledges receipt & validates all elements
- BK Systèmes provides solution per specification
- Additional requests may require a new quote
- Non-explicit provisions are at discretion of parties