





Spécifications Détaillées

-  **L'ORÉAL – Quality-Based Storage Restriction Control**

System:	Speed	WMS
Version:	A.8.6.F	(28.06b1)
Radio	Version:	28.06b
Module STD175: 28.06		

-
- **1. Document Control**
 - **1.1 Version History**

Version Description	Date	Author
1.0	Initial Version	25/03/2023 AKD

-
- **2. Business Context**

As part of the **L'ORÉAL warehouse operations**, the **Multi-BL Reception module** is used for receiving articles.

The reception process is configured to operate in **Declarative Storage mode**.

Additionally, operators may perform storage using:

- The **Standard Radio Storage module (Cariste module)**

-
- **2.1 Business Requirement**

The client requires:

To prevent certain quality-coded items from being stored in specific zones.

This restriction must depend on:

- The **quality code of the item**
- The **zone configuration**

-
- **3. Functional Design**
 - **3.1 Zone Configuration Logic**

The restriction mechanism uses:

- **Zone IC (Information Code):** ZEM_ALPHA1
- Maximum length: **50 characters**
- Quality codes must be separated by: ;
- **Example:**

- DAMAGED;QUARANTINE;BLOCKED

If `ZEM_ALPHA1` is empty:
→ No storage restriction applies.

- **3.2 Important Technical Constraint**

Speed WMS does NOT support variable IC at zone level.

Therefore:

- `ZEM_ALPHA1` must be used
- Limited to 50 characters

- **3.3 Activation Parameter**

Control must only apply if:

- `ACT_TOP17` = 1

If `ACT_TOP17` ≠ 1:
→ No control is performed.

⚠ This control does NOT apply in Speed Admin.
It only applies from the **Radio interface**.

- **4. Functional Flow – Multi-BL Reception (Direct Declarative Storage)**

- **4.1 Operator Steps (Radio)**

1. Select: **Multi-BL Reception**
2. Flash / Select Reception
3. Confirm Direct Storage (if prompted)
4. Flash Support (or auto-generate sequential support)
5. Flash Article Code / EAN
6. Enter Received Quantity
7. Flash Storage Location

- **4.2 Control Point**

Before storage validation:

Use:

- PE863

- **4.3 Validation Logic (PE863)**

Condition: ACT_TOP17 = 1

- **Case 1 – Location belongs ONLY to zones that forbid the quality**

If the flashed location belongs exclusively to zones where:

- Current Quality Code $\in$ ZEM_ALPHA1

Then:

- Display error message:

English:

- Zone XXX is not authorized for storage of items with quality code YYYY
- Clear the location input field
- Block validation

- **Case 2 – Location belongs to multiple zones**

If:

- At least one zone allows the quality
- And another zone forbids it

Then:

→ Storage must be ALLOWED

(Standard behavior continues)

- **5. Functional Flow – Cariste Storage Module**

- **5.1 Operator Steps**

1. Select: **Cariste Storage**
2. Flash Support
3. Flash Storage Location

- **5.2 Control Point**

Before validation:

Use:

- PE222

- **5.3 Validation Logic (PE222)**

Condition: ACT_TOP17 = 1

- **Case 1 – All associated zones forbid the quality**

If the flashed location belongs only to zones where:

- Current Quality Code $\in$ ZEM_ALPHA1

Then:

- Display error message:
 - Zone XXX is not authorized for storage of items with quality code YYYY
 - Return FALSE
 - Block storage
-

- **Case 2 – At least one zone allows the quality**

If:

- Location belongs to multiple zones
- At least one zone allows the quality

Then:

- Return TRUE
 - Allow storage
-

- **6. Technical Implementation**

- **6.1 PE863 – Multi-BL Reception**

- Branch created from STD175 (28.06)
- PE863 located in:
- F175_RMB0380

Add initialization in Speed Radio 28.06b:

- InitBDDPen(
 - "863",
 - "On Validation - F175_RMB0380",

- CodeAPPModuleRadio,
- "Multi-BL Reception - MOD175",
- "pListeSTK_KEYU"
-)

- **PE863 Processing Logic**

If ACT_TOP17 = 1:

- IF location belongs ONLY to zones that forbid quality:
 - → Show error
 - → Clear input field
 - → Block validation
 -
- IF location belongs to multiple zones AND at least one allows quality:
 - → Do nothing
 - → Continue standard storage

- **6.2 PE222 – Cariste Storage**

If ACT_TOP17 = 1:

- IF location belongs ONLY to zones that forbid quality:
 - → Show error
 - → Return FALSE
 -
- IF location belongs to multiple zones AND at least one allows quality:
 - → Return TRUE

- **7. Validation & Legal Statement**

AGL acknowledges and validates all elements described in this document.

BK Systèmes commits to delivering the solution according to the approved specifications within the scope of the agreed quotation.

Any additional request or evolution beyond this document may be subject to additional quotation.



Spécifications Détaillées

All non-explicitly stated provisions are excluded from scope and remain at the discretion of the concerned parties.

Signed

at:

Vaulx-Milieu

Date: 25/03/2025

Company Signature & Stamp: