Lockout/Tagout Procedure for Machine Maintenance

LOTO-003 · Version 2.1 · Standard Operating Procedure

Document control

Document No.	LOTO-003	**Version**	2.1
Status	Approved – Effective	**Classification**	Internal – Safety Critical
Effective date	01-Sep-2026	**Next review date**	31-Aug-2027
Document owner	Plant Director	**Supersedes**	v2.0 dated 10-May-2025
Department	Engineering & Maintenance / EHS		

Review and approval

Role	Name	Designation	Date	Signature
Prepared by	Daisuke Ito	Maintenance Supervisor	14-Aug-2026	*e-signed (DMS)*
Reviewed by	Yui Sato	Site HSE Manager	21-Aug-2026	*e-signed (DMS)*
Approved by	Takeshi Morimoto	Plant Director	26-Aug-2026	*e-signed (DMS)*

Definitions

Term	Meaning
Authorized employee	A person trained and authorized to lock or tag out machines in order to service them.
Affected employee	A person who operates or works in the area of a machine that is being serviced.
Energy-isolating device	A device that physically prevents the transmission or release of energy, such as a disconnect switch or line valve.
Zero energy state	The condition in which all energy sources are isolated and stored energy has been released.

Revision history

Version	Date	Author	Description of change
v1.0	03-Feb-2021	D. Ito	Initial issue based on the corporate energy-control standard.
v2.0	10-May-2025	D. Ito	Pneumatic and hydraulic energy added to clause 2.3.
v2.1	01-Sep-2026	D. Ito	Section 3 added: exception for minor tool changes, at the request of Production to reduce changeover time.

Distribution

The controlled copy of this document is held in the Document Management System (DMS). Printed or downloaded copies are uncontrolled; check the DMS for the current version before use.

Lockout/Tagout Procedure for Machine Maintenance

1 Purpose

1.1 This procedure protects workers from the unexpected start-up of machinery during servicing and maintenance.

2 Procedure

2.1 The authorized employee notifies all affected employees that the machine will be shut down.

2.2 The machine is shut down using its normal stopping procedure.

2.3 All energy sources (electrical, pneumatic, hydraulic) are isolated.

2.4 The authorized employee applies a personal lock and tag to every energy-isolating device.

2.5 The authorized employee verifies zero energy by attempting to start the machine.

2.6 Maintenance or servicing is performed.

2.7 Verification of zero energy must always be performed before any maintenance or servicing begins.

3 Exceptions

3.1 For minor tool changes expected to take less than 10 minutes, the operator may proceed directly to maintenance after shutting down the machine.

4 Restoring equipment

4.1 After maintenance, the authorized employee removes tools, ensures all employees are clear, and removes their lock and tag.

4.2 Only the employee who applied a lock may remove it.

4.3 Equipment must be returned to service as soon as possible.