# Lockout/Tagout Procedure for Machine Maintenance

LOTO-003 · Version 2.1 · Standard Operating Procedure

## Document control

| | | | |
|---|---|---|---|
| **Document No.** | LOTO-003 | **Version** | 2.1 |
| **Status** | Approved – Effective | **Classification** | Internal – Safety Critical |
| **Effective date** | 01-Sep-2026 | **Next review date** | 31-Aug-2027 |
| **Document owner** | Plant Director | **Supersedes** | v2.0 dated 10-May-2025 |
| **Department** | Engineering & Maintenance / EHS | | |

## Review and approval

| Role | Name | Designation | Date | Signature |
|---|---|---|---|---|
| Prepared by | Daisuke Ito | Maintenance Supervisor | 14-Aug-2026 | *e-signed (DMS)* |
| Reviewed by | Yui Sato | Site HSE Manager | 21-Aug-2026 | *e-signed (DMS)* |
| Approved by | Takeshi Morimoto | Plant Director | 26-Aug-2026 | *e-signed (DMS)* |

## Definitions

| Term | Meaning |
|---|---|
| **Authorized employee** | A person trained and authorized to lock or tag out machines in order to service them. |
| **Affected employee** | A person who operates or works in the area of a machine that is being serviced. |
| **Energy-isolating device** | A device that physically prevents the transmission or release of energy, such as a disconnect switch or line valve. |
| **Zero energy state** | The condition in which all energy sources are isolated and stored energy has been released. |

## Revision history

| Version | Date | Author | Description of change |
|---|---|---|---|
| v1.0 | 03-Feb-2021 | D. Ito | Initial issue based on the corporate energy-control standard. |
| v2.0 | 10-May-2025 | D. Ito | Pneumatic and hydraulic energy added to clause 2.3. |
| v2.1 | 01-Sep-2026 | D. Ito | Section 3 added: exception for minor tool changes, at the request of Production to reduce changeover time. |

## Distribution

*The controlled copy of this document is held in the Document Management System (DMS). Printed or downloaded copies are uncontrolled; check the DMS for the current version before use.*

# Lockout/Tagout Procedure for Machine Maintenance

## 1 Purpose

1.1 This procedure protects workers from the unexpected start-up of machinery during servicing and maintenance.

## 2 Procedure

2.1 The authorized employee notifies all affected employees that the machine will be shut down.

2.2 The machine is shut down using its normal stopping procedure.

2.3 All energy sources (electrical, pneumatic, hydraulic) are isolated.

2.4 The authorized employee applies a personal lock and tag to every energy-isolating device.

2.5 The authorized employee verifies zero energy by attempting to start the machine.

2.6 Maintenance or servicing is performed.

2.7 Verification of zero energy must always be performed before any maintenance or servicing begins.

## 3 Exceptions

3.1 For minor tool changes expected to take less than 10 minutes, the operator may proceed directly to maintenance after shutting down the machine.

## 4 Restoring equipment

4.1 After maintenance, the authorized employee removes tools, ensures all employees are clear, and removes their lock and tag.

4.2 Only the employee who applied a lock may remove it.

4.3 Equipment must be returned to service as soon as possible.