

Nex-Gen Lumina — Commercial User Guide

Welcome to Lumina for your business. Permanent residential and commercial lighting that works as hard as you do — and this guide is how you make it work for your property, your brand, and your customers. Your installer has already handled the hardware and the network; this guide is about running the lights day to day.

What you'll need

- The Lumina app on your phone or tablet
 - Your **email and temporary password** from your installer (you'll change the password on first sign-in)
 - A few minutes to walk through the onboarding wizard if this is your first time
 - Your team's email addresses if you want to invite managers or staff
-

1. Signing in

Your installer handed off a Lumina account at install time.

1. Open the **Lumina** app
2. Tap **Sign In**
3. Enter the **email** and **temporary password** your installer provided
4. You'll be prompted to **create a new password** — pick something secure
5. After sign-in, the app recognizes your commercial account and loads the multi-zone dashboard

Tip: If you didn't receive credentials, call your installer directly. They can generate a new account or resend the invitation.

2. Commercial onboarding — 8 quick steps

When your account is first set up (or when you add a new location), you'll walk through an 8-step wizard that tailors the app to your business. It takes about 10 minutes.

Step 1: Business type

Pick what describes your business best — retail, restaurant, bar, office, hotel, mixed-use. This shapes the default settings and day-part suggestions to fit your industry.

Step 2: Brand identity

Set up your brand colors. These become quick presets throughout the app and can be pushed to all your locations.

Step 3: Hours of operation

Define business hours per day. The app uses them to build default schedules and decide when lights should be active.

Step 4: Channels

Configure your lighting channels. Commercial properties typically have several:

Channel role	Example use
Interior	Indoor ambient
Outdoor Facade	Building exterior
Window Display	Storefront windows
Patio	Outdoor dining/seating
Canopy	Covered outdoor structures
Signage / Accent	Signs and architectural accents

Each channel has a **Coverage Policy** (Always On, Smart Fill, Scheduled Only) and a **Daylight Mode** (Soft Dim, Hard Off, Disabled).

Step 5: Your teams

Add team members and assign roles. See **Roles and Permissions** (Section 12) for the four-tier role system.

Step 6: Day parts

Automate lighting transitions through the day:

Day part	Typical hours	Example use
Morning / Open	6 AM – 11 AM	Bright, welcoming
Midday	11 AM – 2 PM	Full brightness, natural feel
Afternoon	2 PM – 5 PM	Maintain visibility
Evening / Dinner	5 PM – 9 PM	Warm, ambient mood
Late Night / Close	9 PM – Close	Dimmed, winding down

Day parts transition your lighting automatically — no manual taps required.

Step 7: Multiple locations

If you manage multiple locations, add them here. Each one gets its own schedule, controllers, and team assignments. Single-location businesses can skip this.

Step 8: Review and go live

Final check on all settings. Tap **Go Live** to activate your lighting system. You can adjust anything later from the **System** tab.

Tip: You can re-run any part of onboarding from **System** → **Settings** if you need to reconfigure business type, channels, or day parts.

3. Dashboard — your command center

The home dashboard is where you run the whole property at a glance.

Hero image

The big image up top shows your property — your installer may have uploaded a photo during setup. You can change it later in **System** → **Settings**.

Power button

Toggles every zone on or off at once. Glows cyan when any zone is active.

Brightness slider

The vertical slider controls master brightness across every active zone. Changes are instant.

Quick presets

One-tap access to your go-to looks, along the right side of the hero image:

Preset	What it does
Run Schedule	Activates tonight's scheduled pattern for every zone
Warm White	Applies your primary white across every zone
Bright White	Applies your complementary white across every zone
Custom Favorites	Any patterns you've saved

Zone status

Below the hero image: a live look at every zone — what's on, what pattern is running, what brightness.

Tonight card

Shows what's scheduled for tonight across your zones, with a color preview.

4. Getting around

Five tabs along the bottom:

Tab	Icon	Purpose
Home	House	Main dashboard with zone overview and master controls
Schedule	Calendar	View and edit lighting schedules per zone
Lumina	Center star	AI assistant — type or speak a lighting command
Explore	Compass	Browse the pattern library and apply to zones
System	Gear	Settings, team management, remote access

5. Zone control — the real power of commercial

Commercial systems split your property into independent **zones** — things like "Storefront," "Patio," "Parking Lot," or "Building Perimeter." Each zone can be controlled separately or together.

The Channel Selector Bar

Anywhere you apply patterns or adjust settings, you'll see a **Channel Selector Bar** at the top. It's how you target specific zones.

Selection	Behavior
All	Commands apply to every zone simultaneously

Individual zone (e.g., "Storefront")

Commands apply only to that zone

How to use it:

1. Tap a zone name in the Channel Selector Bar
2. The bar highlights your selection
3. Any change you make now targets only that zone
4. Tap **All** to control the whole property again

Each zone stands on its own

What you can do with independent zone control:

- Run an animated holiday pattern on the storefront while the parking lot stays on steady bright white
- Dim the patio at closing without affecting the building perimeter
- Schedule different on/off times for each zone based on its purpose

Multi-controller zones

If a zone spans multiple controllers (common for larger buildings), those controllers stay in sync automatically — no action from you. Your installer configured it at setup.

Tip: If a portion of a zone ever falls out of sync, contact your installer — that's a hardware config matter, not something you adjust from the app.

6. Lumina AI — your zone-aware assistant

Lumina understands natural language and knows your zones by name.

Reaching Lumina

- **Lumina tab** (center of the bottom bar) for full-screen chat
- **Chat bar** at the bottom of the dashboard for quick commands

Typing or speaking

Type or tap the **microphone icon** to speak. Voice commands auto-submit after a 2-second pause.

Zone-aware commands

Say this	Lumina does this
"Turn on warm white"	Applies warm white to every zone
"Turn on the storefront"	Powers on only the Storefront zone
"Set patio to 50% brightness"	Adjusts patio brightness only
"Christmas theme on the storefront, bright white on parking lot"	Applies different settings to each zone
"Turn off everything except the parking lot"	Selective zone control
"Brighten up the patio"	Increases patio brightness
"What's running on the storefront?"	Reports current status for that zone
"Schedule warm white on the patio at 7 PM"	Creates a zone-specific schedule
"Turn off all lights"	Powers down every zone

Tip: Lumina learns your zone names and your preferences over time. Use it regularly and it gets sharper.

7. Scheduling

The **Schedule** tab automates your lighting on a weekly basis. Commercial schedules usually revolve around business hours and can be set per zone.

Viewing your schedule

1. Tap **Schedule**
2. The week view shows each day with its scheduled patterns
3. Tap a day to see details — pattern name, times, zones affected
4. Use arrows to move between weeks

Sync status indicator

Below the title bar on the Schedule tab, a small status row shows the result of your last push to the controller:

Indicator	Meaning
Green ✓ "Synced · 3m ago"	Last sync succeeded — schedules are live on every controller
Amber ⚠ "Synced with N warnings"	Schedules saved, but one or more presets didn't write cleanly — usually a brief network blip; tap Sync again
Red ☹ "Controller not reachable..."	The app can't reach a controller — confirm your phone is on the same Wi-Fi as the lighting system, then tap Sync

The row stays hidden until you tap the **Sync** button at the top right at least once per session.

Time format

Lumina respects your preferred time format throughout the schedule UI. Set **System** → **Edit Profile** → **Display Preferences** → **Time Format** to **12-hour (7:05 PM)** or **24-hour (19:05)**. The setting applies to schedule rows, conflict-resolution dialogs, sun-time labels, autopilot weekly previews, day-part displays, and the schedule detail sheet.

Creating a schedule

1. On the Schedule tab, tap +
2. Pick:
 - **Zone** — which zone this schedule applies to, or **All** for everything
 - **Pattern/Scene** — the lighting to display
 - **Start Time** — a clock time, or **Sunset** (see the note below)
 - **End Time** (optional)
 - **Repeat Days** — days of the week
3. Tap **Save**

Schedules live on the controllers themselves — they run even when the app is closed and you're off-site.

Typical business-hours setup

Zone	Schedule	Days
Storefront	Holiday pattern, 6:00 PM to 11:00 PM	Mon–Sun
Storefront	Warm white, 5:30 AM to 7:00 AM	Mon–Sat
Patio	Warm white, 6:00 PM to closing (10 PM)	Mon–Sun
Parking Lot	Bright white, 6:00 PM to 6:00 AM	Every day
Building Perimeter	Bright white, dusk to dawn	Every day

Sunset is a useful anchor for "on when it gets dark, whatever the season" — no seasonal retiming. Two limits: one sunrise schedule and one sunset schedule per property (everything else uses clock times), and offsets aren't available yet, so a sunset block starts at sunset rather than 20 minutes before. Solar timing depends on the controller carrying the site's coordinates; if a sunset schedule won't set, ask your installer to check them.

Auto-Pilot

Lumina's Auto-Pilot generates weekly schedule suggestions based on upcoming holidays, your preferences, and the season. You choose the autonomy level:

Mode	Behavior
Ask Me First	You approve each weekly plan
Smart Suggestions	Auto-applies after 24 hours if you don't respond
Full Auto-Pilot	Applies automatically, no approval needed

You can always override Auto-Pilot by editing any scheduled item manually.

Day-part automation

Day parts are a separate layer that handles lighting transitions throughout the business day. Unlike individual schedules, day parts define a continuous program covering the whole day.

To configure:

1. **System** → **Settings** → **Day Parts** (or configure during onboarding Step 6)
2. Define the time range for each day part
3. Assign a lighting preset to each day part
4. Day parts apply automatically every day

Example restaurant:

Day part	Time	Lighting
Breakfast	6:00 AM – 11:00 AM	Bright white, full brightness
Lunch	11:00 AM – 2:00 PM	Warm white, 80% brightness
Afternoon	2:00 PM – 5:00 PM	Warm white, 70% brightness
Dinner	5:00 PM – 9:00 PM	Amber accent, 60% brightness
Close	9:00 PM – 10:00 PM	Dim warm, 30% brightness
Overnight	10:00 PM – 6:00 AM	Security lights only

Day parts and manual schedules coexist. Manual overrides take priority, and the next day part resumes the auto program.

Tip: Day parts shine for businesses with consistent daily routines. Combine them with seasonal schedules for holidays and events — the manual schedule takes precedence during the event, day parts resume after.

8. Explore — the pattern library

Browsing

1. Tap **Explore**
2. Browse by category:
 - **Holidays** — Christmas, Halloween, 4th of July, and more
 - **Sports** — Team colors and game-day themes
 - **Nature** — Ocean, forest, sunset, aurora
 - **Mood** — Relaxing, energetic, festive
 - **Seasonal** — Spring, summer, fall, winter
 - **Whites** — Tones and temperatures
 - **Solid Colors** — Single-color fills
 - **Animations** — Chase, breathe, rainbow

Applying patterns to a specific zone

1. Open a pattern
2. Use the **Channel Selector Bar** to pick your target zone (or **All**)
3. Tap the pattern to **preview it live** on the selected zone
4. Tap **Apply** to keep it running
5. Tap the **heart icon** to favorite it for one-tap access later

Editing a pattern

- Tap the **edit icon** on any pattern
- Adjust speed, intensity, brightness, colors

- Save as a new custom pattern

Tip: Build a handful of business-signature favorites — your branded colors, your evening warm-white preset. They appear on the dashboard for one-tap access.

9. White presets

Your system uses LEDs with a dedicated white channel, so whites come out clean and true — something standard color-only LEDs can't match.

Built-in presets

Preset	Description
Warm White	Cozy, amber-tinted
Soft White	Gentle, slightly warm
Natural White	Balanced, true-to-life
Cool White	Clean, blue-tinted
Bright White	Pure white from the dedicated channel

Changing your defaults

1. **System** → **My Whites**
2. Tap a preset to preview it live
3. Pick your **Primary** (everyday default) and your **Complement**
4. Tap **Save**

Custom white

Use the R, G, B, and W sliders to blend a custom white. The W slider controls the dedicated white channel independently, giving you precise color-temperature control.

10. My Properties

Commercial accounts can manage multiple properties — multiple storefronts, offices, mixed-use sites — from a single Lumina account.

Getting there

1. **System** → **My Properties**

Adding a property

1. Tap **+** or **Add Property**
2. Enter a name (e.g., "Downtown Storefront", "Warehouse")
3. Start typing the address — suggestions appear as you type. Tap a suggestion to auto-fill, or type it manually.
4. Pick an icon
5. Tap **Save**

Linking controllers to a property

1. Tap **Controllers** on the property card
2. A list of all your registered controllers appears with toggles
3. Toggle on each controller that belongs to this property
4. Changes save automatically

Setting a primary property

1. Tap **Set Primary** on the property card
2. The primary property loads by default when you open the app

11. Remote access — control from anywhere

Lumina lets you control your lights from anywhere — not just when you're on the property Wi-Fi.

How it works

Your installer set up a small **bridge device** on your property network. It relays commands between the Lumina cloud and your local controllers. On the property Wi-Fi, the app talks to controllers directly for instant response. Off-site, commands route through the bridge. The app switches between modes automatically — you don't configure anything.

Verifying

1. **System** → **Remote Access**
2. Confirm the connection mode
3. Confirm status shows **Connected** or **Bridge Online**
4. Tap **Test Bridge** any time to verify

Heads-up: If the bridge is offline, check that the bridge device at your property has power and is on the network. Contact your installer if the issue sticks around.

12. Roles and permissions

Commercial accounts use a 4-tier role system to control access across your organization.

The roles

Role	What they can do
Store Staff	View-only access to their assigned location
Store Manager	Full control of their location — schedules, overrides, patterns
Regional Manager	Manage multiple locations, push to a region, manage users
Corporate Admin	Full access to everything — brand colors, corporate lock, push to all locations

Permission matrix

Permission	Staff	Manager	Regional	Corporate
View own location	✓	✓	✓	✓
Edit schedules	—	✓	✓	✓
Override now (manual control)	—	✓	✓	✓
View all locations	—	—	✓	✓
Push to region	—	—	✓	✓
Push to all locations	—	—	—	✓
Apply corporate lock	—	—	—	✓
Manage users	—	—	✓	✓
Edit brand colors	—	—	—	✓

Corporate lock

When a Corporate Admin applies a lock, local managers cannot override the schedule during the locked period. Use this for brand-wide promotions, holidays, or corporate events.

1. **System** → **Corporate Lock**
2. Pick the schedule or pattern to lock
3. Set the lock period (start and end)
4. Tap **Apply Lock**
5. All affected locations get a notification

Inviting a team member

1. **System** → **Manage Users**
2. Tap **Invite User**
3. Enter their email

4. Pick their **role** (Store Staff, Store Manager, Regional Manager, Corporate Admin)
5. If applicable, assign specific **locations** or **regions**
6. They get an invite to download Lumina and create their account
7. Once they accept, they appear in your user list with their assigned role

Removing a user

1. **System** → **Manage Users**
2. Tap the user
3. Tap **Remove User** — access is revoked immediately

Tip: Give trusted shift managers or key staff the Store Manager role so they can adjust lighting without pulling you in. Use Store Staff for anyone who only needs visibility.

13. Fleet dashboard — multi-location at a glance

If you manage multiple locations, the Fleet Dashboard gives you the whole operation in one view.

Getting in

- Multi-location accounts see the Fleet Dashboard by default
- Single-location accounts see the standard dashboard
- You can switch between fleet and individual views any time

What's there

- **Map view** — all locations on a map with status indicators (green = online, red = offline)
- **List view** — every location with current status, pattern, brightness
- **Filtering** — by region, status, or custom tags
- **Bulk actions** — push a pattern, schedule, or setting to multiple locations at once
- **Quick status** — spot which locations need attention

Tap any location to drill into its individual dashboard.

Tip: Filter the fleet view to quickly identify locations that are offline or running unexpected patterns. Especially useful for regional managers overseeing many sites.

14. Brand identity and corporate push

Corporate Admins can enforce brand consistency across every location.

Setting brand colors

1. **System** → **Settings** → **Brand Identity** (or during onboarding Step 2)
2. Define your primary and secondary brand colors
3. They appear as quick presets on every location's dashboard
4. Tap **Save**

Pushing settings

- **Push to Region** — Regional Managers push a schedule or pattern to every location in their region
- **Push to All** — Corporate Admins push to every location company-wide
- Pushed settings override local schedules until the push expires or is removed

To push:

1. Select the pattern, schedule, or setting
2. Tap **Push to...** and pick **Region** or **All Locations**
3. Optionally set an **expiration date**
4. Confirm — affected locations get a notification

Business profile

1. **System** → **Settings** → **Business Profile**
2. Edit business name, logo, contact info
3. These show on reports and notifications

Heads-up: Pushing to all locations overrides any local schedule changes. Give your location managers a heads-up before a company-wide push.

15. Notifications

Lumina sends notifications that matter for commercial operations:

Notification	When
Controller Offline	A controller at one of your locations stops responding
Holiday Schedule Conflict	An upcoming holiday may affect your schedule
Game Day Alert	A followed team is playing — Game Day mode is available
Corporate Push Received	Your organization has updated your schedule
Lock Expiring	A corporate schedule lock expires within 24 hours

Configure them in **System** → **Settings**. Enable or disable individual types and choose push notifications, in-app alerts, or both.

Tip: Turn on Controller Offline notifications so you hear about connectivity loss right away — before it affects customers.

16. Connection status

The app shows a connection status so you always know where you stand:

Indicator	Meaning
Green dot	Connected — controllers responding normally

Bridge icon (green)	Connected remotely via the bridge
"Reconnecting..."	Temporary connection loss — the app is retrying automatically
"System Offline"	Can't reach any controller — check property power and network

If you see "System Offline" while on-site:

1. Confirm your phone or tablet is on the **same Wi-Fi network** as the lighting system
2. Verify the controllers have power
3. Close and reopen the app

If you see "System Offline" while off-site:

1. The bridge at the property may be offline — check with on-site staff
2. Confirm the property has internet
3. Contact your installer if it sticks

17. Quick reference

Action	How
Turn all lights on/off	Tap the power button on the dashboard
Control a specific zone	Channel Selector Bar → tap the zone name
Control all zones at once	Channel Selector Bar → tap All
Change brightness	Slide the brightness control
Apply warm white	Tap Warm White preset
Apply a pattern to a zone	Explore → select zone in Channel Selector → tap pattern
Ask Lumina	Chat bar — type or tap the microphone

Ask Lumina about a zone	"Set storefront to warm white" or "Turn off the patio"
View schedule	Schedule tab
Add a zone schedule	Schedule → + → select zone
Change white preset	System → My Whites
Check remote access	System → Remote Access
Invite a user	System → Manage Users → Invite User
Remove a user	System → Manage Users → tap user → Remove
Access Fleet Dashboard	Automatic for multi-location accounts, or tap Fleet on the dashboard
Configure day parts	System → Settings → Day Parts
Set brand colors	System → Settings → Brand Identity
Apply corporate lock	System → Corporate Lock → pick schedule → Apply Lock
Push to all locations	Select pattern or schedule → Push to... → All Locations
View role permissions	System → Manage Users → tap a user to see their role

What success looks like

- Your dashboard loads and shows every zone online and responding
- Day parts transition automatically through the day without manual touches
- Auto-Pilot is delivering weekly schedules that match your brand and season
- Staff can make the changes they're supposed to make; can't make the ones they shouldn't
- Off-site remote access works — the bridge indicator stays green week over week

- Your team can describe what's running from a "Lumina, what's on the patio right now?" voice query without opening a screen

If something isn't working

"One zone isn't responding while the others are." Open the Channel Selector Bar — make sure that zone is selected (or switch to **All**). If the issue is with the lights themselves, a portion of the zone may have dropped off — contact your installer.

"The app says 'System Offline' on-site." Your phone isn't on the same Wi-Fi as the lighting system. Switch networks, then close and reopen the app.

"The app says 'System Offline' off-site." The bridge at your property may be offline. Have on-site staff check that the bridge device has power and is on the network. If persistent, contact your installer.

"A manager can't edit the schedule." Check their role — Store Staff is view-only. Bump them to Store Manager in **System** → **Manage Users**.

"A corporate push overrode a schedule I wanted to keep." Corporate pushes take precedence over local schedules until they expire. If it needs to change now, contact your Corporate Admin; they can remove the push.

"A day part isn't transitioning." Confirm the time ranges in **System** → **Settings** → **Day Parts** don't overlap or leave gaps. If a manual schedule is running, it takes priority — day parts resume after.

Need help?

- **In the app:** Ask Lumina — "Help" or "How do I..."
- **Email:** support@nexgenled.com
- **Your installer:** contact the dealer who installed your system

For troubleshooting, see the separate Lumina Troubleshooting Guide.