# **Photomicrosensor (Transmissive)**

# **EE-SX1103**

# **Compact Slot/Terminal Type** (Slot Width: 2 mm)

- Low profile (Height: 5.2 mm) type
- Terminal for PCB mounting





Be sure to read Safety Precautions on Page 3.

RoHS Compliant

# **Ordering Information**

#### **Photomicrosensor**

| Appearance | Sensing<br>method        | Connecting method         | Sensing distance  | Aperture size<br>(H × W) (mm)                            | Output type     | Model     | Minimum packing unit (Unit: pcs) |
|------------|--------------------------|---------------------------|-------------------|--|-----------------|-----------|----------------------------------|
| 5.2        | Transmissive (slot type) | Terminal for PCB mounting | 2 mm (Slot width) | Both emitting<br>side and<br>detecting side<br>1.2 × 0.4 | Phototransistor | EE-SX1103 | 1                                |

Note: Order in multiples of minimum packing unit.

# **Ratings, Characteristics and Exterior Specifications**

#### **Absolute Maximum Ratings** (Ta = 25°C)

|                       |                           |        | •           |      |
|-----------------------|---------------------------|--------|-------------|------|
|                       | Item                      | Symbol | Rated value | Unit |
| Emitter               |                           |        |             |      |
|                       | Forward current           | lF     | 50*1        | mA   |
|                       | Pulse forward current     | IFP    | _           | Α    |
|                       | Reverse voltage           | VR     | 5           | V    |
| Detector              |                           |        |             |      |
|                       | Collector-Emitter voltage | Vceo   | 30          | V    |
|                       | Emitter-Collector voltage | Veco   | 4.5         | V    |
|                       | Collector current         | lc     | 30          | mA   |
|                       | Collector dissipation     | Pc     | 80*1        | mW   |
| Operating temperature |                           | Topr   | -25 to 85   | °C   |
| Storage temperature   |                           | Tstg   | -30 to 100  | °C   |
| Soldering temperature |                           | Tsol   | 260*2       | °C   |

<sup>\*1.</sup> Refer to the temperature rating chart if the ambient temperature exceeds 25°C.

## **Exterior Specifications**

| Connecting method         | Weight (g) | Material |             |  |
|---------------------------|------------|----------|-------------|--|
| Connecting method         | weight (g) | Case     | Lens        |  |
| Terminal for PCB mounting | 0.2        | PPS      | Epoxy resin |  |

# Electrical and Optical Characteristics (Ta = 25°C)

| Item         |   | Value        |      |      | 11   | Condition |  |  |
|--------------|---|--------------|------|------|------|-----------|--|--|
|              |   | Symbol       | MIN. | TYP. | MAX. | Unit      | Condition  |  |
| Emitter      | Emitter                                       |              |      |      | •    |           |  |  |
|              | Forward voltage                               | VF           | _    | 1.3  | 1.6  | ٧         | IF = 50 mA   |  |
|              | Reverse current                               | lR           | _    | _    | 10   | μА        | V <sub>R</sub> = 5 V   |  |
|              | Peak<br>emission<br>wavelength                | λР           | _    | 950  | _    | nm        | IF = 50 mA   |  |
| Detector     |   |              |      |      |      |           |  |  |
|              | Light current                                 | lι           | 0.5  | -    | _    | mA        | IF = 20 mA,<br>VCE = 5 V   |  |
|              | Dark<br>current                               | lo           | _    | _    | 500  | nA        | VcE = 10 V,<br>0 lx  |  |
|              | Leakage current                               | ILEAK        | _    | _    | _    | μА        | _  |  |
|              | Collector-<br>Emitter<br>saturated<br>voltage | Vce<br>(sat) | _    | _    | 0.4  | V         | IF = 20 mA,<br>IL = 0.3 mA   |  |
|              | Peak<br>spectral<br>sensitivity<br>wavelength | λР           | _    | 800  | _    | nm        | Vce = 5 V  |  |
| Rising time  |   | tr           | _    | 10   | _    | μs        | $Vcc = 5 V,$ $RL = 100 \Omega$ $I_F = 20 \text{ mA}$   |  |
| Falling time |   | tf           |      | 10   | _    | μs        | $\label{eq:Vcc} \begin{array}{l} \text{Vcc} = 5 \text{ V}, \\ \text{RL} = 100 \ \Omega \\ \text{IF} = 20 \text{ mA} \end{array}$ |  |

<sup>\*2.</sup> Complete soldering within 3 seconds.

# **Engineering Data (Reference Value)**

Fig 1. Forward Current vs. Collector **Dissipation Temperature Rating** 




Fig 2. Forward Current vs. Forward **Voltage Characteristics (Typical)** 





Fig 3. Light Current vs. Forward **Current Characteristics (Typical)** 



**Voltage Characteristics (Typical)** 







Fig 4. Light Current vs. Collector-Emitter Fig 5. Relative Light Current vs. Ambient Fig 6. Dark Current vs. Ambient **Temperature Characteristics (Typical)** 



**Temperature Characteristics (Typical)** 



**Characteristics (Typical)** 



(Typical)




Fig 7. Response Time vs. Light Current Fig 8. Sensing Position Characteristics Fig 9. Sensing Position Characteristics (Typical)





Fig 10. Response Time Measurement Circuit



#### **Safety Precautions**

To ensure safe operation, be sure to read and follow the Instruction Manual provided with the Sensor.

#### **⚠** CAUTION

This product is not designed or rated for ensuring safety of persons either directly or indirectly. Do not use it for such purposes.



#### **Precautions for Correct Use**

Do not use the product in atmospheres or environments that exceed product ratings.

#### **Precautions for Safe Use**

Do not use the product with a voltage or current that exceeds the rated range.

Applying a voltage or current that is higher than the rated range may result in explosion or fire.

Do not miswire such as the polarity of the power supply voltage.

Otherwise the product may be damaged or it may burn.

This product does not resist water. Do not use the product in places where water or oil may be sprayed onto the product.

### **Dimensions and Internal Circuit**

(Unit: mm)


#### **Photomicrosensor**


#### EE-SX1103




Aperture size (H × W)

| Emitter   | Detector  |
|-----------|-----------|
| 1.2 × 0.4 | 1.2 × 0.4 |





Internal circuit



| Terminal No. | Name      |
|--------------|-----------|
| Α            | Anode     |
| K            | Cathode   |
| С            | Collector |
| E            | Emitter   |

Note: 1. Unless otherwise specified, the tolerances are ±0.2 mm. **2.** Dimensions in parentheses are for reference only.

Dimensions of the slit are those of the primary mold.

Please check each region's Terms & Conditions by region website.

OMRON Corporation
Electronic and Mechanical Components Company

#### **Regional Contact**

Americas

https://www.components.omron.com/

Asia-Pacific

https://ecb.omron.com.sg/

Korea

https://www.omron-ecb.co.kr/

Europe

http://components.omron.eu/

China

https://www.ecb.omron.com.cn/

Japan

https://www.omron.co.jp/ecb/