

1-7-3 Enlarge Bearings 1500rpm Series

Model Name	Frame	Rated Power	Rated Current	Rated Torque	Rated Efficiency	Noise
Unit	(mm)	(kW)	(A)	(Nm)	(%)	(dB)
MSI22C-15CDXS2□AA	90	2.2	4.7	14	89.7	64
MSI30C-15CDXS2□AA		3	6.4	19.1	90.3	64
MSI40C-15CDXS2□AA	100	4	8.5	25.5	90.9	65
MSI55C-15CDXS2□AB	112	5.5	11.9	35	92.1	71
MSI75C-15CDXS2□AB		7.5	15.6	47.8	92.6	71
MSI11D-15CDXS2□AB	132	11	20.8	70	93.6	75
MSI15D-15CDXS2□AB		15	25.8	95.5	94	75
MSI18D-15CDXS2□AB	160	18.5	35	117.8	94.3	76
MSI22D-15CDXS2□AB		22	43	140.1	94.7	76

NOTE: □ represents the installation method: A (IM B3 installation)

Model Name	Frame	Rated Power	Rated Current	Rated Torque	Rated Efficiency	Noise
Unit	(mm)	(kW)	(A)	(Nm)	(%)	(dB)
MSI30D-15CDXS2AAB	180	30	55.5	191	95	79
MSI37D-15CDXS2AAB		37	66	235.6	95.3	81
MSI45D-15CDXS2AAB	200	45	78.5	286.5	95.6	81
MSI55D-15CDXS2AAB	225	55	98.5	350.2	95.8	83
MSI75D-15CDXS2AAB		75	132	477.5	96	86
MSI90D-15CDXS2AAB	250	90	165	573	96.2	86
MSI11E-15CDXS2AAB		110	202	700.3	96.3	93

1-7-4 High Service Factor (SF1.2) 3000rpm Series

Model Name	Frame	Rated Power	Rated Current	Rated Torque	Rated Efficiency	Noise
Unit	(mm)	(kW)	(A)	(Nm)	(%)	(dB)
MSI75C-36CDXF2C1BC	112	3600	7.5	16.5	19.9	91.7
MSI75C-30CDXF2C1BC		3000	7.5	16.5	23.8	91.7
MSI11D-30CDXF2C1BC			11	23	35	92.6
MSI15D-30CDXF2C1BC			15	31	47.8	93.3
MSI18D-30CDXF2C1BC			18.5	38	58.9	93.7
MSI22D-30CDXF2C1BC	132		22	45	70	94
MSI30D-30CDXF2C1BC	160		30	57	95.5	94.5
MSI37D-30CDXF2C1BC			37	69	117.7	94.8