Quick Reference — Weighing a Spool

Weigh every spool when you return it. Weighing at other times is fine too.

Steps

1. **Place the spool on the scale.**
2. **Wait** until the display shows the spool number and remaining weight.
3. **Remove the spool.** The weight is saved.

What the display means

Screen	What to do
Green, "Place spool to begin"	Ready. Place a spool.
"Weighing…"	Wait. Don't lift yet.
Spool #, material, grams, "Weight recorded"	Done. Remove the spool.
"Registered! / NEEDS DETAILS"	New tag. See the Onboarding quick-ref.
Red "Read Error"	Move the spool so the tag sits over the reader.
Orange, "Scale not calibrated"	Tell an admin.

If something looks wrong

- **Read Error every time:** the tag may be damaged. Flag the spool for a new tag.
- **Weight looks wrong:** tell an admin.

Quick Reference — Onboarding a New Spool

Steps — for each new, untagged reel

1. **Stick an OpenPrintTag sticker** on the flat hub face, centered. Press firmly.
2. **Place the spool on the scale.**
3. The display counts down from 2 ("New tag found / Remove to cancel"). **Remove the spool** to cancel; **leave it** to register.
4. The display shows **"Registered! Spool #N / NEEDS DETAILS"**. Open the **Restock** page (or scan the QR code with a phone). Keep the spool on the scale.
5. **Say what it is**, in this order:
   - **Scan the box's barcode** (press the scanner's trigger), before or after placing the spool. A known barcode picks the stock item for you.
   - **Or pick it under "What is this spool?"** Type to narrow the list: Stock List items first, then other products. Greyed items aren't linked yet; tell an admin.
   - **New product?** Pick **+ New product…**, then the catalog search, or **Or enter manually**.
6. **Set the tare** (required): pick a **spool profile**, type it, or put an empty spool of the same type on the scale and press **Capture tare**.
7. **Cost** (optional): type what the reel cost. Blank keeps the current price; `0` clears it.
8. Press **Save & write tag.** First check **"Barcode … will be recorded for …"** above it: right only if you scanned *this* box, else press **clear**. If Save asks about a barcode, the scan and the pick may not match.

Next spool: place it. The page moves to it.

Vendor tag already on it? Just place it. **Already onboarded?** Click **Change this spool's details** to edit it.

If it goes wrong

Don't rewrite station tags with the Prusa app. It retires the spool.

"Read Error" after a failed registration: on **Administration** → **Erase Tag**, press **Start erase mode**, place the spool, press **Stop erase mode**, place it again.

Quick Reference — Inventorying

Checking what's on hand

Open `http://weighstation.local/`.

Page	What it shows
Inventory	Remaining filament by material. Click a row for its spools; click a spool for its history.
Reorder	Stock List items running low. Download, copy or e-mail the list to order.
Administration → Stock List	What we keep in stock, with a popularity score. Items at the top are candidates to drop.
Usage	Filament used by month. CSV download.

Running a shelf audit

1. On **Inventory**, press **Start audit**. Keep the page open.
2. **Weigh every spool.** Each weigh marks it found.
3. Press **Finish audit.** The page lists spools that weren't weighed.
4. For each one, press:
   - **Found** if it's on the shelf.
   - **Close** if it's gone. It's retired.
5. The audit ends when every spool is resolved.

Abandon audit stops the audit. Found and Close already pressed stay.

Retired spools are hidden from Inventory (use the show/hide toggle). A retired spool that's weighed again comes back automatically.

Quick Reference — Tag Erase

Erases every tag placed on the scale while erase mode is on.

Erase only tags from finished spools. Erasing retires the spool.

Steps

1. Open **Administration** → **Erase Tag** (or `http://weighstation.local/erase`).
2. Press **Start erase mode** and confirm. The station screen shows **ERASE MODE** in red.
3. **Place a spool.** It's erased at once. Wait for **"Tag erased"**.
4. **Remove it** and place the next one.
5. Press **Stop erase mode** when done.

Erase mode turns itself off after 10 minutes with no tag placed.

While erase mode is on, any tag placed is erased, including a spool you meant to weigh.