

Snowball Presentation Patch

2023-03-07 Kelcema

Fixtures

Circuit	Name	Patch	Mode	Weight	Rating
A	ADJ Encore Profile 1000 Color	1.1	11 Channel	18.7lbs	144W
A	ADJ Encore Profile 1000 Color	1.12	11 Channel	18.7lbs	144W
A	ADJ Encore Profile 1000 Color	1.23	11 Channel	18.7lbs	144W
A	ADJ Encore Profile 1000 Color	1.34	11 Channel	18.7lbs	144W
A	ADJ Vizi Wash Z19	1.45	45 Channel v.1.6	18.9lbs	276W
A	ADJ Vizi Wash Z19	1.90	45 Channel v.1.6	18.9lbs	276W
A	ADJ Vizi Wash Z19	1.135	45 Channel v.1.6	18.9lbs	276W
B	ADJ 12P HEX IP	2.1	13 Channel	10.5lbs	144W
B	ADJ 12P HEX IP	2.14	13 Channel	10.5lbs	144W
B	ADJ Element Hex	2.27	12 Channel	5.0lbs	42W
B	ADJ 12P HEX IP	2.39	13 Channel	10.5lbs	144W
B	ADJ 12P HEX IP	2.52	13 Channel	10.5lbs	144W
B	Elation Sniper 2R	2.65	14 Channel	20.9lbs	220W
B	ADJ Vizi Wash Z19	2.79	45 Channel v.1.6	18.9lbs	276W
B	ADJ Element Hex	2.124	12 Channel	5.0lbs	42W
B	ADJ Vizi Beam 12RX	2.136	17 Channel	39.6lbs	384W
B	Elation Sniper 2R	2.153	14 Channel	20.9lbs	220W
B	Elation Sniper 2R	2.167	14 Channel	20.9lbs	220W
C	Elation Sniper 2R	2.181	14 Channel	20.9lbs	220W
C	Elation Sniper 2R	2.195	14 Channel	20.9lbs	220W
C	ADJ Vizi Beam 12RX	2.209	17 Channel	39.6lbs	384W
C	ADJ Element Hex	2.226	12 Channel	5.0lbs	42W
C	ADJ Vizi Wash Z19	2.238	45 Channel v.1.6	18.9lbs	276W
C	Elation Sniper 2R	2.283	14 Channel	20.9lbs	220W
C	ADJ 12P HEX IP	2.297	13 Channel	10.5lbs	144W
C	ADJ 12P HEX IP	2.310	13 Channel	10.5lbs	144W
C	ADJ Element Hex	2.323	12 Channel	5.0lbs	42W
C	ADJ 12P HEX IP	2.335	13 Channel	10.5lbs	144W
C	ADJ 12P HEX IP	2.348	13 Channel	10.5lbs	144W
				478.1lbs	5kW 364W