

#	Item	Detalle / Detail
1	Descripción	2500 W/3000 W AC&240 V DC Power Module (Front to Back, Power panel side intake)
2	Part Number	02312TCA
3	Modelo	PAC3KS54-DF
4	Dimensions without packaging (H x W x D) [mm(in.)]	39.6 mm x 66 mm x 350 mm (1.56 in. x 2.60 in. x 13.78 in.)
5	Weight without packaging [kg(lb)]	1.5 kg (3.31 lb)
6	Number of inputs	1
7	Rated input voltage [V]	● AC input: 110 V AC/220 V AC, 50/60 Hz ● HVDC input: 240 V DC
8	Input voltage range [V]	● AC input: 90 V AC to 290 V AC; 45 Hz to 65 Hz (90 V AC $\leq$ input voltage < 176 V AC: up to 1500 W output power; 176 V AC $\leq$ input voltage < 200 V AC: up to 2300 W output power; 200 V AC $\leq$ input voltage $\leq$ 290 V AC: up to 2500 W output power) ● High-voltage DC input: 190 V DC to 290 V DC (190 V DC $\leq$ input voltage < 200 V DC: up to 2300 W output power; 200 V DC $\leq$ input voltage $\leq$ 290 V DC: up to 2500 W output power) NOTE When the maximum output power is 3000 W: ● AC input: When the input voltage is greater than or equal to 176 V AC and less than 200 V AC, the maximum output power is 2800 W. When the input voltage is greater than or equal to 200 V AC and less than or equal to 290 V AC, the maximum output power is 3000 W. ● High-voltage DC input: When the input voltage is greater than or equal to 190 V DC and less than 200 V DC, the maximum output power is 2800 W. When the input voltage is greater than or equal to 200 V DC and less than or equal to 290 V DC, the maximum output power is 3000 W.

9	Maximum input current [A]	16 A
10	Rated output voltage [V]	53.5 V or 55 V
11	Rated output power [W]	2500 W/3000 W NOTE By default, the maximum output power is 2500 W. You can enable the maximum output power of 3000 W using a command. When the maximum output power is 3000 W, the maximum altitude is 2000 m (6562 ft.) and the power module cannot be used together with other power modules.
12	Power dissipation Mode	Heat dissipation with fan
13	Hot swapping	Supported