

#### Is Now Part of



## ON Semiconductor®

# To learn more about ON Semiconductor, please visit our website at www.onsemi.com

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (\_), the underscore (\_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (\_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at <a href="www.onsemi.com">www.onsemi.com</a>. Please email any questions regarding the system integration to Fairchild <a href="guestions@onsemi.com">guestions@onsemi.com</a>.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officer

June 2000 DISTRIBUTION GROUP\*

## MTP3055VL

### N-Channel Logic Level Enhancement Mode Field Effect Transistor

#### **General Description**


This N-Channel Logic Level MOSFET has been designed specifically for low voltage, high speed switching applications i.e. power supplies and power motor controls.


This MOSFET features faster switching and lower gate charge than other MOSFETs with comparable  $R_{\text{DS(ON)}}$  specifications.

The result is a MOSFET that is easy and safer to drive (even at very high frequencies).

#### **Features**

- 12 A, 60 V.  $R_{DS(ON)} = 0.18 \Omega @ V_{GS} = 5 V$
- Critical DC electrical parameters specified at elevated temperature.
- Low drive requirements allowing operation directly from logic drivers. Vgs(th) < 2 V.</li>
- Rugged internal source-drain diode can eliminate the need for an external Zener diode transient suppressor.
- 175°C maximum junction temperature rating.





Absolute Maximum Ratings T<sub>C</sub> = 25°C unless otherwise noted

Symbol	Parameter	Ratings	Units	
V <sub>DSS</sub>	Drain-Source Voltage	60	V	
V <sub>GSS</sub>	Gate-Source Voltage	<u>+</u> 15	V	
I <sub>D</sub>	Drain Current - Continuous	12	A	
	- Pulsed	42		
P <sub>D</sub>	Power Dissipation @ T <sub>C</sub> = 25°C	48	W	
	Derate above 25°C	0.32	W/°C	
T <sub>J</sub> , T <sub>STG</sub>	Operating and Storage Junction Temperature Range	-65 to +175	∘C	
<u> Thermal</u>	Characteristics			
$R_{\theta JC}$	Thermal Resistance, Junction-to- Case	3.13	°C/W	
R <sub>AJA</sub>	Thermal Resistance, Junction-to- Ambient (Note 1)	62.5	∘C/W	

**Package Outlines and Ordering Information** 

Device Marking	Device	Package Information	Quantity
MTP3055VL	MTP3055VL	Rails/Tubes	45 units

<sup>\*</sup> Die and manufacturing source subject to change without prior notification.

Symbol	Parameter	Test Conditions	Min	Тур	Max	Units
DRAIN-S	OURCE AVALANCHE RATI	NGS (Note 2)		•	•	•
W <sub>DSS</sub>	Single Pulse Drain-Source Avalanche Energy	V <sub>DD</sub> = 25 V, I <sub>D</sub> = 12 A			72	mJ
I <sub>AR</sub>	Maximum Drain-Source Avalanche	e Current			12	А
Off Chara	cteristics					
BV <sub>DSS</sub>	Drain-Source Breakdown Voltage	$V_{GS} = 0 \text{ V}, I_{D} = 250 \mu\text{A}$	60			V
$\Delta BV_{DSS} \over \Delta T_{J}$	Breakdown Voltage Temperature Coefficient	$I_D = 250 \mu\text{A}$ , Referenced to $25^{\circ}\text{C}$		55		mV/°C
I <sub>DSS</sub>	Zero Gate Voltage Drain Current	$V_{DS} = 60 \text{ V}, V_{GS} = 0 \text{ V}$			10	μΑ
		$V_{DS} = 60 \text{ V}, V_{GS} = 0 \text{ V}, T_{J} = 150^{\circ}\text{C}$			100	
I <sub>GSSF</sub>	Gate-Body Leakage Current, Forward	V <sub>GS</sub> = 15 V, V <sub>DS</sub> = 0 V			100	nA
I <sub>GSSR</sub>	Gate-Body Leakage Current, Reverse	$V_{GS} = -15 \text{ V}, V_{DS} = 0 \text{ V}$			-100	nA
On Chara	cteristics (Note 2)					
$V_{GS(th)}$	Gate Threshold Voltage	$V_{DS} = V_{GS}, I_{D} = 250 \mu A$	1	1.6	2	V
$\Delta V_{GS(th)} = \Delta T_{.1}$	Gate Threshold Voltage Temperature Coefficient	$I_D$ = 250 $\mu$ A, Referenced to 25°C		-4		mV/°C
R <sub>DS(on)</sub>	Static Drain-Source On-Resistance	$V_{GS} = 5 V, I_D = 6 A,$		0.100	0.180	Ω
$V_{DS(on)}$	Drain-Source On-Voltage On-Resistance	$V_{GS} = 5 \text{ V}, I_{D} = 12 \text{ A}$			2.6	V
g <sub>FS</sub>	Forward Transconductance	$V_{DS} = 8 \text{ V}, I_{D} = 6 \text{ A}$	5	8.7		S
Dvnamic	Characteristics					
C <sub>iss</sub>	Input Capacitance	$V_{DS} = 25 \text{ V}, V_{GS} = 0 \text{ V},$		345	570	pF
Coss	Output Capacitance	f = 1.0 MHz		110	160	pF
$C_{rss}$	Reverse Transfer Capacitance			30	40	pF
Switching	Characteristics (Note 2)					
t <sub>d(on)</sub>	Turn-On Delay Time	$V_{DD} = 30 \text{ V}, I_{D} = 12 \text{ A},$			20	ns
t <sub>r</sub>	Turn-On Rise Time	$V_{GS} = 5 \text{ V}, R_{GEN} = 9.1 \Omega$			190	ns
t <sub>d(off)</sub>	Turn-Off Delay Time				30	ns
t <sub>f</sub>	Turn-Off Fall Time	1			90	ns
Q <sub>g</sub>	Total Gate Charge	V <sub>DS</sub> = 48 V,		7.8	10	nC
Q <sub>gs</sub>	Gate-Source Charge	I <sub>D</sub> = 12 A, V <sub>GS</sub> = 5 V		1.7		nC
Q <sub>gd</sub>	Gate-Drain Charge			3.2		nC
					ı	
	urce Diode Characteristics  Maximum Continuous Drain-Source				12	A
I <sub>SM</sub>	Maximum Pulsed Drain-Source Di				42	A
V <sub>SD</sub>	Drain-Source Diode Forward	$V_{GS} = 0 \text{ V}, I_S = 12 \text{ A}$ (Note 2)			1.3	V
<b>→</b> 2D	Voltage	VGS - V V, IS - IZ / (NOIE 2)			1.5	_ <u> </u>
t <sub>rr</sub>	Drain-Source Reverse Recovery Time	I <sub>F</sub> =12 A, di/dt = 100A/μs		55		nS

<sup>1.</sup>  $R_{0,JA}$  is the sum of the juntion-to-case and case-to-ambient thermal resistance. 2. Pulse Test: Pulse Width  $\leq$  300  $\mu$ s, Duty Cycle  $\leq$  2.0%

#### **TRADEMARKS**

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

	$ACEx^{TM}$	FAST®	ISOPLANAR™	Power247™	SuperFET™
	ActiveArray™	FASTr™	LittleFET™	PowerSaver™	SuperSOT™-3
	Bottomless™	FPS™	$MICROCOUPLER^{TM}$	PowerTrench®	SuperSOT™-6
	CoolFET™	FRFET™	MicroFET™	QFET®	SuperSOT™-8
	$CROSSVOLT^{\text{TM}}$	GlobalOptoisolator™	MicroPak™	$QS^{TM}$	SyncFET™
	DOME™	GTO™ .	MICROWIRE™	QT Optoelectronics™	TinyLogic <sup>®</sup>
	EcoSPARK™	HiSeC™	MSX <sup>TM</sup>	Quiet Series™	TINYOPTO™
	E <sup>2</sup> CMOS <sup>TM</sup>	I <sup>2</sup> C <sup>TM</sup>	MSXPro™	RapidConfigure™	TruTranslation™
	EnSigna™	<i>i-</i> Lo <sup>™</sup>	$OCX^{TM}$	RapidConnect™	UHC™
	FACT™	ImpliedDisconnect™	OCXPro™	μSerDes™	UltraFET®
	FACT Quiet Serie	es <sup>™</sup>	OPTOLOGIC®	SILENT SWITCHER®	VCX <sup>TM</sup>
Across the board. Around the world.™		OPTOPLANAR™	SMART START™		
	The Power France		PACMAN™	SPM <sup>TM</sup>	
				<u> </u>	

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

POPTM

#### LIFE SUPPORT POLICY

 $Programmable \ Active \ Droop^{\tiny\mathsf{TM}}$ 

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

Stealth™

#### PRODUCT STATUS DEFINITIONS

#### **Definition of Terms**

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

Rev. I11

ON Semiconductor and in are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdt/Patent-Marking.pdf">www.onsemi.com/site/pdt/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and exp

#### **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81–3–5817–1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative