

#	Cat-1: Prohibited					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
WN.Z1	WN (R)	AP	Prohibit			
WN.Z2	WN (C)	AP	Prohibit			
WN.Z3	WN (C)	AR	Prohibit			
CO.Z1	CO	AA+GC+GR	Require			
CO.Z3	CO	M1	Require			
V1.Z1	V1	M1	Require			
V1.Z2	V1	M2	Require			
PO.Z1	PO	M1	Require			
PO.Z2	PO	M2	Require			
PO.Z3	PO	V1 (P)	Contain			
#	Cat-2: WN-AC/AR related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
WN.W1	WN		Wmin	8.0		ER0001
WN.S1	WN	WN	Smin	4.0		ER0025
WN.N1	WN	WN	Nmin	7.0		
WN.S2	WN (R)	WN (M)	Smin	9.5		ER0111
WN.S3	WN (C)	WN (M)	Smin	12.0		ER0130
WN.S4	WN (R)	WN (C)	Smin	9.5		ER0132
WN.S5	WN (R)	WN (R)	Smin	8.0		ER0122
WN.S6	WN (C)	WN (C)	Smin	12.0		ER0129
WN.S7	WN (M)	WN (M)	Smin	12.0		ER0104
WN.AP	WN	AP	Smin	5.0		ERWLMN01
WN.AN	WN	AN	Smin	10.0		ERWLMN03
AR.S1	AR	AR	Smin	4.0		ERWLRR03
AR.WR	AR	WN (R)	Emin	10.0		ERWLRR02
AN.WR	AN	WN (R)	Emin	5.0		ERWLRR01
AR.AN	AR	AN	Smin	4.0		ERWLRR04
AC.W1	AC		Rect	28.5	120.0	Table I-2-1
AC.S1	AC	AC	Smin	6.4		
AC.WC	AC	WN (C)	Emin	8.0		
AN.WC	AN	WN (C)	Emin	3.0		ERCSIO04
AC.AN	AC	AN	Sfix	2.8	2.8	ERCSIO11
AC.GC	AC	GC	Efix	1.4	1.4	ERCSIO13
AC.R1	AC	AN (C)	Donut	0.0		
#	Cat-3: AP/AN/DP/DN related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
AP.W1	AP		Wmin	1.4		ER0004
AP.S1	AP	AP	Smin	1.4		ER0028
AP.AN	AP	AN	Smin	2.8		ERWLMP04
AP.WM	PMOS	AP-GC	Wmin/max	3.4	60.0	Table I-2-1
AP.LM	PMOS	GC-AP	Lmin/max	1.0	30.0	Table I-2-1
AP.WN	AP	WN	Emin	7.0		ERWLMP02
DP.W1	DP		Wmin	3.6		
DP.S1	DP	DP	Smin	1.4		=AP.S1
DP.AP	DP	AP (M)	Smin	2.8		ERWLMP08
DP.AN	DP	AN	Smin	2.8		ERWLMP09
AN.W1	AN		Wmin	1.4		ER0004
AN.S1	AN	AN	Smin	1.4		ER0028
AN.AP	AN	AP	Smin	2.8		ERWLMN05
AN.WM	NMOS	AN-GC	Wmin/max	3.4	60.0	Table I-2-1
AN.LM	NMOS	GC-AN	Lmin/max	1.0	30.0	Table I-2-1
AN.WN	AN	WN (M)	Emin	5.0		ERWLMP03
DN.W1	DN		Wmin	3.6		
DN.S1	DN	DN	Smin	1.4		=AN.S1
DN.AP	DN	AP	Smin	2.8		ERWLMN10
DN.AN	DN	AN (M)	Smin	2.8		ERWLMN11
#	Cat-4: GC/CO related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
GC.W1	GC		Wmin	1.0		ER0014
GC.S1	GC	GC	Smin	1.2		ER0038
GC.GR	GC	GR	Smin	1.2		ER0038
GA.AP	GA	AP	Smin	0.4		ERWLMP07
GA.AN	GA	AN	Smin	0.4		ERWLMN09
GC.EP	AP	GC	Emin	1.2		ERMP06/ERMPE02
GC.EN	AN	GC	Emin	1.2		ERMN06/ERMNE02
GA.BG	GA	BG	Prohibit			ER0419
GA.CO	GA	CO	Contain			ER0704
CO.W1	CO		Rect	1.0	97.0	ER0020
CO.WM	CO (M)		Wfix	1.0	1.0	ER0020
CO.WB	CO (B)		Wfix	1.0	1.0	
CO.S1	CO	CO	Smin	1.0		ER0044
CO.CL	CO (L)	CO	Smin	1.6		ER1303

Function:

Wmin/max: L1 Width min/max
 Smin/max: L1 Space min/max (L1=L2)
 Smin/max: L1 Separate L2 min/max
 Emin/max: L1 Enclosed L2 min/max
 Fmin/max: L1 Enclosing L2 min/max
 Wfix: L1 Width equal
 Sfix: Space equal
 Nmin: L1 Notch min
 Efix: Fixed enclosure
 Donut: L1 Souuounded by L2
 Prohibit: Must not overlap
 Require: Must not be outside
 Contain: Must contain
 Rect: Must be a rectangle

CO.SM	CO (M)	CO (M)	Sfix	1.0	1.0	ERMP08/ERMN09
CO.WD	CO (D)		Wfix	1.2	1.2	ERDP05/ERDN05
CO.SD	CO (D)	CO	Smin	1.2		
CO.AD	CO (D)	AP+AN	Emin	1.2		ERDP24/ERDN23
CO.AP	CO	AP	Emin	0.8		ERMP10
CO.AN	CO	AN	Emin	0.8		ERMN11
CL.GC	CO (L)	GC+GR	Prohibit			
CO.GG	CO (M)	GC	Sfix	1.0	1.0	ERMP12/ERMN12
CO.GC	CO	GC+GR	Emin	0.8		ER0050
#	Cat-5: AC/AR/GR related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
AR.W1	RR	RR (W)	Wmin/max	2.8	20.0	Table I-2-1
AR.L1	RR	RR (L)	Lmin/max	13.0	100.0	Table I-2-1
RR.SZ	RR	RROK	Contain			Valid width
RR.RT	RR		Rect			
AR.GC	GC	AR	Smin	1.0		ERRR15
AR.PW	GC (R)		Wmin	2.0		ERRR06
AR.XY	AR	Bevel	XYmin	1.0		
GC.AN	GC (R)	AN	Smin	???	???	
GC.R1	AR	GC (R)	Donut	0.0		
GC.R2	GC (R)	WN (R)	TieDown	0.0		
GR.W1	RS	RS (W)	Wmin/max	4.0	20.0	Table I-2-1
GR.L1	RS	RS (L)	Lmin/max	20.0	100.0	Table I-2-1
RS.SZ	RS	RSOK	Require			Valid width
RS.RT	RS		Rect			
GR.S1	RS	RS	Smin	2.0		ERRS04
CR.W1	CO (RR)		Wmin	1.0		ERRR10
CR.W2	CO (RRW)		Lmin/max	1.6	17.6	CO (L)
CR.W3	CO (RRN)		Wfix	1.0	1.0	ERRR11
CR.AR	CO (RR)	AR	Emin	0.8		ERRR14
CR.AT	CO (RR)	AR (T)	Emin	1.5		ERRR08
CR.ASN	CO (RRN)	ARN (S)	Efix	0.9		ERRR14
CR.ASW	CO (RRW)	ARW (S)	Efix	1.2		ERRR13
CC.W1	CO (C)		Wfix	1.2	1.2	ERCSIO01
CC.S1	CO (C)	CO (C)	SFIX	1.2	1.2	ERCSIO14
CO.SC	CO (C)	CO	Smin	1.2		
CC.AC	CO (C)	AC	Emin	2.9		ERCSIO03
CC.AN	CO (C)	AN	Emin	1.2		ERCSIO02
CS.S1	CO (RS)	CO (RS)	SFIX	1.0	1.0	
CO.GR	CO	GR	Emin	0.8		
CO.GS	CO (RSM)	GR (S)	Efix	1.5	1.5	
CO.RT	CO (RSM)		Rect			
#	Cat-6: BEOL related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
M1.W1	M1		Wmin	1.8		ER0021
M1.W2	M1 (W)		WMIN	10.0		ER0021
M1.W3	M1 (I)		Wmax		45.0	ER1903
M1.S1	M1	M1	Smin	1.4		ER0045
M1.SC	M1 (C)	M1 (C)	Smin/Smax	10.0	10.0	ERCSIO06
M1.CO	M1	CO	Fmin	0.8		ER0051
M1.CC	M1	CO (CC)	Fmin	1.3		ERCSIO02
M1.CL	M1	CO (L)	Fmin	1.2		ER1305
M1.SW	M1 (W)	M1	Smin	2.0		ER1402
V1.W1	V1		Wfix	1.4	1.4	ER0022
V1.S1	V1	V1	Smin	1.5		ER0046
V1.M1	V1	M1	Emin	1.0		ER0052
V1.GA	V1	GA	Smin	1.2		ER1508/ ER1514
V1.CO	V1	CO	Smin	1.0		ER1506
V1.CL	V1	CO (L)	Smin	1.4		ER1507
M2.W1	M2		Wmin	3.0		ER0023
M2.W3	M2 (I)		Wmax		45.0	ER1904
M2.S1	M2	M2	Smin	2.0		ER0047
M2.V1	M2	V1	Fmin	1.0		ER0053
#	Cat-7: ESD related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
APE.WM	PMOSE	APE-GC	Wmin/max	11.0	60.0	Table I-2-1
APE.LM	PMOSE	GC-APE	Lmin/max	2.0	30.0	Table I-2-1
APE.AN	APE	AN	Smin	10.0		ERWLMPE15
APE.XY	APE	Bevel	XYmin	1.4		ERMPE06
APE.CO	APE	CO	Smin	2.0		ERWLMPE16
ANE.WM	NMOSE	ANE-GC	Wmin/max	11.0	60.0	Table I-2-1
ANE.LM	NMOSE	GC-ANE	Lmin/max	2.0	30.0	Table I-2-1
ANE.AP	ANE	AP	Smin	10.0		ERWLMN14
ANE.XY	ANE	Bevel	XYmin	1.4		ERMNE15
ANE.CO	ANE	CO	Smin	2.0		ERWLMN15

COE.W1	CO (E)		Wfix	3.0	3.0	ERMPE12/ERMNE13
COE.S1	CO (E)	CO	Smin	1.6		ERMPE13/ERMNE15
COE.SE	CO (E)	CO (E)	Sfix	1.6	1.6	
CDE.GC	CD (E)	GC	Sfix	7.0		ERMPE04/ERMNE08
CSE.GC	CS (E)	GC	Sfix	3.0		ERMPE03/ERMNE09
COE.AP	CO (E)	AP	Emin	2.5		ERMPE31
COE.AN	CO (E)	AN	Emin	2.5		ERMNE32
COE.APT	CO (E)	AP (T)	Emin	4.0		ERMPE05
COE.ANT	CO (E)	AN (T)	Emin	4.0		ERMNE10
#	Cat-8: PAD related					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
PO.W1	PO		Rect	10.0		ER0024
PO.S1	PO	PO	Smin	20.0		ER0048
PP.W1	PP		Wmin	70.0		ER1809
PP.S1	PP	PP	Smin	64.0		ER1810
M1.PO	M1	PO	Fmin	5.0		ER1703
M2.PO	M2	PO	Fmin	5.0		ER1704
M1.V1P	M1	V1 (P)	Fmin	10.0		ER1811
M2.V1P	M2	V1 (P)	Fmin	10.0		ER1812
M1P.AA	M1 (P)	AA	Smin	14.0		ER1808
M2P.AA	M2 (P)	AA	Smin	14.0		ER1808
M1P.GA	M1 (P)	GA	Smin	14.0		ER1807
M2P.GA	M2 (P)	GA	Smin	14.0		ER1807
M1P.M1	M1 (P)	M1	Smin	14.0		ER1801
M2P.M2	M2 (P)	M2	Smin	14.0		ER1802
M1P.PE	M1 (P)	M1	Ext	14.0	40.0	ER1804
M2P.PE	M2 (P)	M2	Ext	14.0	40.0	ER1803
M2.PW	M2		EXTW	40.0		ER1803
M1.PW	M2		EXTW	40.0		ER1804
#	Cat-9: Electrical / Optional					
Rule	L1	L2	Func	MIN	MAX	IP62 Rule Name
GC.ANT	GC		ANTE	0.0		