



HORMEL THEATRE

AUDIO SYSTEM RIDER

The Phoenix Theatre Company | 1825 N Central Ave, Phoenix, AZ 85004

Audio Supervisor: Matthew Gibney (m.gibney@phoenixtheatre.com) | House A1: Katie Paris

Version 1.0 — July 3, 2026

Hormel is one of PTC's two mainstage venues (recent productions: Dear Evan Hansen, Murder for Two, Suffs). Full-production Dante infrastructure at 48 kHz throughout. This rider reflects the house system of record as of the date above; advance all production-specific needs with the Audio Supervisor.

FRONT OF HOUSE CONTROL

Console	Yamaha CL5 — 48 kHz, Dante-native
System processing	Meyer Galileo 616 speaker processor; Yamaha IMX644 output distribution
Playback	QLab (dedicated Apple Mac Studio + 2× M1 Mac Mini) via Dante Virtual Soundcard and Focusrite Scarlett 18i20 interface
Recording	Nuendo record computer on Dante (virtual soundcheck capable)
Show control	QLab with MSC/LTC integration to Lighting via the interdepartment OSC network (proven signal chain on Dear Evan Hansen)

LOUDSPEAKER SYSTEM (L-ACOUSTICS)

Mains	4× L-Acoustics ARCS Wide (passive, house-dedicated)
Front fills	5× L-Acoustics 5XT ultra-compact coaxial
House delays	4× L-Acoustics X8 compact coaxial
Subwoofers	2× L-Acoustics SB18 (house)
Amplification	4× L-Acoustics LA4X, 1× QSC CX-Q 8K8 network amplifier — all on the audio control network
Paging / lobby	Crown CTS600 amplification for BOH page and FOH mix feed to lobby

STAGE I/O & NETWORK

Stage boxes	2× Yamaha Rio3224-D (Band and FOH positions) — Dante, 48 kHz
Dante network	Fully redundant primary/secondary Dante on dedicated audio VLANs; word clock leader: Focusrite RedNet A8R (shared with Stephenson)
Wireless control	Dedicated audio-control Wi-Fi at FOH and band positions for console/RF remote control
Interdepartment	OSC bridge network to Lighting and Video departments (MSC/LTC show-control integration available)
Cue lights	Dressler PTQLS 16-station cue light system

WIRELESS MICROPHONES (SHURE AXIENT DIGITAL)

Receivers	5× Shure AD4Q four-channel receivers assigned to Hormel (20 channels; 13 AD4Q house-wide)
Bodypacks	Shure ADX1M micro-bodypack pool (52 house-wide, allocated per production)
Handhelds	2× Shure ADX2

RF management	Shure AXT600 Axient Spectrum Manager and antenna distribution shared house-wide
House lav standard	Countryman B3 (LEMO) for vocals; DPA 4099 series (C/V/BC/STC clips) as the instrument-mic house standard

MONITORING & COMMS

Personal mixers	Allen & Heath ME-1 (24-unit house pool) via ME-U hub (1× assigned to Hormel)
Wedges / spot monitors	Shared house stock: QSC K8/K10/K12, JBL EON15, Meyer UPM-1P, EAW JF80 — allocated per production; Galaxy PA5X140/Microspot spot monitors on site
Comms core	Clear-Com Arcadia Central Station (AES67, shared across venues) with HRM-4X remote stations
Wireless comms	Clear-Com FreeSpeak II — 3× IP transceivers in Hormel; HXii wireless beltpack pool (21-pack Hormel assignment)
Assistive listening	Listen Technologies Auri IR transmission (house system)

BAND MICROPHONE STOCK (SELECTED)

Sennheiser e604/e609/e904, MKH-50, MD-441 · DPA 4099 family (largest recurring deployment) · AKG 414 · Shure SM57/KSM137 · Neumann KM184. Full 126-line inventory available on request; allocations advanced per production.

NOT COVERED HERE — ADVANCE WITH THE DEPARTMENT

Company power/tie-in specifications, rigging and line-set schedule, seating capacity/house dimensions, video-projection inventory, and touring-package interconnect points are not part of this document — contact the Audio Supervisor to advance. Network addressing and credentials are not published; visiting engineers requiring Dante or control-network access will be provisioned on site.

Prepared from the AUD-IT department system of record (inventory snapshot 2026-07-03; network register 2026). Subject to change — confirm current configuration when advancing.