

Hormel CL5 — MIDI Remote Control Addendum

QLab-driven input patching & channel color via SysEx · v1.0 · 2026-07-09

WHAT THIS IS

The CL5 accepts Yamaha "Parameter Change" SysEx over MIDI. A QLab MIDI cue can repatch any input channel's source (Dante / Omni / Slot) or set its color mid-show — no hands on the desk. Strings are built with the PTC tool below; the original spreadsheet is retained in Raw/ as the source of the byte format.

THE TOOL

cl5-patch-generator-v2.html (Cowork folder root — runs offline in any browser, no install)

Pick parameter (Input patch / Channel color), channel, and value; copy the QLab-ready string.

Enter = copy string. Cmd/Ctrl+Enter = stack cue on the built-in cue sheet, exportable as a text file.

QLAB SETUP

1. MIDI cue, type SysEx. Paste the tool's QLab string. QLab adds the F0/F7 wrapper itself.
2. One SysEx message = one parameter. Patch + color together = two MIDI cues in a Group cue set to "start all children" — one GO fires both.
3. MIDI patch/route from the QLab Mac to the CL5 per the show's standard MIDI path.

CL5 SETUP (ONE-TIME, SETUP > MIDI/GPI)

- MIDI mode: NRPN · Parameter Change: Rx ON
- Console MIDI channel must match the tool's Device number (default device 1 = "10" byte).

MESSAGE FORMAT (YAMAHA CL PARAMETER CHANGE)

F0 43 1n 3E 19 01 <element x2> <index x2> <channel x2> <data x5> F7

n = device (MIDI ch) 0–F channel = input CH minus 1, two 7-bit bytes data = value, five 7-bit bytes

Element 01 14 index 00 00 = INPUT PATCH (data 0–122: 0=NONE, 1–64=DANTE, 65–72=OMNI, 73–74=PB OUT, 75–122=SLOT1–3)

Element 01 1E index 00 01 = CHANNEL COLOR (data 0–8, CL Editor picker order)

Colors: 0 Blue · 1 Orange · 2 Yellow · 3 Purple · 4 Cyan · 5 Magenta · 6 Red · 7 Green · 8 Off

Blue/Orange are field-confirmed; verify the middle values once on the desk before show-critical use.

WORKED EXAMPLE

Repatch input CH 12 to DANTE1 (patch 1), device 1:

Full SysEx: F0 43 10 3E 19 01 01 14 00 00 00 0B 00 00 00 01 F7

QLab field: 43 10 3E 19 01 01 14 00 00 00 0B 00 00 00 01

(Verified byte-for-byte against the original "CL5 NRPN patch generator v2.xls".)