

SAFE WORK METHOD STATEMENT

Persons responsible for supervising, inspecting work, work methods, plant & equipment and tools	Supervisor/Foreman	Date:	
High Risk Construction Work:	GENERATOR – PETROL - SAFE OPERATION	Project:	
SWMS prepared by Patrick Monaghan - Paneltec Group - Operations Manager and in consultation with management and workers – 2025. SWMS Review Date: August 2026 unless required earlier		Location:	
Signature: _____			
Approval to use this SWMS: "I certify that the attached SWMS has been reviewed by me, is endorsed for compliance with WorkSafe guidelines and is approved for use"			
<u>John Guy</u> Name	<u>Director - Paneltec Pty Ltd</u> Position	<u>0408 449 023</u> 	<u>31/08/2025 – V12.0</u> Date
		 Signature	

RISK MATRIX

Level	Description of Consequence or Impact	Consequence	Likelihood / Probability		
			L <i>Likely</i>	M <i>Moderate</i>	U <i>Unlikely</i>
H (1) <i>(High level of harm)</i>	Potential death, permanent disability or major structural failure/damage. Off-site environmental discharge/release not contained and significant long-term environmental harm.	H (1) <i>(High)</i>	1	1	2
M (2) <i>(Medium level of harm)</i>	Potential temporary disability or minor structural failure/damage. On-site environmental discharge/release contained, minor remediation required, short-term environmental harm.	M (2) <i>(Medium)</i>	1	2	3
L (3) <i>(Low level of harm)</i>	Incident that has the potential to cause persons to require first aid. On-site environmental discharge/release immediately contained, minor level clean up with no short-term environmental harm.	L (3) <i>(Low)</i>	2	3	3
Level	Likelihood / Probability				
Likely	Could happen frequently				
Moderate	Could happen occasionally				
Unlikely	May occur only in exceptional circumstances				

HIERARCHY OF RISK CONTROL

The hierarchy of controls must be applied in the order below for all identified hazards.

Level 1 Eliminate the hazard
Level 2 Substitute the hazard with something safer.
Level 3 Isolate the hazard from people. Reduce the risks through engineering controls.
Level 4 Reduce exposure to the hazard using administrative actions.
Level 5 Use personal protective equipment The control measures that you put in place should be reviewed regularly to make sure they work as planned

ACTIVITY ANALYSIS

Steps in Activity	Potential Hazards	Risk Class	Risk Control Measure	Responsible Person/s	Risk Class After Controls In Place
Training and skill	Un-trained persons could cause injury to themselves and others. Possible property damage.	1	1. All persons on site must carry with them a current 'Construction Induction Card'. 2. All persons working on site must be suitably licensed, trained and competent in the work they are to perform.	Management	2
Personal Protective Clothing & Equipment (PPE)	Personal injury.	1	1. Minimum PPE to be worn on site is: • Hi visibility vests/clothing • Steel toe-capped boots • UV skin protection minimum 15+ UV sunscreen • Head protection as applicable eg sun/hard hat • Long pants and long sleeves	Operator	2
Unloading the generator off delivery vehicle	Struck by mobile plant / vehicle. Strains / back injuries	1	1. Ensure you park the vehicle/trailer out of traffic areas. 2. Unload generator carefully where ever possible away from plant / vehicles. 3. Use team lifting to lift off small generators ensuring good grip and correct lifting posture / technique. 4. Forklift or crane to unload medium size generators where available.	Operators	2
Positioning and powering up generator	Electrocution Strain Inhalation of fumes (carbon dioxide) Slips and trips Noise	1	1. Always make a pre-operational inspection (refer to owner's manual) before you start the engine. You may prevent an accident or equipment damage. 2. Report any defect / damage to supervisor and apply 'Danger do not use' tag until repaired. 3. Ensure generator is set up in well ventilated area. 4. Ensure generator is not set up in access ways. 5. Position generator at a suitable distance away from the work face to minimise noise levels. 6. Place the generator at least 1m away from buildings or other equipment during operation. 7. Operate the generator on a level surface. Electric shock can result if this instruction is not followed.	Operator	2

Steps in Activity	Potential Hazards	Risk Class	Risk Control Measure	Responsible Person/s	Risk Class After Controls In Place
			8. If the generator is tilted, fuel spillage may result. 9. Ensure the RCD on the generator has current electrical test tag. 10. Ensure relevant earth and bonding connections are in accordance with the manufacturer's or supplier's information. The generator frame must be bonded to an earth stake if there is no internal link between the neutral output and the metallic frame of the generator. 11. If the generator is to supply a fixed installation, ensure a Certificate of Electrical Safety is obtained from the electrical contractor. 12. Ensure all safety guards are fitted. 13. Do not over exert when attempting to pull start the generator.		
Operating the Generator	Person injury Equipment damage Electrocution Strain Inhalation of fumes (carbon dioxide) Slips and trips Noise Burns	1	1. Read and understand the Owner's Manual before operating the generator. 2. Exhaust gas contains poisonous carbon monoxide. Never run the generator in an enclosed area. Be sure to provide adequate ventilation. 3. The muffler becomes very hot during operation and remains hot for a while after stopping the engine. Be careful not to touch the muffler while it is hot. 4. Let the engine cool down before storing the generator indoors. 5. The engine exhaust system will be heated during operation and remains hot immediately after stopping the engine. 6. To prevent scalding, pay attention to the warning marks attached to the generator. 7. Know how to stop the generator quickly and understand operation of all the controls. 8. Never permit anyone to operate the generator without proper instructions.	Operator	1

Steps in Activity	Potential Hazards	Risk Class	Risk Control Measure	Responsible Person/s	Risk Class After Controls In Place
			9. Keep children and pets away from the generator when it is in operation. 10. Keep away from rotating parts while the generator is running- all rotating parts shall be guarded. 11. The generator is a potential source of electrical shock when misused. Do not operate with wet hands. 12. Do not operate the generator in rain or snow and do not let it get wet. 13. Read and adhere to all safety labels and directions.		
Refueling the generator	Fire explosion Slips, trips and falls Spills Contact with chemical Inhaled petrol vapour	1	1. Equipment is to be turned off and shut down and allow to cool down. 2. Petrol is extremely flammable and explosive under certain conditions. 3. Refuel in a well ventilated area with the engine stopped. 4. Keep away from cigarette, smoke, and sparks when refueling the generator. 5. Do not used mobile phones in refueling area. 6. Avoid sources of ignition, heat, sparks. 7. Ensure fully charged carbon dioxide, dry chemical or foam extinguisher is in close proximity when refueling. 8. Ensure funnel or nozzle attachment is used when refueling. 9. Avoid contact with eyes, eye protection to be worn. 10. Over spills to be immediately cleaned up. 11. Remove any contaminated clothing and wash prior to re-use. 12. Do not intentionally inhale vapours.	Operator	2
Generator shut down and secure for next use	Fire Strain / back injuries	1	1. Shut down generator allowing for enough time for it to cool down. 2. Use team lifting or forklift/crane to reposition generator.	Operator	2

ENVIRONMENTAL RISK ASSESSMENT & CONTROL MEASURES THAT MAY BE REQUIRED ON SITE DEPENDING ON THE ACTIVITY					
Work Activity Risk	Hazard	Risk Class	Risk Control Measure	Responsible Person/s	Risk Class after Controls in place
Emergencies	Accident/ Incident Fire Spill	1	1. Personnel have been advised at toolbox meeting and are prepared in the event of an incident occurring. 2. Emergency numbers available on site. 3. Fire Extinguishers/First Aid Kits/Spill Kits on site.	Supervisor All	2
Air Quality	Exhaust Fumes Dust	2	1. Control exhaust emissions eg. Regular maintenance, replace old machinery, fit appropriate emission control measures. 2. Dampen milled surface with water cart. 3. Use water cart where required.	Supervisor All	3
Community Relations	Inconvenience as a result of works/traffic management	2	1. Identify from the list of potentially impacted parties who may be impacted by the work being undertaken. 2. Letter drops could be considered (unless specifically required) to notify residents/businesses etc. about works to be undertaken and if it has an effect on them.	Supervisor All	3
Flora & Fauna	Some works may require the removal of vegetation. Native fauna may be at risk from excavation works	2	1. Assess work area for significant vegetation: size of trees, faunal habitat - define work and exclusion areas using fencing and signage. 2. Machinery is to be thoroughly washed down prior to leaving site where noxious weeds are present.	Supervisor All	3
Heritage & Archaeology	Unmonitored excavation at significant sites can lead to loss or destruction of valuable artifacts/relics, and disturbance of historical sites. including cultural heritage and/or archaeological significance	1	1. Undertake a survey of the site to identify any areas of significance. The client's representative may undertake this. Government bodies may be able to assist. 2. Develop a project specific procedure based on the findings and recommendations. 3. Installation of exclusion fencing and signage if required.	Supervisor All	2
Noise Pollution, Community Relations & Vibration	Sensitivity to noise - to public & fauna	1	1. Work undertaken during "normal" hours where possible. 2. Affected residents notified in person or in writing. 3. Plant and equipment regularly serviced & fitted with efficient mufflers. 4. Magnitude of vibration reduced by using smaller plant etc.	Supervisor All	2

Work Activity Risk	Hazard	Risk Class	Risk Control Measure	Responsible Person/s	Risk Class after Controls in place
Soil Management & Water Quality	Soil needs to be managed to ensure that; there are no off-site impacts. Damage to stockpile areas (not prepared properly). Mud deposited onto roadways.	2	1. Wash down machinery in only nominated areas. 2. Not within 20 metres of water courses. 3. Use only approved and nominated stockpile areas. 4. Build bund wall out of material available on site. 5. Drivers to check vehicle tyres/bodies for build up of mud when leaving stockpile sites and remove if necessary.	Supervisor All	3
Fuels and Chemicals	Contamination of waterways due to spillages of oil, degreasers, diesel, etc.	1	1. Store fuel and chemicals in accordance with relevant standards/guidelines. 2. Minimise storage on site and locate storage facilities away from drains and waterways. 3. All containers clearly labelled and Safety Data Sheets are available on site. 4. All drums stored securely and in a bunded area. 5. Spill kits or alternative spill containment materials available on site. 6. Regular maintenance of plant hoses. 7. Use correct refuelling equipment.	Supervisor All	2
Visual Impact Litter and Amenities Waste Management	Litter such as paper, plastic, and other refuse as well as being a possible safety risk may be carried off-site or washed into waterways resulting in pollution and danger to native fauna. Litter is also visually obtrusive. Production generated lighting, litter, mud, dirt and dust may also impact residents.	2	1. Use site induction to communicate the requirement for a tidy site. Also stress consideration for local residents. 2. If as a result of our works, dirt, mud, or litter affects a resident, then we will rectify this problem immediately. 3. Inspect the site frequently and insist on tidiness. Ensure public roads are free of dirt/mud from the work site. 4. Broken-out paved surfaces shall be repaired as soon as possible. 5. Remove all rubbish from site each day. 6. Waste products will be recycled where possible.	Supervisor All	3

Personal Protective Equipment

All site personnel must wear the required PPE specified in the controls above, such as:

Safety Hi-vis Vests/Shirts	Safety Boots	Sunscreen	Broad Brimmed Sun Hat	Sunglasses	Gloves specific to the task	White reflective overalls/night
Hard Hat where required	Safety Glasses	Hearing protection where required	Long clothing	Dust masks	Respiratory equipment if required	

Workers may require Task Specific Training depending on activity each worker will be required to fulfill.

All workers shall hold a current Construction Induction Card						
- If required Client Site Induction - Activity Induction (SWMS & SWP's)	Vehicle Licences (Car or Truck depending on class of vehicle or mobile plant driven)	Plant Operators licences or competency assessments where required	Competencies for Work Zone Traffic Management			
First Aid certificate training	Manual Handling training	Fire Extinguisher training	Fatigue Management Training			

A Site Specific Induction & Toolbox Meeting will be held each day prior to the start of each job.

Legislation & Codes of Practice (refer to company Legislation register for applicable Australian Standards applicable to works)

Work Health & Safety Act 2012 and Work Health & Safety Regulations 2022

Codes of Practice

Confined Spaces - 2020	Hazardous Manual Tasks - 2020	Managing Noise & Preventing Hearing Loss at Work-2020	Managing Risks of Plant in the Workplace - 2018
Construction Work - 2020	How to Manage WH&S Risks - 2018	Managing Risk of Falls at Workplaces - 2020	Managing Electrical Risks in the Workplace -2019
Excavation Work - 2020	First Aid in the Workplace - 2018	Managing Work Environment & Facilities - 2020	WHS Consultation Co-operation & Co-ordination - 2018
Welding Processes - 2021	How to Safely Remove Asbestos - 2020	Managing Risk of Hazardous Chemicals - 2018	Safe Design of Structures - 2018

Plant & Equipment for this activity

- All plant is inspected prior to sending out to site
- Daily maintenance & service checks.
- Daily pre-start checks are conducted on all plant and trucks by the operators and daily checklist filled out.
- Regular servicing at 250hr intervals or as per manufactures specifications. Service History available on request to the office.

List of plant for this Activity

Engineering details/certificates/regulatory approvals/permits/electrical isolation (if applicable):

Implementation, Monitoring and Review of SWMS

The Supervisor on site has the responsibility to:

- Brief each team member on this SWMS before commencing work.
- Ensure control measures have been implemented prior to the start of works.
- Observe work being carried out.
- If controls documented in SWMS are not adequate, stop the work, review the SWMS, adjust as required and re-brief the team.
- Ensure team knows that work is to immediately stop if the SWMS is not being followed.
- Retain this SWMS on site for the duration of the high-risk construction work.
- All persons involved in these particular tasks on site must sign this document as read and understood.

SWMS attendance sheet — I have been given the opportunity to provide input into the development and review of this SWMS

Name (please print clearly)	Signature	Company	Date

Daily pre-start meetings will be held to ensure all workers are informed of control measures and additional safety hazards & controls to be noted on toolbox form.