



# 정보통신 수학 및 실습 Homework



---

학번 : 2016110056

학과 : 불교학부

이름 : 박승원

날짜 : 2017년 3월 16일

---

## Chapter 3 Homework

### 1. Simplify the following equations.

- a)  $\cos(100\pi t) \cos(500\pi t)$
- b)  $4\sin(200\pi t)\cos(300\pi t)$

### 2. Find the frequency of the following signals.

- a)  $\sin(t)$
- b)  $\cos(600\pi t)$

### 3. Evaluate the following functions.

- a)  $\sin(\pi/4)$
- b)  $\tan(\pi)$

### 4. Let the information signal $m(t) = 4\sin(200\pi t)$ and the carrier signal $c(t) = \cos(2 \times 10^6\pi t)$ .

**Simplify the transmission signal  $x(t) = m(t)c(t)$  and find its frequencies.  
Plot the magnitude of each frequency in the frequency domain.**