

Appendix **B**

MATERIAL PROPERTIES

For selected engineering materials. Many other alloys are available.

The following tables contain approximate values for strengths and other specifications of a variety of engineering materials compiled from various sources. In some cases the data are minimum recommended values and in other cases are data from a single test specimen. These data are suitable for use in the engineering exercises contained in this text but should not be considered as statistically valid representations of specifications for any particular alloy or material. The designer should consult the materials' manufacturers for more accurate and up-to-date strength information on materials used in engineering applications or conduct independent tests of the selected materials to determine their ultimate suitability to any application.

Table No.	Description
B-1	Physical Properties of Some Engineering Materials
B-2	Mechanical Properties for Some Wrought-Aluminum Alloys
B-3	Mechanical Properties for Some Carbon Steels
B-4	Mechanical Properties for Some Cast-Iron Alloys
B-5	Mechanical Properties for Some Engineering Plastics

Table B-1 Physical Properties of Some Engineering Materials

Data from Various Sources. * These Properties are Essentially Similar for All Alloys of the Particular Material

Material	Modulus of Elasticity <i>E</i>		Modulus of Rigidity <i>G</i>		Poisson's Ratio ν	Weight Density γ	Mass Density ρ	Specific Gravity
	Mpsi	GPa	Mpsi	GPa				
Aluminum Alloys	10.4	71.7	3.9	26.8	0.34	0.10	2.8	2.8
Beryllium Copper	18.5	127.6	7.2	49.4	0.29	0.30	8.3	8.3
Brass, Bronze	16.0	110.3	6.0	41.5	0.33	0.31	8.6	8.6
Copper	17.5	120.7	6.5	44.7	0.35	0.32	8.9	8.9
Iron, Cast, Gray	15.0	103.4	5.9	40.4	0.28	0.26	7.2	7.2
Iron, Cast, Ductile	24.5	168.9	9.4	65.0	0.30	0.25	6.9	6.9
Iron, Cast, Malleable	25.0	172.4	9.6	66.3	0.30	0.26	7.3	7.3
Magnesium Alloys	6.5	44.8	2.4	16.8	0.33	0.07	1.8	1.8
Nickel Alloys	30.0	206.8	11.5	79.6	0.30	0.30	8.3	8.3
Steel, Carbon	30.0	206.8	11.7	80.8	0.28	0.28	7.8	7.8
Steel, Alloys	30.0	206.8	11.7	80.8	0.28	0.28	7.8	7.8
Steel, Stainless	27.5	189.6	10.7	74.1	0.28	0.28	7.8	7.8
Titanium Alloys	16.5	113.8	6.2	42.4	0.34	0.16	4.4	4.4
Zinc Alloys	12.0	82.7	4.5	31.1	0.33	0.24	6.6	6.6

* Properties of Some Metals and Alloys, International Nickel Co., Inc., NY; Metals Handbook, American Society for Metals, Materials Park, OH.

Table B-2 Mechanical Properties for Some Wrought-Aluminum Alloys

Data from Various Sources. * Approximate Values. Consult Manufacturers for More Accurate Information

Wrought-Aluminum Alloy	Condition	Tensile Yield Strength (2% offset)		Ultimate Tensile Strength		Fatigue Strength at 5E8 cycles		Elongation over 2 in	Brinell Hardness
		kpsi	MPa	kpsi	MPa	kpsi	MPa	%	-HB
1100	Sheet annealed	5	34	13	90			35	23
	Cold rolled	22	152	24	165			5	44
2024	Sheet annealed	11	76	26	179			20	-
	Heat treated	42	290	64	441	20	138	19	-
3003	Sheet annealed	6	41	16	110			30	28
	Cold rolled	27	186	29	200			4	55
5052	Sheet annealed	13	90	28	193			25	47
	Cold rolled	37	255	42	290			7	77
6061	Sheet annealed	8	55	18	124			25	30
	Heat treated	40	276	45	310	14	97	12	95
7075	Bar annealed	15	103	33	228			16	60
	Heat treated	73	503	83	572	14	97	11	150

* Properties of Some Metals and Alloys, International Nickel Co., Inc., NY; Metals Handbook, American Society for Metals, Materials Park, OH.

Table B-3 Mechanical Properties for Some Carbon Steels

Data from Various Sources.* Approximate Values. Consult Manufacturers for More Accurate Information

SAE / AISI Number	Condition	Tensile Yield Strength (2% offset)		Ultimate Tensile Strength		Elongation over 2 in	Brinell Hardness
		kpsi	MPa	kpsi	MPa	%	-HB
1010	Hot rolled	26	179	47	324	28	95
	Cold rolled	44	303	53	365	20	105
1020	Hot rolled	30	207	55	379	25	111
	Cold rolled	57	393	68	469	15	131
1030	Hot rolled	38	259	68	469	20	137
	Normalized @ 1650°F	50	345	75	517	32	149
	Cold rolled	64	441	76	524	12	149
	Q&T @ 1000°F	75	517	97	669	28	255
	Q&T @ 800°F	84	579	106	731	23	302
	Q&T @ 400°F	94	648	123	848	17	495
1035	Hot rolled	40	276	72	496	18	143
	Cold rolled	67	462	80	552	12	163
1040	Hot rolled	42	290	76	524	18	149
	Normalized @ 1650°F	54	372	86	593	28	170
	Cold rolled	71	490	85	586	12	170
	Q&T @ 1200°F	63	434	92	634	29	192
	Q&T @ 800°F	80	552	110	758	21	241
	Q&T @ 400°F	86	593	113	779	19	262
1045	Hot rolled	45	310	82	565	16	163
	Cold rolled	77	531	91	627	12	179
1050	Hot rolled	50	345	90	621	15	179
	Normalized @ 1650°F	62	427	108	745	20	217
	Cold rolled	84	579	100	689	10	197
	Q&T @ 1200°F	78	538	104	717	28	235
	Q&T @ 800°F	115	793	158	1 089	13	444
	Q&T @ 400°F	117	807	163	1 124	9	514
1060	Hot rolled	54	372	98	676	12	200
	Normalized @ 1650°F	61	421	112	772	18	229
	Q&T @ 1200°F	76	524	116	800	23	229
	Q&T @ 1000°F	97	669	140	965	17	277
	Q&T @ 800°F	111	765	156	1 076	14	311
1095	Hot rolled	66	455	120	827	10	248
	Normalized @ 1650°F	72	496	147	1 014	9	13
	Q&T @ 1200°F	80	552	130	896	21	269
	Q&T @ 800°F	112	772	176	1 213	12	363
	Q&T @ 600°F	118	814	183	1 262	10	375

* SAE Handbook, Society of Automotive Engineers, Warrendale PA; Metals Handbook, American Society for Metals, Materials Park, OH.

Table B-4 Mechanical Properties of Some Cast-Iron Alloys

Data from Various Sources. * Approximate Values. Consult Manufacturers for More Accurate Information

Cast-Iron Alloy	Condition	Tensile Yield Strength (2% offset)		Ultimate Tensile Strength		Compressive Strength		Brinell Hardness
		kpsi	MPa	kpsi	MPa	kpsi	MPa	HB
Gray Cast Iron—Class 20	As cast	—	—	22	152	83	572	156
Gray Cast Iron—Class 30	As cast	—	—	32	221	109	752	210
Gray Cast Iron—Class 40	As cast	—	—	42	290	140	965	235
Gray Cast Iron—Class 50	As cast	—	—	52	359	164	1 131	262
Gray Cast Iron—Class 60	As cast	—	—	62	427	187	1 289	302
Ductile Iron 60-40-18	Annealed	47	324	65	448	52	359	160
Ductile Iron 65-45-12	Annealed	48	331	67	462	53	365	174
Ductile Iron 80-55-06	Annealed	53	365	82	565	56	386	228
Ductile Iron 120-90-02	Q & T	120	827	140	965	134	924	325

* Properties of Some Metals and Alloys, International Nickel Co., Inc., NY; Metals Handbook, American Society for Metals, Materials Park, OH.

Table B-5 Properties of Some Engineering Plastics

Data from Various Sources. * Approximate Values. Consult Manufacturers for More Accurate Information

Material	Approximate Modulus of Elasticity E †		Ultimate Tensile Strength		Ultimate Compressive Strength		Elongation over 2 in	Max Temp	Specific Gravity
	Mpsi	GPa	kpsi	MPa	kpsi	MPa	%	°F	
ABS	0.3	2.1	6.0	41.4	10.0	68.9	5-25	160-200	1.05
20-40% glass filled	0.6	4.1	10.0	68.9	12.0	82.7	3	200-230	1.30
Acetal	0.5	3.4	8.8	60.7	18.0	124.1	60	220	1.41
20-30% glass filled	1.0	6.9	10.0	68.9	18.0	124.1	7	185-220	1.56
Acrylic	0.4	2.8	10.0	68.9	15.0	103.4	5	140-190	1.18
Fluoroplastic (PTFE)	0.2	1.4	5.0	34.5	6.0	41.4	100	350-330	2.10
Nylon 6/6	0.2	1.4	10.0	68.9	10.0	68.9	60	180-300	1.14
Nylon 11	0.2	1.3	8.0	55.2	8.0	55.2	300	180-300	1.04
20-30% glass filled	0.4	2.5	12.8	88.3	12.8	88.3	4	250-340	1.26
Polycarbonate	0.4	2.4	9.0	62.1	12.0	82.7	100	250	1.20
10-40% glass filled	1.0	6.9	17.0	117.2	17.0	117.2	2	275	1.35
HMW Polyethylene	0.1	0.7	2.5	17.2	—	—	525	—	0.94
Polyphenylene Oxide	0.4	2.4	9.6	66.2	16.4	113.1	20	212	1.06
20-30% glass filled	1.1	7.8	15.5	106.9	17.5	120.7	5	260	1.23
Polypropylene	0.2	1.4	5.0	34.5	7.0	48.3	500	250-320	0.90
20-30% glass filled	0.7	4.8	7.5	51.7	6.2	42.7	2	300-320	1.10
Impact Polystyrene	0.3	2.1	4.0	27.6	6.0	41.4	2-80	140-175	1.07
20-30% glass filled	0.1	0.7	12.0	82.7	16.0	110.3	1	180-200	1.25
Polysulfone	0.4	2.5	10.2	70.3	13.9	95.8	50	300-345	1.24

* Modern Plastics Encyclopedia, McGraw-Hill, New York; Machine Design Materials Reference Issue, Penton Publishing, Cleveland, OH.

† Most plastics do not obey Hooke's Law. These apparent moduli of elasticity vary with time and temperature.

Appendix C

GEOMETRIC PROPERTIES

DIAGRAMS AND FORMULAS TO CALCULATE THE FOLLOWING PARAMETERS FOR SEVERAL COMMON GEOMETRIC SOLIDS

V = volume

m = mass

C_g = location of center of mass

I_x = second moment of mass about x axis = $\int (y^2 + z^2) dm$


I_y = second moment of mass about y axis = $\int (x^2 + z^2) dm$

I_z = second moment of mass about z axis = $\int (x^2 + y^2) dm$

k_x = radius of gyration about x axis

k_y = radius of gyration about y axis

k_z = radius of gyration about z axis



(a) Rectangular prism

$$V = abc$$

$$m = V \cdot \text{mass density}$$

$$x_{Cg} @ \frac{c}{2}$$

$$y_{Cg} @ \frac{b}{2}$$

$$z_{Cg} @ \frac{a}{2}$$

$$I_x = \frac{m(a^2 + b^2)}{12}$$


$$I_y = \frac{m(a^2 + c^2)}{12}$$

$$I_z = \frac{m(b^2 + c^2)}{12}$$

$$k_x = \sqrt{\frac{I_x}{m}}$$

$$k_y = \sqrt{\frac{I_y}{m}}$$

$$k_z = \sqrt{\frac{I_z}{m}}$$



(b) Cylinder

$$V = \pi r^2 l$$

$$m = V \cdot \text{mass density}$$

$$x_{Cg} @ \frac{l}{2}$$

$$y_{Cg} \text{ on axis}$$


$$z_{Cg} \text{ on axis}$$

$$I_x = \frac{mr^2}{2}$$

$$I_y = I_z = \frac{m(3r^2 + l^2)}{12}$$

$$k_x = \sqrt{\frac{I_x}{m}}$$

$$k_y = k_z = \sqrt{\frac{I_y}{m}}$$



(c) Hollow cylinder

$$V = \pi(b^2 - a^2)l$$

$$m = V \cdot \text{mass density}$$

$$x_{Cg} @ \frac{l}{2}$$

$$y_{Cg} \text{ on axis}$$


$$z_{Cg} \text{ on axis}$$

$$I_x = \frac{m(a^2 + b^2)}{2}$$

$$I_y = I_z = \frac{m(3a^2 + 3b^2 + l^2)}{12}$$

$$k_x = \sqrt{\frac{I_x}{m}}$$

$$k_y = k_z = \sqrt{\frac{I_y}{m}}$$



(d) Right circular cone

$$V = \pi \frac{r^2 h}{3}$$

$$m = V \cdot \text{mass density}$$

$$x_{Cg} @ \frac{3h}{4}$$

$$y_{Cg} \text{ on axis}$$


$$z_{Cg} \text{ on axis}$$

$$I_x = \frac{3}{10} mr^2$$

$$I_y = I_z = \frac{m(12r^2 + 3h^2)}{80}$$

$$k_x = \sqrt{\frac{I_x}{m}}$$

$$k_y = k_z = \sqrt{\frac{I_y}{m}}$$



(e) Sphere

$$V = \frac{4}{3} \pi r^3$$

$$m = V \cdot \text{mass density}$$

$$x_{Cg} \text{ at center}$$

$$y_{Cg} \text{ at center}$$

$$z_{Cg} \text{ at center}$$

$$I_x = I_y = I_z = \frac{2}{5} mr^2$$


$$k_x = k_y = k_z = \sqrt{\frac{I_y}{m}}$$

Appendix D

SPRING DATA

The following catalog pages of helical compression and extension spring data provided courtesy of *Hardware Products Co., Chelsea, Massachusetts*.

EXTENSION SPRINGS



ORDER BY:
SE LENGTH x O.D. x WIRE DIA.

SPECIFY HOOKS OR LOOPS

The figures given for "Maximum Extension" and "lbs. per inch" are for a spring 1" long. For other lengths multiply the "Maximum Extension" and divide the "lbs. per inch" by the length in inches. The "Maximum Load" and "Initial Tension" remain constant for any length.

Example: A spring 1/2" diam. .062" wire and 4" long will have a safe maximum extension of 3.2" and it will require 4 lbs. to deflect it 1 in. The spring will hold approximately 3.3 lbs. before it starts to extend, and will hold a maximum of 16.1 lbs. without permanent stretch. If 8.5 lbs. is hung on the spring it will deflect 1.3". 8.5 lbs. minus 3.3 lbs. divided by 4 lbs. per inch equals 1.3".

FOR QUICK DELIVERY
Call 617-884-9410

NOTE: Stock springs can be ordered in stainless steel or plated. Prices quoted upon request.

Outside dia.	Wire dia.	Catalog No.	Price code	Safe maximum load in pounds	Safe maximum extension in in.	Approx. initial tension in pounds	Pound per inch extension	Stress at max. load (000 omitted)	Weight per foot (lbs.)
1/8	.012	01	EHE	.6	1.9	.07	.27	100	.012
	.016	02	EHD	1.3	.9	.2	1.2	93	.015
	.023	03	EHD	4.2	.35	.9	9.0	90	.02
5/32	.012	04	EHE	.47	3.5	.01	.12	100	.015
	.016	05	EHD	1.1	1.7	.15	.55	93	.019
	.023	06	EHD	3.2	.7	.5	3.9	90	.027
3/16	.016	07	EHD	.87	2.5	1	3	93	.024
	.023	08	EHD	2.6	1.0	.4	7.2	90	.032
	.031	09	EHD	6.5	.45	1.5	10.7	88	.04
7/32	.016	10	EHD	.75	4.0	.01	.18	93	.028
	.023	11	EHD	2.3	1.6	.32	1.2	90	.039
	.031	12	EHD	5.5	.7	1.0	6.5	88	.048
1/4	.023	13	EHD	1.8	1.9	.26	.8	90	.044
	.031	14	EHD	4.7	1.0	.75	3.8	88	.055
	.047	15	EHE	16.0	.3	3.5	40.0	83	.082
5/16	.023	16	EHE	1.5	3.5	.16	.38	90	.058
	.031	17	EHE	3.6	1.6	.55	1.9	88	.072
	.047	18	EHE	12.5	.9	2.2	10.8	83	.108
3/8	.031	19	EHE	2.9	2.5	.37	1.0	88	.084
	.047	20	EHE	10.5	.9	1.7	9.5	83	.13
	.062	21	EHF	23.0	.39	5.3	45.0	79	.16
7/16	.031	22	EHF	2.5	3.5	.26	.63	88	.105
	.047	23	EHF	8.5	1.2	1.4	5.7	83	.163
	.062	24	EHF	20.0	.6	4.3	26.0	79	.2
1/2	.047	25	EHF	7.3	1.6	1.1	3.7	83	.18
	.062	26	EHF	17.0	.8	3.3	16.0	79	.23
	.078	27	EHG	34.0	.45	8.0	57.0	77	.28
5/8	.094	28	EHJ	57.0	.25	16.0	160.0	74	.32
	.047	29	EHG	6.0	3.0	.7	1.7	83	.24
	.062	30	EHG	13.3	1.4	2.1	7.6	79	.3
3/4	.078	31	EHG	27.0	.9	5.7	23.0	77	.37
	.094	32	EHJ	45.0	.4	11.0	73.0	74	.44
	.125	33	EHG	10.5	2.2	1.5	4.1	79	.36
7/8	.078	34	EHJ	22.0	1.3	3.5	14.0	77	.46
	.094	35	EHJ	36.0	.7	8.0	38.0	74	.51
	.125	36	EHK	85.0	.3	22.0	180.0	69	.64
1	.062	37	EHK	9.2	3.3	1.1	2.4	79	.4
	.078	38	EHK	18.0	1.7	2.6	8.7	77	.59
	.094	39	EHL	31.0	1.0	6.0	25.0	74	.64
1 1/4	.125	40	EHM	72.0	.5	17.0	107.0	69	.8
	.078	41	EHL	16.0	2.5	2.0	5.5	77	.67
	.094	42	EHL	26.0	1.5	4.5	13.7	74	.70
1 1/2	.125	43	EHN	65.0	.75	14.0	68.0	69	.90
	.187	44	EHW	200.0	.23	60.0	600.0	63	1.4
	.094	45	EHM	71.0	2.6	2.8	6.8	74	.94
2	.125	46	EHO	47.0	1.2	9.0	31.0	69	1.3
	.187	47	EHZ	148.0	.3	40.0	290.0	63	1.8
	.250	48	EHS	39.0	1.9	6.0	17.0	69	1.4
2 1/2	.187	49	EHAA	122.0	.6	33.0	150.0	63	2.2
	.250	50	EHAC	290.0	.27	90.0	720.0	60	2.6
	.187	51	EHAD	90.0	1.3	20.0	54.0	63	3.1
	.250	52	EHAG	210.0	.6	55.0	260.0	60	3.7

Carried in stock in 3-foot lengths - cut to length and looped to order.

Hardware Products Company, Inc.

191 WILLIAMS STREET • CHELSEA, MA 02150

Appendix E

ATLAS OF GEARED FIVEBAR LINKAGE COUPLER CURVES

C. Zhang, R. L. Norton, T. Hammond

The following pages of coupler curve data are excerpted from the complete work. See Sections 3.6 (p. 103), 4.8 (p. 164), 6.8 (p. 278), and 7.4 (p.319) for more information on the geared fivebar linkage. Use program FIVEBAR to investigate other linkage geometries.

Alpha = Coupler Link 3 / Link 2

Beta = Ground Link 1 / Link 2


Lambda = Gear Ratio = Gear 5 / Gear 2.*


Phase angle is noted on each plot of a coupler curve.


The dots along curves are at every 10 degrees of Link 2's rotation.

Linkage is symmetrical: Link 2 = Link 5 and Link 3 = Link 4


* Note that this lambda is the **inverse** of the λ which is defined in Sections 4.8, 6.8, and 7.4. See also Figures P4-4 (p. 139), P6-4 (p. 229), and P7-4 (p. 263). For example, a gear ratio λ of 2 in this atlas corresponds to a λ of 0.5 in the text and in program FIVEBAR. (The difference merely corresponds to a mirroring of the linkage from left to right.)








PARAMETERS
ALPHA = 3.2
BETA = 2.5
LAMBDA = 2.8





ANSWERS TO SELECTED PROBLEMS

CHAPTER 2 KINEMATICS FUNDAMENTALS

2-1

- | | | | | | | |
|------|-------------------------------|------|------|------|------|------|
| a. 1 | b. 1 | c. 2 | d. 4 | e. 7 | f. 4 | g. 4 |
| h. 4 | i. 4 | j. 2 | k. 1 | l. 1 | m. 2 | n. 2 |
| o. 4 | p. as many as it has sections | | | q. 3 | | |

- 2-5** a. 6 b. 6 c. 3 d. 3 e. 10 f. 3

2-7


- a. pure rotation
- b. complex planar motion
- c. pure translation
- d. pure translation
- e. pure rotation
- f. complex planar motion
- g. pure translation
- h. pure translation
- i. complex planar motion

- 2-8** a. 1 b. 3 c. 3 d. 3 e. 1


- 2-9** force closed

2-10

- a. structure - $DOF = 0$
- b. mechanism - $DOF = 1$
- c. mechanism - $DOF = 1$
- d. mechanism - $DOF = 3$



(a) One possible solution to Problem 3-3



(b) One possible solution to Problem 3-5

FIGURE S3-1

Solutions to Problems 3-3 and 3-5

2-15 a. Grashof b. non-Grashof c. special-case Grashof



2-21

- | | | |
|------------|-------------------------|------------|
| a. $M = 1$ | b. $M = 1$ | c. $M = 1$ |
| d. $M = 1$ | e. $M = -1$ (a paradox) | f. $M = 1$ |
| g. $M = 1$ | h. $M = 0$ (a paradox) | |

2-24 a. $M = 1$

b. $M = 1$

2-26 $M = 1$

**FIGURE S3-2**

Unique solution to
Problem 3-6

CHAPTER 3

GRAPHICAL LINKAGE SYNTHESIS

3-1

- Path generation
- Motion generation
- Function generation
- Path generation
- Path generation

Note that synthesis problems have many valid solutions. We cannot provide a "right answer" to all of these design problems. Check your solution with a cardboard model and/or by putting it into one of the programs supplied with the text.

3-3 See Figure S3-1.

3-5 See Figure S3-1.

3-6 See Figure S3-2.

3-8 See Figure S3-3.

3-10 The solution using Figure 3-17 (p. 106) is shown in Figure S3-4. (Use program FOURBAR to check your solution.)




FIGURE S3-3

One possible solution to Problem 3-8

- 3-22 The transmission angle ranges from 31.5° to 89.9° .
- 3-23 Grashof crank-rocker. Transmission angle ranges from 58.1° to 89.8° .




FIGURE S3-4

Solution to Problem 3-10. Finding the cognates of the fourbar linkage shown in Figure 3-17 (p. 106)

TABLE S4-1 Solutions for Problems 4-6, 4-7, and 4-13

Row	θ_3 open	θ_4 open	Trans Ang	θ_3 crossed	θ_4 crossed	Trans Ang
<i>a</i>	88.8	117.3	28.4	-115.2	-143.6	28.4
<i>c</i>	-53.1	16.5	69.6	173.3	103.6	69.6
<i>e</i>	7.5	78.2	70.7	-79.0	-149.7	70.7
<i>g</i>	-16.3	7.2	23.5	155.7	132.2	23.5
<i>i</i>	-1.5	103.1	75.4	-113.5	141.8	75.4
<i>k</i>	-13.2	31.9	45.2	-102.1	-147.3	45.2
<i>m</i>	-3.5	35.9	39.4	-96.5	-135.9	39.4

TABLE S4-2 Solutions for Problems 4-9 to 4-10

Row	θ_3 open	Slider open	θ_3 crossed	Slider crossed
<i>a</i>	180.1	5.0	-0.43	-3.0
<i>c</i>	205.9	9.8	-25.90	-4.6
<i>e</i>	175.0	16.4	4.20	-23.5
<i>g</i>	212.7	27.1	-32.70	-14.9

TABLE S4-3 Solutions for Problems 4-11 to 4-12

Row	θ_3 open	θ_4 open	R_B open	θ_3 crossed	θ_4 crossed	R_B crossed
<i>a</i>	232.7	142.7	1.79	-79.0	-169.0	-1.79
<i>c</i>	91.4	46.4	2.72	208.7	163.7	-11.20
<i>e</i>	158.2	128.2	6.17	-36.2	-66.2	-9.63

TABLE S4-4 Solutions for Problems 4-16 to 4-17

Row	θ_3 open	θ_4 open	θ_3 crossed	θ_4 crossed
<i>a</i>	173.6	-177.7	-115.2	-124.0
<i>c</i>	17.6	64.0	-133.7	180.0
<i>e</i>	-164.0	-94.4	111.2	41.6
<i>g</i>	44.2	124.4	-69.1	-149.3
<i>i</i>	37.1	120.2	-67.4	-150.5

- 3-36** Grashof double-rocker. Works from 50° to 158° and from 202° to 310° . Transmission angle ranges from 0° to 89.8° .
- 3-42** Non-Grashof triple-rocker. Toggles at $\pm 55.4^\circ$. Transmission angle ranges from 0° to 88.8° .


CHAPTER 4 POSITION ANALYSIS

- 4-6** and **4-7** See Table S4-1 and the file P07-04row.4br.
- 4-9** and **4-10** See Table S4-2.
- 4-11** and **4-12** See Table S4-3.
- 4-13** See Table S4-1.
- 4-14** Open the file P07-04row.4br[†] in Program FOURBAR to see this solution.*
- 4-15** Open the file P07-04row.4br[†] in Program FOURBAR to see this solution.*
- 4-16** See Table S4-4.
- 4-17** See Table S4-4.
- 4-21** Open the file P04-21.4br in Program FOURBAR to see this solution.*
- 4-23** Open the file P04-23.4br in Program FOURBAR to see this solution.*
- 4-25** Open the file P04-25.4br in Program FOURBAR to see this solution.*
- 4-26** Open the file P04-26.4br in Program FOURBAR to see this solution.*
- 4-29** Open the file P04-29.4br in Program FOURBAR to see this solution.*
- 4-30** Open the file P04-30.4br in Program FOURBAR to see this solution.*


CHAPTER 5 ANALYTICAL LINKAGE SYNTHESIS

- 5-8** Given: $\alpha_2 = -62.5^\circ$, $P_{21} = 2.47$, $\delta_2 = 120^\circ$
 For left dyad: Assume: $z = 1.075$, $\phi = 204^\circ$ $\beta_2 = -27^\circ$
 Calculate: $W = 3.67$ @ -113.5°
- For right dyad: Assume: $s = 1.24$, $\psi = 74^\circ$ $\gamma_2 = -40^\circ$
 Calculate: $U = 5.46$ @ -125.6°
- 5-11** See Figure S5-1 for the solution. The link lengths are:
 Link 1 = 4.35, Link 2 = 3.39, Link 3 = 1.94, Link 4 = 3.87
- 5-15** See Figure S5-2 for the solution. The link lengths are:
 Link 1 = 3.95, Link 2 = 1.68, Link 3 = 3.05, Link 4 = 0.89
- 5-19** See Figure S5-3 for the solution. The link lengths are:
 Link 1 = 2, Link 2 = 2.5, Link 3 = 1, Link 4 = 2.5


* These files can be found in the PROBLEM SOLUTIONS folder on the CD-ROM included with this text.

**FIGURE S5-1**

Solution to Problem 5-11. Open the file P05-11 in program FOURBAR for more information

**FIGURE S5-2**

Solution to Problem 5-15. Open the file P05-15 in program FOURBAR for more information.

**FIGURE S5-3**

Solution to Problem 5-19. Open the file P05-19 in program FOURBAR for more information.

5-26 Given: $\alpha_2 = -45^\circ$, $P_{21} = 184.78 \text{ mm}$, $\delta_2 = -5.28^\circ$
 $\alpha_3 = -90^\circ$, $P_{31} = 277.35 \text{ mm}$, $\delta_3 = -40.47^\circ$
 $O_{2x} = 86 \text{ mm}$ $O_{2y} = -132 \text{ mm}$
 $O_{4x} = 104 \text{ mm}$ $O_{4y} = -155 \text{ mm}$

For left dyad: Calculate: $\beta_2 = -85.24^\circ$ $\beta_3 = -164.47^\circ$

Calculate: $W = 110.88 \text{ mm}$ $\theta = 124.24^\circ$

Calculate: $Z = 46.74 \text{ mm}$ $\phi = 120.34^\circ$

For right dyad: Calculate: $\gamma_2 = -75.25^\circ$ $\gamma_3 = -159.53^\circ$

Calculate: $U = 120.70 \text{ mm}$ $\sigma = 104.35^\circ$

Calculate: $S = 83.29 \text{ mm}$ $\psi = 152.80^\circ$

CHAPTER 6 VELOCITY ANALYSIS

- 6-4 and 6-5 See Table S6-1 and the file P07-04row.4br.
 6-6 and 6-7 See Table S6-2.
 6-8 and 6-9 See Table S6-3.
 6-10 and 6-11 See Table S6-4.
 6-47 Open the file P06-47.4br in Program FOURBAR to see this solution.*
 6-48 Open the file P06-48.4br in Program FOURBAR to see this solution.*
 6-49 Open the file P06-49.4br in Program FOURBAR to see this solution.*
 6-51 Open the file P06-51.4br in Program FOURBAR to see this solution.*
 6-62 Open the file P06-62.4br in Program FOURBAR to see this solution.*

CHAPTER 7 ACCELERATION ANALYSIS

- 7-3 and 7-4 See Table S7-1 and the file P07-04row.4br.
 7-5 and 7-6 See Table S7-2.
 7-7 and 7-8 See Table S7-3.
 7-9 See Table S7-4.
 7-39 Open the file P07-39.4br in Program FOURBAR to see this solution.*
 7-40 Open the file P07-40.4br in Program FOURBAR to see this solution.*
 7-41 Open the file P07-41.4br in Program FOURBAR to see this solution.*
 7-42 Open the file P07-42.4br in Program FOURBAR to see this solution.*
 7-44 Open the file P07-44.4br in Program FOURBAR to see this solution.*
 7-56 Tipover at 19.0 to 20.3 mph; load slides at 16.2 to 19.5 mph.

CHAPTER 8 CAM DESIGN

Most of the problems in this cam chapter are design problems with more than one correct solution. Use program DYNACAM to check your solution obtained with *Mathcad* or *TKSolver* and also to explore various solutions and compare them to find the best one for the constraints given in each problem.

- 8-1 See Figure S8-1.

CHAPTER 9 GEAR TRAINS

- 9-1 Pitch diameter = 5.5, circular pitch = 0.785, addendum = 0.25, dedendum = 0.313, tooth thickness = 0.393, and clearance = 0.063.
 9-5 a. $p_d = 4$, b. $p_d = 2.67$

* These files can be found in the PROBLEM SOLUTIONS folder on the CD-ROM included with this text.

TABLE S6-1 Solutions for Problems 6-4 to 6-5

Row	ω_3 open	ω_4 open	V_P mag	V_P ang	ω_3 crossed	ω_4 crossed	V_P mag	V_P ang
<i>a</i>	-6.0	-4.0	40.8	58.2	-0.66	-2.66	22.0	129.4
<i>c</i>	-12.7	-19.8	273.8	-53.3	-22.7	-15.7	119.1	199.9
<i>e</i>	1.85	-40.8	260.5	-12.1	-23.3	19.3	139.9	42.0
<i>g</i>	76.4	146.8	798.4	92.9	239.0	168.6	1435.3	153.9
<i>i</i>	-25.3	25.6	103.1	-13.4	56.9	6.0	476.5	70.4
<i>k</i>	-56.2	-94.8	436.0	-77.4	-55.6	-16.9	362.7	79.3
<i>m</i>	18.3	83.0	680.8	149.2	7.73	-57.0	571.3	133.5

TABLE S6-2 Solutions for Problems 6-6 to 6-7

Row	V_A mag	V_A ang	ω_3 open	V_B mag open	ω_3 crossed	V_B mag crossed
<i>a</i>	14	135	-2.47	-9.87	2.47	-9.92
<i>c</i>	45	-120	5.42	-41.5	-5.42	-3.54
<i>e</i>	250	135	-8.86	-189.7	8.86	-163.8
<i>g</i>	700	60	-28.8	738.9	28.8	-38.9

TABLE S6-3 Solutions for Problems 6-8 to 6-9

Row	V_A mag	V_A ang	V_{slip} open	V_B mag open	ω_3 crossed	V_{slip} crossed
<i>a</i>	-10.3	-10.3	33.5	3.6	3.6	-33.5
<i>c</i>	23.8	23.8	73.0	33.0	33.0	-73.0
<i>e</i>	-2.7	-2.7	-176.0	-8.2	-8.2	176.0

TABLE S6-4 Solutions for Problems 6-10 to 6-11

Row	ω_3 open	ω_4 open	ω_3 crossed	ω_4 crossed
<i>a</i>	32.6	16.9	-75.2	-59.6
<i>c</i>	10.7	-2.6	-8.2	5.1
<i>e</i>	-158.3	-81.3	-116.8	-193.9
<i>g</i>	-8.9	-40.9	-48.5	-16.5
<i>i</i>	-40.1	47.9	59.6	-28.4

TABLE S7-1 Solutions for Problems 7-3 to 7-4

Row	α_3 open	α_4 open	A_p mag	A_p ang	α_3 crossed	α_4 crossed	A_p mag	A_p ang
<i>a</i>	26.1	53.3	419	240.4	77.9	50.7	298	-11.3
<i>c</i>	-154.4	-71.6	4400	238.9	-65.2	-148.0	3554	100.6
<i>e</i>	331.9	275.6	10 260	264.8	1287.7	1344.1	19 340	-65.5
<i>g</i>	-23 510.	-19 783.	172 688	191.0	-43 709.	-47 436.	273 634	-63.0
<i>i</i>	-344.6	505.3	9492	-81.1	121.9	-728.0	27 871	150.0
<i>k</i>	-2693.	-4054.	56 271	220.2	311.0	1672.1	27 759	-39.1
<i>m</i>	680.8	149.2	35 149	261.5	9266.1	10 303.	63 831	103.9

TABLE S7-2 Solutions for Problems 7-5 to 7-6

Row	A_A mag	A_A ang	α_3 open	A_B mag open	A_B ang open	α_3 cross	A_B mag cross	A_B ang cross
<i>a</i>	140	-135	25	124	180	-25	74	180
<i>c</i>	676	153	-29	709	180	29	490	180
<i>e</i>	12 500	45	-447	6653	0	447	11 095	0
<i>g</i>	70 000	150	-1136	62 688	180	1136	58 429	180

TABLE S7-3 Solutions for Problems 7-7 to 7-8

Row	α_3 open	α_4 open	A_{slip} open	α_3 crossed	α_4 crossed	A_{slip} crossed
<i>a</i>	130.5	130.5	-3111.7	-9.9	-9.9	1125.2
<i>c</i>	-212.9	-212.9	3327.9	-217.8	-217.8	6776.4
<i>e</i>	896.3	896.3	2020.1	595.6	595.6	-1044.4

TABLE S7-4 Solutions for Problem 7-9

Row	α_3 open	α_4 open	α_3 crossed	α_4 crossed
<i>a</i>	3191	2492	-6648	-5949
<i>c</i>	314	228	87	147
<i>e</i>	2171	-6524	7781	5414
<i>g</i>	-22 064	-23 717	-5529	-29 133
<i>i</i>	-5697	-3380	-2593	-7184




FIGURE S8-1

Solutions to Problems 8-1 and 8-2

- 9-6** Assume a minimum no. of teeth = 14, then: pinion = 14t and 1.84-in pitch dia. Gear = 126t and 16.58-in pitch dia.
- 9-7** Assume a minimum no. of teeth = 14, then: pinion = 14t and 2.33-in pitch dia. Gear = 112t and 18.67-in pitch dia. An idler gear of any dia. is needed to get the positive ratio.
- 9-10** Two stages of 8:1 and 8.75:1 give 70:1. Using 14 teeth minimum gives stage 1 = 14t (1.4 dia.) to 112t (11.2 dia.). Stage 2 = 16t (1.6 dia.) to 140t (14 dia.).
- 9-12** The square root of 150 is > 10 so will need three stages. $5 \times 5 \times 6 = 150$. Using a minimum no. of teeth = 15 gives 15:75, 15:75 and 15:90 teeth. Pitch dias. are 2.5, 12.5 and 15 in.
- 9-14** The factors $5 \times 6 = 30$. The ratios 14:70 and 12:72 revert to same center distance of 4.2. Pitch dias. are 1.4, 1.2, 7, and 7.2.
- 9-16** The factors $7.5 \times 10 = 75$. The ratios 22:165 and 17:170 revert to same center distance of 6.234. Pitch dias. are 1.467, 1.133, 11, and 11.33.
- 9-19** The factors $2 \times 1.5 = 3$. The ratios 15:30 and 18:27 revert to the same center distance of 3.75. Pitch dias. are 2.5, 5, 3, and 4.5. The reverse train uses the same 1:2 first stage as the forward train, so it needs a second stage of 1:2.25 which is obtained with a 12:27 gearset. The center distance of the 12:27 reverse stage is 3.25 which is less than that of the forward stage. This allows the reverse gears to engage through an idler of any suitable diameter to reverse output direction.
- 9-21** For the low speed of 6:1, the factors $2.333 \times 2.571 = 6$. The ratios 15:35 and 14:36 revert to the same center distance of 3.125. Pitch dias. are 1.875, 4.375, 1.75, and 4.5. The second speed train uses the same 1:2.333 first stage as the low speed train, so it needs a second stage of 1:1.5 which is obtained with a 20:30 gearset which reverts to the same center distance of 3.125. The additional pitch dias. are 2.5 and 3.75. The reverse train also uses the same 1:2.333 first stage as both forward trains, so it needs a second stage of 1:1.714 which is obtained with a 14:24 gearset. The center distance of the 14:24 reverse stage is 2.375 which is less than that of the forward stages. This allows the reverse gears to engage through an idler of any suitable diameter to reverse output direction.

TABLE S9-1 Solution to Problem 9-29

Possible ratios for two-stage compound gear train to give the ratio 2.71828

Pinion1	Gear 1	Ratio1	Pinion 2	Gear 2	Ratio 2	Train ratio	Abs error
25	67	2.68	70	71	1.014	2.71828571	5.71E-06
29	57	1.966	47	65	1.383	2.71826853	1.15E-05
30	32	1.067	31	79	2.548	2.71827957	4.30E-07
30	64	2.133	62	79	1.274	2.71827957	4.30E-07
31	48	1.548	45	79	1.756	2.71827957	4.30E-07
31	64	2.065	60	79	1.317	2.71827957	4.30E-07
31	79	2.548	75	80	1.067	2.71827957	4.30E-07
35	67	1.914	50	71	1.420	2.71828571	5.71E-06

9-25 a. $\omega_2 = 790$, c. $\omega_{arm} = -4.544$, e. $\omega_6 = -61.98$

9-26 a. $\omega_2 = -59$, c. $\omega_{arm} = 61.54$, e. $\omega_6 = -63.33$

9-27 a. 560.2 rpm and 3.57 to 1, b. $x = 560.2 \times 2 - 800 = 320.4$ rpm

9-29 See Table S9-1 for solution. The third row has the smallest error and smallest gears.

CHAPTER 10 DYNAMICS FUNDAMENTALS

10-1 CG @ 7.89 in. from handle end, $I_{zz} = 0.1873$ in-lb-sec², $k = 8.39$ in.

10-2 CG @ 6.74 in. from handle end, $I_{zz} = 0.0918$ in-lb-sec², $k = 7.38$ in.

10-4

a. $x = 3.547$, $y = 4.8835$, $z = 1.4308$, $w = -1.3341$

b. $x = -62.029$, $y = 0.2353$, $z = 17.897$, $w = 24.397$

10-6

a. In series: $k_{eff} = 3.09$, Softer spring dominates
b. In parallel: $k_{eff} = 37.4$, Stiffer spring dominates

10-9

a. In series: $c_{eff} = 1.09$, Softer damper dominates
b. In parallel: $c_{eff} = 13.7$, Stiffer damper dominates

10-12 $k_{eff} = 4.667$, $m_{eff} = 0.278$

10-20 Effective mass in 1st gear = 0.054 bl, 2nd gear = 0.096 bl, 3rd gear = 0.216 bl, 4th gear = 0.862 bl.

10-21 Effective spring constant at follower = 308.35 lb/in.

* These files can be found in the PROBLEM SOLUTIONS folder on the CD-ROM included with this text.

CHAPTER 11 DYNAMIC FORCE ANALYSIS

11-3 Open file P11-03row.sld in program SLIDER to check your solution.*

11-4 Open file P11-03row.sld in program SLIDER to check your solution.*

- 11-5 Open file P11-05row.4br in program FOURBAR to check your solution.*
- 11-6 Open file P11-05row.4br in program FOURBAR to check your solution.*
- 11-7 Open file P11-07row.4br in program FOURBAR to check your solution.*
- 11-12 $F_{12} = 904.0 \text{ N}$, $F_{14} = 1\,440.5 \text{ N}$, $F_{32} = 344.2 \text{ N}$, $F_{43} = 723.2 \text{ N}$
 $T_{12} = -7.7 \text{ N-m}$
- 11-13 Open file P11-13.4br in program FOURBAR to check your solution.*

CHAPTER 12 BALANCING

12-1

- a. $m_b r_b = 0.934$, $\theta_b = -75.5^\circ$
 c. $m_b r_b = 5.932$, $\theta_b = 152.3^\circ$
 e. $m_b r_b = 7.448$, $\theta_b = -80.76^\circ$

12-5

- a. $m_a r_a = 0.814$, $\theta_a = -175.2^\circ$, $m_b r_b = 5.50$, $\theta_b = 152.1^\circ$
 c. $m_a r_a = 7.482$, $\theta_a = -154.4^\circ$, $m_b r_b = 7.993$, $\theta_b = 176.3^\circ$
 e. $m_a r_a = 6.254$, $\theta_a = -84.5^\circ$, $m_b r_b = 3.671$, $\theta_b = -73.9^\circ$

12-6 $m_a = 370.7 \text{ g}$, $\theta_a = -138.6^\circ$, $m_b = 320.2 \text{ g}$, $\theta_b = 43.5^\circ$

12-7 $m_a = 378.4 \text{ g}$, $\theta_a = 97.2^\circ$, $m_b = 376.6 \text{ g}$, $\theta_b = -68.0^\circ$

- 12-8 These are the same linkages as in Problem 11-5. Open the file P11-05row.4br in program FOURBAR to check your solution.* Then use the program to calculate the flywheel data.

- 12-9 Open the file P12-09.4br in program FOURBAR to check your solution.*

CHAPTER 13 ENGINE DYNAMICS

- 13-1 Exact solution = $-42\,679.272 \text{ in/sec}$ @ 299.156° and 200 rad/sec

Fourier series approximation = $-42\,703.63 \text{ in/sec}$ @ 299.156° and 200 rad/sec

Error = -0.0571% ($-0.000\,571$)

- 13-3 Gas torque = $2\,039.5$ (approx.), Gas force = $3\,141.6$

- 13-5 Gas torque = $2\,039.5$ (approx.), Gas torque = $2\,025.7$ (exact)

Error = 0.68% (0.0068)

13-7

- a. $m_b = 0.00748$ at $l_b = 7.2$, $m_p = 0.01251$ at $l_p = 4.31$
 b. $m_b = 0.00800$ at $l_b = 7.2$, $m_a = 0.01200$ at $l_a = 4.80$
 c. $I_{\text{model}} = 0.6912$, Error = 11.48% (0.1148)

- 13-9 $m_{2a} = 0.018$ at $r_a = 3.5$, $I_{\text{model}} = 0.2205$, Error = -26.5% (-0.265)

* These files can be found in the PROBLEM SOLUTIONS folder on the CD-ROM included with this text.

TABLE S15-1
Solutions to Problem
15-6

	ω_n	ω_d	c_c
a.	3.42	3.38	8.2
b.	4.68	4.65	19.7
c.	0.26	0.26	15.5
d.	2.36	2.33	21.2
e.	5.18	5.02	29.0
f.	2.04	1.96	49.0

13-11 Open the file P13-11.eng in program ENGINE to check your solution.*

13-14 Open the file P13-14.eng in program ENGINE to check your solution.*

13-19 Open the file P13-19.eng in program ENGINE to check your solution.*

CHAPTER 14 MULTICYLINDER ENGINES

Use program ENGINE to check your solutions.*

CHAPTER 15 CAM DYNAMICS

15-1 to **15-5** Use program DYNACAM to solve these problems. There is not any *one* right answer to these design problems.

15-6 See Table S15-1

* These files can be found in the PROBLEM SOLUTIONS folder on the CD-ROM included with this text.

INDEX

A

acceleration 4, 144, 300

absolute 302, 307, 308

analysis

analytical 308

graphical 303, 304

angular 522, 531, 541

as free vector 308

definition 300

inverted slider-crank 318

cam 352

centripetal 301, 307, 514

coriolis 313

difference

analytic solution 308, 309

definition 303

equation 302

graphical solution 307

in slider-crank 312

discontinuities in 358

human tolerance of 322

linear 522, 531

modified sine 367, 369

modified trapezoidal 364

multiplier factor (cams) 420

normal 307

of a valve train 709

of any point on link 320

of geared fivebar 319

of piston 324

of slip 318

relative 303, 307

peak 418

sinusoidal 362

tangential 301, 307

tolerance 323

accelerometer 322

across variable 504

actuator 28, 517

addendum 435, 440

circle 440

modification coefficients 444

AGMA 440, 444

air

cylinder 28, 77

motor 65

all-wheel-drive 478

Ampere, Andre Marie 5

amplitude ratio 695

analog duplication 416

analogies 11, 685

analogs 504

analysis 10, 11, 76, 77, 521, 721

definition 8

of mechanisms 3, 22

analytical linkage

synthesis 78, 80, 188, 189, 199

compare to graphical 196

angle

of a vector

definition 156

of approach 437

of recess 437

angular velocity ratio 258, 261, 434

definition 257

animate (in programs) 738, 745

antiparallelogram 48

linkage 265

apparent position 148

applications

assembly machines 385

automobile engine 345

automobile suspension 107, 262

automobile transmission 435

crank-shaper linkage 103

engine valves 374

indexing table drive 371

movie camera 105

of air motors 65

of fluid power cylinders 65

of hydraulic motors 65

of kinematics 6

of solenoids 66

optical adjusting mechanism 263

steam locomotives 48

toggle linkages 81

approximate

circle arc 126, 128

dwell 130

straight line 103, 120, 128

arc of action 437

arm (epicyclic) 462

Artobolevsky 6

asperities 25

atlas of coupler curves
 fourbar 104, 105
 geared fivebar 111,744

automobile
 clutch 554
 suspension 107, 120, 262
 wheel balancer 590

axis
 of rotation 495
 of slip
cam-follower 255, 398
inverted slider-crank 278, 314, 541
slider block 267, 269, 270
 of transmission 437
cam-follower 398
gear teeth 436
inverted slider-crank 278, 541
slider block 267, 269, 270

axle 262

B

babbitt 635

backdrive 80, 448

background
 research 9, 16, 567, 719

backhoe 7

backlash 438, 440
 definition 438

balance
 complete 570
 dynamic 570, 574
tires 590, 591
 mass 571
 shafts 658, 676, 678
 single-plane 571
 static 570, 571, 678
tires 590

balancer
 Lanchester 679
 Nakamura 679

balancing 514
 dynamic 577, 580, 678
 linkages 580
effect on input torque 585, 586
effect on pin forces 583
optimum counterweights 586
shaking force 579, 580
shaking moment 586
 single-cylinder engine 631
 static 573

ball
 and socket 25
 joint 25

bank
 angle 661
 engine 643
 of cylinders 600

Barker 49

base circle
 cam 397, 410
 gear 440, 442, 448
 involute 435
 radius 396

base units 17

beam
 cantilever 511
 double cantilever 511
 indeterminate 32
 simply supported 32

bearing 55
 ball 56
 bushing 59
 effective diameter 58
 effective length 58
 flange-mount 56
 journal 55
 linear ball 56
 pillow block 56
 ratio 58, 59
definition 58
poor, example of 59
 roller 56
 rolling-element 56
 sleeve 55
 spherical rod end 56

belt 6, 24, 432
 flat 451
 synchronous 451
 timing 451
 vee 433, 450

Berkof-Lowen method 580

big end (conrod) 615

binary 33
 link 24

binomial
 expansion 609
 theorem 608, 613

bisector 128

blank paper syndrome 8, 556

blobs 17, 18

bore/stroke ratio 634

Boston rocker 266

bottom dead center (BDC) 601

boundary
 conditions 345, 352, 378, 383

brainstorming 10

brake 462

branch
 defect 173, 228
 definition 173

brute force and ignorance
 (BFI) 726

building blocks 28

bump steer 262

Burmester curves 220

bushing 59
 ball 122

C

earn 6, 24, 78, 126, 325, 345, 685
 and follower 77, 125, 254
 automotive valve 509, 699
 axial 349, 422
 barrel 349, 372
 contour 410
 cylindrical 349
 definition 345
 design
fundamental law of 356
 desmodromic 705
 disk 500, 686
 duplicating machine 417
 dynamic test fixture 415
 face 349
 force-closed 704, 707
 form-closed 704, 705, 707
 geometric generation 413
 ground 424
 hand-dressing 414
 manufacturing 412
 master 416
 materials 412
 mechanisms 503
 milled 424
 plate 349, 708
 plunge cutting 413, 414
 radial 349, 422
 scallops 413, 414
 stationary 406
 three-dimensional 350
 track 704

cam-follower 40, 42, 46, 59

camoid 350

- camshaft 704
 - torque 707
- capacitor 504, 506
- carburetor 603
- carry through 48
- cartesian
 - coordinates 154
 - form 147
 - plot 732
- Cayley diagram 113, 116
 - degenerate 113
- center
 - of curvature 409
 - of gravity 493, 494, 531, 614
 - global* 495
 - of percussion 498, 615
 - of rotation 498, 500, 615
 - point 217
 - circle* 217
- centrifugal force 514, 676
- centrodes 263
 - fixed, moving 265
 - noncircular gears 450
- centros 249
- chain 24
 - drive 432, 451
 - silent 451
- change points 48
- characteristic equation 690, 691
- Chasles' theorem 151, 247
- Chebyshev 112, 119, 120, 218
- chordal action 452
- cinematique 5
- circle
 - arc 122
 - with remote center* 103
 - point 217
 - circle* 217
- circuit
 - defect 173, 228
 - definition 173
- circuits
 - of a linkage 158, 159
 - distinguishing* 175
 - number of* 173
- circular
 - gears 265
 - interpolation 416
 - pitch 440
- civil engineering 5
- clearance 438, 440
- Clerk 603
 - cycle 601
 - engine 603
- clockworks 5
- closed
 - curve 103
 - kinematic chains 28
 - loop 64
 - mechanism 28
- closed-form solution
 - definition 174
- clutch
 - automobile 554, 623
 - synchromesh 474
- coefficient
 - of damping 503, 508
 - of fluctuation 553, 554, 623, 764
 - of friction 501
- cognate 113, 117
 - fourbar linkage 112
 - geared fivebar 113
- colinearity 80, 98
- combined functions
 - for cams 362, 372
- common
 - normal 255, 436, 437
 - tangent 255, 435
- communication 16, 722
- complex
 - motion 23
 - conrod* 614
 - coupler* 28, 103
 - definition* 24, 149
 - Whitworth slider-crank* 45
 - number 154
 - notation* 154, 156
 - plane 154
- component
 - orthogonal 160
- compound
 - epicyclic train 466
 - gear train 445, 453, 454
- compression
 - ignition 605
 - stroke 602
- computer aided
 - drafting 77, 105, 556
 - engineering 77, 78
 - manufacturing 413
- computer graphics 97
- computer programs: *See* programs, computer
- concave 403, 404
- conjugate
 - action 448
 - cams 348, 702, 705
- conjugates 348, 435
- connecting rod 28, 600
- conrod 605, 614, 617
 - two per crank throw 669
- conrodcrank ratio 634
- conservation of energy 515
- conservative mode 686
- constant
 - acceleration 363
 - of integration 688
 - velocity 385
- constrained 28
- construction angle 98
- contact ratio 444
 - minimum 444
- continuation methods 226
- continuous 42
 - motion 385
- continuous numerical control (CNC) 413, 414
- convex 403
- coordinate system 24, 146, 522
 - absolute 17, 146
 - global 146, 191, 537, 740
 - local 146
 - nonrotating* 146, 522, 538, 740
 - rotating* 146, 538, 740
- coriolis acceleration 313, 315
- correction planes 575, 678
- cost 78
- coulomb friction 501, 540
- counter
 - balance 54
 - couple 575
 - rotating eccentrics 676
 - shaft 474
 - weight 573, 585, 633, 678
 - crankshaft* 631
 - optimum balance* 586
- coupler 103, 105, 168, 718
 - as a physical pendulum 586
 - attachment points
 - alternate* 91
 - curve equation 227
 - curves 103, 104, 107, 111, 113, 128
 - atlas of* 105
 - degenerate* 103
 - degree of* 103

design charts 111
double points 104
shapes of 104
symmetrical 107
 definition 28
 output 83, 85, 89, 91
 point 105, 128, 735, 749
 crank 105, 600, 614
 definition 28
 eccentric 58
 phase diagram 644, 659, 761
 short 58
 throw 641
 crank-conrod ratio 608
 crank-rocker 48, 105
 crank-shaper 45
 crank-slider
 quick-return 102
 threebar 525
 crankpin 617
 splayed 675
 crankshaft 603, 641
 balance weights 631
 mirror symmetric 659
 phase angles 763
 phase diagram 644
 creative process 10, 718
 definition 718
 creativity 7, 10, 20, 718
 critical extreme position (CEP)
 346, 351, 353
 critical path motion (CPM) 346,
 351, 385, 386, 391, 395
 crossed
 helical gears 447
 mechanism 158, 210
 crossover shock 422, 438,
 704, 706
 crowned pulley 451
 crunode 104, 111
 cubic function
 finding roots of 174
 current 504
 curvilinear translation 117
 cusp
 on earn 404
 on coupler curve 104, 107, 111
 on moving centrode 267
 cycloid
 curve 104
 gear tooth 435
 geometrically generated 413

cycloidal
 coupler curve 267
 displacement 359, 362, 375
 compared 369
 dynamic force 698
 dynamic torque 708
 single-dwell 382
 vibration 418

cylinder
 air and hydraulic 65
 spacing (IC engines) 762

D

d' Alembert 5, 513, 515, 517, 571,
 617, 619

dampers 511, 696
 combining 504
 in parallel 505
 in series 504

damping 502, 503, 509, 685, 689,
 699
 coefficient 503
 critical 690, 691, 692
 effective 504, 509
 internal 512
 nonlinear 502
 pseudo-viscous 503
 quadratic 502
 ratio 690, 695, 699
 viscous 502

DC component 609

decision matrix 12

dedendum 440, 442
 circle 440

deferred judgment 10

deflection 493, 501
 bending 511
 torsional 511

degree 103, 111, 378

degree of freedom 22, 27, 32, 506
 definition 28
 distribution of 38
 spatial mechanisms 32
 visualizing 27

Dejonge 6

delta
 phase angle 644
 optimum 644
 power stroke angle 654
 triplet 37, 38, 42
 deltoid 49

Denavit, J. 6, 112

density

 mass 493
 weight 493

derived unit 17

descriptive geometry 5, 722

design 7, 78, 717

 axiomatic 15
 by successive analysis 77, 78
 case study 718
 computer aided 13
 definition 7
 detailed 12, 13, 14, 18
 process 3, 7, 8, 14, 20, 76, 493, 717
 qualitative 77
 ratios 634
 simplicity in 46
 specifications 9
 trade-off 60, 553, 634

desmodromic 348, 422, 703

determinant 213

diametral pitch 441

Diesel cycle 605

differential 462
 automotive 478
 center 478
 rear 478
 definition 477
 limited slip 478
 Torsen 478

digitizing increment 419

dimensional synthesis 78,80,
 82, 132
 of a fourbar linkage 82

Dirac delta functions 356

discontinuities 356

discriminant 691

displacement
 carn 352, 373
 definition 147
 total 149

dissipative element 696

Dixon, A. 14

DOF. *See* degree offreedom

dot product 515

double

 crank 48
 dwell 130, 353
 linkage 128, 352
 enveloping wormset 448
 harmonic 375, 708

parallelogram linkage 48
 rocker 48, 80, 89, 119
 drag link 48, 100
 dragged crank 100
 driver 60
 crank 534
 stage 89
 driving torque 538, 612
 duplicate planar linkages 79
 dwell 42, 60, 126, 128, 352, 423
 earn
 double 698
 single 375
 definition 125
 linkages 126
 mechanism 42, 125, 130
 motion 103
 dyad 83, 191, 193, 196, 205, 217
 definition 28
 driver 87, 89, 91
 output 100, 102, 126
 DYNACAM program
 examples
 constant velocity 388
 force 699, 700, 705
 polynomial 382
 radius of curvature 406
 single-dwell 374
 torque 708, 709
 general information 725
 how to run 757, 764
 dynamic
 analysis 18
 balancing
 devices requiring 575
 machine 590
 equilibrium 513
 force 4, 18, 144, 323, 493
 analysis 491, 521
 measurement 709
 friction 501
 models 492
 system 4, 514, 522
 dynamic equivalence 587
 requirements for 614

E

E-Quintet 37
 eccentric
 earn 413
 crank 58
 masses 676, 677

eccentricity
 cam
 definition 398
 using to control pressure angle 401
 earn-follower
 effect on pressure angle 401
 flat-faced 402, 411
 roller 398
 effective
 damping 509
 linkage 345, 433
 links 40, 257
 mass 508
 spring 508
 efficiency 447, 515
 definition 470
 of a conventional gear train 470
 of an epicyclic train 471
 elastomers 450
 electric motors 60, 548
 electrical circuit 504
 electromechanical devices 79
 endpoint specification 351
 energy
 kinetic 241
 in cam-followers 363, 372, 392
 in flywheels 549, 622
 in lever ratios 508
 in resonance 696
 in rotating systems 496
 in virtual work 515, 517
 peak 370
 law of conservation 515
 method 515, 545
 potential 515, 696
 storage 696
 elements 696
 ENGINE
 program 598, 609, 620, 639
 flywheel calculations 623
 engineering 14
 approach 14
 design 4, 7, 76, 126
 costin 78
 definition 7
 human factors 16
 report 16
 engines 60, 600
 inline 641
 six-cylinder 675
 multicylinder 641
 opposed 643

flat-four 675
 twin 674
 radial 643
 rotary 643
 vee 600, 643, 661
 eight 600, 661, 669, 670, 675, 763
 six 661, 675
 twelve 675
 epicyclic gear train
 circulating power in 471
 efficiency of 473
 equation solver 178, 513, 556
 equilibrium 502, 513
 equivalent
 mass 506
 spring 508
 system 503, 509, 685
 Erdman, A. 6, 97, 188, 220
 ergonomics 16
 Euclidean geometry 82
 Euler 5
 equivalents 156
 identity 155
 theorem 150
 Eureka! 721
 Evans, J. 5
 evolute 435
 exhaust stroke 603
 external
 gearset 442
 load 531
 torque 533

F

face width (gears) 440
 Ferguson's paradox 466, 469
 film advance mechanism 105
 finite
 difference method 15
 element method 15
 firing
 angles 763
 even 652
 inline engines 655
 inline four 658, 660, 661
 vee eight 673
 vee engines 674
 order 655, 671, 763
 pattern 652
 uneven 655
 FIVEBAR program

example 52
 cognate offourbar 120
 coupler curves 112
 exact straight line 120
 how to run 725

fixed
 centrode 263, 266
 pivots 90, 93, 105, 112
 specified 93
 flexure hinge 719
 flight simulator 726
 fluctuation 553
 flywheel 63, 497, 545
 calculation
 in program DYNACAM 708
 in program FOURBAR 549
 in program ENGINE 763
 designing
 for fourbar linkage 548
 for 1C engine 622
 effect 585
 engine 622, 623
 in IC engines 675
 materials 554
 moment of inertia of 623
 physical 554
 size 763
 sizing 553

follower 685
 earn 79, 345, 435
 aligned 398
 force-closed 686, 698
 form-closed 702
 system 345, 685
 underdamped 696
 flat-faced 348, 407, 423
 float 422
 force- or form-closed? 422
 Jump 422, 696, 699, 700
 mushroom 348
 roller 704
 rotating 347
 slip 704
 translating 347
 flat-faced 509
 roller 708
 translating or rotating? 421
 velocity 707

foot-pound-second (fps) system 17

force
 analysis
 dynamic 492, 698
 kinetostatic 698, 700, 702, 705
 applied 523, 527

centrifugal 514, 515, 619
 closed 27
 closure 27, 348, 702
 crankpin 628, 631
 dynamic 598
 cam-follower 699, 700, 702, 705, 708
 compared to gravitational 516
 minimizing 362
 external 517, 571
 externally applied 523
 gravitational 516, 522
 impact 699
 inertia 506, 517, 557, 571, 610, 617, 629
 link 107
 main pin 628
 piston sidewall 627
 primary 660
 reaction 534
 secondary 660
 shaking 544, 570, 598
 cancelling 677
 fourbar linkage 584
 in inline engines 646, 660
 in one-cylinder engines 610, 617
 in vee engines 667
 primary 658
 secondary 658
 spring 500, 686
 transducer 590, 709
 transmission 82
 wrist pin 628, 631

form-closure 27, 348, 702

four-stroke cycle 601, 655

fourbar linkage 46, 113, 531, 570
 acceleration 308
 antiparallelogram 48
 change points 48
 classification of 49
 cognates 116
 character of 113
 coupler curves 104
 crank-rocker 40, 80
 double-rocker 80, 83
 linkless 265
 mechanism 718
 nine independent parameters of 224
 optimum straight-line 122
 quick-return 98
 subchain 83
 symmetrical 108
 triple-rocker 48, 80

FOURBAR program 81, 111, 521

examples
 cognates 116
 coupler curve 105
 fivebar equivalent 120
 quick-return 98
 straight-line linkages 120
 three-position synthesis 90, 209
 toggle 171
 two-position synthesis 198
 how to run 725

Fourier 5
 series 609, 648

free body 514, 526
 diagram 522, 531, 619, 626, 686, 689

free choices 84
 for function synthesis 223
 in three-position synthesis 204, 205
 in two-position synthesis 192, 193, 196

free vector 248, 307, 308

frequency
 forcing 695, 696
 fundamental 688, 696, 702
 harmonics 688
 natural 685
 and resonance 696
 cam-follower 699, 700, 703, 713
 circular 688, 694
 undamped 688, 689
 vs. forcing frequency 697
 ratio 695
 response 709

Freudenstein, F. 6, 157

friction 27, 433, 619
 belts 433
 force 528
 in linkages 82
 nonlinear 502
 torque 758
 work 267

frisbee 248

frustration 10, 11, 720

full joint 25, 29

function
 forcing 694, 713
 generation 78, 351
 analytical synthesis 220
 definition 79, 188
 table of free choices 223
 two-position 83

generator 78, 221, 345
functional visualization 9
fundamental frequency 609
fundamental law
 of cam design 359, 698
 of gearing 434, 436, 438
 definition 436
fuzzy logic 226, 228

G

gas
 force 605, 610, 620, 629, 652, 759
 curve 605, 610
 pressure 610, 759
 curve 603, 605, 610
 torque 610, 613, 652, 759
gate 105
Gauss-Jordan elimination 200
gear
 antibacklash 439
 base pitch 444
 bevel 449
 spiral 449
 straight 449
 blank 449
 helical 447
 herringbone 447
 hypoid 450
 idler 453, 744
 rack 449
 ratio 112, 164, 506, 744
 set 119, 265
 shaper 442
 spur 447
 teeth 435
 full-depth 442
 minimum number 442
 unequal addendum 444
 tooth action 432
 train 432, 452
 compound 454
 design algorithm 458
 earliest known reference 432
 epicyclic 461, 462, 465, 475
 error in center distance 438
 irrational ratio 461
 reverted 456, 474
 simple 452
 worm 448
 wormset 448

gearbox 432, 455
geared tiebar
 coupler curves 111
 mechanism 52, 164
 analysis 164, 319
 cognate offourbar 119
 coupler curves 103
 inversions of 53
 program for 744
gearing
 fundamental law of 434
 definition 436
gears 24, 434
 noncircular 265, 450
 profile-shifted 444
gearset 434, 448
 angle of approach 437
 angle of recess 437
 arc of action 437
 changing center distance 438
 contact ratio 444, 446
 external 435
 highest point of single-tooth
 contact 444
 internal 435, 442
 length of action 436, 444
 pressure angle 437
genetic algorithms 226
Geneva
 mechanism 42
 wheel 42
global mass center 580
goal statement 9, 567
graphical
 dimensional synthesis 78
 compare to analytical 196
 tools needed for 83, 89
 position analysis 145
Grashof 47, 144
 condition 46, 47, 49, 89
 geared fivebar 53
 crank-rocker 120
 double-rocker 170
 fivebar 119
 linkage 60
 special case 48
gravitational
 constant 17, 18
 system 17
gravity 323
ground
 definition 28
 pivots 95

plane 112
Gruebler 29
 criterion 38
 equation 29, 32, 33, 40

H

Hachette 5
Hain, K. 6
half
 angle identities 158
 cycloid 393, 394, 395
 joint 27, 33
 period harmonic 393
Hall, A. S. 6, 97, 98, 119
Hammond, T. 111
harmonic 375
 number 675
harmonics 609, 648, 688
Hartenberg, R. 6, 112
helical motion 25
helix angle 25, 447, 448
higher pair 6, 25, 27
Hitchcock chair 266
hob (gear) 442
hodograph 732
Hoeken linkage 120, 122
homogeneous 688
 ODE 688
 solution 689
homotopy methods 226
hood hinge 79
Hrones and Nelson atlas 104
human factors engineering 15, 21
hunting 439
hydraulic
 cylinder 77
 motor 60, 65
hyperboloids 450
hypoid gears 450

I

idea generation 10
ideation 9, 11, 14, 720
 and invention 9
identification of need 8
identity matrix 200
imaginary axis 154

imbalance 590
 inch-pound-second (ips) 17
 inclined plane 5
 incubation 11, 720
 indexes 372
 indexing 125
 table 371
 indices of merit 261
 induction system 602
 inductor 504, 505
 inertia
 balance 658
 vee engine 661, 674
 force 513, 514, 571, 619, 643, 652
 torque 513, 517, 620, 649
 inertial reference frame 146
 infinity of solutions 196, 217
 inflection points 383, 406
 initial conditions 688
 inner ear 322
 input torque 548, 585
 instant centers 249
 earn-follower 254, 400
 fourbar linkage 250, 263, 718
 generate centrodes 265
 permanent 249, 250
 slider-crank 252
 using in linkage design 261
 intake stroke 602
 interference 442
 intermittent motion 42, 385
 internal combustion
 engine 538, 598, 639
 invention 7, 10
 inverse dynamics 492, 521, 698
 inversion
 definition 44
 for three-position
 synthesis 93, 95, 97
 in ideation 11
 of slider-crank 102
 force analysis 541
 position solution 162
 inversions
 distinct 45
 of fourbar linkage 47
 of sixbar linkages 44
 involute 435, 438, 442, 448
 definition 435
 teeth 438

isomer 38, 746
 invalid 38
 number of valid isomers 38
 iteration 8, 11, 13, 77, 82, 84,
 386, 493, 556

J

jacobian 176, 177
 jerk 324, 374
 angular 325, 326
 earn 352
 difference 327
 finite 696, 698
 linear 327
 jitter 128
 joint 6, 25
 earn-follower 56
 cantilevered 57
 force-closed 27
 force index 169, 555
 form-closed 27
 multiple 30, 33
 one-freedom 25
 order 27
 slider 25
 sliding 250
 straddle mounted 58
 two-freedom 25
 joystick 25

K

Kant 5
 Kaufman, R. 97, 188
 Kennedy, Alexander 6
 Kennedy's rule 249, 250
 Kimball, B. 726
 kinematic
 applications 6
 chain 27
 class of 47, 53, 54
 definition 27
 inversion of 47
 pair 6, 25
 structure 30, 32
 synthesis 521
 kinematics 3, 4, 5, 491, 685,
 699, 709
 definition 3
 history of 5, 20
 kinetics 3, 5, 491

kinetostatics 492, 521, 698, 706
 Kinsyn 97
 KISS 15
 Koster 503, 696, 698, 699, 713
 Kota, S. 109
 Kutzbach 29

L

Lagrange 5
 Lanchester balancer 679
 L'Ecole Polytechnic 5
 length of action 436, 444
 Levai
 12 basic epicyclic trains 463
 lever 5
 ratio 506, 511
 limit stops 107
 Linkages 78, 97, 220
 line
 contact 25
 of action 437
 of centers 105
 linear
 acceleration 300, 323
 actuator 65, 66
 algebra 199
 ball bearings 56
 Geneva mechanism 44
 graph 249
 interpolation 414, 419
 jerk 325
 motion 65
 velocity 241
 link 6, 23, 24, 38
 dogbone 587
 output 144
 ratio 105, 111
 shrinkage
 complete 40, 42
 partial 40
 linkage 78
 advantages 59, 60
 assemblability 54
 basic building blocks 24, 53
 compliant 263
 design 24
 disadvantages 60
 inline 586
 linkless 266
 non-quick-return 98
 rotatability 46

self-locking 81, 91
 sixbar 167
 Stephenson's 167
 Watt's 167
 synthesis 78, 80, 112
 torque 82, 90
 transformation 33, 40, 345
 linkages 6, 24
 connected in parallel 53
 connected in series 53
 versus cams 59
 linkless fourbar linkage 267
 load
 lines 61
 torque 61
 load sharing 444
 locomotive 48
 Loerch 188, 211
 log roller 5
 losses 516, 696
 lower pair 6, 25
 lubricant 25
 lubrication 55, 60, 424, 603
 hydrodynamic 55
 problems 56
 seals for 55
 lumped
 mass 576, 616
 model 508, 617, 685
 parameter 506, 511

M

machine 4, 5, 27, 144
 definition 4, 27
 design 3, 5, 18, 59, 76, 325
 machinery
 rotating 497
 mandrel 590
 mass 4, 18, 492, 500, 614, 686, 696, 699
 balance 572
 density 493
 effective 508, 509, 699, 708
 equivalent 614
 lumped 509, 615
 moment 493, 494, 580
 moment of
 inertia 495, 522, 550, 585, 614
 point 492, 498, 571
 mass-radius product 573, 578, 591, 633

mass-spring model 686
 masses
 combining 506
 massless rod 498, 571
 materials 635
 Mathcad 178, 556, 400
 Matlab 400
 matrix
 augmented 200, 205, 213
 coefficient 205
 inverse 200
 solution 199, 513
 solver 199, 513
 MATRIX program
 example
 force analysis 529, 531, 534
 linkage synthesis 209
 force analysis 513
 how to use 201
 May, Rollo 718
 mechanical
 advantage 260, 261, 435
 analog computer 78
 circuit 504
 efficiency 260
 engineering 5
 function generator 78
 system 504
 mechanism 4, 5, 27, 32, 144
 crank-shaper 103
 definition 4, 27
 double-dwell 130
 forces in 491
 non-quick-return 98
 optical adjusting 263
 planar 79
 quick-return 97
 Whitworth 103
 microcomputer 13, 78
 Milton, J. 432
 mirror symmetric 659, 675
 mks system 18
 mobility 28. *See also* degree of freedom
 model 13, 206, 495, 503
 cardboard 13, 81, 85
 dynamic 498
 dynamically equivalent 614
 finite element 600
 lumped mass 617
 lumped parameter 686
 simplified 492
 single *DOF* 512
 statically equivalent 616
 value of 617
 modified
 sine 367, 372, 394, 418, 698
 trapezoid 367, 369, 418
 module 441
 modulus
 of elasticity 509
 of rupture 511
 moment
 primary 658
 secondary 658, 660
 shaking 570, 598, 677
 in inline engines 650, 652
 in vee engines 667
 momentum 492, 603
 Monge, Gaspard 5
 motion
 complex
 definition 149
 generation 89, 189
 analytical synthesis 193
 definition 79
 three-position 89, 91
 two-position 85
 intermittent 65
 parallel 117
 simple harmonic 357, 358
 straight line 77
 motor 28, 60, 517
 AC 60
 closed loop 64
 compound-wound 61, 62
 DC 60
 permanent magnet (PM) 61
 speed controlled 63
 gearmotor 60, 64
 open loop 65
 permanent magnet 61
 series-wound 62
 servo 60
 shunt-wound 62
 speed torque characteristic 548
 stepper 60, 65, 79
 synchronous 63
 universal 60
 movie camera 105
 moving
 centro de 265, 266
 pivots 90, 95, 128
 multiple solutions 15

N

- Nakamura balancer 679
- natural frequency 679, 688, 709
 - circular 688
 - damped 688, 691
 - undamped 688, 691
- Nelson, G. L. 104
- Newton-Raphson
 - method 168, 174, 327
 - chaotic behavior of 175
 - in equation solvers 178
- Newton's
 - equation 17, 686
 - laws 323, 491, 521, 571
 - method 174, 521
 - second law 3
 - third law 527
- no-load speeds 64
- node 24, 28, 38
- noise, vibration, and harshness (NVH) 679
- non-Grashof 47
 - double-rocker 170
- number synthesis 33
- numerical control (NC) 413
- nut 25

O

- objective function 224
- octoid 449
- offset (in slider-crank) 159
- oil bath 424
- open
 - kinematic chain 28
 - mechanism 158, 210
- operator 154
- order
 - defect 228
 - of joints 27
 - of links 33
 - of polynomial 378
- orthogonal 160
- oscillation - earn-follower 696
- Otto cycle 601
- overbalanced crank 633
- overdamped system 691
- overlays 77
- overshoot of response 692

- oversquare engine 634
- overturning moment 402

P

- pairs 25
 - higher 25
 - lower 25
- paradoxes
 - Ferguson's 468
 - Gruebler's 37
- parallel
 - axis theorem 497, 557
 - connections
 - dampers 504
 - springs 504
 - linkage planes 79
 - motion 117
- parallelogram linkage 48, 49
- particular solution 688, 694
- path 79
 - generation 79
 - definition 79
 - precision points 189
 - with coupler curve 103, 105, 107, 112
 - with prescribed timing 79, 220
- pawl
 - driving 44
 - locking 44
- Peaucellier 122
- performance specifications 9, 14, 567, 719
- phase angle
 - crankshaft 641, 763
 - geared fivebar 111, 164, 744
 - optimum 641
 - sign convention 644
- physical pendulum 586
- piecewise continuous function 359
- piezoelectric
 - accelerometer 709
 - force transducer 590
- pin
 - double shear 58
 - forces 610, 623
 - crankpin 626
 - main pin 628
 - wrist pin 626
 - joint 25, 55
 - single shear 58
- pinion 434, 449

- piston 324, 539, 600, 614, 617
 - acceleration 606, 610, 619
 - engine 45
 - position 606
 - pump 45, 538, 601, 639
 - velocity 606
- pitch
 - circle 435, 438, 440
 - curve 397, 404, 406
 - diameters 435, 438
 - diametral 441
 - point 435, 436
- planet gear 462
- platform rocker 266
- polar
 - coordinates 154
 - form 147
 - plot 660, 732
- poles 249
- polodes 265
- polynomial 708
 - 3-4-5 378, 381, 382, 698
 - 4-5-6-7 381, 382, 418
 - function 356, 378
 - design rule 383
- position 144, 147, 241
 - absolute 149
 - analysis 151, 152
 - difference 148
 - equation 147, 243
 - of any point on a link 168
 - relative 148
 - vector 147, 153
- pounds force (lbf) 18
- pounds mass (lbm) 17
- power 61, 259, 504, 516, 653, 706
 - chart 761, 763
 - equation 517
 - stroke 603, 655, 659
 - angles 653, 655, 763
 - to weight ratio 601
- practical
 - considerations 554, 556, 713
- precision
 - points 189, 196
 - position 189, 191, 201
- preload
 - earn-follower spring 699
- preloaded structure 32
- pressure angle
 - earn-follower 396
 - flat-faced 437

- force analysis 708
 - roller 397, 398
 - of gearsets 437
 - primary component
 - of shaking force 609
 - of shaking moment 652
 - prime
 - circle 397, 708
 - radius 396, 405
 - principal axes 23
 - principle
 - of d'Alembert 513
 - of transmissibility 258
 - problem
 - definition 719
 - unstructured 8
 - problem sets
 - Chapter 2 67
 - Chapter 3 132
 - Chapter 4 178
 - Chapter 5 232
 - Chapter 6 281
 - Chapter 7 327
 - Chapter 8 425
 - Chapter 9 479
 - Chapter 10 518
 - Chapter 11 557
 - Chapter 12 592
 - Chapter 13 635
 - Chapter 14 682
 - Chapter 15 714
 - production 13
 - programs, computer
 - coordinate systems in 732, 740
 - copying to clipboard 729
 - creating new files 729
 - disclaimer on liability 726
 - DYNACAM 751
 - continuity check 754
 - drawing the cam 755
 - follower dynamics 756
 - input data 751
 - polynomial functions 753
 - sizing the cam 754
 - ENGINE 757
 - charts 762
 - crank balancing 760
 - flywheel calculations 763
 - multi cylinder 761
 - single cylinder 758
 - examples in 729
 - FIVEBAR 743
 - animation 745
 - coupler point 744
 - dynamics 745
 - input data 744
 - phase angle defined 744
 - FOURBAR 735
 - balancing in 740
 - centrodes 739
 - cognates 743
 - input data 735
 - synthesis 743
 - general information 725
 - home screen 728
 - how to run them 735
 - linkage
 - angle steps 736
 - animation 738
 - autoscaling 739
 - calculation errors 738
 - calculation in 736
 - dynamics 740
 - Grashof condition 738
 - one position 736
 - time steps 737
 - trace on/off 739
 - MATRIX 764
 - opening a file 729
 - operation 727, 743
 - plotting data 731
 - cartesian plots 732
 - polar plots 732
 - printing from 730
 - quitting 734
 - running 728
 - saving data 729
 - SIXBAR 745
 - animation 748
 - dynamics 748
 - input data 746
 - SLIDER 749
 - animation 751
 - calculation 750
 - dynamics 751
 - input data 749
 - support 735
 - units 729
 - user actions possible 728
 - projects
 - Chapter 3 140
 - Chapter 8 429
 - Chapter 11 567
 - Chapter 13 638
 - Chapter 14 683
 - prototypes 13, 511
 - prototyping 12
 - and testing 13
 - pulleys 450
 - pure
 - harmonic 553, 652, 689
 - rolling 27, 104, 498, 570
 - joint 27
 - rotation 24, 85, 241, 614, 617
 - slide 27
 - translation 24, 312, 498, 614, 617
 - pushrod 509
- Q
- quasi-static 513
 - quaternary link 24, 33
 - quick
 - forward 98
 - return 98, 102, 105
 - mechanism 45
 - sixbar 100
- R
- rack 449
 - and pinion 449
 - steering 449
 - radius
 - of curvature 396
 - flat follower 407
 - roller follower 403, 405
 - of gyration 498, 500
 - prime circle 700
 - ratchet 6
 - and pawl 44
 - wheel 44
 - ratio
 - gear 506
 - lever 508
 - reference frame 28
 - relative
 - acceleration. *See* acceleration:
 - relative
 - velocity. *See* velocity: relative
 - report, technical 16
 - resistor 504
 - resonance 696
 - earn-follower
 - force-closed 696
 - form-closed 703
 - resonate 695
 - response
 - complete 695
 - damped 689
 - forced 695

- steady state 695
 - transient 688, 692, 695
 - undamped 686
 - Reuleaux, Franz** 6, 25, 28
 - classification of mechanisms 27
 - reverted**
 - compound train 456
 - gear train design 456
 - revolvability** 54
 - definition 54
 - right angle drives** 449
 - rigid body** 23,24
 - acceleration 308
 - motion 149
 - ring gear** 462
 - rise-dwell-fall-dwell cam** 346, 351
 - rise-fall cam** 346, 351
 - rise-fall-dwell cam** 346, 351, 374
 - Roberts**
 - Chebyshev theorem 112
 - diagram 113
 - straight-line linkage 120
 - Roberts, Richard** 120
 - Roberts, Samuel** 112, 120
 - robot** 28,77
 - rocker**
 - arm 509, 511
 - definition 28
 - infinitely long 40
 - output 83
 - rocking**
 - chair 266
 - couple 575
 - roll-slide joint** 25,27
 - roller** 348
 - chain 451
 - follower 348, 405, 423, 500, 686
 - chrome plated 423
 - crowned 423
 - in valve trains 423
 - materials 423
 - slip 422
 - rolling**
 - centrodes 450
 - cones 449
 - contact 6
 - cylinders 433, 435
 - root finding** 327
 - rotatability** 46,53
 - definition 53
 - of geared fivebar linkage 53
 - of N-bar linkages 53
 - rotation** 23
 - definition 149
 - pure 24
 - balance in 570
 - rotational**
 - DOF 25
 - freedom 27
 - kinetic energy 601
 - rotopole** 85
 - roughness, surface** 419
- S**
- s v a j diagrams** 352
 - polynomials 378
 - Sanders** 327
 - Sandor, G. N.** 6, 97, 188
 - scalar magnitude** 256
 - scaling** 13
 - Scotch yoke** 40,44
 - screw** 6
 - joint 25
 - second**
 - harmonic 609
 - moment
 - of area 511
 - of mass 495
 - secondary component**
 - of shaking force 609
 - of shaking moment 652
 - selection** 12
 - series connections**
 - dampers 504
 - springs 504
 - servo**
 - mechanisms 439
 - motor 64, 79
 - valve 65
 - shaft**
 - encoder 590
 - hollow 462
 - sheave** 450
 - shock** 324
 - SI system** 17
 - simple harmonic motion** 394
 - simultaneous equation**
 - solution 199
 - dynamic forces 512, 522
 - single**
 - cylinder engine 600
 - dwell 130, 374, 382
 - mechanism 124, 126
 - enveloping wormset 448
 - gearset 453
 - sixbar**
 - drag-link quick-return 100
 - linkage 113
 - mechanism 126
 - Watts linkage 89
 - SIXBARprogram** 725
 - differences from FOURBAR 746
 - example 53
 - double-dwell 130, 352
 - quick-return 102
 - single-dwell 128
 - three-position synthesis 93, 211
 - two-position synthesis 89
 - skew axis** 23
 - slider block** 40, 539
 - slider-crank** 40, 45, 60, 103, 250, 538, 541
 - analysis
 - acceleration 311
 - Fourier 605
 - instant centers 252
 - position solution 159
 - vector loop 159
 - inverted 161, 316, 541
 - acceleration 315
 - linkage
 - dynamic model 617
 - in IC engines 598
 - multicylinder 639
 - offset 161
 - one-cylinder 600
 - nonoffset 605
 - offset
 - definition 159
 - sliding**
 - contact 6
 - joints 33
 - slip** 104
 - component 269, 270, 314
 - velocity 313
 - slop** 439
 - slugs** 17, 18
 - solenoid** 28, 66, 77
 - solids modelling** 556
 - solution methods** 512
 - Soni, A.** 117
 - space width (gears)** 438, 440
 - spatial**
 - linkage 107
 - mechanisms 27, 79

specified fixed pivots 93, 95, 211
spreadsheet 513
spring
 compression 510, 511
 constant 55, 500, 509, 511, 686, 700, 704
 definition 501
 effective 506, 508, 698, 704
 free length 699
 helical coil 699
 physical 698, 704
 preload 700
springs 107, 505
 as links 54
 combining 505
 in parallel 506
 in series 505
sprocket 451
standard form equation 220, 222
static
 equivalence 617
 friction 501
stationary configuration 80
steady state 688
Stephenson's
 chain 38, 40
 sixbar 45, 53, 167, 746, 747
stepper motor 60, 65, 69
stiction 501
stiffness 493, 696
stops 44, 372
straight-line
 linkage 5, 77
 optimum 122
 mechanisms 120
 approximate 122
 exact 120
strain gages 709
strength 493
stresses 4, 144, 323, 493
structural
 building block 37
 subchain 38
structure 30, 32
 preloaded 32
Suh, N. P. 15
sun gear 462
superposition 512, 513, 610, 623
surface contact 25
suspension system 262

sweet spot 498
synchromesh 448, 474
 clutch 474
 transmission 474
synonyms 11
synthesis 76, 77, 80, 83
 algorithm 78
 analytical 78, 82
 compare to graphical 196
 elastic energy method 229
 equation 224
 equation methods 227
 optimization methods 227
 optimized 224
 precision 224
 precision point methods 226
 selective precision synthesis 228
 using genetic algorithms 229
 definition 8
 four-position
 analytical 220
 graphical 97
 graphical
 tools needed for 83
 of mechanisms 3, 18, 22
 qualitative 76, 77, 78, 84
 quantitative 78, 97
 three position
 analytical 201, 205, 208
 graphical 89
 motion 201
 specified fixed pivots 211, 214
 two position 83
 analytical 197
 graphical 89
 type 78

T

tabular method 465
tackle 6
tappet 509
ternary link 24, 33, 34
testing 12, 13
thermodynamics 598, 605
three-freedom joint 25
threebar crank-slide 525
through variable 504
time ratio 98, 100, 102
timing diagram 353
Ting, K. L. 53
TKSolver 178, 327, 400, 556

toggle 80, 81, 265, 737
 angle 172
 linkage 81
 position 80, 91, 113, 189, 190
 calculating location 170
 in rock crusher 261
tolerance 414
 (human) of acceleration 323
tooth thickness 438, 440
toothed belts 451
top dead center (TDC) 601
torque 585
 about the mass center 495
 applied 523
 camshaft 706, 708
 converter 475
 driving 517
 dynamic 708
 external 517
 flywheel-smoothed 623
 gas 613
 flywheel smoothing 622
 in four-cylinder inline engine 655, 660
 in one-cylinder engine 610
 in vee engines 669
inertia 610
 flywheel smoothing 622
 in four-cylinder inline engine 658, 660
 in inline engines 649
 in one-cylinder engine 621
 in vee engines 668
 in virtu61 work 517
input 55, 706, 707
oscillations in 707
ratio 260, 435
shaking 544, 610
 in fourbar linkage 586
 in multicylinder engines 652
 in one-cylinder engines 620
source 523, 528, 534, 557
total 660, 673, 763
 engine 622
variation 548
torque-speed relation 61
torque-time
 diagram 551
 function 622
Towfigh, K. 263, 717, 718
trade-offs 78, 126, 374, 703
train ratio 453

transfer
 port 603
 theorem 497
transient 688
 analysis 737
translating
 follower 347
 slider 100
translation 23,24
 curvilinear 117, 149
 definition 149
 rectilinear 149, 348
translational DOF 25
transmission 435, 448, 601
 automatic 468
 automotive 474
 component 269, 270, 314
 crashbox 477
 Ford model T 476
 synchronmesh 474
transmission angle 257, 258, 261, 503, 554
 definition 81, 169
 differences in cognates 113
 extreme values 169
 limited application 169
 minimum 82
 optimal 102
 poor 196
 quick-return linkage 100
trapezoidal
 acceleration 363
 rule 552
triple-rocker 48, 170
truss 38
twobar chain 83, 100
two-dimensional space 23
two-freedom joint 25
two-plane balance 574
two-stroke
 cycle 601, 603, 653
 engine 654
type synthesis 77, 131

U

undercutting 404, 407, 442
underdamped 692, 693
undersquare engine 634
unit vectors 154
units systems 16

unobtainium 614, 698
unstructured problem 8

V

valve 509
 earn 422, 434
 float 699
 spring 509
valves 345
vector
 angle of
 definition 156
 free 248, 307, 308
 loop 191
vee
 angle 643, 661, 674
 belt 450
velocity 144, 241
 absolute 242, 247, 248
 analysis
 algebraic 271
 geared fivebar 278
 graphical 244, 246
 inverted slider-crank 270
 sliding joint 268
 using instant centers 256
 angular 241, 270, 277, 315
 earn 352
 constant 120
 definition 241
 difference 243, 247, 248, 272, 302
 equation 243
 of point on link 279
 of slip 267, 277, 315
 of transmission 278
 ratio 435, 442, 450
 of involute gears 438
 relative 243, 247, 267, 272, 501
vibration
 in cam-
 followers 396, 503, 694, 704
 in engines 652
 in linkages 544
 residual 698
virtual work 515, 517, 545
 equation 517
ViseGrip 261
visualization 721, 722
voltage 504

W

Watt, James 5
Watt's
 chain 38, 53
 linkage 746
 sixbar 40, 45, 83, 167, 746
 straight-line fourbar 120
wear 25
weather systems 315
wedge 5
weight 17
 factor 12
well pump 45
wheel 6
 and axle 5
Whitworth quick-return 45, 103
Willis, Robert 5
windshield wiper linkage 49
Wood, George A. Jr. 717
work 28, 515
Working Model 77, 81, 105, 725
worm 448
 set 448
 wheel 448
wrapping connectors 6
wrist pin 615, 617
writing engineering reports 21

Y

Young's modulus 509, 511

Z

zero velocity 104
Zhang, C. 111, 744