In SAP Business Network Global Track and Trace, it is updated by the "**lastChangeDateTime**" value in the tracked process and "**creationDateTime**" in the event.

- Residence Period

  The period between the end of business and the end of purpose for a data set during which the data remains in the database and can be used in case of subsequent processes related to the original purpose. At the end of the residence period, the data is blocked.

  For the settings of residence period in SAP Business Network Global Track and Trace, refer to Defining Residence and Blocking Periods.

- End of Purpose

  The point in time when the processing of a set of personal data is no longer required for the primary business purpose, for example, when a contract is fulfilled. After the EoP has been reached, the data is blocked and can only be accessed by users with special authorizations (for example, tax auditors).

  In SAP Business Network Global Track and Trace, the value of end of purpose is calculated by the blocking store background job:

  End of Purpose = End of Business + Residence Period

  When the residence period is finished, the tracked process and event lifecycle reach end of purpose.

- Blocking Period

  The period between the residence period and the deletion of the data. In the blocking period, only users with special privileges, such as a Data Protection Officer (DPO), can access the data. At the end of the configured blocking period, the data is deleted.

  For the settings of blocking period in SAP Business Network Global Track and Trace, refer to Defining Residence and Blocking Periods.

- Retention Period

  The period between the end of the last business activity involving a specific object and the deletion of the corresponding data, subject to applicable laws.

  Retention Period = Residence Period + Blocking Period

- Deletion

  The data is deleted and no longer exists in the database.

  In SAP Business Network Global Track and Trace, the value of date of deletion is calculated by the blocking store background job:

  Date of Deletion = End of Business + Residence Period + Blocking Period

Notes

- Blocking store background job operates automatically once a day at 12 a.m. UTC. So any changes of the life cycle status of tracked processes and events take effect after 12 a.m. UTC each day.
- End of Business is updated if an event is reported to a tracked process. The end of business dates of this tracked process and its correlated tracked processes are also updated and consistent with the end of business date of the latest reported event.
- The life cycle status of tracked process is not updated if you directly change the "lifeCycleStatus_code" value of this tracked process. It is only updated by the blocking store background job.

- When considering compliance with data protection regulations, it is also necessary to consider compliance with industry-specific legislation in different countries/regions. A typical potential scenario in certain countries/regions is that personal data shall be deleted after the specified, explicit, and legitimate purpose for the processing of personal data has ended, but only as long as no other retention periods are defined in legislation, for example, retention periods for financial documents. Legal requirements in certain scenarios or countries/regions also often require blocking of data in cases where the specified, explicit, and legitimate purposes for the processing of this data have ended, however, the data still has to be retained in the database due to other legally mandated retention periods. In some scenarios, personal data also includes referenced data. Therefore, the challenge for deletion and blocking is first to handle referenced data and finally other data, such as business partner data.

Defining Residence and Blocking Periods

Context

To define the residence period and blocking period of various applications, do the following:

Procedure

1. Login to the SAP Fiori Launchpad and choose the Retention Management tile.
2. Select an application type.
3. Enter a residence period. Note that if you do not specify a residence period, the system by default assigns a residence period of 12 months for the application type.
4. Enter a blocking period. Note that if you do not specify a blocking period, the system by default assigns a blocking period of 12 months for the application type.
5. Choose Save.

Results

The system stores the entered residence and blocking periods for the specific application type.

ℹ Note

If you have any questions, log your incident in SAP Support Launchpad with component “SBN-LBN-BP-OB”.

Blocking Store

Once the residence period ends, the data moves to the blocking period. In the blocking period, only users with appropriate authorization, such as a data protection officer, can access the data. At the end of the configured blocking period, the system deletes the data.

The data protection officer can log into the SAP Fiori Launchpad and choose the Blocking Store app to access all the documents that are in the blocking period. To view a document, the user can download the document in a text file format by choosing the **Download** button.

- Identifier: Displays the unique identifier for the document.
- Status: Displays the status of the document, for example, in blocking period.
- End of business: Displays the date when the document reached the end of business state.
- App name: Displays the name of the tracked process type / event type with which the data is associated.

- Administration information

ℹ Note

If you have any questions, log your incident in ServiceNow with component "SBN-LBN-BP-OB".

Help and Support

There are several ways you can find help and support on the Fiori launchpad of SAP Business Network Global Track and Trace.

Built-In Support

Built-in support provides efficient, simplified and guided support channels, you can search for knowledge, ask for needed information, get help from recommended solutions. Currently, expert chat is not supported.

To access the built-in support service on the Fiori Launchpad, click the icon on the right corner of the screen. You will see a welcome page where you can sign in, and a list of recommended links for the page.

To gain full access to the built-in functions, you must activate your S-user. For more, see Activating Built-In Support Services.

For more information on how to use this tool, refer to Built-In Support on SAP Help Portal.

In-app Help

When you launch the app, you can turn on the in-app help that provides on-screen explanations of key fields and areas on the screen.

To turn on the in-app help, on the top right on the screen, click the icon.

Once the in-app help is turned on, you can:

- search the displayed help topics for the text that you type;
- click the icon to see the help texts on that topic;
- click the link tiles to see the documentation of this app on SAP Help Portal;
- hide the **Help Topics** panel by clicking the » button on the bottom right.