

AMENDMENT NO. 4 NOVEMBER 2012
TO
IS 418 : 2004 TUNGSTEN FILAMENT LAMPS FOR
DOMESTIC AND SIMILAR GENERAL LIGHTING PURPOSE

(Fourth Revision)

(Page 1, clause 1.1, lines 5 and 6) — Substitute the following for the existing:

‘—rated wattage of 15 W, 25 W, 40 W, 60 W, 75 W and 100 W’.

(Page 1, clause 1.1, lines 15 and 16) — Substitute the following for the existing:

‘The shell diameter of lamps shall be between 54 to 56 mm or 59 to 62 mm.

NOTE — Shell diameter of 59 to 62 mm shall be phased out after one year from the date of issue of this amendment.’

[Page 1, Clause 2.1 (see also Amendment No. 1)] — Insert the following reference at the appropriate place:

‘2407 : 1963 Photometric Integrators’

[Page 2, Clause 5.4 (see also Amendment No. 1)] — Substitute the following for the existing clause:

‘5.4 For the guidance to the lamp manufacturers, the requirements for glass shells are given in IS 1112 (Part 1) and IS 12897 for lamp filament.’

(Page 8, clause A-3, first sentence) — Substitute the following for the existing sentence:

‘Measurement shall be carried out utilizing a suitable photometric integrator as specified in IS 2403.’

(Page 16, Annex G, Table G) — Number the existing table as Table G-1 and add new Table G-2 as follows:

(Page 16, Annex G, Informal Table) — Insert the following NOTE at the end:

NOTE — The Table G-1 shall be withdrawn after one year from the date of issue of this amendment.

Table G-2
(Clause 1.1, 4.1 and 4.3)

GROUPING OF LAMP DATA SHEETS

Sheet No.	Watt	Bulb	Cap	Finish ¹⁾	Life h	Luminous Flux ²⁾
418-IS-4005	15	A55, K55, M55 and PS55	B22d/25x26 and B-22/23 X 26	C, F	1 000	N
418-IS-4010	25	A55, K55, M55 and PS55	B22d/25x26 and B-22/23 X 26	C, F	1 000	H
418-IS-4015	25	A55, K55, M55 and PS55	B22d/25x26 and B-22/23 X 26	C, F	1 000	N
418-IS-4030	40	A55, K55, M55 and PS55	B22d/25x26 and B-22/23 X 26	C, F	1 000	H

Amendment No. 4 to IS 418 : 2004

Sheet No.	Watts	Bulb	Cap	Finish ¹⁾	Life, h	Luminous Flux ²⁾
418-IS-4035	40	A55, K55,M55 and PS55	B22d/25x26 and B-22/23 X 26	C, F	1 000	N
418-IS-4050	60	A55, K55,M55 and PS55	B22d/25x26 and B-22/23 X 26	C, F	1 000	H
418-IS-4055	60	A55, K55,M55 and PS55	B22d/25x26 and B-22/23 X 26	C, F	1 000	N
418-IS-4070	100	A55, K55,M55 and PS55	B22d/25x26 and B-22/23 X 26	C, F	1 000	H
418-IS-4075	100	A55, K55,M55 and PS55	B22d/25x26 and B-22/23 X 26	C, F	1 000	N
418-IS-5005	15	A55, K55,M55 and PS55	E 27/27	C, F	1 000	N
418-IS-5010	25	A55, K55,M55 and PS55	E 27/27	C, F	1 000	H
418-IS-5015	25	A55, K55,M55 and PS55	E 27/27	C, F	1 000	N
418-IS-5030	40	A55, K55,M55 and PS55	E 27/27	C, F	1 000	H
418-IS-5035	40	A55, K55,M55 and PS55	E 27/27	C, F	1 000	N
418-IS-5050	60	A55, K55,M55 and PS55	E 27/27	C, F	1 000	H
418-IS-5055	60	A55, K55,M55 and PS55	E 27/27	C, F	1 000	N
418-IS-5070	100	A55, K55,M55 and PS55	E 27/27	C, F	1 000	H
418-IS-5075	100	A55, K55,M55 and PS55	E 27/27	C, F	1 000	N
¹⁾ C = Clear, F =Frosted ²⁾ N = Normal luminous flux; H = High Luminous flux NOTE — Table G-2 shall be applicable after one year from publication of this amendment.						

(Pages 20 to 28, *Lamp Data Sheet* 418-IS-4005-1 to 418-IS-4075-1, first informal table, col 2, D, Max) — Substitute ‘55 and 62’ for ‘62’.

(Pages 20 to 28, *Lamp Data Sheet* 418-IS-4005-1 to 418-IS-4075-1, first informal table) — Insert the following note at the end:

‘NOTE — D, Max 62 shall be phased out after one year from the date of publication of this amendment.’

(Page 29, *Lamp Data Sheet*. 418-IS-4090-1) — Delete.

(Page 30, *Lamp Data Sheet*. 418-IS-4095-1) — Delete.

(Page 31, *Lamp Data Sheet* 418-IS-4110-1) — Delete.

(Page 32, *Lamp Data Sheet* 418-IS-4115-1) — Delete.

(Pages 33 to 41, *Lamp Data Sheet* 418-IS-5005-1 to 418-IS-5075-1 first informal table, col 2, D, Max) — Substitute ‘55 and 62’ for of ‘62’.

Amendment No. 4 to IS 418 : 2004

(Pages 33 to 41, *Lamp Data Sheet* 418-IS-5005 -1 to 418-IS-5075-1, first informal table) — Insert the following note at the end:

‘NOTE — *D*, *Max* 62 shall be phased out after one year from the date of publication of this amendment.’

(Page 42, *Lamp Data Sheet*. 418-IS-5090-1) — Delete.

(Page 43, *Lamp Data Sheet*. 418-IS-5095-1) — Delete.

(Page 44, *Lamp Data Sheet*. 418-IS-5110-1) — Delete.

(Page 45, *Lamp Data Sheet*. 418-IS-5115-1) — Delete.