

Standard V-Belt Cross-Section Sizes

Classical V-belt profiles (A through E) showing relative sizes and typical power ranges



A

Top: $\frac{1}{2}$ "

H: $\frac{5}{16}$ "

0.5–10 HP



B

Top: $\frac{21}{32}$ "

H: $\frac{13}{32}$ "

1–25 HP



C

Top: $\frac{7}{8}$ "

H: $\frac{17}{32}$ "

15–100 HP



D

Top: $1\text{--}\frac{1}{4}$ "

H: $\frac{3}{4}$ "

50–250 HP



E

Top: $1\text{--}\frac{1}{2}$ "

H: $\frac{29}{32}$ "

100–500 HP