

Instructions

1) First, screw the 6 parts of the lid together. If the holes in your print aren't perfectly round, the M6 screws won't fit. In that case, either enlarge the holes with a #6 drill bit - or use M5 screws. Don't forget the washers.

2) Place the first spacer with its filter inside (Filter + 40mm Spacer) directly on the lid. Take the two rings of the filter, place a stainless steel mesh between them, and screw the two rings together with the small screws. This clamps the mesh between the two rings. Simply place this finished filter into the spacer. That gives you the base. (there are linked comments with pictures of the filter in the description)

3) Now place whatever planters or spacers you want on top.

4) To finish off the top, you'll need the dispenser and lid. Attach the tube to the dispenser, then run the tube down through all the other parts in the middle. Insert the other end of the tube into the pump. Then place the little lid on top and screw it on. Place the pump in the big flower pot and put the whole tower on top of it.

5) Next, print two caps: one for the water inlet and one for the hole where the pump's power cable exits.

6) Depending on which planters you printed, print the corresponding planting pots as well. For the 4- and 5-planters, the shorter pots are needed; for the 1-, 2-, and 3-planters, you can use the standard-length pots.

7) If you like, you can also attach label holders next to each plant. There is also a shorter version available specifically for the 5-plant planter.

There is an „Overview“ Function in BambuStudio, please have a look at it 😊



