


Sensitive Gate Triacs

HAOPIN MICROELECTRONICS CO.,LTD.

Description

Passivated, sensitive gate triacs in a plastic envelope, intended for use in general purpose bidirectional switching and phase control applications, where high sensitivity is required in all four quadrants.



Applications:

- ♦ Motor control
- ♦ Industrial and domestic lighting
- ♦ Heating
- ♦ Static switching

Features

- ♦ Blocking voltage to 600 V
- ♦ On-state RMS current to 1.5 A

| SYMBOL | PARAMETER | Value | UNIT |
|----------|--------------------------------------|-------|------|
| VDRM | Repetitive peak off-state voltages | 600 | V |
| IT (RMS) | RMS on-state current | | А |
| Ітѕм | Non-repetitive peak on-state current | 15 | А |

| SYMBOL | PARAMETER | CONDITIONS | MIN | TYP | MAX | UNIT |
|-----------|--------------------|-----------------------------|-----|-----|-----|------|
| Rth(j-c) | Thermal resistance | resistance Junction to case | | - | 50 | °C/W |
| Rth(j-a) | Thermal resistance | Junction to Ambient | - | - | 120 | °C/W |



Sensitive Gate Triacs

HAOPIN MICROELECTRONICS CO.,LTD.

Limiting values in accordance with the Maximum system(IEC 134)

| SYMBOL | PARAMETER | CONDITIONS | MIN | MAX | UNIT |
|---------------------|---------------------------------------|---|-----|---------|------------------------|
| V _{DRM} | Repetitive peak off-state Voltages | | - | 600 | V |
| I _{T(RMS)} | RMS on-state current | Tc=58℃ | - | 1.5 | А |
| I _{TSM} | Surge On-State Current | One Cycle,50Hz/60Hz,Peak, Non-Repetitive | - | 13.5/15 | А |
| l ² t | I ² t for fusing | | - | 0.41 | A ² S |
| I _{GM} | Peak gate current | | - | 0.5 | Α |
| V _{GM} | Peak gate voltage | | - | 6.0 | V |
| P _{GM} | Peak gate power | | - | 1 | W |
| $P_{G(AV)}$ | Average gate power | | - | 0.1 | W |
| T _{stg} | Storage temperature | | -40 | 150 | $^{\circ}\!\mathbb{C}$ |
| T _j | Operating junction Temperature | | -40 | 125 | °C |

T_J=25°C unless otherwise stated

| SYMBOL | PARAMETER | CONDITIONS | | MIN | TYP | MAX | UNIT | | |
|------------------------|--------------------------------------|---|--|-------------|-------------|--------------------------|----------------|--|--|
| Static characteristics | | | | | | | | | |
| I _{GT} | Gate trigger current | $V_D=6V; R_L=10 \Omega$ | | | - - - | 5 5 5 10 | mA mA mA | | |
| V _{GT} | Gate Trigger voltage | $V_D=6V; R_L=10 \Omega$ | V ⁺ _{GT1} I V ⁻ _{GT1} II V ⁻ _{GT3} III V ⁺ _{GT3} IV | - - - | - - - | 1.8 1.8 1.8 2.0 | > > > | | |
| I _H | Holding Current | | | - | 4.0 | - | mA | | |
| V _{GD} | Non-Trigger Gate Voltage | $Tj=125^{\circ}C$, $V_D=1/2V_{DRM}$ | | 0.2 | - | - | V | | |
| I _{DRM} | Repetitive Peak Off-State Current | V _D =V _{DRM} ;single phase, Half Wave;T _J =125℃ | | - | - | 0.5 | mA | | |
| V _{TM} | Peak On-State Voltage | I _T =1.5A;Inst,Measurement | | - | - | 1.6 | V | | |


Dynamic Characteristics

| (dv/dt)c Ci | Critical rate of rise off- | Tj=125°C;(di/dt)c=-0.5A/ms, $V_D=2/3$ V_{DRM} | 2 | - | - | V/ μS | |
|-------------|----------------------------|--|---|---|---|-------|--|
|-------------|----------------------------|--|---|---|---|-------|--|



Sensitive Gate Triacs


HAOPIN MICROELECTRONICS CO.,LTD.






Sensitive Gate Triacs

HAOPIN MICROELECTRONICS CO.,LTD.







Sensitive Gate Triacs

HAOPIN MICROELECTRONICS CO.,LTD.

MECHANICAL DATA

Dimensions in mm

Net Mass: 0.2 g

TO-92

| | DIMENSIONS | | | | | | | |
|------|------------|---------|------|-------|-------|-------|--|--|
| REF. | Mi | llimete | rs | | ; | | | |
| | Min. | Тур. | Max. | Min. | Тур. | Max. | | |
| А | | 1.35 | | | 0.053 | | | |
| В | | | 4.70 | | | 0.185 | | |
| С | | 2.54 | | | 0.100 | | | |
| D | 4.40 | | | 0.173 | | | | |
| Е | 12.70 | | | 0.500 | | | | |
| F | | | 3.70 | | | 0.146 | | |
| а | | | 0.50 | | | 0.019 | | |

