RAPID FIRE SOFTWARE

Rapid Fire Commander Wi-Fi

Bench setup handbook

Connect OneROM to TunerPro RT over Wi-Fi, with optional Holden ALDL logging through GT Pro.

Contents

Set up and connect 2

Configure TunerPro RT 3

Troubleshooting and bench results 4

Print and fold. In your PDF reader, choose Booklet, A4, both sides and left binding. If your printer asks which edge to flip, choose short edge. Fold the sheet down the middle.

Rapid Fire Commander Wi-Fi on GitHub

Set up and connect

The bench build targets the 4.3-inch Guition JC4880P443C_I_W/Y with 16 MB flash and ESP32-P4 silicon revisions 0.1 through 1.99. It uses the board's existing C6 radio firmware.

Before you start

Have the P4 with the Wi-Fi build installed, a compatible OneROM, a Windows laptop with the Commander Wi-Fi app and TunerPro RT, and a USB data cable for OneROM. For live logging, also have a GT Pro, the matching ADX and an ECU to read from.

Connect the laptop

1. Connect OneROM to **USB2** and power the P4 through **USB3**.

2. On the P4, open **OneROM > TunerPro bridge** for emulation, or **OneROM > TunerPro + GT Pro** to include Holden ALDL logging. Wait for **OneROM ready on USB2**.

3. In Windows, join the network shown on the P4's **Commander Wi-Fi** screen using the password displayed there.

4. Open the **Rapid Fire Commander Wi-Fi** Windows app and select **Connect**.

The Commander Wi-Fi Windows app has no trial timer.

Configure TunerPro RT

Commander presents two local RFC 2217 endpoints. Use your Windows virtual serial port provider to map the endpoints to COM ports, then select the assigned COM numbers in TunerPro RT.

TunerPro RT function	Local endpoint for the COM mapping
OneROM emulation	127.0.0.1:22170
GT Pro ALDL acquisition	127.0.0.1:22171

OneROM emulation

Select the COM port mapped to the OneROM endpoint for emulation. Use a BIN readback to check communication before making changes. For a full BIN upload, keep the engine off and verify the readback before starting it.

GT Pro and ADX logging

Choose **TunerPro + GT Pro** on the P4. Open **Settings > OBDX devices**, select the GT Pro and connect it. In TunerPro RT, select the separate acquisition COM port and load the ADX that matches your ECU and calibration. Start acquisition once the ECU is connected.

Close TunerPro RT before disconnecting the Windows app.

Troubleshooting and bench results

Peer disconnected

The P4 may still be waiting for OneROM. Check the USB2 connection and wait for **OneROM ready on USB2** before connecting from the Windows app.

Start a fresh session

Close TunerPro RT, disconnect the Commander Wi-Fi app and restart the P4. Select the bridge mode again, reconnect Windows to the dashboard's Wi-Fi, and select **Connect**.

TunerPro cannot see a COM port

Check the Windows COM mapping against the table on page 3. For GT Pro logging, use the acquisition COM port and confirm the GT Pro is connected and the correct ADX is loaded.

Bench results

The owner connected the Windows app over Wi-Fi, detected OneROM in TunerPro RT, and reported a successful BIN download and upload with no errors. The matching ADX loaded. Live GT Pro telemetry with an ECU connected remains to be verified on the Wi-Fi build.

Wi-Fi guide and updates on GitHub

Rapid Fire Software support