

1. Simulate the Connectivity Issue

1. Ensure the printer is powered on and working normally.
2. Unplug the printer's USB cable from the computer.
3. Wait a few seconds.

2. Verify the Problem in Device Manager

1. Press Windows + X and select Device Manager.
2. Expand Printers, Print queues, or Universal Serial Bus controllers.
3. Look for:
 - The printer disappearing from the list.
 - A device with a yellow warning icon (!) indicating a hardware problem.
 - An Unknown Device entry.

3. Reconnect the Printer

1. Plug the USB cable back into the computer.
2. Wait a few moments for Windows to attempt detection.

4. Use "Scan for Hardware Changes"

1. In Device Manager, click the Action menu.
2. Select Scan for hardware changes.
3. Observe whether the printer reappears under Printers or Print queues.

5. Resolve Any Remaining Issues

If the printer is still not detected:

1. Right-click the device with the warning icon (if present).
2. Select Update driver → Search automatically for drivers.

3. If that fails:

- Right-click the device and select Uninstall device.
- Click Action → Scan for hardware changes to reinstall it.

4. Verify the USB cable is firmly connected and try a different USB port if necessary.