

```

// NtfyNotifier.h

#define NODEMCU_FILE

#pragma once

#define PRIORITY_DEFAULT "3"
#define PRIORITY_URGENT "5"

#include "CsvOperations.h"

void NtfyNotify(const char *tags, const char *title, const char *message, const char
*priority);
void NotifyItemAdded(const InventoryRecordLine *record);
void NotifyItemDeleted(const char *box_id);

// NtfyNotifier.cpp

#include "NtfyNotifier.h"

#include "CsvOperations.h"
#include "ESP8266HTTPClient.h"
#include "IPAddress.h"
#include "WString.h"
#include "WiFiClient.h"

#include ".common/comm.h"
#include "sensitive_data.cpp"

void NtfyNotify(const char *tags, const char *title, const char *message, const char
*priority)
{
    const String topicPath = String("/") + String(NTFY_TOPIC);

    HTTPClient http;
    IPAddress ntfy_ip;
    WiFiClient esp_client;

    if (!http.begin(esp_client, String(NTFY_SERVER), NTFY_PORT, topicPath))
    {
        d_SerialPrintln("Fatal: HTTP connect failed.");
        http.end();
        return;
    }

    http.addHeader("X-Title", title);
    http.addHeader("X-Priority", priority);
    http.addHeader("X-Tags", tags);
    http.addHeader("Markdown", "yes");

    int http_response = http.POST(message);

    if (http_response > 0)

```

```

        d_SerialPrintf("NTFY Post success. Code %d\n", http_response);
    else
        d_SerialPrintf("NTFY Post Failed. Error %s(%d)\n",
http.errorToString(http_response).c_str(), http_response);

    http.end();
    yield();
}

void NotifyItemAdded(const InventoryRecordLine *record)
{
    String msg = String("**") + record->item_name + "** has been added to box **" +
record->box_id + "**.";
    NtfyNotify("white_check_mark,package", "Item Added", msg.c_str(), "default");
}

void NotifyItemDeleted(const char *box_id)
{
    String msg = String("Item in box **") + box_id + "** has been deleted from
inventory.";
    NtfyNotify("wastebasket", "Item Deleted", msg.c_str(), "default");
}

void BootNotify()
{
    time_t now = time(nullptr);
    struct tm *t = localtime(&now);
    char time_str[32];
    strftime(time_str, sizeof(time_str), "%d/%m/%Y %H:%M:%S", t);
    String msg = String("System booted successfully at **") + time_str + "**. Ready to
monitor inventory.";
    NtfyNotify("white_check_mark,rocket", "System Ready", msg.c_str(), "default");
}

```