## Reolink

## RLA-WE1(Wi-Fi Extender)

## AC1200 Dual-Band Mesh Wi-Fi Extender

- · 2.4/5 GHz Dual-Band Wi-Fi
- Up to 1,500 Sq.ft Coverage
- Easy to Set up
- · Supports Mesh mode with RLN12W



## **Specifications**

| Power Requirements  |   |  |
|---------------------|---|--|
| AC Power            | AC 220~240V 50/60Hz                             |  |
| Wi-Fi               |   |  |
| Wireless Standard   | IEEE 802.11 a/b/g/n/ac                          |  |
| Operating Frequency | 2.4GHz/5GHz                                     |  |
| Wireless Security   | WPA-PSK/WPA2-PSK                                |  |
| Hardware            |   |  |
| Signal Rate         | 2.4GHz: 300Mbps (2T2R); 5GHz:<br>867Mbps (2T2R) |  |
| Ethernet Port       | One 10M/100Mbps; RJ45                           |  |
| Antenna             | 2*5dBi External Antennas                        |  |
| Reset Button        | YES   |  |
| WPS Button          | YES   |  |
| Software            |   |  |
| OS Supported        | iOS, Android                                    |  |

| Working Environment                 |                          |  |
|-------------------------------------|--------------------------|--|
| Operating Temperature               | 0°C~40°C (32°F~104°F)    |  |
| Operating Humidity                  | 10% ~ 90%                |  |
| Mechanical                          |                          |  |
| Dimensions (Not Including Antennas) | 191 x 112 x 51mm         |  |
| Weight (Without Accessories)        | 138g                     |  |
| Warranty                            |                          |  |
| Limited Warranty                    | 2-year limited warranty. |  |