

Categorical Time-Series Analysis

General Notation

Let (X_t) be a *stationary categorical time series*, where each X_t takes values in

$$S = \{s_0, \dots, s_m\}, \quad m \in \mathbb{N}.$$

(X_t) may be *nominal*, in which case the order of the elements in S is arbitrary and solely useful for notational consistency, or *ordinal*, in which case the order of the elements in S reflects the inherent order of the elements. Stationarity requires

$$\begin{aligned} E(X_t) &= \mu_X & \forall t, \\ E(X_t^2) &< \infty & \forall t, \\ \text{Cov}(X_t, X_{t+h}) &= \gamma(h) & \forall t, h. \end{aligned}$$

Marginal Distributions

Since ordinal and nominal scales encode different types of information, their marginal distributions require different representations.

- **Ordinal data:** To integrate the order inherent to S we use the cumulative distribution function (CDF)

$$\mathbf{f} = (f_0, \dots, f_{m-1})^\top, \quad f_i := P(X_t \leq s_i).$$

- **Nominal data:** Since categories are unordered, we use the marginal probability mass function (PMF)

$$\mathbf{p} = (p_0, \dots, p_m)^\top, \quad p_i := P(X_t = s_i),$$

Bivariate Probabilities at Lag h

Temporal dependence can be described by bivariate (lag- h) probabilities:

- **Ordinal series (cumulative):**

$$f_{ij}(h) := P(X_t \leq s_i, X_{t+h} \leq s_j), \quad i, j < m.$$

- **Nominal series (joint):**

$$p_{ij}(h) := P(X_t = s_i, X_{t+h} = s_j), \quad i, j \leq m.$$

These quantities serve as input for dependence measures such as association coefficients or transition structures.

Location

For ordinal data, the measure of location is given by the median and for nominal data the mode

$$\begin{aligned} Med(X_{t \text{ (ord.)}}) &= \min(s_i \in S : F(s_i) \geq \frac{1}{2}) \\ Mod(X_{t \text{ (nom.)}}) &= s_i \in S : P(X_t = s_i) = \operatorname{argmax}(\mathbf{p}) \end{aligned}$$

Measures of Dispersion

Dispersion of categorical variables is commonly quantified via the *Index of Ordinal Variation* (IOV) for ordinal data and the *Index of Qualitative Variation* (IQV) for nominal data. Both measures take values in the interval $[0, 1]$, where 0 indicates no dispersion (degenerate one-point distribution) and 1 indicates maximal dispersion.

For ordinal variables, dispersion is defined in terms of the CDF vector $\mathbf{f}$:

$$\text{IOV} = \frac{4}{m} \sum_{i=0}^{m-1} f_i(1 - f_i), \text{ where } f_i = P(X_t \leq s_i)$$

For nominal variables, dispersion is defined in terms of the PMF $\mathbf{p}$:

$$\text{IQV} = \frac{m+1}{m} \left(1 - \sum_{i=0}^m p_i^2 \right), \quad p_i = P(X_t = s_i).$$

Minimal Dispersion

Both measures attain the value 0 if and only if the distribution is degenerate, that is, if all probability mass is concentrated in a single category.

Ordinal case. A one-point distribution is characterized by a CDF vector $\mathbf{f}$ of the form

$$\mathbf{f} \in \left\{ \begin{pmatrix} 1 \\ 1 \\ \vdots \\ 1 \end{pmatrix}, \begin{pmatrix} 0 \\ 1 \\ \vdots \\ 1 \end{pmatrix}, \dots, \begin{pmatrix} 0 \\ 0 \\ \vdots \\ 1 \end{pmatrix} \right\}.$$

In each case, at every index i either $f_i = 0$ or $f_i = 1$, hence

$$f_i(1 - f_i) = 0 \quad \forall i.$$

Therefore,

$$\text{IOV} = \frac{4}{m} \sum_{i=0}^{m-1} f_i(1 - f_i) = 0.$$

Nominal case. A degenerate distribution has a PMF of the form

$$\mathbf{p} \in \left\{ \begin{pmatrix} 1 \\ 0 \\ \vdots \\ 0 \end{pmatrix}, \begin{pmatrix} 0 \\ 1 \\ \vdots \\ 0 \end{pmatrix}, \dots, \begin{pmatrix} 0 \\ 0 \\ \vdots \\ 1 \end{pmatrix} \right\}.$$

Thus,

$$\sum_{i=0}^m p_i^2 = m \cdot 0 + 1 \cdot 1 = 1,$$

and therefore

$$\text{IQV} = \frac{m+1}{m}(1-1) = 0.$$

Maximal Dispersion

Ordinal case. Dispersion of an ordinal variable is maximal when half of the probability mass lies in the lowest category and half in the highest category; all intermediate categories receive probability zero. This results in a CDF vector

$$\mathbf{f} = \left(\frac{1}{2}, \frac{1}{2}, \dots, \frac{1}{2} \right)^\top.$$

Then

$$f_i(1-f_i) = \frac{1}{2} \left(1 - \frac{1}{2} \right) = \frac{1}{4} \quad \forall i,$$

and thus

$$\text{IOV} = \frac{4}{m} \cdot \sum_{i=0}^{m-1} \frac{1}{4} = \frac{4}{m} \cdot \frac{m}{4} = 1.$$

Nominal case. Maximal dispersion is obtained when probability mass is distributed uniformly across all $m+1$ categories:

$$p_i = \frac{1}{m+1}, \quad i = 0, \dots, m.$$

Then

$$\sum_{i=0}^m p_i^2 = (m+1) \frac{1}{(m+1)^2} = \frac{1}{m+1},$$

so that

$$\text{IQV} = \frac{m+1}{m} \left(1 - \frac{1}{m+1} \right) = \frac{m+1}{m} \cdot \frac{m}{m+1} = 1.$$

Samples Measures

For the estimation of the (cumulative) probabilities based on samples we use the (cumulative) relative frequencies, that can be best expressed if switching from (X_t) to its binarization ($(\mathbf{Z}_t)$ for ordinal variables, $(\mathbf{Y}_t)$ for nominal):

$$\mathbf{Z}_t = (Z_{t,0}, \dots, Z_{t,m-1})^T, Z_{t,i} = I_{\{X_t \leq s_i\}} \quad \mathbf{Y}_t = (Y_{t,0}, \dots, Y_{t,m})^T, Y_{t,i} = I_{\{X_t = s_i\}}$$

Now we can estimate $\mathbf{p}/\mathbf{f}$ by taking the mean about the binarization:

$$\hat{\mathbf{f}} = \frac{1}{n} \sum_{t=1}^n \mathbf{Z}_t, \quad \hat{\mathbf{p}} = \frac{1}{n} \sum_{t=1}^n \mathbf{Y}_t$$

To get the asymptotics of the different sample measures, we first need a CLT on $\hat{\mathbf{f}}/\hat{\mathbf{p}}$, 0 As our data are not (necesarily) independent, the CLT only holds for a stationary process that fullfills a strong mixing condition (e.g. alpha mixing; Bradley 2005). The stationarity of $\mathbf{Z}_t/\mathbf{Y}_t$ follows from the stationarity of X_t , as the transforming function is deterministic.

A sequence is said to be α -mixing, if:

For any event $A \in \sigma(X_s : s \leq t)$ and event $B \in \sigma(X_s : s \geq t + h)$ the α -coefficient $\alpha(h) = \sup |P(A \cup B) - P(A)P(B)|$ goes to 0 for $h \rightarrow \infty$

If α -mixing is satisfied it holds that:

$$\sqrt{n}(\widehat{\mathbf{Z}}_t - \mathbf{f}) \xrightarrow{d} \mathcal{N}(0, \Sigma), \quad \text{with } \Sigma = (\sigma_{i,j})_{i,j=0, \dots, m-1}$$

$$\text{where } \sigma_{i,j} = \text{Cov}(Z_{0,i}, Z_{0,j}) + \sum_{h=1}^{\infty} (\text{Cov}(Z_{0,i}, Z_{h,j}) + \text{Cov}(Z_{h,i}, Z_{0,j}))$$

$$\text{and } \text{Cov}(Z_{t,i}, Z_{s,j}) = \begin{cases} f_{ij}(t-s) - f_i f_j & \text{if } t \geq s \\ f_{ji}(s-t) - f_i f_j & \text{if } s \geq t \end{cases}$$

To now derive the asymptotics of the dispersion measures (scalar functions) we can apply the delta method (i.e. Theorem on 5.25 on Asymptotic Distribution of $g(\mathbf{X}_n)$ in the formulary) according to which the following holds:

$$n^{\frac{1}{2}}(IOV(\hat{\mathbf{f}}) - IOV(\mathbf{f})) \xrightarrow{d} \mathcal{N}(0, \mathbf{G}\Sigma\mathbf{G})$$

$$\text{Where } G_{1 \times m} = \left[\frac{\partial IOV(\mathbf{f})}{\partial \hat{f}_0}, \dots, \frac{\partial IOV(\mathbf{f})}{\partial \hat{f}_{m-1}} \right]'$$

The derivations for other dispersion metrics are analogous.

Modelling Missingness

To model the missingness amplitude modulation is used. The concept stems from physics and allows to model a stochastic process that runs concurrent to another one and modulates its amplitude. In the case of missingness the main process $(X_t)_t$ is either there or not there. Therefore we can define our amplitude modulating process as

$$O_t \in \{0, 1\} \quad \forall t$$

where $O_t = 1$ if (X_t) is observed and 0 if it isn't