POWERPOD LITE

22 kW

AC Fast Charger

Full speed. At home.

PRIVATE CHARGING

Document No.	**RD012**
Date	**December 2025**
Drafted by	**RIOD India**
Website	**riod.energy**

POWERPOD Lite 22 kW is a high-power personal EV charging station. Three-phase 22 kW fast charging for rapid overnight top-ups. Compatible with all EVs with Type 2 connectors.

Key Features

22 kW Type 2 Connector
Fastest AC charging for all 4-wheelers

RFID / Plug-and-Play
Controlled or open authentication modes

Full Protection Suite
OV, UV, OC, surge, ground fault, residual current (IGPC5)

LED Charging Indicator
LED strip shows real-time charging status

IP65 Weatherproof
Rated for indoor and outdoor installation

In-built Energy Meter
Class 1 accuracy metering

Applications

- Homes
- Apartments
- Private Offices
- Villas

Compatible Vehicles in India

Supports all EVs with Type 2 (IEC 62196) AC charging:

Brand	Models
TATA	Nexon EV, Nexon EV Max, Tiago EV, Tigor EV, Punch EV, Curvv EV, Harrier EV
MAHINDRA	XEV 9e, BE 6, XUV400
MG MOTOR	Windsor EV, ZS EV, Comet EV
HYUNDAI	Creta Electric, Ioniq 5, Kona Electric
MARUTI SUZUKI	e-Vitara
KIA	EV6, EV9
BMW	i4, iX1
MERCEDES-BENZ	EQC, EQE, G580 EQ
AUDI	Q4 e-tron, e-tron
VOLVO	EX40, XC40 Recharge, C40 Recharge
PORSCHE	Taycan
CITROEN	eC3
BYD	Atto 3, Seal, e6
VINFAST	Limo Green
LEXUS	RZ 450e

Technical Specifications

Product Information	
Charging Type	AC Level 2
Input/Output Rating	Three Phase: 22 kW / 32A
Input/Output Voltage	Three Phase: 415 V, 50 Hz
Socket Outlet	Type 2 (IEC 62196) with 5m Cable
Protection	OV, UV, OC, Short Circuit, Surge, OT, Ground Fault, Residual Current (IGPC5)
Energy Meter	In-built, Class 1 Accuracy

User Interface	
User Authentication	RFID / Plug-and-Play
Status Indications	LED Strip (Green – Charging, Orange – Idle, Red – Error)

General Characteristics	
IP Rating	IP65
Operating Temperature	–30 °C to 55 °C
Storage Temperature	–40 °C to 70 °C
Humidity	< 95%, non-condensing
Mounting	Wall Mount
Dimensions (H × W × D)	350 × 230 × 170 mm

Warranty	
Warranty Period	24 Months

For More Information

- EV Charger Selection Guide: https://riod.energy/ev-charger-selection-guide
- All Product Documents: https://riod.energy/resources
- Contact Us: hello@riod.in | +91 974 600 6455

riod.energy | hello@riod.in | +91 974 600 6455