POWERPOD LITE

3.3 kW

AC Charger

Affordable. Smart. Always ready.

PRIVATE CHARGING

Document No.	**RD010**
Date	**December 2025**
Drafted by	**RIOD India**
Website	**riod.energy**

POWERPOD Lite 3.3 kW is a compact AC charging dock designed for your home or private parking. Simple plug-and-play installation with RFID-based access control delivers a reliable, secure charging experience at an affordable price.

Key Features

Premium Quality
Reliable charging at an affordable price

Sleek & Compact
Minimal footprint, easy to install anywhere

IP65 Weatherproof
Rated for indoor and outdoor installation

LED Charging Indicator
LED strip shows real-time charging status

RFID / Plug-and-Play
Controlled or open authentication modes

Full Protection Suite
OV, UV, OC, surge, ground fault, residual current (IGPC5)

Applications

- Homes
- Apartments
- Private Offices
- Villas

Compatible Vehicles in India

Supports all EVs compatible with 3-PIN plug (16A) charging:

Brand	Models
TATA	Tiago EV, Tigor EV, Nexon EV, Nexon EV Max, Punch EV, Curvv EV
MAHINDRA	XUV400, XEV 9e, BE 6
MG MOTOR	Comet EV, Windsor EV, ZS EV
HYUNDAI	Creta Electric, Kona Electric
CITROEN	eC3
BYD	e6, Atto 3
KIA	EV6 (via portable EVSE)
MARUTI SUZUKI	e-Vitara (via portable EVSE)

Technical Specifications

Product Information	
Charging Type	Home Charging, AC Level 1
Input/Output Rating	Single Phase: 3.3 kW / 16A
Input/Output Voltage	Single Phase: 230 V, 50 Hz
Socket Outlet	16A 3-PIN Power Socket (with Shutter)
Protection	OV, UV, OC, Short Circuit, Surge, OT, Ground Fault, Residual Current (IGPC5)
Energy Meter	In-built, Class 1 Accuracy

User Interface	
User Authentication	RFID / Plug-and-Play
Status Indications	LED Strip (Green – Charging, Orange – Idle, Red – Error)

General Characteristics	
IP Rating	IP65
Operating Temperature	–30 °C to 55 °C
Storage Temperature	–40 °C to 70 °C
Humidity	< 95%, non-condensing
Mounting	Wall Mount
Dimensions (H × W × D)	350 × 230 × 170 mm
Weight	1.64 Kg

Warranty	
Warranty Period	24 Months

For More Information

- EV Charger Selection Guide: https://riod.energy/ev-charger-selection-guide
- All Product Documents: https://riod.energy/resources
- Contact Us: hello@riod.in | +91 974 600 6455

riod.energy | hello@riod.in | +91 974 600 6455