



FPVspeed™

DIY Module Series

FPV Video Receiver

FS3364R

3.3G 64CH

KEY FEATURES

- Channel: 64CH
- Power Supply: +5V
- High Sensitivity Reception: -97dBm
- High/Low Level Transition Channel
- Supports Soldering of 6-pin 1.27MM Dip Switch for Channel Switching
- Supports Secondary Development And DIY Enthusiasts
- Dimensions: L37 x W26.3mm

APPLICATIONS

- FPV Drone Racing
- UAV Communication Systems
- Remote Vehicle Monitoring
- Wireless Video Transmission Systems



THE CHANNEL TABLE

FS3364R Receiver Module Channel Setting Table

0 represents ground or low level, 1 represents floating or high level.			CH1	CH2	CH3	CH4	CH5	CH6	CH7	CH8
			CS3/CS2/ CS1	CS3/CS2/ CS1	CS3/CS2/ CS1	CS3/CS2/ CS1	CS3/CS2/ CS1	CS3/CS2/ CS1	CS3/CS2/ CS1	CS3/CS2/ CS1
			0/0/0	0/0/1	0/1/0	0/1/1	1/0/0	1/0/1	1/1/0	1/1/1
FR 1	S3/S2/S1	0/0/0	3360	3380	3400	3420	3440	3460	3480	3500
FR 2	S3/S2/S1	0/0/1	3200	3220	3240	3260	3280	3300	3320	3340
FR 3	S3/S2/S1	0/1/0	3330	3350	3370	3390	3410	3430	3450	3470
FR 4	S3/S2/S1	0/1/1	3170	3190	3210	3230	3250	3270	3290	3310
FR 5	S3/S2/S1	1/0/0	3320	3345	3370	3395	3420	3445	3470	3495
FR 6	S3/S2/S1	1/0/1	3310	3330	3355	3380	3405	3430	3455	3480
FR 7	S3/S2/S1	1/1/0	3220	3240	3260	3280	3300	3320	3340	3360
FR 8	S3/S2/S1	1/1/1	3060	3080	3100	3120	3140	3160	3180	3200