Predictor corrector method

Friday, 29 August 2025 9:04 AM

Milne's Predictor Corrector Method

Adam's k step explicit method ⇒

$$y_{n+1} = y_{n-l} + \sum_{m=0}^{k-1} \beta_m^{(l)} \nabla^m f_n$$

where $\beta_m^{(l)} = \int_{-l}^{1} (-1)^m \binom{-s}{m} ds = \int_{-l}^{1} \frac{s(s+1)\dots(s+m-1)}{m!} ds$

Taking $l = 3$, $k = 4$, we get

$$y_{n+1} = y_{n-3} + \sum_{m=0}^{3} \beta_m^{(3)} \nabla^m f_n$$

$$\beta_m^{(3)} = \int_{-3}^{1} \frac{s(s+1)\dots(s+m-1)}{m!} ds \qquad m = 0, 1, 2, 3$$

$$\beta_0^{(3)} = \int_{-3}^{1} ds = 4$$

$$\beta_1^{(3)} = \int_{-3}^{1} s\,ds = \frac{1-9}{2} = -4$$

$$\beta_2^{(3)} = \int_{-3}^{1} \frac{s(s+1)}{2} ds = \int_{-3}^{1} \frac{s^2+s}{2} ds = \left(\frac{1+27}{6} + \frac{1-9}{4}\right) = \frac{\cancel{28}^{14}}{\cancel{6}_{3}} - 2 = \frac{8}{3}$$

$$\beta_3^{(3)} = \int_{-3}^{1} \frac{s(s+1)(s+2)}{6} ds = \int_{-3}^{1} \frac{s^3+3s^2+2s}{6} ds = \frac{1-81}{24} + \frac{1+27}{6} + \frac{1-9}{6} = -\frac{\cancel{80}^{10}}{\cancel{24}_{3}} + \frac{\cancel{28}^{14}}{\cancel{6}_{3}} - \frac{\cancel{8}^{4}}{\cancel{6}_{3}} = 0$$

m	0	1	2	3
$\beta_m^{(3)}$	4	-4	$8/3$	0

$$y_{n+1} = y_{n-3} + h\left[4f_n - 4\nabla f_n + \frac{8}{3}\nabla^2 f_n\right]$$
$$= y_{n-3} + h\left[\cancel{4f_n} - 4(\cancel{f_n} - f_{n-1}) + \frac{8}{3}(f_n - 2f_{n-1} + f_{n-2})\right]$$
$$= y_{n-3} + h\left[\frac{8}{3}f_n - \frac{4}{3}f_{n-1} + \frac{8}{3}f_{n-2}\right]$$

$$\boxed{y_{n+1} = y_{n-3} + \frac{4}{3}h\left[2f_n - f_{n-1} + 2f_{n-2}\right]}$$

This is called Milne's Predictor formula. It is of order 4.

Milne's corrector formula → Adam's k step implicit formula is given by

$$y_{n+1} = y_{n-l} + \sum_{m=0}^{k} \gamma_m^{(l)} \nabla^m f_{n+1}$$

where $\gamma_m^{(l)} = \int_{-l}^{1} (-1)^m \binom{1-s}{m} ds = \int_{-l}^{1} \frac{(s-1)s\dots(s+m-2)}{m!} ds$

Take $l = 1$, $k = 3$

$$y_{n+1} = y_{n-1} + h\sum_{m=0}^{3} \gamma_m^{(1)} \nabla^m f_{n+1}, \text{ where}$$

$$\gamma_m^{(1)} = \int_{-1}^{1} \frac{(s-1)s\dots(s+m-2)}{m!} ds \qquad m = 0, 1, 2, 3$$

$$\gamma_0^{(1)} = \int_{-1}^{1} ds = 2$$

$$\gamma_1^{(1)} = \int_{-1}^{1} (s-1)\,ds = \left(\frac{s^2}{2} - s\right)\Big|_{-1}^{1} = -2$$

$$\gamma_2^{(1)} = \int_{-1}^{1} \frac{(s^2-s)}{2} ds = \frac{1}{3}$$

$$\gamma_3^{(1)} = 0$$

m	0	1	2	3
$\gamma_m^{(1)}$	2	-2	$1/3$	0

$$\boxed{y_{n+1} = y_{n-1} + \frac{h}{3}\left[f_{n+1} + 4f_n + f_{n-1}\right]}$$

This is called Milne's corrector formula. It is of order 4.

The Milne's P-C pair (Predictor-corrector pair) is defined as

$P:\ y_{n+1} = y_{n-3} + \frac{4}{3}h\left[2f_n - f_{n-1} + 2f_{n-2}\right]$

$C:\ y_{n+1} = y_{n-1} + \frac{h}{3}\left[f_{n+1} + 4f_n + f_{n-1}\right]$

(looks like Simpson's one-third rule)

Predictor corrector schemes →

① PECE scheme - This is explained as follows →

i) P - Find an approx. for y_{n+1} using the predictor formula and denote it by $y_{n+1}^{(P)}$.

ii) E - Evaluate $f(x_{n+1}, y_{n+1}^{(P)}) = f_{n+1}^{(P)}$

iii) C - Find the new approx. for y_{n+1} by using $f_{n+1} = f(x_{n+1}, y_{n+1}^{(P)})$ on RHS of corrector formula. Denote it by $y_{n+1}^{(C)}$.

iv) Evaluate $f_{n+1}^{(C)} = f(x_{n+1}, y_{n+1}^{(C)})$

We then go to the next step / iteration / nodal point.

Solution at x_{n+2} ⇒

$P:\ y_{n+2}^{(P)} = y_{n-2} + \frac{4}{3}h\left[2f_{n+1}^{(C)} - f_n + 2f_{n-1}\right]$

$E:\ f_{n+2}^{(P)} = f(x_{n+2}, y_{n+2}^{(P)})$

$C:\ y_{n+2}^{(C)} = y_{n-2} + \frac{h}{3}\left[f_{n+2}^{(P)} + 4f_{n+1}^{(C)} + f_n\right]$

$E:\ f_{n+2}^{(C)} = f(x_{n+2}, y_{n+2}^{(C)})$

Then go to the next step.

② P(EC)^{2}E Scheme PECECE



P: predict Find $y_{n+1}^{(0)} = y_{n+1}^{(P)}$

E: Evaluate $f_{n+1}^{(0)} = f(x_{n+1}, y_{n+1}^{(0)})$

C: Find $y_{n+1}^{(1)} = y_{n+1}^{(1)}$

E: Evaluate $f_{n+1}^{(1)} = f(x_{n+1}, y_{n+1}^{(1)})$

C: Find $y_{n+1}^{(2)} = y_{n+1}^{(2)}$

E: Find $f_{n+1}^{(2)} = f(x_{n+1}, y_{n+1}^{(2)})$

And then proceed to Next Step.



1. P: Predict
   $y_{n+1}^{(0)} = y_n +$ (Predictor formula using $f_n, f_{n-1}, \dots$)
2. E: Evaluate
   $f_{n+1}^{(0)} = f(x_{n+1}, y_{n+1}^{(0)})$
3. C: Correct (1st correction)
   $y_{n+1}^{(1)} = y_n +$ (Corrector formula using $f_{n+1}^{(0)}, f_n, f_{n-1}, \dots$)
4. E: Evaluate again
   $f_{n+1}^{(1)} = f(x_{n+1}, y_{n+1}^{(1)})$
5. C: Correct (2nd correction)
   $y_{n+1}^{(2)} = y_n +$ (Corrector formula using $f_{n+1}^{(1)}, f_n, f_{n-1}, \dots$)
6. E: Final evaluation
   $f_{n+1}^{(2)} = f(x_{n+1}, y_{n+1}^{(2)})$

Then proceed to the next step with $y_{n+1}^{(2)}$ and $f_{n+1}^{(2)}$.

In this, for the next iteration, the evaluated value of fn+1 using yn+1(P) is used, instead of the one using yn+1(C) like in PECE.

③ PEC scheme



P(EC) Scheme

P: predict y_{n+1} and denote it by $y_{n+1}^{(P)}$

E: Evaluate $f_{n+1}^{(P)} = f(x_{n+1}, y_{n+1}^{(P)})$

C: Find $y_{n+1}^{(C)}$ from the Corrector formula

Go to Next Step

We also have PECEC = P(EC)^2 scheme.

Simplest predictor-corrector method

$P:\ y_{n+1} = y_n + hf(x_n, y_n)$ 1st order

$C:\ y_{n+1} = y_n + \frac{h}{2}\left[f_{n+1} + f\right]$ 2nd order

PECE →

$P:\ y_1^{(P)} = y_0 + hf(x_0, y_0)$

$E:\ f_1^{(P)} = f(x_1, y_1^{(P)})$

$C:\ y_1^{(C)} = y_0 + \frac{h}{2}\left[f_1^{(P)} + f_0\right]$

$E:\ f_1^{(C)} = f(x_1, y_1^{(C)})$

Proceed to next step.

Problem Use Milne's predictor-corrector method to obtain the solution of $y' = f(x, y)$ at $x = 1.2$ and $x = 1.5$ given that $y(0) = 0$, $y(0.3) = 0.04986$, $y(0.6) = 0.2221$, $y(0.9) = 0.5596$ using PECE scheme.
(If nothing is mentioned, PECE is default scheme).

* If initial values not given, use single step method to find them.

Solution $P:\ y_{n+1} = y_{n-3} + \frac{4}{3}h\left[2f_n - f_{n-1} + 2f_{n-2}\right]$

$C:\ y_{n+1} = y_{n-1} + \frac{1}{3}h\left[f_{n+1} + 4f_n + f_{n-1}\right]$

$n = 3$ $P:\ y_4 = y_0 + \frac{4h}{3}\left[2f_3 - f_2 + 2f_1\right]$

$C:\ y_4 = y_2 + \frac{h}{3}\left[f_4 + 4f_3 + f_2\right]$

$f(x, y) = x + y$ [given]

$f_1 = f(x_1, y_1) = x_1 + y_1 = 0.3 + 0.0499 = 0.3499$

$f_2 = 0.8221$

$f_3 = 1.4596$

$P:\ y_4^{(P)} = 0 + \frac{4}{3} \times 0.3\,(2 \times 1.4596 - 0.8221 + 2 \times 0.3499) = 1.1187$

$E:\ f_4^{(P)} = f(x_4, y_4^{(P)}) = 1.2 + 1.1187 = 2.3187$

$C:\ y_4^{(C)} = 0.2221 + \frac{0.3}{3}\left[2.3187 + 4 \times 1.4596 + 0.8221\right] = 1.1200$

$E:\ f_4^{(C)} = f(x_4, y_4^{(C)}) = 1.2 + 1.1200 = 2.3200$

$$\boxed{y(1.2) \sim y_4^{(C)} = 2.3200}$$

Now, for $n = 4$ ⇒

$P:\ y_5^{(P)} = y_1 + \frac{4h}{3}\left[2f_4^{(C)} - f_3 + 2f_2\right]$

$C:\ y_5^{(C)} = y_3 + \frac{h}{3}\left[f_5^{(P)} + 4f_4^{(C)} + f_3\right]$

$f_2 = 0.8221$, $f_3 = 1.4596$, $f_4^{(C)} = f_4 = 2.3200$

$P:\ y_5^{(P)} = 0.04987 + \frac{4 \times 0.3}{3}\left[2 \times 2.3200 - 1.4596 + 2 \times 0.8221\right] = 1.9798$

$E:\ f_5^{(P)} = f(x_5, y_5^{(P)}) = 1.5 + 1.9798 = 3.4798$

$C:\ y_5^{(C)} = 0.5596 + \frac{0.3}{3}\left[3.4798 + 2.32 \times 2 + 1.4596\right] = 1.9816$

$E:\ f_5^{(C)} = 1.5 + 1.9816 = 3.4816$



k	0	1	2	3	4	5
x_k	0	0.3	0.6	0.9	1.2	1.5
y_k	0	0.0498	0.2221	0.5596	1.1200	1.9816

$y' = f(x, y)$ $y(x_0) = y_0$

$$\int_{x_{n-1}}^{x_{n+1}} y'\,dx = \int_{x_{n-1}}^{x_{n+1}} f(x, y(x))\,dx$$

↳ Approximate by Simpson's $\frac{1}{3}$ rule

$$y(x_{n+1}) - y(x_{n-1}) \approx \frac{h}{3}\left[f(x_{n-1}, y_{n-1}) + 4f(x_n, y_n) + f(x_{n+1}, y_{n+1})\right]$$

$$\Rightarrow y_{n+1} = y_{n-1} + \frac{h}{3}\left[f_{n-1} + 4f_n + f_{n+1}\right]$$

This is Milne's corrector method (a 2 step method).

General linear k step method

$$\boxed{\sum_{j=0}^{k} \alpha_j y_{n+j} = h\sum_{j=0}^{k} \beta_j f(x_{n+j}, y_{n+j})} \quad -①$$

$\alpha_0, \alpha_1, \dots, \alpha_k$ and $\beta_0, \beta_1, \dots, \beta_k$ are real constants such that $\alpha_0^2 + \beta_0^2 \neq 0 \Leftrightarrow |\alpha_0| + |\beta_0| \neq 0$ [To ensure it is k step]

[$\beta_k = 0$ → explicit method, $\beta_k \neq 0$ → Implicit method] $\alpha_k \neq 0$

Why linear? Uses only linear combinations of $\{y_n\}$, $\{f(x_n, y_n)\}$

Eg. 4 step Adams Bashforth method

$$y_{n+4} = y_{n+3} + \frac{1}{24}h\left[55f_{n+3} - 59f_{n+2} + 37f_{n+1} - 9f_n\right]$$

is an example of an explicit 4 step general linear method.

4 step Adam Moulton method

$$y_{n+4} = y_{n+3} + \frac{1}{24}\left[9f_{n+4} + 19f_{n+3} - 5f_{n+2} - 9f_{n+1}\right]$$

is an eg. of implicit 4 step method.

Zero stability

A linear k step method is said to be zero stable if ∃ a const. K s.t. for any 2 seq. $\{y_n\}$, $\{\tilde{y}_n\}$ which have been generated by the same formula but diff. initial data as $y_0, y_1, \dots, y_{k-1}$ and $\tilde{y}_0, \tilde{y}_1, \dots, \tilde{y}_{k-1}$ respectively, we have

$$\boxed{|y_n - \tilde{y}_n| \leq M \max\{|y_0 - \tilde{y}_0|, |y_1 - \tilde{y}_1|, \dots, |y_{k-1} - \tilde{y}_{k-1}|\}}$$

A general k step method in ①, consider its 1st & 2nd characteristic polynomial respectively.

$$\rho(z) = \sum_{j=0}^{k} \alpha_j z^j$$

$$\sigma(z) = \sum_{j=0}^{k} \beta_j z^j \qquad \text{where } \alpha_k \neq 0,\ \alpha_0^2 + \beta_0^2 \neq 0$$

A linear multistep method is zero stable for any ODE of the form $y' = f(x, y)$ where f satisfies the Lipschitz condition $|f(x, y) - f(x, z)| \leq L|y - z|$ iff its 1st characteristic polynomial



(Theorem) A linear multistep method is zero stable for any ODE of the form $y' = f(x, y)$ where f satisfies the Lipschitz condition $|f(x,y) - f(x,z)| \leq L|y - z|$ iff (if and only if) (necessary & sufficient condition) its first characteristic polynomial ⟺ has all zeros inside the closed unit disc, with any which lies on the unit circle being simple.

Roots of 1st characteristic polynomial lie inside the closed unit disc & those on the circle are simple, is often called root condition. (multiplicity = 1)



Roots of first characteristic polynomial lie in the closed unit disc and those on the circle are simple, is often called Root Condition.

Proof Necessary. Consider k-step LMM (linear multistep method), applied to $y' = 0$

$\alpha_k y_{n+k} + \alpha_{k-1} y_{n+k-1} + \dots + \alpha_1 y_{n+1} + \alpha_0 y_n = 0 \rightarrow ①$

The general solution of k-th order difference equation



$y_n = \sum_s p_s(n) z_s^n \rightarrow ②$

Here z_s is a zero of the first characteristic polynomial $\rho(z)$, and the polynomial $p_s(\cdot)$ has degree one less than the multiplicity of the zero.



Clearly, if $|z_s| > 1$, then there are starting values for which the corresponding solutions grow like $|z_s|^n$ and if its multiplicity is $m > 1$, then the solutions are growing like n^{m-1}

In either case, there are solutions that grow unbounded as $n \to \infty$ i.e., $h \to 0$ with fixed nh.

Considering the starting data $y_0, y_1, \dots, y_{k-1}$ which give rise to such an unbiased solution y_n and the starting data $\hat{y}_0 = \dots = \hat{y}_{k-1} = 0$ for which the corresponding solution is $\hat{y}_n$ with $\hat{y}_n = 0$ ∀n, we see that

$$|y_n - \hat{y}_n| \leq K \max\{|y_0 - \hat{y}_0|, \dots, |y_{k-1} - \hat{y}_{k-1}|\}$$

cannot hold.

∴ If the root condition is violated, zero stability is not possible.

Sufficient - This proof is too long & technical.

LMM (linear multistep method)

Eg. $11y_{n+3} + 27y_{n+2} - 27y_{n+1} - 11y_n = 3h\left[f_{n+3} + 9f_{n+2} + 9f_{n+1} + f_n\right]$

is not zero stable.

First char. polynomial $\rho(z) = 11z^3 + 27z^2 - 27z - 11$ has roots $z_1 = 1$, $z_2 \approx -0.3181$, $z_3 \approx -3.1356$

$|z_3| > 1$

$$\sum_{j=0}^{k} \alpha_j y_{n+j} = h\sum_{j=0}^{k} \beta_j f(x_{n+j}, y_{n+j}) = h\sum_{j=0}^{k} \beta_j f_{n+j} \qquad [f_{n+j} = f(x_{n+j}, y_{n+j})]$$

General LMM

$$\alpha_k y_{n+k} + \alpha_{k-1} y_{n+k-1} + \dots + \alpha_0 y_n = h\{\beta_k f_{n+k} + \beta_{k-1} f_{n+k-1} + \dots + \beta_0 f_n\} \quad -①$$

If E is the shift operator ⇒

$E^0 = I \rightarrow y_n$

$E y_n = y_{n+1}$

⋮

$E^k y = y_{n+k}$

$$(\alpha_k E^k + \alpha_{k-1} E^{k-1} \dots + \alpha_0 I) y_n = h[\beta_k E^k + \beta_{k-1} E^{k-1} \dots \beta_0 I] f_n$$

Let

$\rho(E) = \alpha_k E^k + \alpha_{k-1} E^{k-1} + \dots + \alpha_0 I$

$\sigma(E) = \beta_k E^k + \beta_{k-1} E^{k-1} + \dots + \beta_0 I$

$\rho(E) y_n = h\sigma(E) f_n$

$\rho(E) y_n - h\sigma(E) f_n = 0$

Apply this to $y' = \lambda y$ (test eq.) ⇒

$\rho(E) y_n - h\sigma(E)\lambda y_n = 0$ This is difference eq. of k-th order.

Its characteristic eq. is (let $\lambda h = \bar{h}$)

$$\rho(\xi) - \bar{h}\sigma(\xi) = 0$$

$\pi(\xi, \bar{h}) = \rho(\xi) - \bar{h}\sigma(\xi)$ −(*) ⇒ stability polynomial of ①

Let the roots of char. polynomial be $\xi_1, \xi_2, \dots, \xi_k$.

Def 1. An LMM ① is said to be absolutely stable if $|\xi_j| < 1$ ∀ $j = 1, 2, \dots, k$ where ξ_j is a root of (*).

2. If $|\xi_j| < |\xi_1|$ ∀ $j = 2, 3, \dots, k$, then ξ_1 is the root which tends to ±1 as $h \to 0$ (relatively stable).

3.



Interval of absolute stability: An interval (α, β) of the real line is called an interval of absolute stability, if the method is absolutely stable for all $\bar{h} \in (\alpha, \beta)$.

Interval of Relative stability.

4. The method ① is said to be strongly stable if the modulus of no root of $\rho(\xi)$ [1st char. polynomial] exceeds 1 & the roots of modulus 1 must be simple.

5. Weakly stable - Method ① is said to be weakly stable if the roots with unit modulus are not simple.



Absolute stability ⇒ Strong stability

Weak stability ⇒ Conditional stability

$y_{n+2} - 5y_{n+1} + 6y_n = f(n)$ — difference equation

$\Delta^2 y_n - 2\Delta y_n + 2y_n = f(n)$

Homogeneous $y_{n+2} - 5y_{n+1} + 6y_n = 0$

$Y_{n+2} - 5Y_{n+1} + 6Y_n = 0$

$(E^2 - 5E + 6) y_n = 0$

Put $y_n = \xi^n k$

$y_{n+1} = \xi^{n+1}$, $y_{n+2} = \xi^{n+2}$

$$(\xi^2 - 5\xi + 6) y_n = 0 \Rightarrow \xi = 2, 3$$



$(E^2 - 5E + 6) y_n = 0$

Put y_n ~

$y_n = \zeta^n k$ where

$y_{n+1} = \zeta^{n+1}$, $y_{n+2} = \zeta^{n+2}$

$(\zeta^2 - 5\zeta + 6) y_n = 0$ → char. polynomial / auxiliary equation

$(\zeta - 2)(\zeta - 3) = 0$

$\zeta = 2, 3$

$y_n = C_1 2^n + C_2 3^n$

C_1, C_2 are const.

$(\zeta^2 - 2\zeta + 1) y_n = 0$

$(\zeta - 1)^2 = 0$

$\zeta = 1, 1$

$y_n = (C_1 + C_2 n) 1^n.$

General methods for locating intervals of absolute stability

1. Schur criterion
2. Routh-Hurwitz criterion

1. Consider the polynomial

$\phi(r) = c_k r^k + \dots + c_1 r + c_0$ $\quad c_k \neq 0$, $c_0 \neq 0$

with complex coeff. The polynomial ϕ is said to be Schur polynomial if each of its roots r_s satisfies $|r_s| < 1$, $s = 1, \dots, k$

Let us consider the polynomial

$\hat{\phi}(r) = \bar{c}_0 r^k + \bar{c}_1 r^{k-1} + \dots + \bar{c}_k$ where $\bar{c}$ denotes complex conjugate of c.

Further, we denote

$$\phi_1(r) = \frac{1}{r}\left[\hat{\phi}(0)\phi(r) - \phi(0)\hat{\phi}(r)\right]$$

Degree of $\phi_1 \leq k - 1$

Theorem (Schur's criterion) The polynomial ϕ is Schur polynomial iff $|\hat{\phi}(0)| > |\phi(0)|$ and ϕ_1 is a Schur polynomial.

2. Consider the mapping $z = \frac{r-1}{r+1}$ of the open disc $|r| < 1$ of complex r-plane to left half plane $Re(z) < 0$ of complex z-plane.

Inverse map ⇒ $r = \frac{1+z}{1-z}$

Under this transformation, the function $\pi(r, \bar{h}) = \rho(r) - \bar{h}\sigma(r)$ becomes

$$\pi(z, \bar{h}) = \rho\left(\frac{1+z}{1-z}\right) - \bar{h}\sigma\left(\frac{1+z}{1-z}\right) \qquad (\bar{h} = \lambda h)$$

Multiply by $(1-z)^k$ ⇒ We get a polynomial of the form

$$a_0 z^k + a_1 z^{k-1} + \dots + a_k \quad -(**)$$



The roots of the stability polynomial $\pi(r, \bar{h})$ lie inside the open disc $|r| < 1$ if and only if the roots of the polynomial (**) lie on the left half plane $Re\,z < 0$.
(Routh-Hurwitz Criterion)

The root of (**) lie in the open left half plane iff all the principal minors of the k×k matrix

$$Q = \begin{bmatrix} a_1 & a_3 & a_5 & \dots & a_{2k-1} \\ a_0 & a_2 & a_4 & \dots & a_{2k-2} \\ 0 & a_1 & a_3 & \dots & a_{2k-3} \\ 0 & a_0 & a_2 & \dots & a_{2k-4} \\ \vdots & & & & \\ 0 & 0 & \dots & & a_k \end{bmatrix}$$

Determinants of the top left square matrices are the principal minors.

are +ve and $a_0 > 0$, we assume $a_j = 0$ if $j > k$.

1) For $k = 2$: $a_0 > 0$, $a_1 > 0$, $a_2 > 0$
2) For $k = 3$: $a_0 > 0$, $a_1 > 0$, $a_1 a_2 - a_3 a_0 > 0$
3) For $k = 4$: $a_0 > 0$, $a_1 > 0$, $a_1 a_2 - a_3 a_0 > 0$, $a_1 a_2 a_3 - a_0 a_3^2 - a_4 a_1^2 > 0$

This represents necessary & sufficient condition for ensuring that the roots of (**) lie on the open left half plane.

[Asymptotic stability → A-stability]

$$\sum_{j=0}^{k} \alpha_j y_{n+j} = h\sum_{j=0}^{k} \beta_j f_{n+j} \quad -(I)$$

$$\Rightarrow \alpha_k y(x + kh) + \alpha_{k-1} y(x + (k-1)h) + \dots + \alpha_0 y(x) - h\left[\beta_k y'(x + kh) + \beta_{k-1} y(x + (k-1)h) + \dots + \beta_0 y'(x)\right]$$
$$= \underset{\text{This may be regarded as a linear operator that acts on any diff. function } y(x).}{L}(y(x), h) \quad -①$$

Expand $L(y(x), h)$ in powers of h ⇒

$$y(x + mh) = y(x) + mhy'(x) + \frac{(mh)^2}{2!}y''(x) + \dots$$

$$hy(x + mh) = hy(x) + mh^2 y'(x) + \frac{m^2 h^3}{2!}y''(x) + \dots$$

It turns out that

$$L(y(x), h) = c_0 y(x) + c_1 h y'(x) + \dots + c_v h^v y^{(v)}(x) \dots \quad -②$$

Here the coeff. $c_0, c_1, \dots$ do not depend on the choice of function $y(x)$.

$c_0 = \alpha_0 + \alpha_1 + \dots + \alpha_k$

$c_1 = \alpha_1 + 2\alpha_2 + \dots + k\alpha_k - (\beta_0 + \beta_1 + \dots + \beta_k)$

⋮

$$c_q = \frac{1}{q!}(\alpha_1 + 2^q\alpha_2 + \dots + k^q\alpha_k) - \frac{1}{(q-1)!}(\beta_1 + 2^{q-1}\beta_2 + \dots + k^{q-1}\beta_k)$$

Order if A given diff. operator ② is said to be order p if $c_0 = c_1 = \dots = c_p = 0$ but $c_{p+1} \neq 0$

① is equivalent to

$$\alpha_k y_{n+t+k} + \dots + \alpha_0 y_{n+t} = h(\beta_k f_{n+t+k} + \dots + \beta_0 f_{n+t}) \quad -③$$

Here t is any integer. We may associate ③ with the diff. operator

$$L_t[y(x), h] = \alpha_k y_{n+t+k} + \dots + \alpha_0 y_{n+t} - h\left[\beta_k f_{n+t+k} + \dots + \beta_0 f_{n+t}\right]$$

$$L_t[y(x), h] = \alpha_k y(x + (t+k)h) + \dots + \alpha_0 y(x + th) - h\left[\beta_k f(x + (t+k)h) + \dots + \beta_0 f(x + th)\right] \quad -④$$

and we define the order as the order of the 1st non vanishing term with Taylor's expansion in powers of h minus 1.

It is an imp. fact that order p & constant c_{p+1} do not depend on t. For, expanding ④ in powers of h is equivalent to expanding ② in h, just, $y(x)$ is now replaced by $y(x + th)$.

We find that if L is of order p, then $L_t(y(x), h) = L(y(x + th), h) = c_{p+1} h^{p+1} y^{(p+1)}(y + th) + O(h^{p+2})$

since $y(x)$ is assumed sufficiently diff., $y^{(p+1)}(x + th) = y^{(p+1)}(x) + O(h)$

$$L_t(y(x + th), h) = c_{p+1} h^{p+1} y^{(p+1)}(x) + O(h^{p+2})$$

∴ Order remains the same.

Error constant of ① is $c = \frac{c_{p+1}}{\beta_0 + \beta_1 + \dots \beta_k}$

Consistency If $p \geq 1$, method ① is said to be consistent. i.e., $c_0 = c_1 = 0$, or $\rho(1) = 0$ and $\rho'(1) = \sigma(1)$

[ρ and σ are 1st & 2nd char. poly.]

$p \geq 1$ ⇒ Condition of consistency.

Truncation error of the LMM ① is defined as ⇒

$$T_n = \frac{\sum_{j=0}^{k} \alpha_j y(x_{n+j}) - \sum_{j=0}^{k} \beta_j y'(x_{n+j})}{h\sum_{j=0}^{k} \beta_j} \quad -(II)$$

$\sigma(1) = \sum \beta_j \neq 0$

The numerical scheme (I) is said to be consistent with the diff. equation $y' = f(x, y)$ if the TE (II) is s.t. for any $\varepsilon > 0$, ∃ $h(\varepsilon)$ for which $|T_n| < \varepsilon$ for $0 < h < h(\varepsilon)$

and any k+1 points $(x_n, y_n) \dots (x_{n+k+1}, y_{n+k+1})$ or any solution of IVP $y' = f(x, y)$, $y(x_0) = y_0$



Order order of accuracy p.

$|T_n| \leq Kh^p$. $0 < h \leq h_0$

From ② $T_n = \frac{1}{h\sigma(1)}\left[c_0 y(x_n) + c_1 h y'(x_n) + \dots + c_p h^p y^{(p)}(x_n) + \dots\right]$

where $c_0 = \sum_{j=0}^{k} \alpha_j$

$c_1 = \sum_{j=1}^{k} j\alpha_j - \sum_{j=0}^{k} \beta_j$

$c_2 = \sum_{j=1}^{k} \frac{j^2}{2!}\alpha_j - \sum_{j=0}^{k} j\beta_j$

$c_q = \sum_{j=1}^{k} \frac{j^q}{q!}\alpha_j - \sum_{j=0}^{k} \frac{j^{q-1}}{(q-1)!}\beta_j$