

DC Absence-of-Voltage Checks (Reference Procedure)

Before you start — equipment preparation:

Set the Fluke to DC. · Set the Proving Unit to DC.

Step	What to do	Expected reading
1. Prove meter on DC source (LIVE)	Place the Fluke test leads on the proving unit and confirm the meter displays the expected reading.	240 V
2. DC dead checks	With the Fluke in DC mode, place the test leads across: A-B, A-C, B-C, A-G, B-G, C-G, A-N, B-N, C-N, N-G. Verify each reads zero.	0.0 V (all)
3. Re-prove meter on DC source (LIVE)	With the Fluke still in DC mode, test the proving unit again and confirm the meter still reads 240 V. This confirms the meter is still working.	240 V