

SmartBrew X200 Coffee Maker

User Manual & Troubleshooting Guide

1. Overview

The SmartBrew X200 is a programmable drip coffee maker with a 12-cup glass carafe, built-in burr grinder, and Wi-Fi connectivity for scheduling brews from the SmartBrew app. The unit operates on 120V AC and draws a maximum of 1200W during brewing and grinding.

2. Setup Instructions

Remove all packaging materials before first use. Rinse the carafe and filter basket with warm water. Fill the water reservoir to the desired line, insert a paper filter or the reusable mesh filter, and add ground coffee or whole beans if using the built-in grinder. Press the POWER button to turn the unit on, then press BREW to begin.

3. Technical Specifications

Specification	Value
Power	120V AC, 60Hz, 1200W max
Carafe Capacity	12 cups (1.8 liters)
Grinder Type	Conical burr
Wi-Fi	802.11 b/g/n, 2.4GHz only
Warranty	2 years limited
Dimensions	9.5 in W x 14 in D x 13 in H
Weight	6.8 lbs

4. Troubleshooting

If the machine does not power on, check that it is plugged into a working outlet and that the reservoir lid is fully closed, as the safety switch prevents operation when the lid is open. If the coffee tastes weak, increase the grind setting toward FINE or use the STRONG brew mode. If the Wi-Fi light blinks red, the unit has failed to connect to the network; hold the WIFI button for 5 seconds to reset the connection and re-pair using the SmartBrew app.

5. Cleaning and Maintenance

Descale the machine every 60 brew cycles using a 1:1 mixture of white vinegar and water run through a normal brew cycle without coffee, followed by two cycles of plain water. Wipe the exterior with a damp cloth only; do not immerse the base unit in water. The carafe and filter basket are top-rack dishwasher safe.

6. Warranty Information

The SmartBrew X200 is covered by a 2 year limited warranty against defects in materials and workmanship from the date of purchase. The warranty does not cover damage from descaling neglect, unauthorized repairs, or use with voltages other than 120V AC. Contact support@smartbrew-example.com with your order number to initiate a warranty claim.