WeatherStation PRO

SMARTPHONE WI-FI & WEATHER LOCATION SETUP GUIDE
Firmware: Aurora Build 0009.2

Connect your station to home Wi-Fi, update your Wi-Fi password, and change the city used for weather forecasts.

1 Connect your smartphone to WeatherStation PRO

1. Turn on your WeatherStation PRO.

2. On the touchscreen, open Settings and select Change Wi-Fi.

3. On your smartphone, open Settings → Wi-Fi.

4. Connect to WeatherStation_Setup (no password required).

5. If the phone warns “No Internet Connection,” choose to stay connected.

6. Open your smartphone browser and enter http://192.168.4.1.

SETUP NETWORK: WeatherStation_Setup | ADDRESS: http://192.168.4.1

2 Configure your home Wi-Fi

1. On the configuration page, enter your home Wi-Fi network name (SSID).

2. Enter your home Wi-Fi password.

3. Tap Save and restart.

4. Wait for the station to restart and connect to your home network.

Important: Use a compatible 2.4 GHz Wi-Fi network. The temporary WeatherStation_Setup network has no password; the password you enter is for your home router.

3 Change your Wi-Fi password or router

1. On WeatherStation PRO, open Settings → Change Wi-Fi.

2. Connect your phone to WeatherStation_Setup.

3. Open http://192.168.4.1.

4. Enter your home Wi-Fi network name and new password.

5. Tap Save and restart.

Re-enter the full password even if your network name has not changed.

4 Change the weather forecast location

1. On the station, open Settings → Change Location.

2. Connect your smartphone to WeatherStation_Setup.

3. Open http://192.168.4.1.

4. Enter the new city in the Location field (for example: Florence, Rome, Milan).

5. Tap Save and restart.

6. Wait for the station to resolve the city and download updated weather data.

Note: If the station is offline, the setup page may also request Wi-Fi credentials. The location service uses the first matching city result.

5 Troubleshooting

Setup network not visible: Return to the setup screen on WeatherStation PRO and choose Restart AP.

Phone says “No Internet”: This is expected: the setup network provides local configuration only.

Configuration page does not open: Confirm that the phone is connected to WeatherStation_Setup. Type http://192.168.4.1 (not https). If necessary, temporarily turn off mobile data.

Wi-Fi connection fails: Check your network name, password, 2.4 GHz compatibility and signal strength, then repeat setup.

Weather location does not update: Check internet access and enter a recognizable city name; allow time for weather data to refresh.

6 Source code and project links

Download Arduino Firmware (ZIP):
https://github.com/Simch1/WeatherStation_PRO/archive/refs/heads/main.zip

GitHub repository:
https://github.com/Simch1/WeatherStation_PRO

WeatherStation PRO — Designed for makers, powered by ESP32.