S C - 3 0 0
R E C I P E R E P O R T
F O R M A T E D I T O R
U S E R
M A N U A L

P R E L I M I N A R Y

D R A F T

Do Not Duplicate or Redistribute
Without Written Permission
By the GE Company

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

TABLE OF CONTENTS

1.0	INTRODUCTION	2
2.0	PURPOSE OF REPORT FORMAT FILES	3
3.0	CREATING A REPORT FORMAT FILE	4
4.0	LINKING A REPORT FORMAT FILE	15

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

1.0 Introduction

The SCREPORT editor is user to generate the format files used when printing a recipe report. It is a very powerful full screen editor with special commands for embedding ingredient (tag) names and report variables. Creating a report format file is a two step process. First, the user must create the format file adding text and embedding ingredietns and report variables as needed. At the completion of this phase, the user has generated a file named SC-???.ULK, where ??? is the three character classname. This file cannot be used by the on-line system, however, as its structure is not compatible with the on-line recipe report generator. Consequently, the user must generate, using the **Alarm Linker** configuration tool, the corresponding SC-???.RPT file. This process replaces all ingredient names by their database prefix and offset. See the Alarm Linker User's Guide for additional information regarding this second step.

1.1 Index Terms

Throughout this document, the term **user** refers to the person, male or female, who is using SCREPORT to develop a recipe report format file. The term **operator** refers to the person who runs the system after it has been configured, installed, and is on-line. The terms **SCREPORT** and **report editor** are used interchangably.

1.2 Starting the Report Editor

The Report Editor is invoked by entering the following at the Concurrent DOS prompt:

>SCREPORT <cr>

The user will be prompted to enter the three character recipe class name for which this report format file is being edited. The name must be three characters, no more, no less, and may not include spaces (e.g. 'DFR' is legal while 'D R' and 'DF ' are not).

1.3 Required Files

The following files must be present in the current directory/path in order to use the Report Editor:

SCREPORT.COM
SCREPORT.000
SCREPORT.001

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

2.0 Purpose of Recipe Report Format Files

When the operator requests a recipe report or recipe active report, the text, ingredients, and formats thereof to be used when printing the report are contained in the file SC-???.RPT, where ??? is the three character class name. Text will be printed character for character as defined in the format file. In addition, ingredients, which are embedded in the format file, will have their values included in the report. How the value is formatted is determined by the ingredient's symbol code and suffix, which are also embedded in the format file. Finally, special report variables may be embedded in the format file. These variables correspond to such things as the current time and date according to the system clock.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.0 Creating a Report Format File

Creating a report format file is done in much the same way as creating a text file with a common word processor. In fact, since SCREPORT was written based upon the MicroStar word processor, many of the commands native to WordStar are included in SCREPORT. Additional functions have been provided to support the embedding of ingredients and report variables. A pull down menu system allows even a novice to use sophisticated editing commands with relative ease.

3.1 Text Editing Operations

The text editing functions have been divided into several command groups as outlined below.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.1.1 Report Editor Quick Command Reference

Command	Description	Command	Description
^A	Left word	^Q^S	To left on line
^S	Left character	^Q^D	To right on line
^D	Right character	^Q^J	Jump to marker
^F	Right word	^Q^I	Toggle auto indent mode
^E	Up line	^Q^R	To top of file
^X	Down line	^Q^C	To end of file
^R	Up page	^Q^B	To begin of block
^C	Down page	^Q^K	To end of block
^W	Scroll up	^Q1	Jump to marker 1
^Z	Scroll down	^Q2	Jump to marker 2
RETURN	New line	...	...
^N	Insert line	^Q9	Jump to marker 9
^G,DEL	Delete character	^Q^Y	Delete line right
BKSPC	Delete left character	^Q^F	Find string
^I	Tab	^Q^A	Find and replace
^T	Delete word	^K^D	Save and open class
^Y	Delete line	^K^S	Save class and resume
^V	Toggle insert mode	^K^X	Exit to Concurrent DOS
^L	Find next occurence	^K^Q	Abandon and open class
^J	Beginning/end of line	^K1	Set marker 1
^P	Insert char by ASCII	...	...
^O^O	Open new window	^K9	Set marker 9
^O^L	Set left margin	^K^B	Set begin of block
^O^R	Set right margin	^K^K	Set end of block
^O^C	Center text	^K^H	Hide/unhide block
^O^K	Change case	^K^C	Copy block
^O^S	Set undo limit	^K^V	Move block
^O^W	Toggle wordwrap mode	^K^Y	Delete block
^O^G	Go to other window	^K^W	Write block to file
^O^I	Go to column	^K^R	Read block from file
^O^N	Go to line	^K^M	Set marker
^O^Y	Destroy window	^K^T	Define tab width
ESC	Undo last change	F10	Help

Note: ^ indicates control key depressed

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.1.2 Cursor Movement Commands

The cursor movement commands do not change text; they simply reposition the cursor. Predefined commands to move the cursor are listed below.

Arrow keys - Move the cursor one character in the direction indicated by the arrow.
Control A - Move cursor left one word.
Control F - Move cursor right one word.
Control S - Move cursor left one character.
Control D - Move cursor right one character.
Control E - Move cursor up one line.
Control X - Move cursor down one line.
Control R - Move cursor up one page.
Control C - Move cursor down one page.
Control W - Scroll screen up one line.
Control Z - Scroll screen down one line.
Control J - Move cursor to beginning of line, unless it is already at the beginning of the line, in which case it is moved to the end of the line.
Control Q S - Move cursor the left on the current line.
Control Q D - Move cursor to the right on the current line.
Control Q R - Move cursor to the beginning of the file.
Control Q C - Move cursor to the end of the file.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.1.3 Text Deletion Commands

Commands are defined to remove text on a character by character or line by line basis. These commands are listed below.

Back space - Deletes the character to the left of the cursor.
Delete - Deletes the character under the cursor.
Control Y - Deletes the entire current line.
Control T - Deletes the current word under the cursor.
Control O Y - Deletes the current window.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.1.4 Word Processing Commands

Commands are defined to support general word processing functions. These commands are listed below.

Control V - Toggle insert mode. When insert mode is on, all characters are inserted before the character under the cursor. This is done by shifting the entire line to the right and then adding the newly typed character. When insert mode is off, the character under the cursor is overwritten by the newly typed character.
Control O K - Change case of character under cursor. If the character is in lower case, it will be capitalized. If the character is already a capital letter, it will switched to lower case.
Control O C - Center the text on the current line between the left and right margins.
Control I (Tab key) - Moves the cursor to the next predefined tab stop.
Control K T - Define tab width. Use this command to set the number of characters skipped when the tab key (^I) is depressed.
Control N - Insert a new line before the current line.
Control O L - Set the column to be used as the left margin of the current document.
Control O R - Set the column to be used as the right margin of the current document.
Control Q I - Toggle auto indent mode. When in auto indent mode, the cursor is moved, after typing a carriage return, to the column on the new line where the first non-blank character of the previous line is found. With auto indent off, the cursor is moved to the left margin on the new line after a carriage return is struck.
Control K M - Set marker 1 to 9. Markers can be placed at special locations throughout the document. The user may then move around within the format file simply by jumping to one of these preset markers.
Control Q J - Jump to one of the preset markers, 1 to 9.
Control Q F - Find string. This command can be used to find a string in the format file. Following the first found occurrence, successive matching strings can be found using the **Control L** command.
Control Q A - Find string and replace. This command works like the find command described above, except the user may replace the found string with a replacement string.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.1.5 Multiple Windows and Text Buffers

Ocassionally it may be useful to open a second window on the current recipe class format file. This is made possible with the SCREPORT window management facility.

3.1.6 Window Commands

SCREPORT provides commands for manipulating windows. These commands are listed below.

Control O O - Open a second window. This command creates the second window on the currently loaded format file. The user is asked to enter the size in lines the second window is to be.
Control O Y - Delete the current window. If the user has both windows open, this command will delete the window currently containing the cursor.
Control O G - Go to the other window. This command moves the cursor from the currently active window to the other window.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.1.7 Block Commands

Commands are available to manipulate blocks (several lines) of text in SCREPORT. These commands are detailed below.

Control K B - Mark the beginning of a block. Before any block operations can be performed, both the beginning and end of the block must be marked to delineate which lines are to be contained within the block.
Control K K - Mark the end of the block.
Control K V - Move the currently marked block to the current position of the cursor. The block will be inserted after the current line. This operation actually moves the block as opposed to making a copy of it.
Control K C - Copy the currently marked block. This operation works exactly like the move operation described above, except that the block is left intact in its original position as well.
Control K H - Hide/unhide the currently marked block. When a block has been marked, the text contained within it is highlighted. This command can be used to turn off (hide) the highlighting. Once turned off, the highlighting can be toggled back on by again executing this command. While hidden, no operations may be performed on a block.
Control K W - Write currently marked block to a disk file leaving the block intact in the current file.
Control K R - Read a block in from a disk file. This file must have been created using SCREPORT. Other types of files will result in a read error.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.1.8 Class Commands

These commands allow the user to read and save or optionally exit without saving recipe class format files. The commands are listed below.

Control K S - Save the current class, then resume the editing session. This command can be used to save work without losing one's place in the format file.
Control K D - Save the current class, then go back to the main menu allowing the user to enter a different class to edit.
Control K X - This command exits the SCREPORT program returning the user to Concurrent DOS. The user will be asked if changes should be saved before exiting if the user has made changes to the class.
Control K Q - Allows the user to abandon any changes made to the current class, and then enter a different class to edit. Confirmation to abandon changes will be requested.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.2 Pull Down Menu System

The pull down menu system allows the user to execute any of the commands available in SCREPORT simply by selecting from a list the command to be executed. The commands work in the same fashion as when executed using a sequence of control keys. However, with the pull down menus, even a novice user can access advanced SCREPORT functions without needing separate documentation. The pull down menu system is selected using function key eight (F8). This will result in the menu at the top of the screen being highlighted. Simply choose the sub-menu from the list of menus using the left/right arrow keys. Once the user has chosen the sub-menu, he simply selects the function to be performed from that menu. The escape key is used to step back out from the pull down menus.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.3 Embedding Ingredient Markers

This command is used to place a recipe ingredient in the report format file. This command is activated using function key four (F4). Upon invoking this command, the user will be asked to enter the one to nine character name of the ingredient (tag) to insert, followed by the symbol code and suffix used to format the value of the ingredient when the report is printed. The user may abandon the insertion process by typing the escape key. Filling out all three fields results in the ingredient being added to the format file. A special yellow graphics symbol marks the location in the text where the value of the ingredient will be placed once the report is printed. This marker is manipulated like any other character (deleted, moved, copied, etc.). The user must take care to allow sufficient space right of the marker to allow for the value to be included when the report is printed.

3.4 Modifying Embedded Ingredient Markers

Use function key five (F5) to modify an existing embedded ingredient definition. Before invoking this command, the cursor must be move to an existing yellow ingredient marker. The user may then change the name, symbol code, symbol suffix, or any combination thereof. Pressing the escape key abandons the modification process.

3.5 Embedding Report Variable Markers

Use function key six (F6) to add a special report variable to the format file. Report variables are used to include special information in the report, such as recipe name, time of day, etc. After pressing the F^ key, the user is presented with a list of available report variables to select from. Use the arrow keys to select the report variable to be embedded. Press the return key to enter the selection, or the escape key to abandon the process. If the recipe name variable (NAM) is selected, additional menus will pop up for more information. Simply enter the requested information followed by a carriage return. When the addition is complete, a magenta graphic symbol will be placed in the text to mark the location of the variable. Like the ingredient marker, it is manipulated like normal text. When report variables are included, care must be taken to allow sufficient space right of the marker for the data included when the report is printed. The amount of data included is dependent upon the report variable.

3.6 Examining Embedded Marker Definitions

Use function key one (F1) to examine the contents of either an embedded ingredient or report variable. Move the cursor to the marker to examine, then press F1. Press escape to exit the examination process.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

3.7 Exploding Embedded Marker Definitions by Name

Use function key two (F2) to examine the names of all embedded markers in the current window. The ingredient markers will be temporarily replaced with the name of the ingredient while the report variable markers will be replaced with the three character mnemonic which describes the marker. Pressing the escape key exits this process and returns the screen to normal.

3.8 Exploding Embedded Marker Definitions by Symbol

Use function key three (F3) to examine all markers in the current window, according to their symbol codes. The report variables are displayed as with **F2** above, but the ingredients are displayed using the format which will be used when the report is printed. Values of all ingredients are defaulted to zero. This function is very useful in that it shows the user exactly how much space to leave for each ingredient in the report.

3.9 Examining/Modifying Report Output Direction Indicator

Use function key seven (F7) to examine/change the report direction indicator. This is used to determine where to send the report when printed. Options include any one of the serial/parallel ports or a disk file. Press the escape or return key to abandon/save the output direction identifier.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88

4.0 Linking a Report Format File

After a report format file has been completed, but before it can be used by the on-line system, it must be linked using the generate option of the Alarm Linker configuration tool. This process replaces all ingredient names with their respective database prefix and offset pairs. In addition, ingredients which are undefined are reported to the user. This process creates the SC-???.RPT files from the SC-???.ULK files which were made with information regarding the generation process. Refer to the **SC-300 System Configuration Manual** for additional information regarding the generation process.

Copyright (C) 1988 General Electric Company, Drives Department, Erie, PA 16531 5/24/88