

PIN Number (Arduino Mega)	Ucomm. (V)	Direction	Relay Module PIN Number	Wire Color	Purpose	Power Consumption (W)
Outputs						
Relay Module (Terminal) #1						
D47	~220	Output	1.1	black	Living Room: General Lighting TRACK №4	10
D45	~220	Output	1.2	white	Living Room: General Lighting TRACK №3	10
D43	~220	Output	1.3	grey	Living Room: General Lighting TRACK №2	10
D41	~220	Output	1.4	lilac	Living Room: General Lighting TRACK №1	10
D39	~220	Output	1.5	blue	Bathroom: General Lighting	15
D37	~220	Output	1.6	green	Hallway: Night Lighting	12
D35	~220	Output	1.7	yellow	Hallway: General Lighting	20
D33	~220	Output	1.8	orange	Bedroom: General Lighting	40
D32	~220	Output	1.9	red	Sanitary Unit: General Lighting	28
D34	~220	Output	1.10	brown	Kitchen: Bar Counter	10
D36	~220	Output	1.11	black	Kitchen: General Lighting	32
D38	~220	Output	1.12	white	Loggia: General Lighting	15
D40	=12	Output	1.13	grey	Bathroom: Local Lighting	50
D42	=12	Output	1.14	lilac	Bedroom: Local Lighting	65
D44	=12	Output	1.15	blue	Hallway: Local Lighting	22
D46	=12	Output	1.16	green	Reserve	-
Relay Module (Terminal) #2						
D30	=12	Output	2.1	black	Sanitary Unit: Local Lighting	48
D28	=12	Output	2.2	white	Living Room: Local Lighting	32
D26	=12	Output	2.3	grey	Reserve	-
D24	=12	Output	2.4	lilac	Siren	-
D22	~220	Output	2.5	blue	Sanitary Unit: Дзеркало	35
D48	~220	Output	2.6	green	Boiler Start/Pause	-
D11	~220	Output	2.7	yellow	Acoustic Door Bell	-
D9	~220	Output	2.8	orange	Reserve	-
D7	~220	Output	2.9	red	Reserve	-
D5	~220	Output	2.10	brown	Reserve	-
D3	~220	Output	2.11	black	Reserve	-
D2	~220	Output	2.12	white	Reserve	-
D4	~220	Output	2.13	grey	Reserve	-
D6	~220	Output	2.14	lilac	Reserve	-
D8	~220	Output	2.15	blue	Reserve	-
D10	~220	Output	2.16	green	Reserve	-
Additional Outputs						
PIN Number (Arduino Mega)	Direction		Relay Module PIN Number	Wire Color	Purpose	Power Consumption (W)
D12	Output		K	grey	K (GSM-modem) On/Off	-
D13	Output		SSR DC-DC	black	Kitchen Furniture Lighting	60
D52	Output		SSR DC-AC (B2)		Sanitary Unit: Ventilation	15
D53	Output		SSR DC-AC (B1)		Bedroom/Restroom: Ventilation	12
Data Exchange						
PIN Number (Arduino Mega)	Direction		Relay Module PIN Number	Wire Color	Purpose	
D14 (txd3)	Data		10	grey (outermost)	Serial3 port Rx (YM34)	
D15 (rxid3)	Data		11	grey (in the middle)	Serial3 port Tx (YM34)	
D16 (txd2)	Data		R	grey	Serial2 port (GSM-modem)	
D17 (rxid2)	Data		T	grey /red	Serial2 port (GSM-modem)	
D18 (txd1)	Data		10 (UART5_RX)	grey	Serial1 port (OrangePi)	
D19 (rxid1)	Data		8 (UART5_TX)	grey	Serial1 port (OrangePi)	
D20 (SDA)	Data			yellow	I2C	
D21 (SCL)	Data			orange	I2C	

No	PIN Number (Arduino Mega)	Direction	Relay Module PIN Number	Wire Color	Purpose	
Inputs						
1	D50	Digital Output	-	brown	Power Supply 220V/12V	20 Br (x.x.)
2	D51	Digital Input	15	red	Signal from switch in hallway	
3	D49	Digital Input	14	orange	Signal from switch in bedroom	
4	D23	Digital Input	13	yellow	Signal from switch in bathroom	
5	D25	Digital Input	12	green	Signal from switch in sanitary unit	
6	D27	Digital Input	11	blue	Signal from switch in living room	
7	D29	Digital Input	10	lilac	Signal from switch in kitchen	
8	D31	Digital Input	9	grey	Signal from switch in loggia	
9	A15/D69	Analog/Digital Input	8	brown	Valet	
10	A13/D67	Analog/Digital Input	7	red	Voltage Sensor (220B)	
11	A11/D65	Digital Output	6	orange	Temperature Sensors Power	
12	A9/D63	Analog/Digital Input	5	yellow	Doorbell Button	
13	A7/D61	Analog/Digital Input	4	green	Reed Switch on Entrance Door	
14	A5/D59	Analog/Digital Input	3	blue	Lock Bolt	
15	D20 (SDA)	Data	2	yellow	I2C	
16	D21 (SCL)	Data	1	orange	I2C	
17	A3/D57	Analog/Digital Input	-	lilac	DC Current Sensor	
18	A1/D55	Analog/Digital Input	-	grey	AC Current Sensor	
19	A0/D54	Analog/Digital Input	-	brown	Air Temperature Sensor outside	
20	A2/D56	Analog/Digital Input	-	red	Air Temperature Sensor inside	
21	A4/D58	Analog/Digital Input	-	orange	Reed Switch on Living Room Window	
22	A6/D60	Analog/Digital Input	-	yellow	IR LED	
23	A8/D62	Analog/Digital Input	-	green	reserve	
24	A10/D64	Analog/Digital Input	-	blue	reserve	
25	A12/D66	Analog/Digital Input	-	lilac	reserve	
26	A14/D68	Analog/Digital Input	-	grey	reserve	