



Customer Service

Generated on: 2026-09-29 09:43:17 GMT+0000

SAP S/4HANA | 2025 FPS01 (Feb 2026)

Public

Original content: https://help.sap.com/docs/SAP_S4HANA_ON-PREMISE/f4a255a5de524e3992155767996fb1fd?locale=en-US&state=PRODUCTION&version=2025.001

Warning

This document has been generated from SAP Help Portal and is an incomplete version of the official SAP product documentation. The information included in custom documentation may not reflect the arrangement of topics in SAP Help Portal, and may be missing important aspects and/or correlations to other topics. For this reason, it is not for production use.

For more information, please visit <https://help.sap.com/docs/disclaimer>.

Meter Reading Data (Move-In)

Use

When you create a move-in, the system proposes an existing meter reading result for all the billing-relevant registers allocated to the devices for billing purposes. Ensure you have configured the system accordingly in Customizing under [SAP Utilities > Device Management > Meter Reading > Basic Settings > Define Control Parameters for Meter Reading Data Processing](#).

- If the system proposes a meter reading result then choose one of the following two options:
- If you adopt the meter reading result, the system adds the meter reading reason **Move-in** to the result.
- If you change the meter reading result, a new result is created with the meter reading reason **Move-in**.
- If the system does not propose a meter reading result, you can have it estimate a result or enter one manually. In both cases, the system creates a new meter reading result from the adopted/changed result and gives it the meter reading reason **Move-In**.
- If the system does not propose a meter reading result, and you do not enter one manually, a service notification or service order is created for the current register. For more information see [service notifications and orders](#).

You can also suppress the meter reading proposal or define an interval as required. If you do this, the system only makes a proposal if the meter reading result on which the proposal is based was taken during the interval. Ensure you have configured the system accordingly in Customizing under [SAP Utilities > Device Management > Meter Reading > Basic Settings > Define Control Parameters for Meter Reading Data Processing](#). Ensure that you make an appropriate entry in the **Move-in prop. inter.** (Interval for determining default value) and the **Display default move-in value** checkbox alongside it.

You can find additional information on meter reading data processing in the section on the [meter reading](#) component.