Administration Guide | PUBLIC
Document Version: 2023.3 – 2025-02-26

Error Code Reference and Exception Troubleshooting

© 2026 SAP SE or an SAP affiliate company. All rights reserved.

Content

1 Before You Start. 50
1.1 About This Document. 50
1.2 Target Audience. 51
1.3 What's New in This Document. 51
1.4 Additional Information. 53
1.5 Document Abbreviations. 53

2 Working with Error Causes and Codes. 56

3 Access by Modules. 60
3.1 AGGREGATIONPOLICY. 64
3.2 ALLOWANCE. 64
3.3 CC-SEC-AUTH. 65
3.4 CHANGEID. 65
3.5 CHANGELIST. 66
3.6 CHARGECOMPONENT. 66
3.7 CHARGEPLAN. 67
3.8 CHARGINGPLAN. 67
3.9 CICLASS. 68
3.10 CONTRACT. 68
3.11 CONTRACTSTATE. 69
3.12 CUSTOMERDATA. 70
3.13 CUSTOMERMANAGEMENTAREA. 70
3.14 DICTIONARY. 71
3.15 HCI. 71
3.16 MACROCOMPONENT. 72
3.17 MAPPINGTABLE. 73
3.18 MAPPINGTABLECOMPONENT. 73
3.19 MONITORINGPLAN. 74
3.20 OPERATIONALSTATUS. 75
3.21 PREPAIDACCOUNTSTATE. 75
3.22 RANGETABLE. 76
3.23 RANGETABLECOMPONENT. 76
3.24 REFILLPLAN. 77
3.25 RESTCHARGING. 77
3.26 RFC. 78
3.27 SPENDINGSTATUS. 78

3.28 SQL. 79
3.29 SUBSCRIBERDATA. 80
3.30 SUBSCRIBERACCOUNT. 80
3.31 TRANSPORTREQUEST. 81

4 Error Code Index. 82
4.1 AGGREGATIONPOLICY-1. 342
4.2 AGGREGATIONPOLICY-2. 343
4.3 AGGREGATIONPOLICY-3. 345
4.4 AGGREGATIONPOLICY-4. 346
4.5 AGGREGATIONPOLICY-5. 348
4.6 AGGREGATIONPOLICY-6. 349
4.7 AGGREGATIONPOLICY-7. 351
4.8 AGGREGATIONPOLICY-8. 352
4.9 AGGREGATIONPOLICY-9. 354
4.10 AGGREGATIONPOLICY-10. 355
4.11 AGGREGATIONPOLICY-11. 357
4.12 AGGREGATIONPOLICY-12. 358
4.13 AGGREGATIONPOLICY-13. 360
4.14 AGGREGATIONPOLICY-14. 361
4.15 AGGREGATIONPOLICY-15. 363
4.16 AGGREGATIONPOLICY-16. 364
4.17 AGGREGATIONPOLICY-18. 366
4.18 AGGREGATIONPOLICY-19. 367
4.19 AGGREGATIONPOLICY-20. 369
4.20 AGGREGATIONPOLICY-22. 370
4.21 AGGREGATIONPOLICY-23. 372
4.22 AGGREGATIONPOLICY-24. 373
4.23 AGGREGATIONPOLICY-25. 374
4.24 AGGREGATIONPOLICY-26. 376
4.25 ALLOWANCE-1. 377
4.26 ALLOWANCE-2. 379
4.27 ALLOWANCE-3. 380
4.28 ALLOWANCE-4. 382
4.29 ALLOWANCE-6. 383
4.30 ALLOWANCE-10. 385
4.31 ALLOWANCE-11. 386
4.32 ALLOWANCE-12. 388
4.33 ALLOWANCE-13. 389
4.34 ALLOWANCE-14. 391
4.35 ALLOWANCE-15. 392
4.36 ALLOWANCE-16. 394

4.37 ALLOWANCE-17. 395
4.38 ALLOWANCE-18. 397
4.39 ALLOWANCE-20. 398
4.40 ALLOWANCE-21. 400
4.41 ALLOWANCE-22. 402
4.42 ALLOWANCE-25. 403
4.43 ALLOWANCE-26. 405
4.44 ALLOWANCE-27. 406
4.45 ALLOWANCE-28. 407
4.46 ALLOWANCE-29. 409
4.47 ALLOWANCE-30. 410
4.48 ALLOWANCE-36. 412
4.49 ALLOWANCE-37. 413
4.50 ALLOWANCE-38. 415
4.51 ALLOWANCE-39. 416
4.52 ALLOWANCE-40. 418
4.53 ALLOWANCE-41. 419
4.54 ALLOWANCE-42. 421
4.55 ALLOWANCE-43. 422
4.56 ALLOWANCE-44. 424
4.57 ALLOWANCE-45. 425
4.58 ALLOWANCE-46. 427
4.59 ALLOWANCE-47. 428
4.60 ALLOWANCE-48. 430
4.61 ALLOWANCE-49. 431
4.62 ALLOWANCE-50. 433
4.63 ALLOWANCE-51. 434
4.64 ALLOWANCE-52. 436
4.65 ALLOWANCE-58. 437
4.66 ALLOWANCE-59. 439
4.67 ALLOWANCE-60. 440
4.68 ALLOWANCE-61. 442
4.69 ALLOWANCE-62. 443
4.70 ALLOWANCE-63. 445
4.71 ALLOWANCE-64. 446
4.72 ALLOWANCE-65. 448
4.73 ALLOWANCE-66. 449
4.74 ALLOWANCE-67. 451
4.75 ALLOWANCE-68. 452
4.76 ALLOWANCE-69. 454
4.77 ALLOWANCE-70. 456

4.78 ALLOWANCE-71. 457
4.79 ALLOWANCE-72. 459
4.80 ALLOWANCE-73. 460
4.81 ALLOWANCE-74. 462
4.82 ALLOWANCE-75. 463
4.83 ALLOWANCE-76. 465
4.84 ALLOWANCE-77. 466
4.85 ALLOWANCE-78. 468
4.86 ALLOWANCE-79. 470
4.87 ALLOWANCE-80. 471
4.88 ALLOWANCE-81. 473
4.89 ALLOWANCE-83. 475
4.90 ALLOWANCE-84. 476
4.91 ALLOWANCE-85. 478
4.92 ALLOWANCE-86. 479
4.93 ALLOWANCE-87. 481
4.94 ALLOWANCE-88. 482
4.95 ALLOWANCE-89. 484
4.96 ALLOWANCE-90. 485
4.97 ALLOWANCE-91. 487
4.98 ALLOWANCE-92. 488
4.99 ALLOWANCE-93. 490
4.100 ALLOWANCE-94. 491
4.101 ALLOWANCE-95. 493
4.102 ALLOWANCE-96 (Revoked). 494
4.103 ALLOWANCE-97. 496
4.104 ALLOWANCE-98. 497
4.105 ALLOWANCE-99. 499
4.106 ALLOWANCE-100. 500
4.107 ALLOWANCE-101. 502
4.108 ALLOWANCE-102. 504
4.109 ALLOWANCE-103. 505
4.110 ALLOWANCE-104. 507
4.111 ALLOWANCE-105. 508
4.112 ALLOWANCE-106. 510
4.113 ALLOWANCE-107. 511
4.114 ALLOWANCE-108. 513
4.115 ALLOWANCE-109. 514
4.116 ALLOWANCE-110. 516
4.117 ALLOWANCE-111. 517
4.118 ALLOWANCE-112. 519

4.119 ALLOWANCE-120. 520
4.120 ALLOWANCE-121. 522
4.121 ALLOWANCE-122. 523
4.122 ALLOWANCE-123. 525
4.123 ALLOWANCE-127. 526
4.124 ALLOWANCE-128. 528
4.125 ALLOWANCE-129. 529
4.126 ALLOWANCE-133. 531
4.127 ALLOWANCE-134. 532
4.128 ALLOWANCE-135. 534
4.129 ALLOWANCE-138. 535
4.130 ALLOWANCE-141. 537
4.131 ALLOWANCE-142. 538
4.132 ALLOWANCE-143. 540
4.133 ALLOWANCE-144. 541
4.134 ALLOWANCE-145. 543
4.135 ALLOWANCE-146. 544
4.136 ALLOWANCE-147. 546
4.137 ALLOWANCE-148. 547
4.138 ALLOWANCE-149. 549
4.139 ALLOWANCE-150. 550
4.140 ALLOWANCE-151. 552
4.141 ALLOWANCE-152. 553
4.142 ALLOWANCE-153. 555
4.143 ALLOWANCE-200. 556
4.144 ALLOWANCE-201. 558
4.145 ALLOWANCE-202. 559
4.146 ALLOWANCE-209. 561
4.147 ALLOWANCE-210. 562
4.148 ALLOWANCE-211. 564
4.149 ALLOWANCE-212. 565
4.150 ALLOWANCE-213. 567
4.151 ALLOWANCE-214. 568
4.152 ALLOWANCE-216. 570
4.153 ALLOWANCE-217. 571
4.154 ALLOWANCE-218. 572
4.155 ALLOWANCE-219. 574
4.156 ALLOWANCE-220. 575
4.157 ALLOWANCE-221. 577
4.158 ALLOWANCE-222. 578
4.159 ALLOWANCE-223. 580

4.160 ALLOWANCE-224. 581
4.161 ALLOWANCE-225. 583
4.162 ALLOWANCE-226. 584
4.163 ALLOWANCE-227. 586
4.164 ALLOWANCE-229. 587
4.165 ALLOWANCE-230. 589
4.166 ALLOWANCE-232. 590
4.167 ALLOWANCE-233. 592
4.168 ALLOWANCE-234. 593
4.169 ALLOWANCE-235. 595
4.170 ALLOWANCE-236. 596
4.171 ALLOWANCE-237. 598
4.172 ALLOWANCE-238. 599
4.173 ALLOWANCE-239. 601
4.174 ALLOWANCE-240. 602
4.175 ALLOWANCE-241. 604
4.176 ALLOWANCE-242. 605
4.177 ALLOWANCE-243. 607
4.178 ALLOWANCE-244. 608
4.179 ALLOWANCE-245. 610
4.180 ALLOWANCE-246. 611
4.181 ALLOWANCE-248. 613
4.182 ALLOWANCE-249. 614
4.183 ALLOWANCE-250. 615
4.184 ALLOWANCE-251. 617
4.185 ALLOWANCE-252. 618
4.186 ALLOWANCE-253. 620
4.187 ALLOWANCE-254. 621
4.188 ALLOWANCE-255. 623
4.189 ALLOWANCE-256. 625
4.190 ALLOWANCE-257. 626
4.191 ALLOWANCE-258. 628
4.192 ALLOWANCE-259. 629
4.193 ALLOWANCE-260. 631
4.194 ALLOWANCE-261. 632
4.195 ALLOWANCE-262. 634
4.196 ALLOWANCE-263. 635
4.197 ALLOWANCE-264. 637
4.198 ALLOWANCE-265. 638
4.199 ALLOWANCE-266. 639
4.200 ALLOWANCE-267. 641

4.201 ALLOWANCE-268. 643
4.202 ALLOWANCE-269. 644
4.203 ALLOWANCE-270. 646
4.204 ALLOWANCE-271. 647
4.205 ALLOWANCE-272. 649
4.206 ALLOWANCE-273. 650
4.207 ALLOWANCE-274. 652
4.208 ALLOWANCE-276. 653
4.209 ALLOWANCE-277. 655
4.210 ALLOWANCE-278. 656
4.211 ALLOWANCE-279. 657
4.212 ALLOWANCE-280. 659
4.213 ALLOWANCE-281. 661
4.214 ALLOWANCE-282. 662
4.215 ALLOWANCE-283. 664
4.216 ALLOWANCE-284. 665
4.217 ALLOWANCE-285. 667
4.218 ALLOWANCE-286. 668
4.219 ALLOWANCE-287. 670
4.220 ALLOWANCE-288. 671
4.221 ALLOWANCE-289. 673
4.222 ALLOWANCE-290. 674
4.223 ALLOWANCE-291. 676
4.224 ALLOWANCE-300. 677
4.225 ALLOWANCE-301. 679
4.226 ALLOWANCE-302. 680
4.227 ALLOWANCE-303. 682
4.228 ALLOWANCE-304. 683
4.229 ALLOWANCE-305. 685
4.230 ALLOWANCE-306. 686
4.231 ALLOWANCE-307. 688
4.232 ALLOWANCE-308. 689
4.233 ALLOWANCE-309. 691
4.234 ALLOWANCE-310. 692
4.235 ALLOWANCE-311. 694
4.236 ALLOWANCE-312. 695
4.237 ALLOWANCE-313. 697
4.238 ALLOWANCE-314. 698
4.239 ALLOWANCE-315. 700
4.240 ALLOWANCE-316. 701
4.241 ALLOWANCE-317. 703

4.242 ALLOWANCE-318. . . . 704
4.243 ALLOWANCE-319. . . . 706
4.244 ALLOWANCE-320. . . . 707
4.245 ALLOWANCE-321. . . . 709
4.246 ALLOWANCE-322. . . . 710
4.247 ALLOWANCE-323. . . . 712
4.248 ALLOWANCE-324. . . . 713
4.249 ALLOWANCE-325. . . . 715
4.250 ALLOWANCE-326. . . . 717
4.251 ALLOWANCE-327. . . . 718
4.252 ALLOWANCE-328. . . . 720
4.253 ALLOWANCE-329. . . . 721
4.254 ALLOWANCE-330. . . . 723
4.255 ALLOWANCE-336. . . . 724
4.256 ALLOWANCE-337. . . . 726
4.257 ALLOWANCE-338. . . . 727
4.258 ALLOWANCE-339. . . . 729
4.259 ALLOWANCE-340. . . . 730
4.260 ALLOWANCE-341. . . . 732
4.261 ALLOWANCE-342. . . . 733
4.262 ALLOWANCE-343. . . . 735
4.263 ALLOWANCE-344. . . . 736
4.264 ALLOWANCE-345. . . . 738
4.265 ALLOWANCE-346. . . . 739
4.266 ALLOWANCE-347. . . . 741
4.267 ALLOWANCE-348. . . . 743
4.268 ALLOWANCE-350 (Revoked). . . . 744
4.269 ALLOWANCE-352. . . . 746
4.270 ALLOWANCE-353. . . . 748
4.271 ALLOWANCE-354. . . . 749
4.272 ALLOWANCE-356. . . . 751
4.273 ALLOWANCE-357. . . . 752
4.274 ALLOWANCE-359. . . . 754
4.275 ALLOWANCE-360. . . . 755
4.276 ALLOWANCE-361. . . . 757
4.277 ALLOWANCE-363. . . . 758
4.278 ALLOWANCE-364. . . . 760
4.279 ALLOWANCE-365. . . . 761
4.280 ALLOWANCE-366. . . . 763
4.281 ALLOWANCE-367. . . . 764
4.282 ALLOWANCE-368. . . . 766

4.283 ALLOWANCE-369. 767
4.284 ALLOWANCE-370. 769
4.285 ALLOWANCE-371. 771
4.286 ALLOWANCE-372. 772
4.287 ALLOWANCE-373. 774
4.288 ALLOWANCE-374. 775
4.289 ALLOWANCE-375. 777
4.290 ALLOWANCE-376. 778
4.291 ALLOWANCE-377. 780
4.292 ALLOWANCE-378. 781
4.293 ALLOWANCE-379. 783
4.294 ALLOWANCE-380. 784
4.295 ALLOWANCE-381. 785
4.296 ALLOWANCE-382. 787
4.297 ALLOWANCE-387. 788
4.298 ALLOWANCE-386. 790
4.299 ALLOWANCE-384. 791
4.300 ALLOWANCE-385. 793
4.301 ALLOWANCE-388. 794
4.302 ALLOWANCE-389. 796
4.303 ALLOWANCE-390. 797
4.304 ALLOWANCE-391. 799
4.305 ALLOWANCE-392. 800
4.306 ALLOWANCE-393 (Revoked). 802
4.307 ALLOWANCE-394. 803
4.308 ALLOWANCE-395 (Revoked). 805
4.309 ALLOWANCE-396. 806
4.310 ALLOWANCE-397. 808
4.311 ALLOWANCE-398. 809
4.312 ALLOWANCE-399. 811
4.313 ALLOWANCE-400. 813
4.314 ALLOWANCE-401. 814
4.315 ALLOWANCE-402. 816
4.316 ALLOWANCE-403. 817
4.317 ALLOWANCE-404. 819
4.318 ALLOWANCE-405. 820
4.319 ALLOWANCE-406. 822
4.320 ALLOWANCE-407. 823
4.321 ALLOWANCE-408. 825
4.322 ALLOWANCE-409. 826
4.323 ALLOWANCE-410. 828

4.324 ALLOWANCE-411. 829
4.325 ALLOWANCE-412. 831
4.326 ALLOWANCE-413. 832
4.327 ALLOWANCE-414. 834
4.328 ALLOWANCE-415. 835
4.329 ALLOWANCE-416. 837
4.330 ALLOWANCE-417. 838
4.331 ALLOWANCE-418. 840
4.332 ALLOWANCE-419. 841
4.333 ALLOWANCE-420. 843
4.334 ALLOWANCE-421. 844
4.335 ALLOWANCE-432. 846
4.336 ALLOWANCE-433. 847
4.337 ALLOWANCE-434. 849
4.338 ALLOWANCE-435. 850
4.339 ALLOWANCE-436. 852
4.340 ALLOWANCE-437. 853
4.341 ALLOWANCE-438. 855
4.342 ALLOWANCE-439. 856
4.343 ALLOWANCE-440. 858
4.344 ALLOWANCE-441. 859
4.345 ALLOWANCE-442. 861
4.346 ALLOWANCE-443. 862
4.347 ALLOWANCE-444. 864
4.348 ALLOWANCE-445. 865
4.349 ALLOWANCE-446. 867
4.350 ALLOWANCE-447. 868
4.351 ALLOWANCE-448. 870
4.352 ALLOWANCE-449. 871
4.353 ALLOWANCE-450. 873
4.354 ALLOWANCE-451. 874
4.355 ALLOWANCE-452. 876
4.356 ALLOWANCE-453. 877
4.357 ALLOWANCE-454. 879
4.358 ALLOWANCE-455. 880
4.359 ALLOWANCE-456. 882
4.360 ALLOWANCE-457. 883
4.361 ALLOWANCE-458. 885
4.362 ALLOWANCE-459. 886
4.363 ALLOWANCE-460. 888
4.364 ALLOWANCE-461. 889

4.365 ALLOWANCE-462. 890
4.366 ALLOWANCE-463. 892
4.367 ALLOWANCE-464. 893
4.368 ALLOWANCE-465. 895
4.369 ALLOWANCE-466. 896
4.370 ALLOWANCE-470. 898
4.371 ALLOWANCE-471. 899
4.372 ALLOWANCE-472. 901
4.373 ALLOWANCE-473. 902
4.374 ALLOWANCE-474. 904
4.375 ALLOWANCE-475. 905
4.376 ALLOWANCE-476. 907
4.377 ALLOWANCE-477. 908
4.378 ALLOWANCE-478. 910
4.379 ALLOWANCE-479. 911
4.380 ALLOWANCE-480. 913
4.381 ALLOWANCE-481. 914
4.382 ALLOWANCE-482. 916
4.383 ALLOWANCE-483. 917
4.384 ALLOWANCE-484. 919
4.385 ALLOWANCE-485. 920
4.386 ALLOWANCE-486. 922
4.387 ALLOWANCE-487. 923
4.388 ALLOWANCE-488. 925
4.389 ALLOWANCE-489. 926
4.390 ALLOWANCE-490. 928
4.391 ALLOWANCE-491. 929
4.392 ALLOWANCE-492. 931
4.393 ALLOWANCE-493. 932
4.394 ALLOWANCE-494. 934
4.395 ALLOWANCE-495. 936
4.396 ALLOWANCE-496. 937
4.397 ALLOWANCE-497. 939
4.398 ALLOWANCE-498. 940
4.399 ALLOWANCE-499. 942
4.400 ALLOWANCE-500. 943
4.401 ALLOWANCE-501. 944
4.402 ALLOWANCE-502. 946
4.403 ALLOWANCE-503. 948
4.404 ALLOWANCE-504. 949
4.405 ALLOWANCE-505. 951

4.406 ALLOWANCE-506. 952
4.407 ALLOWANCE-507. 954
4.408 ALLOWANCE-508. 955
4.409 ALLOWANCE-509. 957
4.410 CC-SEC-AUTH-2. 959
4.411 CC-SEC-AUTH-3. 960
4.412 CC-SEC-AUTH-4. 961
4.413 CC-SEC-AUTH-5. 963
4.414 CC-SEC-AUTH-6. 964
4.415 CC-SEC-AUTH-7. 966
4.416 CC-SEC-AUTH-8. 967
4.417 CC-SEC-AUTH-9. 969
4.418 CC-SEC-AUTH-10. 970
4.419 CC-SEC-AUTH-11. 972
4.420 CC-SEC-AUTH-1000. 973
4.421 CC-SEC-AUTH-1001. 974
4.422 CHANGEID-1. 976
4.423 CHANGEID-2. 977
4.424 CHANGEID-3. 979
4.425 CHANGEID-4. 980
4.426 CHANGEID-5. 982
4.427 CHANGEID-6. 983
4.428 CHANGEID-7. 984
4.429 CHANGEID-8. 986
4.430 CHANGEID-9. 987
4.431 CHANGEID-10. 989
4.432 CHANGEID-11. 990
4.433 CHANGEID-12. 992
4.434 CHANGELIST-1. 993
4.435 CHANGELIST-2. 994
4.436 CHANGELIST-3. 996
4.437 CHANGELIST-4. 997
4.438 CHANGELIST-5. 999
4.439 CHANGELIST-6. 1000
4.440 CHANGELIST-7. 1002
4.441 CHANGELIST-8. 1003
4.442 CHANGELIST-9. 1004
4.443 CHANGELIST-10. 1006
4.444 CHANGELIST-11. 1007
4.445 CHANGELIST-12. 1009
4.446 CHANGELIST-13. 1010

4.447 CHANGELIST-14. 1012
4.448 CHANGELIST-15. 1013
4.449 CHANGELIST-16. 1014
4.450 CHANGELIST-17. 1016
4.451 CHANGELIST-18. 1017
4.452 CHANGELIST-19. 1019
4.453 CHANGELIST-20 (Revoked). 1020
4.454 CHANGELIST-22. 1022
4.455 CHANGELIST-23. 1023
4.456 CHANGELIST-24. 1025
4.457 CHANGELIST-25. 1026
4.458 CHANGELIST-26. 1028
4.459 CHANGELIST-27. 1029
4.460 CHANGELIST-28. 1031
4.461 CHANGELIST-29. 1032
4.462 CHANGELIST-30. 1034
4.463 CHARGECOMPONENT-1. 1035
4.464 CHARGECOMPONENT-2. 1037
4.465 CHARGECOMPONENT-3. 1038
4.466 CHARGECOMPONENT-4. 1040
4.467 CHARGECOMPONENT-5. 1041
4.468 CHARGECOMPONENT-6. 1043
4.469 CHARGECOMPONENT-7. 1044
4.470 CHARGECOMPONENT-8. 1046
4.471 CHARGECOMPONENT-9. 1047
4.472 CHARGECOMPONENT-10. 1049
4.473 CHARGECOMPONENT-11. 1050
4.474 CHARGECOMPONENT-12. 1052
4.475 CHARGECOMPONENT-13. 1053
4.476 CHARGECOMPONENT-14. 1055
4.477 CHARGECOMPONENT-15. 1056
4.478 CHARGECOMPONENT-16. 1058
4.479 CHARGECOMPONENT-17. 1059
4.480 CHARGECOMPONENT-18. 1061
4.481 CHARGECOMPONENT-19. 1062
4.482 CHARGECOMPONENT-20. 1063
4.483 CHARGECOMPONENT-21. 1065
4.484 CHARGECOMPONENT-22. 1066
4.485 CHARGECOMPONENT-23. 1068
4.486 CHARGECOMPONENT-24. 1069
4.487 CHARGECOMPONENT-25. 1071

4.488 CHARGECOMPONENT-26. 1072
4.489 CHARGECOMPONENT-27. 1074
4.490 CHARGECOMPONENT-28. 1075
4.491 CHARGECOMPONENT-29. 1077
4.492 CHARGECOMPONENT-30. 1078
4.493 CHARGECOMPONENT-31. 1079
4.494 CHARGECOMPONENT-32. 1081
4.495 CHARGECOMPONENT-33. 1082
4.496 CHARGECOMPONENT-34. 1084
4.497 CHARGECOMPONENT-35. 1085
4.498 CHARGECOMPONENT-36. 1087
4.499 CHARGECOMPONENT-37. 1088
4.500 CHARGECOMPONENT-38. 1090
4.501 CHARGECOMPONENT-39. 1091
4.502 CHARGECOMPONENT-40. 1093
4.503 CHARGECOMPONENT-41. 1094
4.504 CHARGECOMPONENT-42. 1096
4.505 CHARGECOMPONENT-43. 1097
4.506 CHARGECOMPONENT-44. 1099
4.507 CHARGECOMPONENT-45. 1100
4.508 CHARGECOMPONENT-46. 1101
4.509 CHARGECOMPONENT-47. 1103
4.510 CHARGECOMPONENT-48. 1104
4.511 CHARGECOMPONENT-49. 1106
4.512 CHARGECOMPONENT-50. 1107
4.513 CHARGECOMPONENT-51. 1109
4.514 CHARGECOMPONENT-52. 1110
4.515 CHARGECOMPONENT-53. 1112
4.516 CHARGECOMPONENT-54. 1113
4.517 CHARGECOMPONENT-55. 1115
4.518 CHARGECOMPONENT-56. 1116
4.519 CHARGECOMPONENT-57. 1118
4.520 CHARGECOMPONENT-58. 1119
4.521 CHARGECOMPONENT-59. 1121
4.522 CHARGECOMPONENT-60. 1122
4.523 CHARGECOMPONENT-61. 1124
4.524 CHARGECOMPONENT-62. 1125
4.525 CHARGECOMPONENT-63. 1127
4.526 CHARGECOMPONENT-64. 1128
4.527 CHARGECOMPONENT-65. 1130
4.528 CHARGECOMPONENT-66. 1131

4.529 CHARGECOMPONENT-67. 1133
4.530 CHARGECOMPONENT-68. 1134
4.531 CHARGECOMPONENT-69. 1136
4.532 CHARGECOMPONENT-70. 1138
4.533 CHARGECOMPONENT-71. 1139
4.534 CHARGECOMPONENT-72. 1141
4.535 CHARGECOMPONENT-73. 1142
4.536 CHARGECOMPONENT-74. 1144
4.537 CHARGECOMPONENT-75. 1145
4.538 CHARGECOMPONENT-76. 1147
4.539 CHARGECOMPONENT-77. 1148
4.540 CHARGECOMPONENT-78. 1150
4.541 CHARGECOMPONENT-79. 1151
4.542 CHARGECOMPONENT-80. 1153
4.543 CHARGECOMPONENT-81. 1154
4.544 CHARGECOMPONENT-82. 1156
4.545 CHARGECOMPONENT-83. 1157
4.546 CHARGECOMPONENT-84. 1159
4.547 CHARGECOMPONENT-85. 1160
4.548 CHARGECOMPONENT-86. 1162
4.549 CHARGECOMPONENT-87. 1163
4.550 CHARGECOMPONENT-88. 1165
4.551 CHARGECOMPONENT-89. 1166
4.552 CHARGECOMPONENT-90. 1167
4.553 CHARGECOMPONENT-91. 1169
4.554 CHARGECOMPONENT-92. 1170
4.555 CHARGECOMPONENT-93. 1172
4.556 CHARGECOMPONENT-94. 1173
4.557 CHARGECOMPONENT-95. 1175
4.558 CHARGECOMPONENT-96. 1176
4.559 CHARGECOMPONENT-97. 1178
4.560 CHARGECOMPONENT-98. 1180
4.561 CHARGECOMPONENT-99. 1182
4.562 CHARGECOMPONENT-100. 1184
4.563 CHARGECOMPONENT-101. 1186
4.564 CHARGECOMPONENT-102. 1187
4.565 CHARGECOMPONENT-103. 1189
4.566 CHARGECOMPONENT-104. 1190
4.567 CHARGECOMPONENT-105. 1192
4.568 CHARGECOMPONENT-106. 1193
4.569 CHARGECOMPONENT-107. 1195

4.570 CHARGECOMPONENT-108. 1196
4.571 CHARGECOMPONENT-109. 1198
4.572 CHARGECOMPONENT-110. 1199
4.573 CHARGECOMPONENT-111. 1201
4.574 CHARGECOMPONENT-112. 1202
4.575 CHARGECOMPONENT-113. 1204
4.576 CHARGECOMPONENT-114. 1205
4.577 CHARGECOMPONENT-115. 1206
4.578 CHARGECOMPONENT-116. 1208
4.579 CHARGECOMPONENT-117. 1209
4.580 CHARGEPLAN-1. 1211
4.581 CHARGEPLAN-2. 1212
4.582 CHARGEPLAN-3. 1214
4.583 CHARGEPLAN-4. 1215
4.584 CHARGEPLAN-5. 1217
4.585 CHARGEPLAN-6 (Revoked). 1218
4.586 CHARGEPLAN-7 (Revoked). 1220
4.587 CHARGEPLAN-8 (Revoked). 1222
4.588 CHARGEPLAN-9 (Revoked). 1223
4.589 CHARGEPLAN-10 (Revoked). 1225
4.590 CHARGEPLAN-11 (Revoked). 1227
4.591 CHARGEPLAN-12 (Revoked). 1228
4.592 CHARGEPLAN-13 (Revoked). 1230
4.593 CHARGEPLAN-14. 1232
4.594 CHARGEPLAN-15. 1233
4.595 CHARGEPLAN-16. 1235
4.596 CHARGEPLAN-17. 1236
4.597 CHARGEPLAN-18. 1238
4.598 CHARGEPLAN-19. 1239
4.599 CHARGEPLAN-20. 1241
4.600 CHARGEPLAN-21. 1242
4.601 CHARGEPLAN-22. 1244
4.602 CHARGEPLAN-23. 1245
4.603 CHARGEPLAN-24. 1247
4.604 CHARGEPLAN-25. 1248
4.605 CHARGEPLAN-26. 1250
4.606 CHARGEPLAN-27. 1251
4.607 CHARGEPLAN-28. 1253
4.608 CHARGEPLAN-29. 1254
4.609 CHARGEPLAN-30. 1256
4.610 CHARGEPLAN-31. 1257

4.611 CHARGEPLAN-32. 1259
4.612 CHARGEPLAN-33. 1260
4.613 CHARGEPLAN-34. 1262
4.614 CHARGEPLAN-35. 1263
4.615 CHARGEPLAN-36. 1265
4.616 CHARGEPLAN-37. 1266
4.617 CHARGEPLAN-38. 1268
4.618 CHARGEPLAN-39. 1269
4.619 CHARGEPLAN-40. 1271
4.620 CHARGEPLAN-41. 1272
4.621 CHARGEPLAN-42. 1274
4.622 CHARGEPLAN-43. 1275
4.623 CHARGEPLAN-44. 1277
4.624 CHARGEPLAN-45. 1278
4.625 CHARGEPLAN-46. 1280
4.626 CHARGEPLAN-47. 1281
4.627 CHARGEPLAN-48. 1283
4.628 CHARGEPLAN-49. 1284
4.629 CHARGEPLAN-50. 1286
4.630 CHARGEPLAN-51. 1287
4.631 CHARGEPLAN-52. 1289
4.632 CHARGEPLAN-53. 1290
4.633 CHARGEPLAN-54. 1292
4.634 CHARGEPLAN-55. 1293
4.635 CHARGEPLAN-56. 1295
4.636 CHARGEPLAN-57. 1297
4.637 CHARGEPLAN-58. 1298
4.638 CHARGEPLAN-59. 1300
4.639 CHARGEPLAN-60. 1301
4.640 CHARGEPLAN-61. 1303
4.641 CHARGEPLAN-62. 1304
4.642 CHARGEPLAN-63. 1306
4.643 CHARGEPLAN-64. 1307
4.644 CHARGEPLAN-65. 1309
4.645 CHARGEPLAN-66. 1310
4.646 CHARGEPLAN-67. 1312
4.647 CHARGEPLAN-68. 1314
4.648 CHARGEPLAN-69. 1315
4.649 CHARGEPLAN-70. 1317
4.650 CHARGEPLAN-71. 1318
4.651 CHARGEPLAN-72. 1320

4.652 CHARGEPLAN-73. 1321
4.653 CHARGEPLAN-74. 1323
4.654 CHARGEPLAN-75. 1325
4.655 CHARGEPLAN-76. 1326
4.656 CHARGEPLAN-77. 1328
4.657 CHARGEPLAN-78. 1329
4.658 CHARGEPLAN-79. 1331
4.659 CHARGEPLAN-80. 1332
4.660 CHARGEPLAN-81. 1334
4.661 CHARGEPLAN-82. 1335
4.662 CHARGEPLAN-83. 1337
4.663 CHARGEPLAN-84. 1338
4.664 CHARGEPLAN-85. 1340
4.665 CHARGEPLAN-86. 1341
4.666 CHARGEPLAN-87. 1343
4.667 CHARGEPLAN-88. 1344
4.668 CHARGEPLAN-89. 1346
4.669 CHARGEPLAN-90. 1347
4.670 CHARGEPLAN-91. 1349
4.671 CHARGEPLAN-92. 1350
4.672 CHARGEPLAN-93. 1352
4.673 CHARGEPLAN-94. 1353
4.674 CHARGEPLAN-95. 1355
4.675 CHARGEPLAN-96. 1356
4.676 CHARGEPLAN-97 (Revoked). 1358
4.677 CHARGEPLAN-98. 1360
4.678 CHARGEPLAN-99. 1361
4.679 CHARGEPLAN-100. 1363
4.680 CHARGEPLAN-101. 1364
4.681 CHARGEPLAN-102. 1366
4.682 CHARGEPLAN-103. 1367
4.683 CHARGEPLAN-104. 1369
4.684 CHARGEPLAN-105. 1370
4.685 CHARGEPLAN-106. 1372
4.686 CHARGEPLAN-107. 1373
4.687 CHARGEPLAN-108. 1375
4.688 CHARGEPLAN-109. 1377
4.689 CHARGEPLAN-110. 1378
4.690 CHARGEPLAN-111. 1380
4.691 CHARGEPLAN-112. 1381
4.692 CHARGEPLAN-113. 1383

4.693 CHARGEPLAN-114. 1384
4.694 CHARGEPLAN-115. 1386
4.695 CHARGEPLAN-116. 1387
4.696 CHARGEPLAN-117. 1389
4.697 CHARGEPLAN-118. 1391
4.698 CHARGEPLAN-119. 1392
4.699 CHARGEPLAN-120. 1393
4.700 CHARGEPLAN-121. 1395
4.701 CHARGEPLAN-122. 1396
4.702 CHARGEPLAN-123. 1398
4.703 CHARGEPLAN-124. 1399
4.704 CHARGEPLAN-125. 1401
4.705 CHARGEPLAN-126. 1402
4.706 CHARGEPLAN-127. 1404
4.707 CHARGEPLAN-128. 1406
4.708 CHARGEPLAN-129. 1407
4.709 CHARGEPLAN-130. 1409
4.710 CHARGEPLAN-131. 1410
4.711 CHARGEPLAN-132. 1412
4.712 CHARGEPLAN-133. 1413
4.713 CHARGEPLAN-134. 1415
4.714 CHARGEPLAN-135. 1416
4.715 CHARGEPLAN-136. 1418
4.716 CHARGEPLAN-137. 1420
4.717 CHARGEPLAN-138. 1421
4.718 CHARGEPLAN-139. 1423
4.719 CHARGEPLAN-140. 1424
4.720 CHARGEPLAN-141. 1426
4.721 CHARGEPLAN-142. 1427
4.722 CHARGEPLAN-143. 1428
4.723 CHARGEPLAN-144. 1430
4.724 CHARGEPLAN-145. 1431
4.725 CHARGEPLAN-146. 1433
4.726 CHARGEPLAN-147. 1434
4.727 CHARGEPLAN-148. 1436
4.728 CHARGEPLAN-149. 1438
4.729 CHARGEPLAN-150. 1439
4.730 CHARGEPLAN-151. 1441
4.731 CHARGEPLAN-152. 1442
4.732 CHARGEPLAN-153. 1444
4.733 CHARGEPLAN-154. 1446

4.734 CHARGEPLAN-155. 1447
4.735 CHARGEPLAN-156. 1449
4.736 CHARGEPLAN-157. 1450
4.737 CHARGEPLAN-158. 1452
4.738 CHARGEPLAN-159. 1453
4.739 CHARGEPLAN-160. 1455
4.740 CHARGEPLAN-161. 1456
4.741 CHARGEPLAN-162. 1458
4.742 CHARGEPLAN-163. 1460
4.743 CHARGEPLAN-164. 1461
4.744 CHARGEPLAN-165. 1463
4.745 CHARGEPLAN-166. 1464
4.746 CHARGEPLAN-167. 1466
4.747 CHARGEPLAN-168. 1468
4.748 CHARGEPLAN-169. 1469
4.749 CHARGEPLAN-170. 1471
4.750 CHARGEPLAN-171. 1472
4.751 CHARGEPLAN-172. 1474
4.752 CHARGEPLAN-173. 1475
4.753 CHARGEPLAN-174. 1476
4.754 CHARGEPLAN-175. 1478
4.755 CHARGEPLAN-176. 1479
4.756 CHARGEPLAN-177. 1481
4.757 CHARGEPLAN-178. 1482
4.758 CHARGEPLAN-179. 1484
4.759 CHARGEPLAN-180. 1485
4.760 CHARGEPLAN-181. 1487
4.761 CHARGEPLAN-182. 1489
4.762 CHARGEPLAN-183. 1490
4.763 CHARGEPLAN-184. 1492
4.764 CHARGEPLAN-185. 1493
4.765 CHARGEPLAN-186. 1495
4.766 CHARGEPLAN-187. 1496
4.767 CHARGEPLAN-188. 1498
4.768 CHARGEPLAN-189. 1499
4.769 CHARGEPLAN-190. 1501
4.770 CHARGEPLAN-191. 1502
4.771 CHARGEPLAN-192. 1504
4.772 CHARGEPLAN-193. 1506
4.773 CHARGEPLAN-194. 1507
4.774 CHARGEPLAN-195. 1509

4.775 CHARGEPLAN-196. 1510
4.776 CHARGEPLAN-198. 1512
4.777 CHARGEPLAN-199. 1513
4.778 CHARGEPLAN-200. 1515
4.779 CHARGEPLAN-201. 1516
4.780 CHARGEPLAN-202. 1518
4.781 CHARGEPLAN-203. 1519
4.782 CHARGEPLAN-204. 1521
4.783 CHARGEPLAN-205. 1522
4.784 CHARGEPLAN-206. 1524
4.785 CHARGEPLAN-207. 1525
4.786 CHARGEPLAN-208. 1527
4.787 CHARGEPLAN-209. 1528
4.788 CHARGEPLAN-210. 1530
4.789 CHARGEPLAN-211. 1531
4.790 CHARGEPLAN-212. 1533
4.791 CHARGEPLAN-213. 1534
4.792 CHARGEPLAN-214. 1536
4.793 CHARGEPLAN-215. 1537
4.794 CHARGEPLAN-216. 1539
4.795 CHARGEPLAN-217. 1540
4.796 CHARGEPLAN-218. 1542
4.797 CHARGEPLAN-219. 1543
4.798 CHARGEPLAN-220. 1545
4.799 CHARGEPLAN-221. 1546
4.800 CHARGEPLAN-222. 1548
4.801 CHARGEPLAN-223. 1549
4.802 CHARGEPLAN-224. 1551
4.803 CHARGEPLAN-225. 1552
4.804 CHARGEPLAN-226. 1554
4.805 CHARGEPLAN-227. 1555
4.806 CHARGEPLAN-228. 1557
4.807 CHARGEPLAN-229. 1558
4.808 CHARGEPLAN-230 (Revoked). 1560
4.809 CHARGEPLAN-231. 1562
4.810 CHARGEPLAN-232. 1563
4.811 CHARGEPLAN-233. 1565
4.812 CHARGEPLAN-234. 1566
4.813 CHARGEPLAN-235. 1568
4.814 CHARGEPLAN-236. 1569
4.815 CHARGEPLAN-237. 1571

4.816 CHARGEPLAN-238. 1572
4.817 CHARGEPLAN-239. 1574
4.818 CHARGEPLAN-240. 1575
4.819 CHARGEPLAN-241. 1577
4.820 CHARGEPLAN-242. 1578
4.821 CHARGEPLAN-243. 1580
4.822 CHARGEPLAN-244. 1581
4.823 CHARGEPLAN-245. 1583
4.824 CHARGEPLAN-246. 1585
4.825 CHARGEPLAN-247. 1586
4.826 CHARGEPLAN-248. 1588
4.827 CHARGEPLAN-249. 1589
4.828 CHARGEPLAN-250. 1591
4.829 CHARGEPLAN-251. 1592
4.830 CHARGEPLAN-252. 1594
4.831 CHARGEPLAN-253. 1595
4.832 CHARGEPLAN-254. 1597
4.833 CHARGEPLAN-255. 1599
4.834 CHARGEPLAN-256. 1600
4.835 CHARGEPLAN-257. 1602
4.836 CHARGEPLAN-258 (Revoked). 1603
4.837 CHARGEPLAN-259. 1605
4.838 CHARGEPLAN-260. 1607
4.839 CHARGEPLAN-261. 1608
4.840 CHARGEPLAN-262. 1610
4.841 CHARGEPLAN-263. 1611
4.842 CHARGEPLAN-264. 1613
4.843 CHARGEPLAN-265. 1614
4.844 CHARGEPLAN-266. 1616
4.845 CHARGEPLAN-267. 1617
4.846 CHARGEPLAN-269. 1619
4.847 CHARGEPLAN-270. 1620
4.848 CHARGEPLAN-271. 1622
4.849 CHARGEPLAN-272. 1623
4.850 CHARGEPLAN-273. 1625
4.851 CHARGEPLAN-274. 1627
4.852 CHARGEPLAN-275. 1628
4.853 CHARGEPLAN-276. 1630
4.854 CHARGEPLAN-277. 1631
4.855 CHARGEPLAN-278. 1633
4.856 CHARGEPLAN-279. 1634

4.857 CHARGEPLAN-280. 1636
4.858 CHARGEPLAN-281. 1637
4.859 CHARGEPLAN-282. 1639
4.860 CHARGEPLAN-283. 1640
4.861 CHARGEPLAN-284. 1642
4.862 CHARGEPLAN-285. 1643
4.863 CHARGEPLAN-286. 1645
4.864 CHARGEPLAN-287. 1646
4.865 CHARGEPLAN-288. 1648
4.866 CHARGEPLAN-289. 1650
4.867 CHARGEPLAN-290. 1651
4.868 CHARGEPLAN-291. 1653
4.869 CHARGINGPLAN-1. 1654
4.870 CHARGINGPLAN-2. 1655
4.871 CHARGINGPLAN-3. 1657
4.872 CHARGINGPLAN-4. 1658
4.873 CHARGINGPLAN-5. 1660
4.874 CHARGINGPLAN-6. 1661
4.875 CHARGINGPLAN-7. 1663
4.876 CHARGINGPLAN-8. 1664
4.877 CHARGINGPLAN-9. 1666
4.878 CHARGINGPLAN-10. 1667
4.879 CHARGINGPLAN-11. 1669
4.880 CHARGINGPLAN-12. 1671
4.881 CHARGINGPLAN-13. 1672
4.882 CHARGINGPLAN-14. 1674
4.883 CHARGINGPLAN-15. 1675
4.884 CHARGINGPLAN-16. 1677
4.885 CHARGINGPLAN-17. 1678
4.886 CHARGINGPLAN-18. 1680
4.887 CHARGINGPLAN-19. 1681
4.888 CHARGINGPLAN-20. 1683
4.889 CHARGINGPLAN-21. 1684
4.890 CHARGINGPLAN-22. 1686
4.891 CHARGINGPLAN-23. 1687
4.892 CHARGINGPLAN-24. 1689
4.893 CHARGINGPLAN-25. 1691
4.894 CHARGINGPLAN-26. 1692
4.895 CHARGINGPLAN-27. 1694
4.896 CHARGINGPLAN-28. 1695
4.897 CHARGINGPLAN-29. 1697

4.898 CHARGINGPLAN-30. 1698
4.899 CHARGINGPLAN-31. 1700
4.900 CHARGINGPLAN-32. 1701
4.901 CHARGINGPLAN-33. 1703
4.902 CHARGINGPLAN-34. 1704
4.903 CHARGINGPLAN-35. 1706
4.904 CICLASS-1. 1707
4.905 CICLASS-2. 1709
4.906 CICLASS-3. 1710
4.907 CICLASS-4. 1712
4.908 CICLASS-5. 1713
4.909 CICLASS-6. 1715
4.910 CICLASS-7. 1716
4.911 CICLASS-8. 1718
4.912 CICLASS-9. 1719
4.913 CICLASS-10. 1721
4.914 CICLASS-11. 1722
4.915 CICLASS-12. 1724
4.916 CICLASS-13. 1725
4.917 CICLASS-14. 1727
4.918 CICLASS-15. 1728
4.919 CICLASS-16. 1730
4.920 CICLASS-17. 1731
4.921 CICLASS-18. 1733
4.922 CICLASS-19. 1734
4.923 CICLASS-20. 1736
4.924 CICLASS-21. 1737
4.925 CICLASS-22. 1739
4.926 CICLASS-23. 1740
4.927 CICLASS-24. 1742
4.928 CICLASS-25. 1743
4.929 CICLASS-26. 1745
4.930 CONTRACT-1. 1746
4.931 CONTRACT-2. 1748
4.932 CONTRACT-3. 1749
4.933 CONTRACT-4. 1751
4.934 CONTRACT-5. 1752
4.935 CONTRACT-6. 1753
4.936 CONTRACT-7. 1755
4.937 CONTRACT-8. 1756
4.938 CONTRACT-9. 1758

4.939 CONTRACT-10. 1759
4.940 CONTRACT-11. 1761
4.941 CONTRACT-12. 1762
4.942 CONTRACT-13. 1764
4.943 CONTRACT-14. 1765
4.944 CONTRACT-15. 1767
4.945 CONTRACT-16. 1768
4.946 CONTRACT-17. 1770
4.947 CONTRACT-18. 1771
4.948 CONTRACT-19. 1773
4.949 CONTRACT-20. 1774
4.950 CONTRACT-21. 1776
4.951 CONTRACT-22. 1777
4.952 CONTRACT-23. 1779
4.953 CONTRACT-24. 1780
4.954 CONTRACT-25. 1782
4.955 CONTRACT-26. 1783
4.956 CONTRACT-27. 1785
4.957 CONTRACT-28. 1786
4.958 CONTRACT-29. 1788
4.959 CONTRACT-30 (Revoked). 1790
4.960 CONTRACT-31. 1791
4.961 CONTRACT-32. 1793
4.962 CONTRACT-33. 1794
4.963 CONTRACT-34. 1796
4.964 CONTRACT-35. 1797
4.965 CONTRACT-36. 1799
4.966 CONTRACT-37. 1801
4.967 CONTRACT-38. 1802
4.968 CONTRACT-39. 1804
4.969 CONTRACT-40 (Revoked). 1805
4.970 CONTRACT-41 (Revoked). 1807
4.971 CONTRACT-42 (Revoked). 1808
4.972 CONTRACT-43 (Revoked). 1810
4.973 CONTRACT-44 (Revoked). 1812
4.974 CONTRACT-45 (Revoked). 1813
4.975 CONTRACT-46 (Revoked). 1815
4.976 CONTRACT-47. 1817
4.977 CONTRACT-48. 1818
4.978 CONTRACT-49. 1820
4.979 CONTRACT-50. 1821

4.980 CONTRACT-51. 1823
4.981 CONTRACT-52. 1824
4.982 CONTRACT-53. 1826
4.983 CONTRACT-54. 1827
4.984 CONTRACT-55. 1829
4.985 CONTRACT-56. 1830
4.986 CONTRACT-57. 1832
4.987 CONTRACT-58. 1833
4.988 CONTRACT-59. 1835
4.989 CONTRACT-60. 1836
4.990 CONTRACT-61. 1838
4.991 CONTRACT-62. 1840
4.992 CONTRACT-63. 1841
4.993 CONTRACT-64. 1843
4.994 CONTRACT-65. 1844
4.995 CONTRACT-66. 1846
4.996 CONTRACT-67. 1847
4.997 CONTRACT-68. 1849
4.998 CONTRACT-69. 1851
4.999 CONTRACT-70. 1852
4.1000 CONTRACT-71. 1854
4.1001 CONTRACT-72. 1855
4.1002 CONTRACT-73. 1857
4.1003 CONTRACT-74. 1858
4.1004 CONTRACT-75. 1860
4.1005 CONTRACT-76. 1861
4.1006 CONTRACT-77. 1863
4.1007 CONTRACT-78. 1865
4.1008 CONTRACT-79. 1866
4.1009 CONTRACT-80. 1868
4.1010 CONTRACT-81. 1869
4.1011 CONTRACT-82. 1871
4.1012 CONTRACT-83. 1873
4.1013 CONTRACT-84. 1874
4.1014 CONTRACT-85. 1876
4.1015 CONTRACT-86. 1877
4.1016 CONTRACT-87. 1879
4.1017 CONTRACT-88. 1880
4.1018 CONTRACT-89. 1882
4.1019 CONTRACT-90. 1883
4.1020 CONTRACT-91. 1885

4.1021 CONTRACT-92. 1886
4.1022 CONTRACT-93. 1888
4.1023 CONTRACT-94. 1890
4.1024 CONTRACT-95. 1891
4.1025 CONTRACT-96. 1893
4.1026 CONTRACT-97. 1894
4.1027 CONTRACT-98. 1896
4.1028 CONTRACT-99. 1897
4.1029 CONTRACT-101. 1899
4.1030 CONTRACT-102. 1900
4.1031 CONTRACT-103. 1902
4.1032 CONTRACT-104. 1903
4.1033 CONTRACT-105. 1905
4.1034 CONTRACT-106. 1907
4.1035 CONTRACT-107. 1908
4.1036 CONTRACT-108. 1910
4.1037 CONTRACT-109. 1912
4.1038 CONTRACT-110. 1913
4.1039 CONTRACT-111. 1915
4.1040 CONTRACT-112. 1916
4.1041 CONTRACT-113. 1918
4.1042 CONTRACT-114. 1919
4.1043 CONTRACT-115. 1921
4.1044 CONTRACT-116. 1922
4.1045 CONTRACT-117. 1924
4.1046 CONTRACT-118. 1926
4.1047 CONTRACT-119. 1927
4.1048 CONTRACT-120. 1929
4.1049 CONTRACT-121. 1931
4.1050 CONTRACT-122. 1932
4.1051 CONTRACTSTATE-1. 1934
4.1052 CONTRACTSTATE-2. 1935
4.1053 CONTRACTSTATE-3. 1937
4.1054 CONTRACTSTATE-4. 1938
4.1055 CONTRACTSTATE-5. 1940
4.1056 CONTRACTSTATE-6. 1942
4.1057 CONTRACTSTATE-7. 1943
4.1058 CONTRACTSTATE-8. 1945
4.1059 CONTRACTSTATE-9. 1946
4.1060 CONTRACTSTATE-10. 1948
4.1061 CONTRACTSTATE-11. 1949

4.1062 CONTRACTSTATE-12. 1951
4.1063 CONTRACTSTATE-13. 1952
4.1064 CONTRACTSTATE-14. 1954
4.1065 CUSTOMERDATA-1. 1955
4.1066 CUSTOMERDATA-2. 1957
4.1067 CUSTOMERDATA-3. 1958
4.1068 CUSTOMERDATA-4. 1960
4.1069 CUSTOMERDATA-5. 1961
4.1070 CUSTOMERDATA-6. 1963
4.1071 CUSTOMERDATA-7. 1964
4.1072 CUSTOMERDATA-8. 1966
4.1073 CUSTOMERDATA-9. 1967
4.1074 CUSTOMERDATA-10. 1969
4.1075 CUSTOMERDATA-11. 1970
4.1076 CUSTOMERDATA-12. 1972
4.1077 CUSTOMERDATA-13. 1973
4.1078 CUSTOMERDATA-14. 1975
4.1079 CUSTOMERDATA-15. 1976
4.1080 CUSTOMERDATA-16. 1978
4.1081 CUSTOMERDATA-17. 1979
4.1082 CUSTOMERDATA-18. 1981
4.1083 CUSTOMERDATA-19. 1982
4.1084 CUSTOMERDATA-20. 1984
4.1085 CUSTOMERDATA-21. 1986
4.1086 CUSTOMERDATA-22. 1987
4.1087 CUSTOMERDATA-23. 1989
4.1088 CUSTOMERDATA-24. 1990
4.1089 CUSTOMERDATA-25. 1992
4.1090 CUSTOMERDATA-26. 1993
4.1091 CUSTOMERDATA-27. 1995
4.1092 CUSTOMERDATA-28. 1996
4.1093 CUSTOMERDATA-29. 1998
4.1094 CUSTOMERDATA-30. 1999
4.1095 CUSTOMERMANAGEMENTAREA-1. 2001
4.1096 CUSTOMERMANAGEMENTAREA-2. 2002
4.1097 CUSTOMERMANAGEMENTAREA-3. 2004
4.1098 CUSTOMERMANAGEMENTAREA-4. 2005
4.1099 CUSTOMERMANAGEMENTAREA-5. 2007
4.1100 CUSTOMERMANAGEMENTAREA-6. 2008
4.1101 CUSTOMERMANAGEMENTAREA-7. 2010
4.1102 CUSTOMERMANAGEMENTAREA-8. 2011

4.1103 CUSTOMERMANAGEMENTAREA-9. 2013
4.1104 CUSTOMERMANAGEMENTAREA-10. 2014
4.1105 CUSTOMERMANAGEMENTAREA-11. 2016
4.1106 CUSTOMERMANAGEMENTAREA-12. 2017
4.1107 DICTIONARY-1. 2019
4.1108 DICTIONARY-2. 2020
4.1109 DICTIONARY-3. 2022
4.1110 DICTIONARY-4. 2023
4.1111 DICTIONARY-5. 2025
4.1112 DICTIONARY-6. 2026
4.1113 DICTIONARY-7. 2028
4.1114 DICTIONARY-8. 2029
4.1115 HCI-1. 2031
4.1116 HCI-2. 2032
4.1117 HCI-3. 2034
4.1118 HCI-4. 2035
4.1119 HCI-5. 2037
4.1120 HCI-6. 2038
4.1121 HCI-7. 2040
4.1122 HCI-8. 2041
4.1123 HCI-9. 2043
4.1124 HCI-10. 2044
4.1125 HCI-11. 2046
4.1126 HCI-12. 2047
4.1127 HCI-13. 2049
4.1128 HCI-14. 2050
4.1129 HCI-15. 2052
4.1130 HCI-16. 2053
4.1131 HCI-17. 2055
4.1132 HCI-18. 2056
4.1133 HCI-19. 2058
4.1134 HCI-20. 2059
4.1135 HCI-21. 2061
4.1136 HCI-22. 2062
4.1137 HCI-23. 2064
4.1138 HCI-24. 2065
4.1139 HCI-25. 2067
4.1140 HCI-26. 2068
4.1141 HCI-27. 2069
4.1142 HCI-28. 2071
4.1143 HCI-31. 2072

4.1144 MACROCOMPONENT-1. 2074
4.1145 MACROCOMPONENT-2. 2076
4.1146 MACROCOMPONENT-3. 2077
4.1147 MACROCOMPONENT-4. 2079
4.1148 MACROCOMPONENT-5. 2081
4.1149 MACROCOMPONENT-6. 2082
4.1150 MACROCOMPONENT-7. 2084
4.1151 MACROCOMPONENT-8. 2086
4.1152 MACROCOMPONENT-9. 2087
4.1153 MACROCOMPONENT-10. 2089
4.1154 MACROCOMPONENT-11. 2091
4.1155 MACROCOMPONENT-12. 2093
4.1156 MAPPINGTABLE-1. 2094
4.1157 MAPPINGTABLE-2. 2096
4.1158 MAPPINGTABLE-3. 2097
4.1159 MAPPINGTABLE-4. 2099
4.1160 MAPPINGTABLE-5. 2101
4.1161 MAPPINGTABLE-6 (Revoked). 2102
4.1162 MAPPINGTABLE-7. 2104
4.1163 MAPPINGTABLE-8 (Revoked). 2105
4.1164 MAPPINGTABLE-9. 2107
4.1165 MAPPINGTABLE-10. 2109
4.1166 MAPPINGTABLE-11. 2110
4.1167 MAPPINGTABLE-12. 2112
4.1168 MAPPINGTABLE-13. 2114
4.1169 MAPPINGTABLE-15. 2116
4.1170 MAPPINGTABLE-16. 2117
4.1171 MAPPINGTABLE-17. 2119
4.1172 MAPPINGTABLE-18. 2121
4.1173 MAPPINGTABLE-19. 2123
4.1174 MAPPINGTABLE-20. 2124
4.1175 MAPPINGTABLE-21. 2126
4.1176 MAPPINGTABLE-22. 2127
4.1177 MAPPINGTABLE-23. 2129
4.1178 MAPPINGTABLE-24. 2130
4.1179 MAPPINGTABLE-101. 2132
4.1180 MAPPINGTABLE-102. 2133
4.1181 MAPPINGTABLE-103. 2135
4.1182 MAPPINGTABLE-104. 2136
4.1183 MAPPINGTABLE-105. 2138
4.1184 MAPPINGTABLE-107. 2139

4.1185 MAPPINGTABLE-108. 2141
4.1186 MAPPINGTABLE-109. 2142
4.1187 MAPPINGTABLE-110. 2144
4.1188 MAPPINGTABLE-111. 2145
4.1189 MAPPINGTABLE-112. 2147
4.1190 MAPPINGTABLE-113. 2148
4.1191 MAPPINGTABLE-114. 2150
4.1192 MAPPINGTABLE-115. 2151
4.1193 MAPPINGTABLE-116. 2153
4.1194 MAPPINGTABLE-117. 2154
4.1195 MAPPINGTABLE-118. 2156
4.1196 MAPPINGTABLE-201. 2157
4.1197 MAPPINGTABLE-202. 2159
4.1198 MAPPINGTABLE-203. 2160
4.1199 MAPPINGTABLE-204. 2162
4.1200 MAPPINGTABLE-205. 2163
4.1201 MAPPINGTABLE-206. 2165
4.1202 MAPPINGTABLE-207. 2166
4.1203 MAPPINGTABLE-208. 2168
4.1204 MAPPINGTABLE-209. 2169
4.1205 MAPPINGTABLE-210. 2171
4.1206 MAPPINGTABLE-211. 2172
4.1207 MAPPINGTABLE-212. 2174
4.1208 MAPPINGTABLE-213. 2175
4.1209 MAPPINGTABLE-215. 2177
4.1210 MAPPINGTABLE-217 (Revoked). 2178
4.1211 MAPPINGTABLE-218. 2180
4.1212 MAPPINGTABLE-219. 2181
4.1213 MAPPINGTABLE-220. 2183
4.1214 MAPPINGTABLE-221. 2184
4.1215 MAPPINGTABLE-222. 2186
4.1216 MAPPINGTABLE-224. 2187
4.1217 MAPPINGTABLE-225. 2189
4.1218 MAPPINGTABLE-226. 2190
4.1219 MAPPINGTABLE-227. 2192
4.1220 MAPPINGTABLE-228. 2193
4.1221 MAPPINGTABLE-229. 2195
4.1222 MAPPINGTABLE-230. 2196
4.1223 MAPPINGTABLE-231. 2198
4.1224 MAPPINGTABLE-232. 2199
4.1225 MAPPINGTABLE-233. 2201

4.1226 MAPPINGTABLE-234. 2202
4.1227 MAPPINGTABLE-235. 2204
4.1228 MAPPINGTABLE-236. 2205
4.1229 MAPPINGTABLE-237. 2207
4.1230 MAPPINGTABLE-238. 2208
4.1231 MAPPINGTABLE-239. 2210
4.1232 MAPPINGTABLE-240. 2211
4.1233 MAPPINGTABLE-241. 2213
4.1234 MAPPINGTABLE-242. 2214
4.1235 MAPPINGTABLE-243. 2215
4.1236 MAPPINGTABLE-244. 2217
4.1237 MAPPINGTABLE-245. 2218
4.1238 MAPPINGTABLE-246. 2220
4.1239 MAPPINGTABLE-247. 2221
4.1240 MAPPINGTABLE-248. 2223
4.1241 MAPPINGTABLE-249. 2224
4.1242 MAPPINGTABLE-250. 2226
4.1243 MAPPINGTABLE-251. 2227
4.1244 MAPPINGTABLE-252. 2229
4.1245 MAPPINGTABLE-253. 2231
4.1246 MAPPINGTABLE-254. 2232
4.1247 MAPPINGTABLE-255. 2234
4.1248 MAPPINGTABLE-256. 2235
4.1249 MAPPINGTABLE-257. 2237
4.1250 MAPPINGTABLE-258. 2239
4.1251 MAPPINGTABLE-259. 2240
4.1252 MAPPINGTABLE-260. 2242
4.1253 MAPPINGTABLE-262. 2243
4.1254 MAPPINGTABLE-263. 2245
4.1255 MAPPINGTABLE-264. 2247
4.1256 MAPPINGTABLE-265. 2248
4.1257 MAPPINGTABLE-266. 2250
4.1258 MAPPINGTABLECOMPONENT-1. 2252
4.1259 MAPPINGTABLECOMPONENT-2. 2253
4.1260 MAPPINGTABLECOMPONENT-3. 2255
4.1261 MAPPINGTABLECOMPONENT-4. 2256
4.1262 MAPPINGTABLECOMPONENT-5. 2258
4.1263 MAPPINGTABLECOMPONENT-6. 2259
4.1264 MAPPINGTABLECOMPONENT-7. 2261
4.1265 MAPPINGTABLECOMPONENT-8. 2262
4.1266 MAPPINGTABLECOMPONENT-9. 2264

4.1267 MAPPINGTABLECOMPONENT-10. 2265
4.1268 MAPPINGTABLECOMPONENT-11. 2267
4.1269 MAPPINGTABLECOMPONENT-12. 2269
4.1270 MAPPINGTABLECOMPONENT-13. 2271
4.1271 MONITORINGPLAN-1. 2272
4.1272 MONITORINGPLAN-2. 2274
4.1273 MONITORINGPLAN-3. 2275
4.1274 MONITORINGPLAN-4. 2277
4.1275 MONITORINGPLAN-5. 2278
4.1276 MONITORINGPLAN-6. 2280
4.1277 MONITORINGPLAN-7. 2281
4.1278 MONITORINGPLAN-8. 2283
4.1279 MONITORINGPLAN-9. 2284
4.1280 MONITORINGPLAN-10. 2286
4.1281 MONITORINGPLAN-11. 2287
4.1282 MONITORINGPLAN-12. 2289
4.1283 MONITORINGPLAN-13. 2290
4.1284 MONITORINGPLAN-14. 2292
4.1285 MONITORINGPLAN-15. 2293
4.1286 MONITORINGPLAN-16. 2295
4.1287 MONITORINGPLAN-17. 2296
4.1288 MONITORINGPLAN-18. 2298
4.1289 MONITORINGPLAN-19. 2299
4.1290 MONITORINGPLAN-20. 2301
4.1291 MONITORINGPLAN-21. 2302
4.1292 MONITORINGPLAN-22. 2304
4.1293 MONITORINGPLAN-23. 2305
4.1294 MONITORINGPLAN-24. 2307
4.1295 MONITORINGPLAN-25. 2308
4.1296 MONITORINGPLAN-26. 2310
4.1297 MONITORINGPLAN-27. 2311
4.1298 MONITORINGPLAN-28. 2313
4.1299 MONITORINGPLAN-29. 2314
4.1300 MONITORINGPLAN-30. 2316
4.1301 MONITORINGPLAN-31. 2317
4.1302 MONITORINGPLAN-32. 2319
4.1303 MONITORINGPLAN-33. 2321
4.1304 MONITORINGPLAN-34. 2322
4.1305 MONITORINGPLAN-35. 2324
4.1306 MONITORINGPLAN-36. 2325
4.1307 MONITORINGPLAN-37. 2327

4.1308 MONITORINGPLAN-38. 2328
4.1309 MONITORINGPLAN-39. 2330
4.1310 MONITORINGPLAN-40. 2331
4.1311 MONITORINGPLAN-41. 2333
4.1312 MONITORINGPLAN-42. 2335
4.1313 MONITORINGPLAN-43. 2336
4.1314 MONITORINGPLAN-44. 2338
4.1315 MONITORINGPLAN-45. 2339
4.1316 MONITORINGPLAN-46. 2341
4.1317 MONITORINGPLAN-47. 2343
4.1318 MONITORINGPLAN-48. 2344
4.1319 MONITORINGPLAN-49. 2346
4.1320 MONITORINGPLAN-50. 2347
4.1321 MONITORINGPLAN-51. 2349
4.1322 MONITORINGPLAN-52. 2350
4.1323 MONITORINGPLAN-53. 2352
4.1324 MONITORINGPLAN-54. 2353
4.1325 MONITORINGPLAN-55. 2355
4.1326 MONITORINGPLAN-56. 2356
4.1327 MONITORINGPLAN-57. 2358
4.1328 MONITORINGPLAN-58. 2359
4.1329 MONITORINGPLAN-59. 2361
4.1330 MONITORINGPLAN-60. 2362
4.1331 MONITORINGPLAN-61. 2364
4.1332 MONITORINGPLAN-62. 2365
4.1333 MONITORINGPLAN-63. 2367
4.1334 MONITORINGPLAN-64. 2368
4.1335 OPERATIONALSTATUS-1. 2370
4.1336 OPERATIONALSTATUS-2. 2371
4.1337 OPERATIONALSTATUS-3. 2373
4.1338 OPERATIONALSTATUS-4. 2374
4.1339 OPERATIONALSTATUS-5. 2376
4.1340 OPERATIONALSTATUS-6. 2377
4.1341 OPERATIONALSTATUS-7. 2379
4.1342 OPERATIONALSTATUS-8. 2380
4.1343 OPERATIONALSTATUS-9. 2382
4.1344 OPERATIONALSTATUS-10. 2383
4.1345 OPERATIONALSTATUS-11. 2385
4.1346 OPERATIONALSTATUS-12. 2386
4.1347 PREPAIDACCOUNTSTATE-1. 2388
4.1348 PREPAIDACCOUNTSTATE-2. 2389

4.1349 PREPAIDACCOUNTSTATE-3. 2391
4.1350 PREPAIDACCOUNTSTATE-4. 2392
4.1351 PREPAIDACCOUNTSTATE-5. 2394
4.1352 PREPAIDACCOUNTSTATE-6. 2395
4.1353 PREPAIDACCOUNTSTATE-7. 2397
4.1354 RANGETABLE-1. 2398
4.1355 RANGETABLE-2. 2400
4.1356 RANGETABLE-3. 2401
4.1357 RANGETABLE-4. 2403
4.1358 RANGETABLE-5. 2404
4.1359 RANGETABLE-6. 2406
4.1360 RANGETABLE-7. 2407
4.1361 RANGETABLE-8. 2409
4.1362 RANGETABLE-9. 2410
4.1363 RANGETABLE-10. 2412
4.1364 RANGETABLE-11. 2413
4.1365 RANGETABLE-12. 2415
4.1366 RANGETABLE-13. 2416
4.1367 RANGETABLE-14. 2418
4.1368 RANGETABLE-15. 2419
4.1369 RANGETABLE-16. 2420
4.1370 RANGETABLE-17. 2422
4.1371 RANGETABLE-18. 2423
4.1372 RANGETABLE-19. 2425
4.1373 RANGETABLE-20. 2426
4.1374 RANGETABLE-21. 2428
4.1375 RANGETABLE-22. 2429
4.1376 RANGETABLE-23. 2431
4.1377 RANGETABLE-24. 2432
4.1378 RANGETABLE-25. 2434
4.1379 RANGETABLE-26. 2435
4.1380 RANGETABLE-27. 2437
4.1381 RANGETABLE-28. 2439
4.1382 RANGETABLE-29. 2440
4.1383 RANGETABLE-30. 2442
4.1384 RANGETABLE-107. 2443
4.1385 RANGETABLE-108. 2445
4.1386 RANGETABLE-109. 2446
4.1387 RANGETABLE-110. 2448
4.1388 RANGETABLE-111. 2449
4.1389 RANGETABLE-112. 2451

4.1390 RANGETABLE-120. 2452
4.1391 RANGETABLE-121. 2454
4.1392 RANGETABLE-122. 2455
4.1393 RANGETABLE-123. 2457
4.1394 RANGETABLE-126. 2458
4.1395 RANGETABLE-128. 2460
4.1396 RANGETABLE-129. 2461
4.1397 RANGETABLE-130. 2463
4.1398 RANGETABLE-131. 2464
4.1399 RANGETABLE-132. 2466
4.1400 RANGETABLE-133. 2467
4.1401 RANGETABLE-134. 2469
4.1402 RANGETABLE-135. 2470
4.1403 RANGETABLE-136. 2472
4.1404 RANGETABLE-137. 2473
4.1405 RANGETABLE-138. 2475
4.1406 RANGETABLE-139. 2476
4.1407 RANGETABLE-140. 2478
4.1408 RANGETABLE-141. 2479
4.1409 RANGETABLE-142. 2481
4.1410 RANGETABLE-143. 2482
4.1411 RANGETABLE-145 (Revoked). 2484
ALLOWANCE-350 (Revoked). 2484
4.1412 RANGETABLE-146. 2485
4.1413 RANGETABLE-147. 2487
4.1414 RANGETABLE-148. 2488
4.1415 RANGETABLE-149. 2490
4.1416 RANGETABLE-150. 2491
4.1417 RANGETABLE-151. 2493
4.1418 RANGETABLE-152. 2494
4.1419 RANGETABLE-153. 2496
4.1420 RANGETABLE-154. 2497
4.1421 RANGETABLE-155. 2499
4.1422 RANGETABLE-156. 2500
4.1423 RANGETABLE-157. 2502
4.1424 RANGETABLE-158. 2503
4.1425 RANGETABLE-159. 2505
4.1426 RANGETABLE-160. 2506
4.1427 RANGETABLE-161. 2508
4.1428 RANGETABLE-162. 2509
4.1429 RANGETABLE-163. 2511

4.1430 RANGETABLE-229. 2512
4.1431 RANGETABLE-230. 2514
4.1432 RANGETABLE-231. 2515
4.1433 RANGETABLE-232. 2517
4.1434 RANGETABLE-233. 2518
4.1435 RANGETABLE-234. 2520
4.1436 RANGETABLE-235. 2521
4.1437 RANGETABLE-236. 2523
4.1438 RANGETABLE-237. 2524
4.1439 RANGETABLE-238. 2526
4.1440 RANGETABLE-239. 2527
4.1441 RANGETABLE-240. 2529
4.1442 RANGETABLE-241. 2530
4.1443 RANGETABLE-242. 2532
4.1444 RANGETABLE-243. 2533
4.1445 RANGETABLE-244. 2535
4.1446 RANGETABLE-245. 2536
4.1447 RANGETABLE-246. 2538
4.1448 RANGETABLE-247. 2539
4.1449 RANGETABLE-248. 2541
4.1450 RANGETABLE-249. 2542
4.1451 RANGETABLE-250. 2544
4.1452 RANGETABLE-251. 2545
4.1453 RANGETABLE-252. 2547
4.1454 RANGETABLE-253. 2548
4.1455 RANGETABLE-254. 2549
4.1456 RANGETABLE-255. 2551
4.1457 RANGETABLE-256. 2553
4.1458 RANGETABLE-257. 2554
4.1459 RANGETABLE-258. 2556
4.1460 RANGETABLE-259. 2557
4.1461 RANGETABLE-260. 2559
4.1462 RANGETABLE-261. 2561
4.1463 RANGETABLE-262. 2562
4.1464 RANGETABLE-263. 2564
4.1465 RANGETABLE-264. 2566
4.1466 RANGETABLE-265. 2567
4.1467 RANGETABLE-266. 2569
4.1468 RANGETABLE-267. 2571
4.1469 RANGETABLE-268. 2573
4.1470 RANGETABLE-269. 2574

4.1471 RANGETABLECOMPONENT-1. 2576
4.1472 RANGETABLECOMPONENT-2. 2577
4.1473 RANGETABLECOMPONENT-3. 2579
4.1474 RANGETABLECOMPONENT-4. 2580
4.1475 RANGETABLECOMPONENT-5. 2582
4.1476 RANGETABLECOMPONENT-6. 2583
4.1477 RANGETABLECOMPONENT-7. 2585
4.1478 RANGETABLECOMPONENT-8. 2586
4.1479 RANGETABLECOMPONENT-9. 2588
4.1480 RANGETABLECOMPONENT-10. 2589
4.1481 RANGETABLECOMPONENT-11. 2591
4.1482 RANGETABLECOMPONENT-12. 2592
4.1483 RANGETABLECOMPONENT-13. 2594
4.1484 RANGETABLECOMPONENT-14. 2595
4.1485 RANGETABLECOMPONENT-15. 2597
4.1486 RANGETABLECOMPONENT-16. 2598
4.1487 RANGETABLECOMPONENT-17. 2600
4.1488 RANGETABLECOMPONENT-18. 2601
4.1489 RANGETABLECOMPONENT-19. 2603
4.1490 RANGETABLECOMPONENT-20. 2605
4.1491 RANGETABLECOMPONENT-21. 2606
4.1492 RANGETABLECOMPONENT-22. 2608
4.1493 RANGETABLECOMPONENT-23. 2610
4.1494 RANGETABLECOMPONENT-24. 2611
4.1495 RANGETABLECOMPONENT-25. 2613
4.1496 RANGETABLECOMPONENT-26. 2614
4.1497 RANGETABLECOMPONENT-27. 2616
4.1498 RANGETABLECOMPONENT-28. 2617
4.1499 REFILLPLAN-1. 2619
4.1500 REFILLPLAN-2. 2620
4.1501 REFILLPLAN-3. 2622
4.1502 REFILLPLAN-4. 2623
4.1503 REFILLPLAN-5. 2625
4.1504 REFILLPLAN-6 (Revoked). 2626
4.1505 REFILLPLAN-7 (Revoked). 2628
4.1506 REFILLPLAN-8 (Revoked). 2630
4.1507 REFILLPLAN-9 (Revoked). 2631
4.1508 REFILLPLAN-10 (Revoked). 2633
4.1509 REFILLPLAN-11 (Revoked). 2635
4.1510 REFILLPLAN-12 (Revoked). 2636
4.1511 REFILLPLAN-13 (Revoked). 2638

4.1512 REFILLPLAN-14. 2640
4.1513 REFILLPLAN-15. 2641
4.1514 REFILLPLAN-16. 2643
4.1515 REFILLPLAN-18. 2644
4.1516 REFILLPLAN-22. 2646
4.1517 REFILLPLAN-23. 2647
4.1518 REFILLPLAN-24. 2649
4.1519 REFILLPLAN-25. 2650
4.1520 REFILLPLAN-26. 2652
4.1521 REFILLPLAN-28. 2653
4.1522 REFILLPLAN-29. 2655
4.1523 REFILLPLAN-30. 2656
4.1524 REFILLPLAN-31. 2658
4.1525 REFILLPLAN-32. 2659
4.1526 REFILLPLAN-33. 2661
4.1527 REFILLPLAN-34. 2662
4.1528 REFILLPLAN-35. 2664
4.1529 REFILLPLAN-36. 2665
4.1530 REFILLPLAN-37. 2667
4.1531 REFILLPLAN-38. 2669
4.1532 REFILLPLAN-39. 2670
4.1533 REFILLPLAN-40. 2672
4.1534 REFILLPLAN-43. 2673
4.1535 REFILLPLAN-44. 2675
4.1536 REFILLPLAN-45. 2676
4.1537 REFILLPLAN-48. 2678
4.1538 REFILLPLAN-49. 2679
4.1539 REFILLPLAN-50. 2681
4.1540 REFILLPLAN-51. 2682
4.1541 REFILLPLAN-52. 2684
4.1542 REFILLPLAN-53. 2685
4.1543 REFILLPLAN-54. 2687
4.1544 REFILLPLAN-55. 2688
4.1545 REFILLPLAN-56. 2690
4.1546 REFILLPLAN-57. 2691
4.1547 REFILLPLAN-58. 2693
4.1548 REFILLPLAN-59. 2694
4.1549 REFILLPLAN-60. 2696
4.1550 REFILLPLAN-61. 2697
4.1551 REFILLPLAN-62. 2699
4.1552 REFILLPLAN-63. 2701

4.1553 REFILLPLAN-64. 2702
4.1554 REFILLPLAN-65. 2704
4.1555 REFILLPLAN-66. 2705
4.1556 REFILLPLAN-67. 2707
4.1557 REFILLPLAN-68. 2708
4.1558 REFILLPLAN-69. 2710
4.1559 REFILLPLAN-70. 2711
4.1560 REFILLPLAN-71. 2713
4.1561 REFILLPLAN-72. 2715
4.1562 REFILLPLAN-73. 2716
4.1563 REFILLPLAN-74. 2718
4.1564 REFILLPLAN-75. 2719
4.1565 REFILLPLAN-76. 2721
4.1566 REFILLPLAN-77. 2722
4.1567 REFILLPLAN-78. 2724
4.1568 REFILLPLAN-79. 2726
4.1569 REFILLPLAN-80. 2727
4.1570 REFILLPLAN-81. 2729
4.1571 REFILLPLAN-82. 2730
4.1572 REFILLPLAN-83. 2732
4.1573 REFILLPLAN-84. 2733
4.1574 REFILLPLAN-91. 2735
4.1575 REFILLPLAN-92. 2736
4.1576 REFILLPLAN-93. 2738
4.1577 REFILLPLAN-94. 2739
4.1578 REFILLPLAN-96. 2741
4.1579 REFILLPLAN-97 (Revoked). 2742
4.1580 REFILLPLAN-104. 2744
4.1581 REFILLPLAN-106. 2745
4.1582 REFILLPLAN-108. 2747
4.1583 REFILLPLAN-109. 2748
4.1584 REFILLPLAN-110. 2750
4.1585 REFILLPLAN-115. 2751
4.1586 REFILLPLAN-117. 2753
4.1587 REFILLPLAN-118. 2755
4.1588 REFILLPLAN-119. 2756
4.1589 REFILLPLAN-120. 2757
4.1590 REFILLPLAN-121. 2759
4.1591 REFILLPLAN-126. 2760
4.1592 REFILLPLAN-127. 2762
4.1593 REFILLPLAN-128. 2763

4.1594 REFILLPLAN-129. 2765
4.1595 REFILLPLAN-130. 2767
4.1596 REFILLPLAN-132. 2768
4.1597 REFILLPLAN-133. 2770
4.1598 REFILLPLAN-134. 2771
4.1599 REFILLPLAN-135. 2773
4.1600 REFILLPLAN-136. 2774
4.1601 REFILLPLAN-138. 2776
4.1602 REFILLPLAN-140. 2777
4.1603 REFILLPLAN-142. 2779
4.1604 REFILLPLAN-143. 2780
4.1605 REFILLPLAN-144. 2782
4.1606 REFILLPLAN-145. 2783
4.1607 REFILLPLAN-146. 2785
4.1608 REFILLPLAN-147. 2786
4.1609 REFILLPLAN-170. 2788
4.1610 REFILLPLAN-171. 2790
4.1611 REFILLPLAN-172. 2791
4.1612 REFILLPLAN-173. 2793
4.1613 REFILLPLAN-174. 2794
4.1614 REFILLPLAN-175. 2796
4.1615 REFILLPLAN-176. 2797
4.1616 REFILLPLAN-177. 2799
4.1617 REFILLPLAN-178. 2800
4.1618 REFILLPLAN-179. 2802
4.1619 REFILLPLAN-180. 2803
4.1620 REFILLPLAN-181. 2805
4.1621 REFILLPLAN-182. 2806
4.1622 REFILLPLAN-183. 2808
4.1623 REFILLPLAN-184. 2809
4.1624 REFILLPLAN-185. 2811
4.1625 REFILLPLAN-186. 2812
4.1626 REFILLPLAN-187. 2814
4.1627 REFILLPLAN-188. 2815
4.1628 REFILLPLAN-189. 2817
4.1629 REFILLPLAN-190. 2819
4.1630 REFILLPLAN-191. 2820
4.1631 REFILLPLAN-201. 2822
4.1632 REFILLPLAN-202. 2823
4.1633 REFILLPLAN-203. 2825
4.1634 REFILLPLAN-204. 2826

4.1635 REFILLPLAN-205 (Revoked). 2828
4.1636 REFILLPLAN-206. 2829
4.1637 REFILLPLAN-207. 2831
4.1638 REFILLPLAN-208. 2832
4.1639 REFILLPLAN-209. 2834
4.1640 REFILLPLAN-210. 2836
4.1641 REFILLPLAN-211. 2837
4.1642 REFILLPLAN-212. 2838
4.1643 REFILLPLAN-213. 2840
4.1644 REFILLPLAN-214. 2841
4.1645 REFILLPLAN-215. 2843
4.1646 REFILLPLAN-216 (Revoked). 2844
4.1647 REFILLPLAN-217 (Revoked). 2846
4.1648 REFILLPLAN-218 (Revoked). 2848
4.1649 REFILLPLAN-219. 2849
4.1650 REFILLPLAN-232. 2851
4.1651 REFILLPLAN-233. 2852
4.1652 REFILLPLAN-234. 2854
4.1653 REFILLPLAN-235. 2856
4.1654 REFILLPLAN-236. 2857
4.1655 REFILLPLAN-237. 2859
4.1656 REFILLPLAN-239. 2860
4.1657 REFILLPLAN-240. 2862
4.1658 REFILLPLAN-241. 2863
4.1659 REFILLPLAN-242. 2865
4.1660 REFILLPLAN-243. 2867
4.1661 REFILLPLAN-244. 2868
4.1662 REFILLPLAN-245. 2870
4.1663 REFILLPLAN-246. 2871
4.1664 REFILLPLAN-247. 2873
4.1665 REFILLPLAN-248. 2874
4.1666 REFILLPLAN-302. 2876
4.1667 REFILLPLAN-304. 2877
4.1668 REFILLPLAN-305. 2879
4.1669 REFILLPLAN-306. 2880
4.1670 REFILLPLAN-307. 2882
4.1671 REFILLPLAN-309. 2883
4.1672 REFILLPLAN-310. 2885
4.1673 REFILLPLAN-311. 2886
4.1674 REFILLPLAN-312. 2888
4.1675 REFILLPLAN-313. 2889

4.1676 REFILLPLAN-314. 2891
4.1677 REFILLPLAN-315. 2892
4.1678 REFILLPLAN-316. 2894
4.1679 REFILLPLAN-317. 2895
4.1680 REFILLPLAN-318. 2897
4.1681 REFILLPLAN-319. 2898
4.1682 REFILLPLAN-320. 2900
4.1683 REFILLPLAN-321. 2901
4.1684 REFILLPLAN-322. 2903
4.1685 REFILLPLAN-323. 2904
4.1686 REFILLPLAN-324. 2906
4.1687 REFILLPLAN-325. 2907
4.1688 REFILLPLAN-326. 2909
4.1689 REFILLPLAN-327. 2910
4.1690 REFILLPLAN-333. 2912
4.1691 REFILLPLAN-334. 2913
4.1692 REFILLPLAN-335. 2915
4.1693 REFILLPLAN-336. 2916
4.1694 REFILLPLAN-337. 2918
4.1695 REFILLPLAN-400. 2919
4.1696 REFILLPLAN-401. 2921
4.1697 REFILLPLAN-402. 2922
4.1698 REFILLPLAN-403. 2924
4.1699 REFILLPLAN-404. 2925
4.1700 REFILLPLAN-405. 2927
4.1701 REFILLPLAN-406. 2928
4.1702 REFILLPLAN-407. 2930
4.1703 REFILLPLAN-408. 2931
4.1704 REFILLPLAN-409. 2933
4.1705 REFILLPLAN-410. 2934
4.1706 REFILLPLAN-411. 2936
4.1707 REFILLPLAN-450. 2937
4.1708 REFILLPLAN-451. 2939
4.1709 REFILLPLAN-452. 2940
4.1710 REFILLPLAN-453. 2942
4.1711 REFILLPLAN-454. 2943
4.1712 REFILLPLAN-455. 2945
4.1713 REFILLPLAN-456. 2946
4.1714 REFILLPLAN-457. 2948
4.1715 REFILLPLAN-458. 2949
4.1716 REFILLPLAN-459. 2951

4.1717 REFILLPLAN-460. 2952
4.1718 REFILLPLAN-461. 2954
4.1719 REFILLPLAN-462 (Revoked). 2955
4.1720 REFILLPLAN-475. 2957
4.1721 REFILLPLAN-476. 2958
4.1722 REFILLPLAN-477. 2960
4.1723 REFILLPLAN-478. 2961
4.1724 REFILLPLAN-479. 2963
4.1725 REFILLPLAN-480. 2965
4.1726 REFILLPLAN-481. 2966
4.1727 REFILLPLAN-482. 2968
4.1728 REFILLPLAN-483. 2969
4.1729 REFILLPLAN-484. 2971
4.1730 REFILLPLAN-485. 2972
4.1731 REFILLPLAN-486. 2974
4.1732 REFILLPLAN-488. 2975
4.1733 REFILLPLAN-489. 2977
4.1734 REFILLPLAN-490. 2978
4.1735 REFILLPLAN-491. 2980
4.1736 REFILLPLAN-492. 2981
4.1737 REFILLPLAN-493. 2983
4.1738 REFILLPLAN-494. 2984
4.1739 REFILLPLAN-495. 2986
4.1740 REFILLPLAN-496. 2987
4.1741 REFILLPLAN-497. 2989
4.1742 REFILLPLAN-498. 2990
4.1743 REFILLPLAN-499. 2992
4.1744 REFILLPLAN-500. 2993
4.1745 REFILLPLAN-501. 2995
4.1746 REFILLPLAN-502. 2996
4.1747 REFILLPLAN-503. 2998
4.1748 REFILLPLAN-504. 2999
4.1749 REFILLPLAN-505. 3001
4.1750 REFILLPLAN-506. 3002
4.1751 REFILLPLAN-507. 3004
4.1752 REFILLPLAN-508. 3005
4.1753 REFILLPLAN-510. 3007
4.1754 REFILLPLAN-511. 3008
4.1755 REFILLPLAN-512. 3010
4.1756 REFILLPLAN-513. 3011
4.1757 REFILLPLAN-514. 3013

4.1758 REFILLPLAN-515. 3014
4.1759 REFILLPLAN-516. 3016
4.1760 REFILLPLAN-517. 3017
4.1761 REFILLPLAN-518. 3019
4.1762 REFILLPLAN-519. 3021
4.1763 REFILLPLAN-520. 3022
4.1764 REFILLPLAN-521. 3024
4.1765 REFILLPLAN-522. 3025
4.1766 REFILLPLAN-523 (Revoked). 3027
4.1767 REFILLPLAN-525. 3029
4.1768 REFILLPLAN-526. 3030
4.1769 REFILLPLAN-527. 3032
4.1770 REFILLPLAN-528. 3033
4.1771 REFILLPLAN-529. 3035
4.1772 REFILLPLAN-530. 3036
4.1773 REFILLPLAN-531. 3038
4.1774 REFILLPLAN-532. 3039
4.1775 REFILLPLAN-533. 3041
4.1776 REFILLPLAN-534. 3043
4.1777 REFILLPLAN-535. 3044
4.1778 REFILLPLAN-536. 3046
4.1779 REFILLPLAN-537. 3047
4.1780 REFILLPLAN-538. 3049
4.1781 REFILLPLAN-539. 3050
4.1782 REFILLPLAN-540. 3052
4.1783 REFILLPLAN-541. 3053
4.1784 REFILLPLAN-542. 3055
4.1785 REFILLPLAN-543. 3056
4.1786 REFILLPLAN-544. 3058
4.1787 REFILLPLAN-545. 3059
4.1788 REFILLPLAN-546. 3061
4.1789 REFILLPLAN-547. 3062
4.1790 REFILLPLAN-548. 3063
4.1791 RESTCHARGING-1. 3065
4.1792 RESTCHARGING-2. 3066
4.1793 RFC-1. 3068
4.1794 RFC-2. 3070
4.1795 SPENDINGSTATUS-1. 3072
4.1796 SPENDINGSTATUS-2. 3073
4.1797 SPENDINGSTATUS-3. 3075
4.1798 SPENDINGSTATUS-4. 3076

4.1799 SPENDINGSTATUS-5. 3078
4.1800 SPENDINGSTATUS-6. 3079
4.1801 SPENDINGSTATUS-100. 3081
4.1802 SPENDINGSTATUS-101. 3082
4.1803 SPENDINGSTATUS-200. 3084
4.1804 SPENDINGSTATUS-201. 3085
4.1805 SPENDINGSTATUS-202. 3086
4.1806 SPENDINGSTATUS-203. 3088
4.1807 SPENDINGSTATUS-300. 3090
4.1808 SPENDINGSTATUS-301. 3091
4.1809 SPENDINGSTATUS-400. 3093
4.1810 SPENDINGSTATUS-401. 3094
4.1811 SPENDINGSTATUS-402. 3095
4.1812 SQL-1. 3097
4.1813 SQL-2. 3098
4.1814 SQL-3. 3100
4.1815 SQL-4. 3101
4.1816 SQL-5. 3103
4.1817 SQL-6. 3105
4.1818 SQL-7. 3106
4.1819 SQL-8. 3108
4.1820 SQL-9. 3109
4.1821 SQL-10. 3111
4.1822 SQL-11. 3112
4.1823 SQL-12. 3114
4.1824 SQL-13. 3115
4.1825 SQL-14. 3117
4.1826 SQL-15. 3118
4.1827 SQL-16. 3120
4.1828 SQL-17. 3121
4.1829 SQL-18. 3123
4.1830 SQL-19. 3124
4.1831 SQL-20. 3126
4.1832 SQL-21. 3127
4.1833 SQL-22. 3129
4.1834 SQL-23. 3130
4.1835 SQL-24. 3132
4.1836 SQL-25. 3133
4.1837 SQL-26. 3135
4.1838 SQL-27. 3136
4.1839 SQL-28. 3138

4.1840 SQL-29. 3139
4.1841 SQL-30. 3141
4.1842 SQL-31. 3142
4.1843 SQL-32. 3144
4.1844 SQL-33. 3145
4.1845 SQL-34. 3147
4.1846 SQL-35. 3148
4.1847 SQL-36. 3150
4.1848 SQL-37. 3151
4.1849 SQL-38. 3153
4.1850 SQL-39. 3154
4.1851 SQL-40. 3156
4.1852 SQL-41. 3157
4.1853 SQL-42. 3159
4.1854 SQL-43. 3160
4.1855 SQL-44. 3162
4.1856 SQL-45. 3163
4.1857 SQL-46. 3165
4.1858 SQL-47. 3166
4.1859 SQL-48. 3168
4.1860 SQL-49. 3169
4.1861 SQL-50. 3171
4.1862 SQL-51. 3172
4.1863 SQL-52. 3174
4.1864 SQL-53. 3175
4.1865 SQL-54. 3177
4.1866 SQL-55. 3178
4.1867 SQL-56. 3180
4.1868 SQL-57. 3181
4.1869 SQL-58. 3183
4.1870 SQL-59. 3184
4.1871 SQL-60. 3186
4.1872 SQL-61. 3187
4.1873 SQL-62. 3189
4.1874 SQL-63. 3190
4.1875 SQL-64. 3192
4.1876 SUBSCRIBERDATA-1. 3193
4.1877 SUBSCRIBERDATA-2. 3195
4.1878 SUBSCRIBERDATA-3. 3196
4.1879 SUBSCRIBERDATA-4. 3198
4.1880 SUBSCRIBERDATA-5. 3199

4.1881 SUBSCRIBERDATA-6. 3201
4.1882 SUBSCRIBERDATA-7. 3202
4.1883 SUBSCRIBERDATA-8. 3204
4.1884 SUBSCRIBERDATA-9. 3205
4.1885 SUBSCRIBERDATA-10. 3207
4.1886 SUBSCRIBERDATA-11. 3208
4.1887 SUBSCRIBERDATA-12. 3210
4.1888 SUBSCRIBERDATA-13. 3211
4.1889 SUBSCRIBERDATA-14. 3213
4.1890 SUBSCRIBERACCOUNT-1. 3214
4.1891 SUBSCRIBERACCOUNT-2. 3216
4.1892 SUBSCRIBERACCOUNT-3. 3217
4.1893 SUBSCRIBERACCOUNT-4. 3219
4.1894 SUBSCRIBERACCOUNT-5. 3220
4.1895 SUBSCRIBERACCOUNT-6. 3222
4.1896 TRANSPORTREQUEST-1. 3223
4.1897 TRANSPORTREQUEST-2. 3225
4.1898 TRANSPORTREQUEST-3. 3226
4.1899 TRANSPORTREQUEST-4. 3228
4.1900 TRANSPORTREQUEST-5. 3229
4.1901 TRANSPORTREQUEST-6. 3230
4.1902 TRANSPORTREQUEST-7. 3232
4.1903 TRANSPORTREQUEST-8. 3233
4.1904 TRANSPORTREQUEST-9. 3235
4.1905 TRANSPORTREQUEST-10. 3236
4.1906 TRANSPORTREQUEST-11. 3238

1 Before You Start

This SAP product documentation provides you with user assistance about the SAP Convergent Charging software product when developing or implementing the integration between your client application (or system) and the SAP CC systems in your SAP system landscape.

> → Recommendation
>
> For offline consultation, you can download this document on SAP Help Portal: https://help.sap.com

Refer to the SAP CC 2023 Web Services Documentation (SOAP), SAP CC 2023 REST API Documentation for Implementation and the Java/XML API Reference (Core Library). Consult the documentation set of SAP CC for more information.

Giving you the best user experience is our priority. Therefore, we do our best to provide you with the clearest and the most complete documentation possible.

For this purpose, feel free to leave additional feedback by using the dedicated feature on the Help Portal. Please write some details about your suggestion. Based on SAP user feedbacks, we improve your documentation and deliver Frequently Asked Questions (FAQs) about all aspects of working with SAP Convergent Charging efficiently. We complete these solutions with our best time-saving and task-completion tips and tricks.

You can also visit our page Community Questions and Answers for SAP Convergent Charging.

About This Document [page 50]

Target Audience [page 51]

What's New in This Document [page 51]

Additional Information [page 53]

Document Abbreviations [page 53]

1.1 About This Document

The **Error Code Reference** documentation is **a non-exhaustive list of the errors that can be returned to a client application** sending request messages to the SAP CC Core Server system.

- Your application (or system) sends service operation requests by using the different technical interfaces of SAP Convergent Charging 2023 system:
  - Web Services (WS)
  - REST APIs
  - HTTP Communication Interface (HCI)
  - Message TCP
- The user interfaces of SAP Convergent Charging send their operation requests to the SAP CC system

Some business or technical issues may occur. The SAP CC system can audit these operations by recording the isolated or cascaded failures.

This user assistance is intended for troubleshooting purposes and for understanding why an operation was not executed or has failed in the SAP CC Core Server system (aka SAP Convergent Charging system).

View the information topic [page 60] that relates to your situation and continue your investigations.

The Error Code Reference contains the following main sections:

- Working with Error Causes and Codes [page 56]
  This section summarizes the different types of errors and when they may occur
- Access by Modules [page 60]
  This section contains the list of the different modules, representing a set of error messages related to a same module
- Log A-Z Index
  This section contains the list of all available error messages and resolution plans

1.2 Target Audience

This documentation is intended for the following audiences:

- Solution and Technology Consultants
- Project Team Member (Implementation, Integration)
- Application and System Administrators
- Operation Team Expert
- Support Specialist (SAP SE, Local Support Team)

1.3 What's New in This Document

What's New in SAP CC 2023 FPS 3?

As of version 2023 FPS 3, SAP Convergent Charging (SAP CC) provides you with a few content modifications.

- New errors in the technical module `CHARGECOMPONENT` are created:
  - CHARGECOMPONENT-116 [page 1208]
  - CHARGECOMPONENT-117 [page 1209]

What's New in SAP CC 2023 FPS 2?

As of version 2023 FPS 2, SAP Convergent Charging (SAP CC) provides you with a few content modifications.

- New errors in the technical module `MAPPINGTABLE` are created:
  - MAPPINGTABLE-262 [page 2243]
  - MAPPINGTABLE-263 [page 2245]
  - MAPPINGTABLE-264 [page 2247]
  - MAPPINGTABLE-265 [page 2248]
  - MAPPINGTABLE-266 [page 2250]
- New errors in the technical module `RANGETABLE` are created:
  - RANGETABLE-258 [page 2556]
  - RANGETABLE-259 [page 2557]
  - RANGETABLE-260 [page 2559]
  - RANGETABLE-261 [page 2561]
  - RANGETABLE-262 [page 2562]
  - RANGETABLE-263 [page 2564]
  - RANGETABLE-264 [page 2566]
  - RANGETABLE-265 [page 2567]
  - RANGETABLE-266 [page 2569]
  - RANGETABLE-267 [page 2571]
  - RANGETABLE-268 [page 2573]
  - RANGETABLE-269 [page 2574]

What's New in SAP CC 2023 FPS 1?

As of version 2023 FPS 1, SAP Convergent Charging (SAP CC) provides you with a few content modifications.

- New errors in the technical module `HCI` are created:
  - HCI-25 [page 2067]
  - HCI-26 [page 2068]
  - HCI-27 [page 2069]
  - HCI-28 [page 2071]
  - HCI-31 [page 2072]

What's New in SAP CC 2023 (in FPS 0)?

As of major release 2023, SAP Convergent Charging (SAP CC) provides you with a few content modifications.

- New errors in the technical module `CHARGEPLAN` are created:
  - CHARGEPLAN-289 [page 1650]

- CHARGEPLAN-290 [page 1651]
- CHARGEPLAN-291 [page 1653]

- A new error in the technical module `CONTRACT` is created:
  - CONTRACT-122 [page 1932]
- A new error in the technical module `MACROCOMPONENT` is created:
  - MACROCOMPONENT-12 [page 2093]

1.4 Additional Information

For more information about specific topics, see the quick links as shown in the table below:

Content	Quick Link
SAP CC documentation	help.sap.com/cc2023
Related SAP notes	support.sap.com/notes
Related release notes	https://support.sap.com/en/my-support/knowledge-base.html
Released Platforms	Supported Database Platforms
SAP Solution Manager	http://support.sap.com/solutionmanager

1.5 Document Abbreviations

Abbreviation	Meaning
3GPP	3rd Generation Partnership Project
AAA	Authentication, Authorization, and Accounting
AVP	Attribute-Value Pair
API	Application Programming Interface
BART	Batch Acquisition and Rating Toolset
BIT	Billable Item
BSS	Business Support System
CCA	Credit Control Answer
CCR	Credit Control Request
CDR	Call Detail Record (Telecommunications industry), or more generally Consumption Detail Record

Abbreviation	Meaning
CI	Chargeable Item
CIF	Charging output Integration Framework
CIT	Charged Item
CRM	Customer Relationship Management
CSR	Customer Sale Representative
CSV	Comma Separated Value
CTS	Change and Transport System
DSR	Distributed Statistics Record
ECUR	Event Charging with Unit Reservation
GLAS	SAP Global License Auditing Service
GUI	Graphical User Interface
HA	High Availability
HCI	HTTP Communication Interface
HTTP	HyperText Transfer Protocol
HTTPS	HyperText Transfer Protocol Secured
IEC	Import/Export Connector
IEC (Diameter)	Immediate Event Charging
IMSI	International Mobile Subscriber Identity
ISDN	Integrated Services Digital Network
JDBC	Java Database Connectivity
LRU	Least Recently Used
MMS	Multimedia Messaging Service
MSISDN	Mobile Station ISDN Number
OCS	Online Charging System
OFCS	Offline Charging System
OSS	Operational Support System
QoS	Quality of Service
RAC	Real Application Cluster
RDBMS	Relational Database Management System
REST	REpresentational State Transfer
RIF	Rerating Integration Framework
RRL	Reservation Renewal Listener
SLD	System Landscape Directory
SCIM	System for Cross-domain Identity Management

Abbreviation	Meaning
SCP	Service Control Point
SCUR	Session Charging with Unit Reservation
SMD	SAP Manager Diagnostic
SSL	Secure Socket Layer
SSRL	Spending Status Report Listener
TAF	Transparent Application Failover
TIF	Transaction Integration Framework
TLS	Transport Layer Security
TV	Tag;Value
URL	Uniform Resource Locator
USID	User Service Identifier
UTI	User Technical Identifier
VAT	Value Added Tax
VSA	Vendor Specific Attribute
XML	eXtended Markup Language

2 Working with Error Causes and Codes

Implementation

During the implementation project, you use this documentation when integrating the business services provided by the Web Services (WS) technical interface of SAP Convergent Charging. Refer to the error handling information provided with its SOAP[1] or REST[2] API[3] specifications for each service operation that you can implement in your SAP system landscape.

You can view some errors translated from the HCI[4] technical interface that is used by the SAP CC user interfaces (Core Tool or Cockpit).

Note that you can partially use this documentation when developing your applications with the Java APIs of SAP CC for troubleshooting certain operations requested via the Message TCP technical interface.

Technical Operations

During the *project implementation phase* or the *productive operation phase*, the errors detailed in this documentation may be visible in:

- **Logs or traces** of the applications and systems that connect to the SAP CC systems
- **Audited user operations** that you can view and inspect with the app Display User Operations in SAP Convergent Charging 2023 Cockpit
- **XML**[5] **messages** exchanged between the SAP CC system and an SAP CC user interface

Errors

SAP Convergent Charging manages different types of errors replied in the operation responses. An error may include:

- A **failure category** such as already exists, does not exist, invalid, prerequisite missing, incompatible configuration, illegal state, or temporary illegal state. The definitions of these categories depend on the technical interfaces and their specification. See the corresponding documentation.
- A **comprehensive message**

---

1 Simple Object Access Protocol
2 REpresentational State Transfer
3 Application Programming Interface
4 HTTP Communication Interface
5 eXtended Markup Language

- An **error cause**
- An **error stack of 'caused-by' information items**

SAP CC handles several error patterns that are specialized to the requested service operations. The failure categories are defined in the corresponding SAP CC API specifications.

Each error cause includes:

- A unique identifier composed with:
  - A technical module name
  - A numerical cause code
- An **intelligent message** completed dynamically
- Suggested **actions and steps** for troubleshooting the issue

> ⚠ Caution
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

> Example
>
> See the technical details that specify the responses of the `Find Subscriber Accounts` operation provided in the SAP CC 2023 Web Services Documentation (SOAP).
>
> You can see also the technical details of the `Charge a Single Chargeable Item (Offline Charging or Soft Real-Time)` operation.

Error Codes

Errors are listed and grouped by technical modules [page 60]. The code of an error is unique. It is composed of the name of the module followed by a number identifying the error inside the module.

Error Messages

SAP CC provides you with a comprehensive message that explains why the processing has failed in the SAP CC system or why the SAP CC system did not trigger the execution of the expected process.

For a better experience, the system completes a message with runtime information such as identifiers, names, references, indexes, or dates/times. For example, it can be the code of an object managed in the SAP CC system or in its back-end database.

> **Note**
>
> The meaning of an error message depends on the software layers and on the internal architecture of the SAP CC systems. The error message relates to the internal vision of the SAP CC system.
>
> You may have to translate the message terms to the SAP CC terminology. Consider the concept views and the data model views for the technical interface that has transported the error message. Refer to the appropriate specifications:
>
> - SAP CC 2023 Web Services Documentation (SOAP)
> - Java/XML API Reference (Core Library)

Next Actions and Steps (Troubleshooting)

Use this information to troubleshoot your issue with a cause analysis and a solution.

Deprecated and Revoked Error Codes

As SAP Convergent Charging evolves over time, rare error codes may become obsolete because of some enhancements in the SAP CC system or data.

When a feature or a function of SAP CC becomes deprecated, some error codes can be deprecated or revoked.

When a feature is revoked, some error codes can become revoked.

Feature deprecation is announced whereas error code deprecation or revocation cannot be announced in advance.

Error Code	Definition
Deprecated	**Deprecated error codes** are error codes that the newest versions of your SAP CC system still generate but they may become revoked. Some newest error codes may replace the obsolete codes
Revoked	**Revoked error codes** are error codes that the newest versions of your SAP CC system will not generate anymore. The codes are not signaled whereas some old log messages or traces for the SAP CC system or for other systems may contain these codes with an error message.

> **Example**
>
> For example, with this software evolution, the code MAPPINGTABLE-232 [page 2199] replaces the MAPPINGTABLE-6 (Revoked) [page 2102] error code.

Related Documentation

- SAP CC 2023 Administration and Operation Guide
- SAP CC 2023 Application Help
- SAP CC 2023 Web Services Documentation (SOAP)
- Java/XML API Reference (Core Library)
- SAP CC 2023 Primary Help for Core Tool

3 Access by Modules

Module	Definition
AGGREGATIONPOLICY [page 64]	The `AGGREGATIONPOLICY` module groups few error codes that relate to errors occurring when processing basic operation requests on aggregation policies.
ALLOWANCE [page 64]	The `ALLOWANCE` module groups multiple error codes that relate to errors occurring when implementing basic operations on allowancesgroups multiple error codes that relate to errors occurring when implementing basic operations on allowances: • Allowance plan • Allowance logic
CC-SEC-AUTH [page 65]	Errors related to authentication, mainly describing logon and password issues.
CHANGEID [page 65]	Errors occurring when issues are encountered when using change identifiers.
CHANGELIST [page 66]	Errors which occur when implementing basic operations on change lists.
CHARGECOMPONENT [page 66]	Errors which occur when implementing basic operations on charge components (including price plans and charging plans). A charge component is a reusable charge that is added to different charge plans to design the pricing logic for several customer services.
CHARGEPLAN [page 67]	Errors which occur when implementing basic operations on charge plans and charge plan items. A charge plan item represents a reusable charge customized in a charge plan.
CHARGINGPLAN [page 67]	Errors which occur when the execution of a price plan or a charging plan fails during a rating or charging operation.
CICLASS [page 68]	Errors which occur when implementing basic operations on chargeable item classes.
CONTRACT [page 68]	Errors that occur when using or implementing some basic operations (create, search, modify, and delete) on charging contracts (pricing and charging view for provider contracts) and included contract items. This customer master data relates to: • An end customer for the subscription- and usage-based services • A pricing catalog for these value-added services • The ordered and contracted terms

Module	Definition
CONTRACTSTATE [page 69]	Errors which occur when implementing operations dedicated to the management of the initial state of charging contracts during the migration of master data related to end customers. A charging contract is the charging data that is part of the overall provider contract. It is a partial view of this master data and is stored in SAP CC. **Note** Refer to the SAP CC 2023 Web Services Documentation (SOAP) for more information about the necessary Customizing activities to implement the customer data migration.
CUSTOMERDATA [page 70]	Errors which occur when exporting or importing customer data with the Web Services. **Note** These errors relate to the contract transfer feature in case this feature is implemented on your landscape. This feature is available if SAP CC is integrated with SAP CRM and SAP ERP, it enables you to transport contracts from one SAP CC system to another SAP CC system.
CUSTOMERMANAGEMENTAREA [page 70]	Errors which occur when an SAP CC user manages some customer management areas (CMAs) with the SAP CC Core Tool user interface: • Maintain (Create, Modify, and Delete) • Get (Search) These operations are only available in the SAP CC Core Tool user interface when the SAP system landscape includes SAP CRM or SAP ERP systems. These errors must not be visible by an SAP CC user.
DICTIONARY [page 71]	Errors related to the counter dictionary.
HCI [page 71]	The HCI[6] module groups multiple generic error codes that relate to some XML[7] communication validation.
MACROCOMPONENT [page 72]	Errors which occur when managing (creating, changing, or importing) some reusable charges or refill logic objects that include a price plan (or a charging plan or the refill logic) configured with a logic component named Macro Operator to use an existing pricing macro in the pricing catalog.

[6] HTTP Communication Interface
[7] eXtended Markup Language

Module	Definition

MAPPINGTABLE [page 73]	Errors that occur when using or implementing some basic operations (create, search, modify, import, and delete) on the following master data:
	• In service pricing catalogs:
	  • Mapping table classes
	  • Mapping tables
	• In customer master data:
	  • Subscriber mapping tables

MAPPINGTABLECOMPONENT [page 73]	Errors which occur when managing (creating, changing, or importing) some reusable charges or refill logic objects that include a price plan (or a charging plan or the refill logic) configured with a logic component named Mapping Table Lookup in Cockpit and Mapping Table Introducer in Core Tool.
MONITORINGPLAN [page 74]	Errors which occur when: • Implementing the find operations for monitoring plans via the Web Services technical interface • Using basic operations (create, search, modify, and delete) that manage monitoring plans stored in SAP CC. These private operations are available in the HCI[8] technical interface that is used by the SAP CC Core Tool user interface
OPERATIONALSTATUS [page 75]	Errors which occur when modifying the operational status of a charging contract with the Web Service operation `chargingContractOperationalStatusChange`.
PREPAIDACCOUNTSTATE [page 75]	Errors which occur when implementing operations dedicated to the management of the initial state of prepaid accounts in subscriber accounts during the migration of master data related to end customers.

RANGETABLE [page 76]	Errors that occur when using or implementing some basic operations (create, search, modify, import, and delete) on the following master data:
	• In service pricing catalogs:
	  • Range table classes
	  • Range tables
	• In customer master data:
	  • Subscriber range tables

[8] HTTP Communication Interface

Module	Definition
RANGETABLECOMPONENT [page 76]	Errors which occur when managing (creating, changing, or importing) some reusable charges or refill logic objects that include a price plan (or a charging plan or the refill logic) configured with a logic component named Range Table Lookup in Cockpit and Range Table Introducer in Core Tool. This logic component enables to design the pricing logic that uses data tables: Range tables of the pricing catalog of the service provider or subscriber range tables assigned to a subscriber account.
REFILLPLAN [page 77]	Errors which occur when using basic operations on: • Refill Item Classes • Refill Logic • Refill Plans • Refill Record Classes
RESTCHARGING [page 77]	Errors which occur when the call of a REST API for an event- or a session-based rating operation fails.
RFC [page 78]	Errors that occur when calling or executing remote function calls (RFCs).
SPENDINGSTATUS [page 78]	The `SPENDINGSTATUS` module groups multiple error codes that relate to errors occurring when processing operations that manages spending status descriptions stored in SAP Convergent Charging 2023: • Create • Modify • Search • Delete These private operations are available in the *HCI technical interface* that is used by the SAP CC Cockpit and the SAP CC Core Tool user interfaces.
SQL [page 79]	The `SQL` module groups few error codes that relate to the initialization and usage of the backend database.
SUBSCRIBERDATA [page 80]	Errors related to the import or the export of subscriber data. Subscriber data (or customer related data) consists in: • A subscriber account • Subscriptions • Accesses • Counter snapshots Note that the import and the export of subscriber data are mainly used during a migration.

Module	Definition
SUBSCRIBERACCOUNT [page 80]	Errors which occur when implementing operations dedicated to the management of subscriber accounts.
TRANSPORTREQUEST [page 81]	Errors which occur when implementing basic operations on transport requests.

3.1 AGGREGATIONPOLICY

Summary

The `AGGREGATIONPOLICY` module groups few error codes that relate to errors occurring when processing basic operation requests on aggregation policies.

Additional Information

SAP CC 2023 Application Help

Error Codes

Refer to the complete list of error codes related to aggregation policies by filtering the *Error Code* column of the Error Code Index [page 82] with **`aggregationpolicy`**.

3.2 ALLOWANCE

Summary

The `ALLOWANCE` module groups multiple error codes that relate to errors occurring when implementing basic operations on allowancesgroups multiple error codes that relate to errors occurring when implementing basic operations on allowances:

- Allowance plan
- Allowance logic

Additional Information

See Master Data chapter in the SAP CC 2023 Application Help documentation.

Error Codes

Refer to the complete list of error codes related to allowances by filtering the *Error Code* column of the Error Code Index [page 82] with **`allowance`**.

3.3 CC-SEC-AUTH

Summary

Errors related to authentication, mainly describing logon and password issues.

Error Codes

Refer to the complete list of error codes related to authentication by filtering the *Error Code* column of the Error Code Index [page 82] with **`cc-sec-auth`**.

3.4 CHANGEID

Summary

Errors occurring when issues are encountered when using change identifiers.

Error Codes

Refer to the complete list of error codes related to change identifiers by filtering the *Error Code* column of the Error Code Index [page 82] with **`changeid`**.

3.5 CHANGELIST

Summary

Errors which occur when implementing basic operations on change lists.

Error Codes

Refer to the complete list of error codes related to change lists by filtering the *Error Code* column of the Error Code Index [page 82] with **`changelist`**.

3.6 CHARGECOMPONENT

Summary

Errors which occur when implementing basic operations on charge components (including price plans and charging plans). A charge component is a reusable charge that is added to different charge plans to design the pricing logic for several customer services.

Additional Information

SAP CC 2023 Application Help

Error Codes

Refer to the complete list of error codes related to charge components by filtering the *Error Code* column of the Error Code Index [page 82] with **`chargecomponent`**.

3.7 CHARGEPLAN

Summary

Errors which occur when implementing basic operations on charge plans and charge plan items. A charge plan item represents a reusable charge customized in a charge plan.

Error Codes

Refer to the complete list of error codes related to charge plans by filtering the *Error Code* column of the Error Code Index [page 82] with **`chargeplan`**.

3.8 CHARGINGPLAN

Summary

Errors which occur when the execution of a price plan or a charging plan fails during a rating or charging operation.

Error Codes

Refer to the complete list of error codes related to charging plans by filtering the *Error Code* column of the Error Code Index [page 82] with **`chargingplan`**.

3.9 CICLASS

Summary

Errors which occur when implementing basic operations on chargeable item classes.

Error Codes

Refer to the complete list of error codes related to chargeable item classes by filtering the *Error Code* column of the Error Code Index [page 82] with **`ciclass`**.

3.10 CONTRACT

Summary

Errors that occur when using or implementing some basic operations (create, search, modify, and delete) on charging contracts (pricing and charging view for provider contracts) and included contract items.

This customer master data relates to:

- An end customer for the subscription- and usage-based services
- A pricing catalog for these value-added services
- The ordered and contracted terms

Additional Information

For more information and user assistance about the master data concepts (provider contracts, subscriber accounts), consult the SAP CC 2023 Application Help

> **Note**
>
> For more implementation and integration information about contracts in SAP CC, refer to the documentation for the corresponding technical interfaces (Web Services (WS), HCI[9]). See the related specifications (SOAP[10] APIs[11], Java APIs, or XML[12] APIs) such as:

- SOAP:
  - Charging Contract Management web service
  - Create or Change a Charging Contract (WS) operation
- Java (or XML):
  - `com.highdeal.contract.hci` Java package

Error Codes

Refer to the complete list of error codes related to charging contracts and charging contract items by filtering the *Error Code* column of the Error Code Index [page 82] with **`contract`**.

3.11 CONTRACTSTATE

Summary

Errors which occur when implementing operations dedicated to the management of the initial state of charging contracts during the migration of master data related to end customers.

A charging contract is the charging data that is part of the overall provider contract. It is a partial view of this master data and is stored in SAP CC.

> ⓘ Note
>
> Refer to the SAP CC 2023 Web Services Documentation (SOAP) for more information about the necessary Customizing activities to implement the customer data migration.

Error Codes

Refer to the complete list of error codes related to contract states by filtering the *Error Code* column of the Error Code Index [page 82] with **`contractstate`**.

[9] HTTP Communication Interface
[10] Simple Object Access Protocol
[11] Application Programming Interface
[12] eXtended Markup Language

3.12 CUSTOMERDATA

Summary

Errors which occur when exporting or importing customer data with the Web Services.

> **Note**
>
> These errors relate to the contract transfer feature in case this feature is implemented on your landscape. This feature is available if SAP CC is integrated with SAP CRM and SAP ERP, it enables you to transport contracts from one SAP CC system to another SAP CC system.

Additional Information

SAP CC 2023 Application Help

Error Codes

Refer to the complete list of error codes related to customer data by filtering the *Error Code* column of the Error Code Index [page 82] with `customerdata`.

3.13 CUSTOMERMANAGEMENTAREA

Summary

Errors which occur when an SAP CC user manages some customer management areas (CMAs) with the SAP CC Core Tool user interface:

- Maintain (Create, Modify, and Delete)
- Get (Search)

These operations are only available in the SAP CC Core Tool user interface when the SAP system landscape includes SAP CRM or SAP ERP systems. These errors must not be visible by an SAP CC user.

> **Note**
>
> - SAP CC Core Tool may display some error codes in the below list. Use this technical documentation for troubleshooting purpose. In a production system landscape, contact your SAP Support Team.
> - These private operations are available in the HCI[13] technical interface that is used by the SAP CC Core Tool user interface. The operations cannot be implemented in a connected system.

Error Codes

Refer to the complete list of error codes related to customer management areas by filtering the *Error Code* column of the Error Code Index [page 82] with **`customermanagementarea`**.

3.14 DICTIONARY

Summary

Errors related to the counter dictionary.

Error Codes

Refer to the complete list of error codes related to the counter dictionary by filtering the *Error Code* column of the Error Code Index [page 82] with **`dictionary`**.

3.15 HCI

Summary

The HCI[14] module groups multiple generic error codes that relate to some XML[15] communication validation.

[13] HTTP Communication Interface

> ### Example
>
> Typical errors are:
>
> - Errors on data types
> - Errors on the data structure

Error Codes

Refer to the complete list of error codes related to XML communication by filtering the *Error Code* column of the Error Code Index [page 82] with **`hci`**.

3.16 MACROCOMPONENT

Summary

Errors which occur when managing (creating, changing, or importing) some reusable charges or refill logic objects that include a price plan (or a charging plan or the refill logic) configured with a logic component named Macro Operator to use an existing pricing macro in the pricing catalog.

> ### Note
>
> All these errors are embedded in a CHARGECOMPONENT [page 66] error or in a REFILLPLAN [page 77] error. Check the error stack in the operation response answered by the SAP CC system.

Error Codes

Refer to the complete list of error codes related to macros by filtering the *Error Code* column of the Error Code Index [page 82] with **`macrocomponent`**.

[14] HTTP Communication Interface
[15] eXtended Markup Language

3.17 MAPPINGTABLE

Summary

Errors that occur when using or implementing some basic operations (create, search, modify, import, and delete) on the following master data:

- In service pricing catalogs:
  - Mapping table classes
  - Mapping tables
- In customer master data:
  - Subscriber mapping tables

> **Note**
>
> As of release 4.1 of SAP CC, some error codes are revoked [page 58] and replaced because the mapping tables (in pricing catalogs) and the subscriber mapping tables can have up to 20 input and 30 output columns.
>
> For example, with this software evolution, the code 232 [page 2199] replaces the code 6 [page 2102].

Error Codes

Refer to the complete list of error codes related to mapping tables and classes by filtering the *Error Code* column of the Error Code Index [page 82] with **`mappingtable`**.

3.18 MAPPINGTABLECOMPONENT

Summary

Errors which occur when managing (creating, changing, or importing) some reusable charges or refill logic objects that include a price plan (or a charging plan or the refill logic) configured with a logic component named Mapping Table Lookup in Cockpit and Mapping Table Introducer in Core Tool.

> ⓘ Note
>
> All these errors are embedded in a CHARGECOMPONENT [page 66] error or in a REFILLPLAN [page 77] error. Check the error stack in the operation response answered by the SAP CC system.

Error Codes

Refer to the complete list of error codes related to Mapping Table Lookup or Mapping Table Introducer component by filtering the *Error Code* column of the Error Code Index [page 82] with **`mappingtablecomponent`**.

3.19 MONITORINGPLAN

Summary

Errors which occur when:

- Implementing the find operations for monitoring plans via the Web Services technical interface
- Using basic operations (create, search, modify, and delete) that manage monitoring plans stored in SAP CC. These private operations are available in the HCI[16] technical interface that is used by the SAP CC Core Tool user interface

> ⓘ Note
>
> SAP CC Core Tool may display some error codes in the below list. Use this technical documentation for troubleshooting purpose. In a production system landscape, contact your SAP Support Team.

Error Codes

Refer to the complete list of error codes related to monitoring plans by filtering the *Error Code* column of the Error Code Index [page 82] with **`monitoringplan`**.

[16] HTTP Communication Interface

3.20 OPERATIONALSTATUS

Summary

Errors which occur when modifying the operational status of a charging contract with the Web Service operation `chargingContractOperationalStatusChange`.

Error Codes

Refer to the complete list of error codes related to the operational status of a charging contracts by filtering the *Error Code* column of the Error Code Index [page 82] with **`operationalstatus`**.

3.21 PREPAIDACCOUNTSTATE

Summary

Errors which occur when implementing operations dedicated to the management of the initial state of prepaid accounts in subscriber accounts during the migration of master data related to end customers.

> **Note**
>
> Refer to the specifications of the SAP CC 2023 Web Services Documentation (SOAP) documentation for more information about the necessary *Customizing* activities to implement a customer data migration.

Error Codes

Refer to the complete list of error codes related to the management of the initial state of prepaid accounts by filtering the *Error Code* column of the Error Code Index [page 82] with **`prepaidaccountstate`**.

3.22 RANGETABLE

Summary

Errors that occur when using or implementing some basic operations (create, search, modify, import, and delete) on the following master data:

- In service pricing catalogs:
  - Range table classes
  - Range tables
- In customer master data:
  - Subscriber range tables

Error Codes

Refer to the complete list of error codes related to range tables and classes by filtering the *Error Code* column of the Error Code Index [page 82] with **`rangetable`**.

3.23 RANGETABLECOMPONENT

Summary

Errors which occur when managing (creating, changing, or importing) some reusable charges or refill logic objects that include a price plan (or a charging plan or the refill logic) configured with a logic component named Range Table Lookup in Cockpit and Range Table Introducer in Core Tool.

This logic component enables to design the pricing logic that uses data tables: Range tables of the pricing catalog of the service provider or subscriber range tables assigned to a subscriber account.

> **Note**
>
> All these errors are embedded in a CHARGECOMPONENT [page 66] error or in a REFILLPLAN [page 77] error. Check the error stack in the operation response answered by the SAP CC system.

Error Codes

Refer to the complete list of error codes related to Range Table Lookup or Range Table Introducer component by filtering the *Error Code* column of the Error Code Index [page 82] with **`rangetablecomponent`**.

3.24 REFILLPLAN

Summary

Errors which occur when using basic operations on:

- Refill Item Classes
- Refill Logic
- Refill Plans
- Refill Record Classes

Error Codes

Refer to the complete list of error codes related to refill plans and other refill features by filtering the *Error Code* column of the Error Code Index [page 82] with **`refillplan`**.

3.25 RESTCHARGING

Summary

Errors which occur when the call of a REST API for an event- or a session-based rating operation fails.

Error Codes

Refer to the complete list of error codes related to REST APIs by filtering the *Error Code* column of the Error Code Index [page 82] with **`restcharging`**.

3.26 RFC

Errors that occur when calling or executing remote function calls (RFCs).

Summary

The `RFC` module groups a few error codes that relate to remote function calls (RFCs) via the *RFC/JCo* technical interface of SAP Convergent Charging.

The call (and its remote execution) of a remote function module in a distant system may lead to various errors handled by SAP Convergent Charging:

Category	Error Codes	Process or Function
Errors occurring when immediately loading output items (billable items or corresponding consumption items) into SAP Convergent Invoicing in its SAP system.	• RFC-1 [page 3068] • RFC-2 [page 3070]	Immediate Loading of Billable Items

Additional Information

Refer to the SAP CC 2023 Application Help for more information and user assistance about the concepts, features, and processes and functions.

Error Codes

Refer to the complete list of error codes related to RFC errors by filtering the *Error Code* column of the Error Code Index [page 82] with **`rfc`**.

3.27 SPENDINGSTATUS

Summary

The `SPENDINGSTATUS` module groups multiple error codes that relate to errors occurring when processing operations that manages spending status descriptions stored in SAP Convergent Charging 2023:

- Create
- Modify
- Search
- Delete

These private operations are available in the *HCI technical interface* that is used by the SAP CC Cockpit and the SAP CC Core Tool user interfaces.

Additional Information

SAP CC 2023 Application Help

Error Codes

Refer to the complete list of error codes related to spending status descriptionsd by filtering the *Error Code* column of the Error Code Index [page 82] with **`spendingstatus`**.

3.28 SQL

Summary

The SQL module groups few error codes that relate to the initialization and usage of the backend database.

Error Codes

Refer to the complete list of error codes related to the backend database by filtering the *Error Code* column of the Error Code Index [page 82] with **`sql`**.

3.29 SUBSCRIBERDATA

Summary

Errors related to the import or the export of subscriber data. Subscriber data (or customer related data) consists in:

- A subscriber account
- Subscriptions
- Accesses
- Counter snapshots

Note that the import and the export of subscriber data are mainly used during a migration.

Error Codes

Refer to the complete list of error codes related to the import or the export of subscriber data by filtering the *Error Code* column of the Error Code Index [page 82] with **`subscriberdata`**.

3.30 SUBSCRIBERACCOUNT

Summary

Errors which occur when implementing operations dedicated to the management of subscriber accounts.

Error Codes

Refer to the complete list of error codes related to the management of subscriber accounts by filtering the *Error Code* column of the Error Code Index [page 82] with **`subscriberaccount`**.

3.31 TRANSPORTREQUEST

Summary

Errors which occur when implementing basic operations on transport requests.

Error Codes

Refer to the complete list of error codes related to transport requests by filtering the *Error Code* column of the Error Code Index [page 82] with `transportrequest`.

4 Error Code Index

Error Code	Message	Action
AGGREGATION-POLICY-1 [page 342]	`The code of the Aggregation Policy is missing.`	Set a code to the Aggregation Policy. Verify your changes.
AGGREGATION-POLICY-2 [page 343]	`The owner of the "{aggregationPolicyCode}" Aggregation Policy is missing.`	Set an owner to the Aggregation Policy. Verify your changes.
AGGREGATION-POLICY-3 [page 345]	`The code of the Charged Item Class for the "{aggregationPolicyCode}" Aggregation Policy is missing.`	Add the code of the Charged Item Class for the Aggregation Policy. Verify your changes.
AGGREGATION-POLICY-4 [page 346]	`The "{itemClassCode}" Charged Item Class of the "{aggregationPolicyCode}" Aggregation Policy does not exist.`	Specify an existing code for the Charged Item Class or create a new Charged Item Class with this code. Verify your changes.
AGGREGATION-POLICY-5 [page 348]	`Rule #{ruleIndex} has no field name.`	Set a field name to the rule or delete this rule. Verify your changes.
AGGREGATION-POLICY-6 [page 349]	`The "{fieldName}" field name used by Rule #{ruleIndex} is already used by Rule #{previousRuleIndex}.`	Set another field name to the rule or delete this rule. Verify your changes.
AGGREGATION-POLICY-7 [page 351]	`The "{fieldName}" field name used by Rule #{ruleIndex} does not exist in the "{itemClassCode}" Charged Item Class.`	The field name must exist in the specified Charged Item Class. Specify an existing field name for the rule, or add a new field in the Charged Item Class. Verify your changes.

Error Code	Message	Action
AGGREGATION-POLICY-8 [page 352]	`Rule #{ruleIndex} using the "{fieldName}" field name has no aggregation operator.`	Specify an aggregation operator for the rule or delete this rule. Verify your changes.
AGGREGATION-POLICY-9 [page 354]	`Rule #{ruleIndex} uses an aggregation operator which is not compatible with the "{fieldType}" type of the "{fieldName}" field. Compatible types are: {expectedTypes}.`	Specify an aggregation operator which is compatible with the type of the specified field name. Verify your changes.
AGGREGATION-POLICY-10 [page 355]	`The Aggregation Policy is missing.`	Specify an Aggregation Policy in the creation operation. Verify your changes.
AGGREGATION-POLICY-11 [page 357]	`Unable to create the Aggregation Policy. "{aggregationPolicyCode}" code already exists.`	Specify another code for the Aggregation Policy to create. Verify your changes.
AGGREGATION-POLICY-12 [page 358]	`Unable to modify the Aggregation Policy. "{aggregationPolicyCode}" Aggregation Policy does not exist.`	Specify an existing code for the Aggregation Policy to modify. Verify your changes.
AGGREGATION-POLICY-13 [page 360]	`Unable to modify the "{aggregationPolicyCode}" Aggregation Policy. Modification of the Charged Item Class is not allowed.`	Specify the Charged Item Class which is already specified in the Aggregation Policy. Verify your changes.
AGGREGATION-POLICY-14 [page 361]	`Unable to delete the Aggregation Policy. "{aggregationPolicyCode}" Aggregation Policy does not exist.`	Specify an existing code for the Aggregation Policy to delete. Verify your changes.
AGGREGATION-POLICY-15 [page 363]	`The owner of the Aggregation Policy ({aggregationPolicyOwner}) is different from the owner of Charged Item Class ({itemClassOwner}).`	Specify another owner for the Aggregation Policy. Verify your changes.

Error Code	Message	Action
AGGREGATION-POLICY-16 [page 364]	`Unable to delete the Aggregation Policy. "{aggregationPolicyCode}" Aggregation Policy is used by the following Charge Plan(s): {chargePlanCodes}.`	Modify the Charge Plan(s) to remove the reference to this Aggregation Policy. Verify your changes.
AGGREGATION-POLICY-18 [page 366]	`Missing value for the field name of Number Report Condition #{numberReportConditionIndex}.`	Set a field name to the Number Report Condition or delete this Number Report Condition. Verify your changes.
AGGREGATION-POLICY-19 [page 367]	`The "{fieldName}" field name used by Number Report Condition #{numberReportConditionIndex} does not exist in the "{itemClassCode}" Charged Item Class.`	The field name must exist in the specified Charged Item Class. Specify an existing field name for the Number Report Condition, or add a new field in the Charged Item Class. Verify your changes.
AGGREGATION-POLICY-20 [page 369]	`Missing value for Number Report Condition #{numberReportConditionIndex} using the "{fieldName}" field name.`	Set a value to the Number Report Condition. Verify your changes.
AGGREGATION-POLICY-22 [page 370]	`Incorrect "{value}" value for the Duration-based Report Condition.`	Set a value greater than 0 in the Duration-based Report Condition. Verify your changes.
AGGREGATION-POLICY-23 [page 372]	`Invalid unit for the Duration-based Report Condition.`	Set a valid unit in the Duration-based Report Condition. Verify your changes.
AGGREGATION-POLICY-24 [page 373]	`The Aggregation Policy can contain a maximum of one Duration-based Report Condition.`	Set only one Duration-based Report Condition in the Aggregation Policy. Verify your changes.

Error Code	Message	Action
AGGREGATION-POLICY-25 [page 374]	`Unable to delete the Aggregation Policy. "{aggregationPolicyCode}" Aggregation Policy is used by the following Allowance Plan(s): {allowancePlanCodes}.`	Modify the Allowance Plan(s) to remove the reference to this Aggregation Policy. Verify your changes.
AGGREGATION-POLICY-26 [page 376]	`The Aggregation Policy is missing.`	Specify an Aggregation Policy in the modification operation. Verify your changes.
ALLOWANCE-1 [page 377]	`The ID of the Allowance Plan is missing.`	Add the ID of the Allowance Plan. Verify your changes.
ALLOWANCE-2 [page 379]	`The owner of the Allowance Plan "{allowancePlanId}" is missing.`	Add the owner of the Allowance Plan. Verify your changes.
ALLOWANCE-3 [page 380]	`The description of the Allowance Plan "{allowancePlanId}" is missing.`	Add a description to the Allowance Plan. Verify your changes.
ALLOWANCE-4 [page 382]	`The status of the Allowance Plan "{allowancePlanId}" is missing.`	Add a status to the Allowance Plan. Verify your changes.
ALLOWANCE-6 [page 383]	`Error while validating the Allowance Plan "{allowancePlanId}".`	Verify your changes.
ALLOWANCE-10 [page 385]	`The Counter at the index {counterIndex} is empty.`	Replace it by a valid Counter or remove it. Verify your changes.
ALLOWANCE-11 [page 386]	`The name of the Counter at index {counterIndex} is missing.`	Add a name to the Counter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-12 [page 388]	`The name "{counterName}" of the Counter at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter. Verify your changes.
ALLOWANCE-13 [page 389]	`The Counter "{counterName}" at index {counterIndex} does not refer to a Counter of the Allowance Plan Item.`	Link the Counter or remove it. Verify your changes.
ALLOWANCE-14 [page 391]	`The description of the Counter "{counterName}" at index {counterIndex} is missing.`	Add a description to the Counter. Verify your changes.
ALLOWANCE-15 [page 392]	`The initial value of the Counter "{counterName}" at index {counterIndex} is missing.`	Add an initial value to the Counter. Verify your changes.
ALLOWANCE-16 [page 394]	`The Parameter at the index {parameterIndex} is empty.`	Replace it by a valid Parameter or remove it. Verify your changes.
ALLOWANCE-17 [page 395]	`The name of the Parameter at index {parameterIndex} is missing.`	Add a name to the Parameter. Verify your changes.
ALLOWANCE-18 [page 397]	`The name "{parameterName}" of the Parameter at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter. Verify your changes.
ALLOWANCE-20 [page 398]	`The type of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown (the supported types are string, number, date).`	Add a type to the Parameter or change it into a supported one: string, number, date. Verify your changes.
ALLOWANCE-21 [page 400]	`The description of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a description to the Parameter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-22 [page 402]	`Error while validating the Parameter "{parameterName}" at index {parameterIndex}.`	Verify your changes.
ALLOWANCE-25 [page 403]	`The parameter additional information "{additionalInformationName}" at index {additionalInformationIndex} is unknown.`	Remove this additional information or replace it with a known one. Verify your changes.
ALLOWANCE-26 [page 405]	`The data type of the parameter is not defined.`	Add this additional information or remove any additional information. Verify your changes.
ALLOWANCE-27 [page 406]	`The parameter is a mapping table ID but no mapping table class is defined.`	Add the additional information of the mapping table class. Verify your changes.
ALLOWANCE-28 [page 407]	`The parameter is a range table ID but no range table class is defined.`	Add the additional information of the range table class. Verify your changes.
ALLOWANCE-29 [page 409]	`The parameter is a mapping table key and could not be linked to a mapping table class.`	Remove the additional information of the mapping table class. Verify your changes.
ALLOWANCE-30 [page 410]	`The parameter cannot declare additional information without a data type.`	Add the additional information of a data type or remove any additional information. Verify your changes.
ALLOWANCE-36 [page 412]	`The Allowance Plan Item at index {allowancePlanItemIndex} is empty.`	Replace it by a valid Allowance Plan Item or remove it. Verify your changes.
ALLOWANCE-37 [page 413]	`The ID of the Allowance Plan Item at index {allowancePlanItemIndex} is missing.`	Add an ID to the Allowance Plan Item. Verify your changes.

Error Code	Message	Action
ALLOWANCE-38 [page 415]	`The ID "{allowancePlanItemId}" of the Allowance Plan Item at index {secondIndex} is already used by the Allowance Plan Item at index {firstIndex}.`	Change the ID of the Allowance Plan Item. Verify your changes.
ALLOWANCE-39 [page 416]	`No Allowance Logic is specified.`	Add the Allowance Logic to the Allowance Plan Item. Verify your changes.
ALLOWANCE-40 [page 418]	`Error while validating the Allowance Plan Item "{allowancePlanItemId}" at index {allowancePlanItemIndex}.`	Verify your changes.
ALLOWANCE-41 [page 419]	`The ID of the master Allowance Logic referred to by the Allowance Plan Item is missing.`	Add an ID to the master Allowance Logic in the Allowance Plan Item. Verify your changes.
ALLOWANCE-42 [page 421]	`The ID of the master Allowance Logic referred to by the Allowance Plan Item and the code "{retrievedAllowanceLogicCode}" of the retrieved Allowance Logic do not match.`	Contact the support. Verify your changes.
ALLOWANCE-43 [page 422]	`The owner of the Allowance Plan and the owner of the Allowance Logic. The owner of the Allowance Plan is "{allowancePlanOwner}". The owner of the Allowance Logic is "{allowanceLogicOwner}".`	Set the ID the master Allowance Logic that has the same owner as the Allowance Plan. Verify your changes.
ALLOWANCE-44 [page 424]	`The name of the Counter at index {counterIndex} is missing.`	Add a name to the Counter. Verify your changes.
ALLOWANCE-45 [page 425]	`The name "{counterName}" of the Counter at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-46 [page 427]	`The name of the Counter Reference at index {counterReferenceIndex} is missing.`	Add a name to the Counter Reference. Verify your changes.
ALLOWANCE-47 [page 428]	`The name "{counterName}" of the Counter Reference at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter Reference. Verify your changes.
ALLOWANCE-48 [page 430]	`The initial value of the Counter "{counterName}" at index {counterIndex} is missing.`	Add an initial value to the Counter. Verify your changes.
ALLOWANCE-49 [page 431]	`The Counter "{counterName}" at index {counterIndex} does not exist in the Allowance Logic "{allowanceLogicId}".`	Remove this Counter. Verify your changes.
ALLOWANCE-50 [page 433]	`The target name of the Counter Reference "{counterReferenceName}" at index {counterReferenceIndex} is missing.`	Add a target name to the Counter Reference. Verify your changes.
ALLOWANCE-51 [page 434]	`The Counter "{targetName}" targeted by the Counter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} does not exist.`	Change the target name of the Counter Reference into an existing one or create a new Counter in the Allowance Plan with this target name. Verify your changes.
ALLOWANCE-52 [page 436]	`The Counter Reference "{counterRefName}" at index {counterRefIndex} does not exist in the Allowance Logic "{allowanceLogicId}".`	Remove this Counter Reference. Verify your changes.
ALLOWANCE-58 [page 437]	`The name of the Parameter at index {parameterIndex} is missing.`	Add a name to the Parameter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-59 [page 439]	`The name "{parameterName}" of the Parameter at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter. Verify your changes.
ALLOWANCE-60 [page 440]	`The name of the Parameter Reference at index {parameterIndex} is missing.`	Add a name to the Parameter Reference. Verify your changes.
ALLOWANCE-61 [page 442]	`The name "{parameterReferenceName}" of the Parameter Reference at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter Reference. Verify your changes.
ALLOWANCE-62 [page 443]	`The Parameter "{parameterName}" of the Allowance Logic points to an unknown mapping table "{parameterValue}".`	Change the value to a known mapping table. Verify your changes.
ALLOWANCE-63 [page 445]	`The Parameter "{parameterName}" of the Allowance Logic points to an unknown range table "{parameterValue}".`	Change the value to a known range table. Verify your changes.
ALLOWANCE-64 [page 446]	`The type of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown (the supported types are string, number, date).`	Add a type to the Parameter or change it into a supported one: string, number, date. Verify your changes.
ALLOWANCE-65 [page 448]	`The date value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a date value to the Parameter. Verify your changes.
ALLOWANCE-66 [page 449]	`The number value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a number value to the Parameter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-67 [page 451]	`The string value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a string value to the Parameter. Verify your changes.
ALLOWANCE-68 [page 452]	`The type "{parameterType}" of the Parameter "{parameterName}" at index {parameterIndex} is unsupported (the supported types are string, number, date).`	Use a supported type (string, number, date) for the Parameter. Verify your changes.
ALLOWANCE-69 [page 454]	`The Parameter "{parameterName}" at index {parameterIndex} does not exist in the Allowance Logic "{allowanceLogicId}".`	Remove this Parameter. Verify your changes.
ALLOWANCE-70 [page 456]	`Error while validating the Parameter "{parameterName}" at index {parameterIndex}.`	Verify your changes.
ALLOWANCE-71 [page 457]	`The target name of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is missing.`	Add a target name to the Parameter Reference. Verify your changes.
ALLOWANCE-72 [page 459]	`The Parameter "{targetName}" targeted by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} does not exist.`	Change the target name of the Parameter Reference into an existing one or create a new Parameter in the Allowance Plan with this target name. Verify your changes.
ALLOWANCE-73 [page 460]	`The type of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is missing or unknown (the supported types are string, number, date).`	Add a type to the Parameter Reference or change it into a supported one: string, number, date. Verify your changes.

Error Code	Message	Action
ALLOWANCE-74 [page 462]	`The type "{parameterReferenceType}" of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not compatible with the type "{parameterType}" of the targeted Parameter.`	Link the Parameter Reference to a compatible Parameter. Verify your changes.
ALLOWANCE-75 [page 463]	`Error while validating the Parameter Reference "{parameterName}" at index {parameterIndex}.`	Verify your changes.
ALLOWANCE-76 [page 465]	`The Parameter Reference "{parameterRefName}" at index {parameterRefIndex} does not exist in the Allowance Logic "{allowanceLogicId}".`	Remove this Parameter Reference. Verify your changes.
ALLOWANCE-77 [page 466]	`The Parameter "{cpParameterName}" of the Allowance Plan referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as a mapping table ID.`	Declare the data type of the mapping table ID and the additional information of the mapping table class in the Parameter. Verify your changes.
ALLOWANCE-78 [page 468]	`The Parameter "{cpParameterName}" of the Allowance Plan referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declares an incompatible mapping table class "{cpParameterMappingTableClass}" while the Parameter Reference is of class "{parameterReferenceMappingTableClass}".`	Declare the data type of the mapping table ID and the additional information of the mapping table class in the Parameter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-79 [page 470]	`The Parameter "{cpParameterName}" of the Allowance Plan referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as a range table ID.`	Declare the data type of the range table ID and the additional information of the range table class in the Parameter. Verify your changes.
ALLOWANCE-80 [page 471]	`The Parameter "{cpParameterName}" of the Allowance Plan referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declares an incompatible range table class "{cpParameterRangeTableClass}" while the Parameter Reference is of class "{parameterReferenceRangeTableClass}".`	Declare the data type of the range table ID and the additional information of the range table class in the Parameter. Verify your changes.
ALLOWANCE-81 [page 473]	`The Parameter "{cpParameterName}" of the Allowance Plan referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as a mapping table key.`	Declare the additional information of the data type of the mapping table key in the Parameter. Verify your changes.
ALLOWANCE-83 [page 475]	`The Parameter is declared as a mapping table ID while it does not exist in the Allowance Logic.`	Remove the additional information of the data type of the mapping table ID from the Parameter. Verify your changes.
ALLOWANCE-84 [page 476]	`The Parameter is declared as a mapping table ID but it does not have a STRING type.`	Declare the parameter as a STRING. Verify your changes.

Error Code	Message	Action
ALLOWANCE-85 [page 478]	`The mapping table class "{parameterMappingTableClass}" declared in the Parameter is incompatible with the one declared in the Allowance Logic "{allowanceLogicMappingTableClass}".`	Declare the right mapping table class. Verify your changes.
ALLOWANCE-86 [page 479]	`The Parameter "{parameterName}" at index {parameterIndex} points to an unknown mapping table "{parameterValue}".`	Change the value to a known mapping table. Verify your changes.
ALLOWANCE-87 [page 481]	`The Parameter is declared as a range table ID while it does not exist in the Allowance Logic.`	Remove the additional information of the data type of the range table ID from the Parameter. Verify your changes.
ALLOWANCE-88 [page 482]	`The Parameter is declared as a range table ID but it does not have a STRING type.`	Declare the parameter as a STRING. Verify your changes.
ALLOWANCE-89 [page 484]	`The range table class "{parameterRangeTableClass}" declared in the Parameter is incompatible with the one declared in the Allowance Logic "{allowanceLogicRangeTableClass}".`	Declare the right range table class. Verify your changes.
ALLOWANCE-90 [page 485]	`The Parameter "{parameterName}" at index {parameterIndex} points to an unknown range table "{parameterValue}".`	Change the value to a known range table. Verify your changes.
ALLOWANCE-91 [page 487]	`The Parameter is declared as a mapping table key while it does not exist in the Allowance Logic.`	Remove the additional information of the data type of the mapping table key from the Parameter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-92 [page 488]	`The Parameter is declared with a mapping table key but has a wrong type "{parameterType}" while it should be "{allowanceLogicType}".`	Declare the right type for the parameter. Verify your changes.
ALLOWANCE-93 [page 490]	`The mapping table ID "{mappingTableIdName}" is not declared whereas it is used in the Allowance Logic.`	Add the corresponding mapping table ID parameter. Verify your changes.
ALLOWANCE-94 [page 491]	`The range table ID "{rangeTableIdName}" is not declared whereas it is used in the Allowance Logic.`	Add the corresponding range table ID parameter. Verify your changes.
ALLOWANCE-95 [page 493]	`The mapping table key "{mappingTableKeyName}" of type "{mappingTableKeyType}" is not declared whereas it is used in the Allowance Logic.`	Add the corresponding mapping table ID parameter. Verify your changes.
ALLOWANCE-96 (Revoked) [page 494]	`The Charged Item Mapping is missing in the Allowance Plan Item.`	Set the Charged Item Mapping of the Allowance Plan Item. Verify your changes.
ALLOWANCE-97 [page 496]	`The class of the Charged Item Mapping is missing.`	Add a class to the Charged Item Mapping. Verify your changes.
ALLOWANCE-98 [page 497]	`Error while validating the Charged Item Mapping of class "{citcClass}".`	Verify your changes.
ALLOWANCE-99 [page 499]	`The name of the Charged Item Mapping Entry at index {chargedItemMappingEntryIndex} is missing.`	Add a name to the Charged Item Mapping Entry. Verify your changes.

Error Code	Message	Action
ALLOWANCE-100 [page 500]	`The name "{chargedItemMappingEntryName}" of the Charged Item Mapping Entry at index {secondIndex} is already used by the Charged Item Mapping Entry at index {firstIndex}.`	Change the name of the Charged Item Mapping Entry. Verify your changes.
ALLOWANCE-101 [page 502]	`The type of the Charged Item Mapping Entry "{chargedItemMappingEntryName}" at index {chargedItemMappingEntryIndex} is missing or unknown (the supported types are string, number, date, boolean).`	Add a type to the Charged Item Mapping Entry or change it into a supported one: string, number, date, boolean. Verify your changes.
ALLOWANCE-102 [page 504]	`The Charged Item Mapping contains the "{entryName}" entry. This entry does not exist in the "{chargedItemClassId}" Charged Item Class.`	Remove the entry from the Charged Item Mapping or replace it by an existing property of the Charged Item Class. Verify your changes.
ALLOWANCE-103 [page 505]	`The Charged Item Mapping contains the entry "{entryName}" with the type: {entryType}. This type is not compatible with the one defined in the Charged Item Class "{chargedItemClassId}": {propertyType}.`	Change the type of the Charged Item Mapping entry. Verify your changes.
ALLOWANCE-104 [page 507]	`The Allowance Plan is missing in the CreateAllowancePlanOp operation.`	Add the Allowance Plan to the CreateAllowancePlanOp operation. Verify your changes.
ALLOWANCE-105 [page 508]	`The Allowance Plan "{allowancePlanId}" already exists.`	Use another ID or use the `ModifyAllowancePlanOp` operation to modify the Allowance Plan. Verify your changes.
ALLOWANCE-106 [page 510]	`The status of the new Allowance Plan "{allowancePlanId}" must be set to open.`	Set the status of this new Allowance Plan to open. Verify your changes.

Error Code	Message	Action
ALLOWANCE-107 [page 511]	`The ID of the Allowance Logic "{allowanceLogicId}" does not match any Allowance Logic.`	Set the ID of an existing Allowance Logic object. Verify your changes.
ALLOWANCE-108 [page 513]	`The code of the charged item class "{chargedItemClassCode}" does not match any charged item class.`	Set the code of an existing charged item class. Verify your changes.
ALLOWANCE-109 [page 514]	`The Allowance Plan is missing in the ModifyAllowancePlanOp operation.`	Add the Allowance Plan to the `ModifyAllowancePlanOp` operation. Verify your changes.
ALLOWANCE-110 [page 516]	`The Allowance Plan with the ID {allowancePlanId} does not exist.`	Change the ID of the Allowance Plan into an existing one or first create the Allowance Plan. Verify your changes.
ALLOWANCE-111 [page 517]	`Impossible to modify the Allowance Plan because the specified owner {specifiedOwner} does not correspond to the owner {realOwner} existing in the Allowance Plan.`	Change the owner into the owner of the Allowance Plan or create a new Allowance Plan for the specified owner. Verify your changes.
ALLOWANCE-112 [page 519]	`The description of the Allowance Plan "{allowancePlanId}" cannot be modified because the Allowance Plan has been released.`	Create a new Allowance Plan. Verify your changes.
ALLOWANCE-120 [page 520]	`The parameter "{parameterName}" cannot be removed because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.
ALLOWANCE-121 [page 522]	`The parameter "{parameterName}" cannot be added because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.

Error Code	Message	Action
ALLOWANCE-122 [page 523]	`The description of the parameter "{parameterName}" cannot be modified because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.
ALLOWANCE-123 [page 525]	`The type of the parameter "{parameterName}" cannot be modified because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.
ALLOWANCE-127 [page 526]	`The counter "{counterName}" cannot be removed because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.
ALLOWANCE-128 [page 528]	`The counter "{counterName}" cannot be added because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.
ALLOWANCE-129 [page 529]	`The description of the counter "{counterName}" cannot be modified because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.
ALLOWANCE-133 [page 531]	`The allowance plan item "{allowancePlanItemId}" cannot be removed because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.
ALLOWANCE-134 [page 532]	`The allowance plan item "{allowancePlanItemId}" cannot be added because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.

Error Code	Message	Action
ALLOWANCE-135 [page 534]	`The allowance plan item "{allowancePlanItemId}" cannot be modified because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.
ALLOWANCE-138 [page 535]	`The Allowance Plan "{allowancePlanId}" whose status is already set to released cannot be set to open.`	Set the status of this new Allowance Plan to released. Verify your changes.
ALLOWANCE-141 [page 537]	`The Allowance Logic "{allowanceLogicId}" is unknown.`	Change the allowanceLogicId into an existing Allowance Logic identifier. Verify your changes.
ALLOWANCE-142 [page 538]	`The code of the charged item class "{chargedItemClassCode}" does not match any charged item class.`	Set the code of an existing charged item class. Verify your changes.
ALLOWANCE-143 [page 540]	`Internal server error. The Allowance Plan Item refers to no known Allowance Logic.`	Contact the support. Verify your changes.
ALLOWANCE-144 [page 541]	`The Allowance Plan Item already refers to the Allowance Logic "{originalAllowanceLogicId}" and cannot refer to the Allowance Logic "{newAllowanceLogicId}" at the same time.`	Use the Allowance Logic already referred to by the Allowance Plan Item or create a new Allowance Plan Item. Verify your changes.
ALLOWANCE-145 [page 543]	`Internal server error. The Allowance Plan Item refers to an unknown charged item class.`	Contact the support. Verify your changes.
ALLOWANCE-146 [page 544]	`The code of the charged item class "{chargedItemClassCode}" does not match any charged item class.`	Add the code of an existing charged item class. Verify your changes.

Error Code	Message	Action
ALLOWANCE-147 [page 546]	`The ID of the Allowance Plan is missing in the DeleteAllowancePlanOp operation.`	Set the ID of the Allowance Plan to the `DeleteAllowancePlanOp` operation. Verify your changes.
ALLOWANCE-148 [page 547]	`The Allowance Plan "{allowancePlanId}" cannot be deleted because it does not exist.`	Use an existing ID for the Allowance Plan. Verify your changes.
ALLOWANCE-149 [page 549]	`Error while deleting the Allowance Plan "{allowancePlanId}". The Allowance Plan is still linked to one or more Charging Contract Items.`	First delete all Charging Contract Items referring to the Allowance Plan. Verify your changes.
ALLOWANCE-150 [page 550]	`The mandatory filter in the SearchAllowancePlanOp operation is missing.`	Add the filter to the `SearchAllowancePlanOp` operation. Verify your changes.
ALLOWANCE-151 [page 552]	`An error occurred during the execution of the SearchAllowancePlanOp operation: {errorMessage}.`	Verify your changes.
ALLOWANCE-152 [page 553]	`The code of the charged item class is empty or null.`	Set the code of an existing charged item class. Verify your changes.
ALLOWANCE-153 [page 555]	`The owner of the Allowance Plan and the owner of the Charged Item Class do not match. The owner of the Allowance Plan is "{allowancePlanOwner}". The owner of the Charged Item Class is "{chargedItemClassOwner}".`	Set the code of a Charged Item Class that has the same owner as the Allowance Plan. Verify your changes.
ALLOWANCE-200 [page 556]	`The Allowance Logic has no ID.`	Set the ID of the Allowance Logic. Verify your changes.

Error Code	Message	Action
ALLOWANCE-201 [page 558]	`The Allowance Logic "{allowanceLogicId}" has no owner.`	Set the owner of the Allowance Logic. Verify your changes.
ALLOWANCE-202 [page 559]	`The Allowance Logic "{allowanceLogicId}" has no allowance logic tree.`	Add the allowance logic tree to the Allowance Logic. Verify your changes.
ALLOWANCE-209 [page 561]	`The name of the recurring trigger is not set.`	Set the name of the recurring trigger. Verify your changes.
ALLOWANCE-210 [page 562]	`The recurring trigger "{recurringAllowanceName}" does not contain any allowance component.`	Add an allowance component to the recurring trigger. Verify your changes.
ALLOWANCE-211 [page 564]	`The recurring trigger "{recurringRateName}" is invalid because the component tree is invalid.`	Check the validity of the rate components in the recurring trigger. Verify your changes.
ALLOWANCE-212 [page 565]	`The name of the one-shot trigger is not set.`	Set the name of the one-shot trigger. Verify your changes.
ALLOWANCE-213 [page 567]	`The one-shot trigger "{oneShotAllowanceName}" does not contain any allowance component.`	Add an allowance component to the one-shot trigger. Verify your changes.
ALLOWANCE-214 [page 568]	`The one-shot trigger "{oneshotRateName}" is invalid because the component tree is invalid.`	Check the validity of the components in oneshot allowance. Verify your changes.
ALLOWANCE-216 [page 570]	`The counter has no name.`	Set the counter name. Verify your changes.
ALLOWANCE-217 [page 571]	`The counter "{counterDescriptionName}" has no initial value.`	Set the initial value of the counter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-218 [page 572]	`The counter "{counterDescriptionName}" is duplicated.`	Set the counter to a unique name. Verify your changes.
ALLOWANCE-219 [page 574]	`The parameter "{parameterName}" is duplicated.`	Set the parameter to a unique name. Verify your changes.
ALLOWANCE-220 [page 575]	`The Allowance Logic is missing in the CreateAllowanceLogicOp operation.`	Add the Allowance Logic to the `CreateAllowanceLogicOp` operation. Verify your changes.
ALLOWANCE-221 [page 577]	`The Allowance Logic "{allowanceLogicId}" already exists.`	Use another ID or use the `ModifyAllowanceLogicOp` operation to modify the Allowance Logic. Verify your changes.
ALLOWANCE-222 [page 578]	`The Allowance Logic is missing in the ModifyAllowanceLogicOp operation.`	Add the Allowance Logic to the `ModifyAllowanceLogicOp` operation. Verify your changes.
ALLOWANCE-223 [page 580]	`The Allowance Logic "{allowanceLogicCode}" cannot be modified because it does not exist.`	Check the ID of the Allowance Logic. Verify your changes.
ALLOWANCE-224 [page 581]	`The Allowance Logic owner "{allowanceLogicOwner}" is not modifiable in the Allowance Logic "{allowanceLogicId}".`	Check the owner of the Allowance Logic. Verify your changes.
ALLOWANCE-225 [page 583]	`The ID of the Allowance Logic is missing in the DeleteAllowanceLogicOp operation.`	Add the ID of the Allowance Logic to the `DeleteAllowanceLogicOp` operation. Verify your changes.
ALLOWANCE-226 [page 584]	`The Allowance Logic "{allowanceLogicId}" cannot be deleted because it is referred to by the following Allowance Plans: {allowancePlanIds}.`	First delete the Allowance Plan(s). Verify your changes.

Error Code	Message	Action
ALLOWANCE-227 [page 586]	`The Allowance Logic "{allowanceLogicId}" cannot be deleted because it does not exist.`	Check the code of the Allowance Logic. Verify your changes.
ALLOWANCE-229 [page 587]	`The one-shot trigger "{oneShotAllowanceName}" event is not set.`	Set a valid event in the one-shot trigger. Verify your changes.
ALLOWANCE-230 [page 589]	`The event "{oneShotEventName}" of the one-shot trigger "{oneShotAllowanceName}" is not a valid event.`	Set a valid event in the one-shot trigger. Verify your changes.
ALLOWANCE-232 [page 590]	`The Allowance Plan "{allowancePlanId}" cannot be deleted because it is referred to by the following Refill Logic objects: {refillLogicIds}.`	First delete the Refill Logic object(s). Verify your changes.
ALLOWANCE-233 [page 592]	`The Allowance Plan "{allowancePlanId}" cannot be deleted because it is referred to by the following Charge Components: {chargeComponentIds}.`	First delete the Charge Component(s). Verify your changes.
ALLOWANCE-234 [page 593]	`The parameter has no name.`	Set the parameter name. Verify your changes.
ALLOWANCE-235 [page 595]	`The parameter "{parameterName}" has no value.`	Set the parameter value. Verify your changes.
ALLOWANCE-236 [page 596]	`The mapping table class "{mappingTableClassId}" defined in the parameter "{parameterName}" does not exist in the SAP CC system.`	Specify the identifier of an existing mapping table class for the additional information value. Verify your changes.

Error Code	Message	Action
ALLOWANCE-237 [page 598]	`The mapping table "{mappingTableId}" defined in the parameter "{parameterName}" does not exist in the SAP CC system.`	Specify the identifier of an existing mapping table for the additional information value. Verify your changes.
ALLOWANCE-238 [page 599]	`The range table class "{rangeTableClassId}" defined in the parameter "{parameterName}" does not exist in the SAP CC system.`	Specify the identifier of an existing range table class for the additional information value. Verify your changes.
ALLOWANCE-239 [page 601]	`The range table "{rangeTableId}" defined in the parameter "{parameterName}" does not exist in the SAP CC system.`	Specify the identifier of an existing range table for the additional information value. Verify your changes.
ALLOWANCE-240 [page 602]	`The additional information named "{addInfoName}" defined in the parameter "{parameterName}" is not supported.`	Check the validity of the parameter. The supported values are: dataType, mappingTableClass and rangeTableClass. Verify your changes.
ALLOWANCE-241 [page 604]	`The additional information value "{addInfoValue}" defined in the parameter "{parameterName}" is not a valid data type.`	Check the validity of the parameter additional information. Verify your changes.
ALLOWANCE-242 [page 605]	`The additional information value "{addInfoValue}" requires that the parameter "{parameterName}" is of type string.`	The type is wrong. Check the type and change it into string. Verify your changes.
ALLOWANCE-243 [page 607]	`The parameter "{parameterName}" does not define a mapping table class.`	Specify the identifier of an existing mapping table class for the additional information value. Verify your changes.
ALLOWANCE-244 [page 608]	`The parameter "{parameterName}" does not define a range table class.`	Specify the identifier of an existing range table class for the additional information value. Verify your changes.

Error Code	Message	Action
ALLOWANCE-245 [page 610]	`The recurring trigger "{recurringAllowanceName}" frequency is not set.`	Set a valid frequency in the recurring trigger. Verify your changes.
ALLOWANCE-246 [page 611]	`The chargeable item class ID of the usage allowance "{usageAllowanceName}" is not set.`	Set a valid chargeable item class ID in the usage allowance. Verify your changes.
ALLOWANCE-248 [page 613]	`No allowance plan is specified.`	Specify an allowance plan in the create allowance component. Verify your changes.
ALLOWANCE-249 [page 614]	`The allowance plan "{allowancePlanId}" does not exist.`	Specify the identifier of an existing allowance plan. Verify your changes.
ALLOWANCE-250 [page 615]	`The allowance plan "{allowancePlanId}" is not released.`	Specify the identifier of a released allowance plan. Verify your changes.
ALLOWANCE-251 [page 617]	`The parameter "{parameterName}" does not exist in the allowance plan "{allowancePlanId}".`	Specify a parameter name that exists in the allowance plan. Verify your changes.
ALLOWANCE-252 [page 618]	`The parameter "{parameterName}" does not have the same type as in the allowance plan "{allowancePlanId}".`	Specify the same parameter type as in the allowance plan. Verify your changes.
ALLOWANCE-253 [page 620]	`The parameter "{parameterName}" of the allowance plan "{allowancePlanId}" is not defined in the create allowance component.`	Specify a value for the parameter. Verify your changes.
ALLOWANCE-254 [page 621]	`The mapping table "{mappingTableId}" referenced by the parameter "{parameterName}" does not exist.`	Specify the identifier of an existing mapping table. Verify your changes.

Error Code	Message	Action
ALLOWANCE-255 [page 623]	`The mapping table "{mappingTableId}" referenced by the parameter "{parameterName}" is not related to the mapping table class "{mappingTableClassId}".`	Specify the identifier of an mapping table related to the mapping table class. Verify your changes.
ALLOWANCE-256 [page 625]	`The range table "{rangeTableId}" referenced by the parameter "{parameterName}" does not exist.`	Specify the identifier of an existing range table. Verify your changes.
ALLOWANCE-257 [page 626]	`The range table "{rangeTableId}" referenced by the parameter "{parameterName}" is not related to the range table class "{rangeTableClassId}".`	Specify the identifier of a range table related to the range table class. Verify your changes.
ALLOWANCE-258 [page 628]	`The counter "{counterName}" does not exist in the allowance plan "{allowancePlanId}".`	Specify a counter name that exists in the allowance plan. Verify your changes.
ALLOWANCE-259 [page 629]	`The counter "{counterName}" of the allowance plan "{allowancePlanId}" is not defined in the create allowance component.`	Specify a value for the counter. Verify your changes.
ALLOWANCE-260 [page 631]	`The context property name "{contextPropertyName}" specified in the start date is not valid.`	Specify a valid context property name in the start date. Verify your changes.
ALLOWANCE-261 [page 632]	`The context property name "{contextPropertyName}" specified in the end date is not valid.`	Specify a valid context property name in the end date. Verify your changes.
ALLOWANCE-262 [page 634]	`The context property name "{contextPropertyName}" specified in the parameter "{parameterName}" is not valid.`	Specify a valid context property name for the parameter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-263 [page 635]	`The context property name "{contextPropertyName}" specified in the counter "{counterName}" is not valid.`	Specify a valid context property name for the counter. Verify your changes.
ALLOWANCE-264 [page 637]	`The code of the charged item class is empty or null.`	Set the code of an existing charged item class. Verify your changes.
ALLOWANCE-265 [page 638]	`The code of the charged item class is empty or null.`	Set the code of an existing charged item class. Verify your changes.
ALLOWANCE-266 [page 639]	`The code of the charged item aggregation policy "{chargedItemAggregationPolicyCode}" does not match any charged item aggregation policy.`	Set the code of an existing charged item aggregation policy. Verify your changes.
ALLOWANCE-267 [page 641]	`The code of the charged item aggregation policy "{chargedItemAggregationPolicyCode}" does not match any charged item aggregation policy.`	Set the code of an existing charged item aggregation policy. Verify your changes.
ALLOWANCE-268 [page 643]	`The code of the charged item aggregation policy "{chargedItemAggregationPolicyCode}" does not match any charged item aggregation policy.`	Set the code of an existing charged item aggregation policy. Verify your changes.
ALLOWANCE-269 [page 644]	`The Allowance Plan "{allowancePlanId}" does not contain any Allowance Plan Item.`	Add an Allowance Plan Item to the Allowance Plan. Verify your changes.
ALLOWANCE-268 [page 643]	`The code of the charged item aggregation policy "{chargedItemAggregationPolicyCode}" does not match any charged item aggregation policy.`	Set the code of an existing charged item aggregation policy. Verify your changes.

Error Code	Message	Action
ALLOWANCE-271 [page 647]	`The type "{parameterType}" of the Parameter "{parameterName}" at index {parameterIndex} is not compatible with the type "{logicParameterType}" of the corresponding Allowance Logic Parameter.`	Set the correct type for the Parameter. Verify your changes.
ALLOWANCE-272 [page 649]	`The type "{parameterReferenceType}" of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not compatible with the type "{logicParameterType}" of the corresponding Allowance Logic Parameter.`	Set the correct type for the Parameter Reference. Verify your changes.
ALLOWANCE-273 [page 650]	`The value of the Charged Item Mapping Entry "{chargedItemMappingEntryName}" at index {chargedItemMappingEntryIndex} is not set.`	Set either a value or a property name in the Charged Item Mapping Entry. Verify your changes.
ALLOWANCE-274 [page 652]	`The allowance plan "{allowancePlanId}" does not belong to the same owner as the charge component or refill logic.`	Specify an allowance plan with the same owner as the charge component or refill logic. Verify your changes.
ALLOWANCE-276 [page 653]	`The Allowance Interface is missing in the modify operation.`	Add an Allowance Interface to the modify operation. Verify your changes.
ALLOWANCE-277 [page 655]	`Error while validating the Allowance Interface.`	Verify your changes.
ALLOWANCE-278 [page 656]	`The name of the Parameter at index {parameterIndex} is missing.`	Set a name for the Parameter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-279 [page 657]	`The name "{parameterName}" of the Parameter at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter. Verify your changes.
ALLOWANCE-280 [page 659]	`The description of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Set a description for the Parameter. Verify your changes.
ALLOWANCE-281 [page 661]	`The type of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown (the supported types are string, number, date).`	Set a type for the Parameter or change it into a supported one: string, number, date. Verify your changes.
ALLOWANCE-282 [page 662]	`The default value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Set a default value for the Parameter. Verify your changes.
ALLOWANCE-283 [page 664]	`The type of the Parameter "{parameterName}" at index {parameterIndex} cannot be changed from {previousParameterType} to {newParameterType}.`	Set the same type for the Parameter. Verify your changes.
ALLOWANCE-284 [page 665]	`The Parameter "{parameterName}" cannot be removed.`	Set the Parameter. Verify your changes.
ALLOWANCE-285 [page 667]	`The name of the Counter at index {counterIndex} is missing.`	Set a name for the Counter. Verify your changes.
ALLOWANCE-286 [page 668]	`The name "{counterName}" of the Counter at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter. Verify your changes.
ALLOWANCE-287 [page 670]	`The description of the Counter "{counterName}" at index {counterIndex} is missing.`	Set a description for the Counter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-288 [page 671]	`The default value of the Counter "{counterName}" at index {counterIndex} is missing.`	Set a default value for the Counter. Verify your changes.
ALLOWANCE-289 [page 673]	`The Counter "{counterName}" cannot be removed.`	Verify your changes.
ALLOWANCE-290 [page 674]	`The context property name "{contextPropertyName}" specified in the parameter "{parameterName}" does not correspond to a parameter of type mapping table identifier.`	Specify a context property name that corresponds to a parameter of type mapping table identifier. Verify your changes.
ALLOWANCE-291 [page 676]	`The context property name "{contextPropertyName}" specified in the parameter "{parameterName}" does not correspond to a parameter of type range table identifier.`	Specify a context property name that corresponds to a parameter of type range table identifier. Verify your changes.
ALLOWANCE-300 [page 677]	`The Allowance Event Class is missing in the CreateAllowanceEventClassOp operation.`	Add the Allowance Event Class to the `CreateAllowanceEventClassOp` operation. Verify your changes.
ALLOWANCE-301 [page 679]	`The Allowance Event Class has no ID.`	Set the ID of the Allowance Event Class. Verify your changes.
ALLOWANCE-302 [page 680]	`The owner of the Allowance Event Class "{allowanceEventClassId}" is missing in the CreateAllowanceEventClassOp operation.`	Add the owner of the Allowance Event Class to the `CreateAllowanceEventClassOp` operation. Verify your changes.
ALLOWANCE-303 [page 682]	`The Allowance Event Class "{allowanceEventClassId}" already exists.`	Use another ID or use the `ModifyAllowanceEventClassOp` operation to modify the Allowance Event Class. Verify your changes.
ALLOWANCE-304 [page 683]	`The name is missing in one of the Allowance Event Class properties.`	Add a name to the Allowance Event Class property. Verify your changes.

Error Code	Message	Action
ALLOWANCE-305 [page 685]	`The property "{allowanceEventClassPropertyName}" of type "{allowanceEventClassPropertyType}" cannot be removed or changed from the Allowance Event Class "{allowanceEventClassId}" because it is referenced by the following Allowance Logic object(s): {allowanceLogicIds}.`	Keep the property as it was created initially in the Allowance Event Class. Verify your changes.
ALLOWANCE-306 [page 686]	`The name "{allowanceEventClassPropertyName}" of the Allowance Event Class property is already used.`	Change the name of the Allowance Event Class property. Verify your changes.
ALLOWANCE-307 [page 688]	`The Allowance Event Class is missing in the ModifyAllowanceEventClassOp operation.`	Add the Allowance Event Class to the `ModifyAllowanceEventClassOp` operation. Verify your changes.
ALLOWANCE-308 [page 689]	`The Allowance Event Class has no ID.`	Set the ID of the Allowance Event Class. Verify your changes.
ALLOWANCE-309 [page 691]	`The owner of the Allowance Event Class "{allowanceEventClassId}" cannot be modified.`	Set the owner of the Allowance Event Class Verify your changes.
ALLOWANCE-310 [page 692]	`The Allowance Event Class "{allowanceEventClassId}" cannot be deleted because it does not exist.`	Check the ID of the Allowance Event Class. Verify your changes.
ALLOWANCE-311 [page 694]	`The parameter "{parameterName}" specified as a sorting criterion does not exist in the Allowance Interface.`	Set the name of a parameter that exists in the Allowance Interface in the sorting criterion. Verify your changes.

Error Code	Message	Action
ALLOWANCE-312 [page 695]	`The parameter "{parameterName}" is specified more than once as a sorting criterion.`	Set the parameter as a sorting criterion only once. Verify your changes.
ALLOWANCE-313 [page 697]	`The parameter "{parameterName}" is specified as a sorting criterion of type "{typeInSortingCriterion}" while its type is "{typeInAllowanceInterface}" in the Allowance Interface.`	Set the correct type for the parameter in the sorting criterion. Verify your changes.
ALLOWANCE-314 [page 698]	`The parameter "{parameterName}" cannot be used as a sorting criterion because it is of type "string".`	Use the name of another parameter as a sorting criterion. Verify your changes.
ALLOWANCE-315 [page 700]	`The counter "{counterName}" specified as a sorting criterion does not exist in the Allowance Interface.`	Set the name of a counter that exists in the Allowance Interface in the sorting criterion. Verify your changes.
ALLOWANCE-316 [page 701]	`The counter "{counterName}" is specified more than once as a sorting criterion.`	Set the counter as a sorting criterion only once. Verify your changes.
ALLOWANCE-317 [page 703]	`The counter "{counterName}" is specified as a sorting criterion of type "{typeInSortingCriterion}" while its type must be "number".`	Set the counter to the type "number" in the sorting criterion. Verify your changes.
ALLOWANCE-318 [page 704]	`The sorting criterion "{sortingCriterion}" is unknown.`	Set a valid sorting criterion. Verify your changes.
ALLOWANCE-319 [page 706]	`The name of the event-based trigger is not set.`	Set the name of the event-based trigger. Verify your changes.
ALLOWANCE-320 [page 707]	`The allowance event class ID of the event-based trigger "{eventAllowanceName}" is not set.`	Set a valid allowance event class ID in the usage allowance. Verify your changes.

Error Code	Message	Action
ALLOWANCE-321 [page 709]	`The Allowance Event Class "{allowanceEventClassName}" referred to in the event-based trigger "{eventAllowanceName}" is already used.`	Use an existing but not already used Allowance Event Class in the event-based trigger. Verify your changes.
ALLOWANCE-322 [page 710]	`The Allowance Event Class "{allowanceEventClassName}" referred to in the event-based trigger "{eventAllowanceName}" does not exist.`	Use an existing Allowance Event Class in the event-based trigger. Verify your changes.
ALLOWANCE-323 [page 712]	`The owner of the allowance logic and the owner of the Allowance Event Class referenced by the event-based trigger "{eventAllowanceName}" do not match. The owner of the allowance logic is "{allowanceLogicOwner}". The owner of the Allowance Event Class is "{allowanceEventClassOwner}".`	Set a chargeable item class that has the same owner as the allowance logic in the usage allowance. Verify your changes.
ALLOWANCE-324 [page 713]	`The event-based trigger "{eventAllowanceName}" cannot be added because the Allowance Logic is referenced more than once in the Allowance Plan "{allowancePlanId}".`	Do not add an event-based trigger to the Allowance Logic or remove the duplicate Allowance Logic from the Allowance Plan. Verify your changes.
ALLOWANCE-325 [page 715]	`The Allowance Event Class "{allowanceEventClassName}" referenced by the event-based trigger "{eventAllowanceName}" is already used in the Allowance Plan "{allowancePlanId}" by the Allowance Logic "{allowanceLogicId}".`	Select another Allowance Event Class in the event-based trigger. Verify your changes.
ALLOWANCE-326 [page 717]	`The event-based trigger "{eventAllowanceName}" does not contain any allowance component.`	Add an allowance component to the event-based trigger. Verify your changes.

Error Code	Message	Action
ALLOWANCE-327 [page 718]	`The event-based trigger "{eventAllowanceName}" is invalid because the component tree is invalid.`	Check the validity of the components in the event-based trigger. Verify your changes.
ALLOWANCE-328 [page 720]	`Rating failure of the charge activation "{chargeActivationName}" in the allowance "{allowanceUniqueIdentifier}".`	Fix the logic tree of the allowance logic. Verify your changes.
ALLOWANCE-329 [page 721]	`Rating event failure of the charge activation "{chargeActivationName}" in the allowance "{allowanceUniqueIdentifier}".`	Fix the logic tree of the allowance logic. Verify your changes.
ALLOWANCE-330 [page 723]	`The Allowance Event Class "{allowanceEventItemClassName}" referred to in the allowance logic "{allowanceLogicName}" is already used by another allowance logic.`	Set the allowance logic with the Allowance Event Class not already used in another allowance logic. Verify your changes.
ALLOWANCE-336 [page 724]	`The Allowance Event Class "{allowanceEventClassId}" cannot be deleted because it is referenced at least by one Allowance Event Sender operator or Event-Based Trigger Rate in the following: - Charge(s): {chargeIds}. - Refill Logic object(s): {refillLogicIds}. - Allowance Logic object(s): {allowanceLogicIds}.`	First delete the Allowance Logic. Verify your changes.
ALLOWANCE-337 [page 726]	`No Allowance Event Class is specified.`	Specify an Allowance Event Class. Verify your changes.
ALLOWANCE-338 [page 727]	`The Allowance Event Class "{allowanceEventClassId}" does not exist.`	Specify the identifier of an existing Allowance Event Class. Verify your changes.

Error Code	Message	Action
ALLOWANCE-339 [page 729]	`The owner of the Allowance Logic and the owner of the Allowance Event Class referenced by the component do not match. The owner of the Allowance Logic is "{allowanceLogicOwner}". The owner of the Allowance Event Class is "{allowanceEventClassOwner}".`	Set an Allowance Event Class that has the same owner as the Allowance Logic. Verify your changes.
ALLOWANCE-340 [page 730]	`The property at index {propertyIndex} does not have a name.`	Specify a property name. Verify your changes.
ALLOWANCE-341 [page 732]	`The property "{propertyName}" is specified more than once.`	Specify the property only once. Verify your changes.
ALLOWANCE-342 [page 733]	`The property "{propertyName}" does not exist in the Allowance Event Class "{allowanceEventClassId}".`	Specify a property name which exists in the Allowance Event Class. Verify your changes.
ALLOWANCE-343 [page 735]	`The property "{propertyName}" does not have the same type as in the Allowance Event Class "{allowanceEventClassId}".`	Specify the same property type as in the Allowance Event Class. Verify your changes.
ALLOWANCE-344 [page 736]	`The property "{propertyName}" does not have a value.`	Specify a value for the property. Verify your changes.
ALLOWANCE-345 [page 738]	`The property "{propertyName}" does not have a context property value.`	Specify a context property value for the property. Verify your changes.
ALLOWANCE-346 [page 739]	`The context property name "{contextPropertyName}" specified in the property "{propertyName}" is not valid.`	Specify a valid context property name for the property. Verify your changes.

Error Code	Message	Action
ALLOWANCE-347 [page 741]	`No properties can be added to the Allowance Event Class "{allowanceEventClassId}" because it is referenced at least by one Allowance Event operator in the following: - Charge(s): {chargeIds}. - Refill Logic object(s): {refillLogicIds}. - Allowance Logic object(s): {allowanceLogicIds}.`	Specify a value for the property. Verify your changes.
ALLOWANCE-348 [page 743]	`The type "{parameterType}" of the parameter "{parameterName}" at index {parameterIndex} is not equal to the type "{parameterTypeInterface}" of the parameter in the Allowance Interface.`	Link the Parameter or remove it. Verify your changes.
ALLOWANCE-350 (Revoked) [page 744]	`The code of the Charged Item Class of the Allowance Plan Item "{allowancePlanItemId}" cannot be changed from "{chargedItemClassCode}" to "{newChargedItemClassCode}" because the Allowance Plan "{allowancePlanId}" has been released.`	Set the code of the original Charged Item Class. Verify your changes.
ALLOWANCE-352 [page 746]	`The parameter additional information "{additionalInformationName}" at index {additionalInformationIndex} does not have a value.`	Set of a value for this additional information. Verify your changes.
ALLOWANCE-353 [page 748]	`The clause property "{clausePropertyName}" is unknown.`	Set a valid clause property: A parameter or a counter defined in the Allowance Interface or a default Allowance property (unique identifier, activation date or expiration date). Verify your changes.
ALLOWANCE-354 [page 749]	`The parameter "{parameterName}" specified as a clause property does not exist in the Allowance Interface.`	Set the name of a parameter that exists in the Allowance Interface. Verify your changes.

Error Code	Message	Action
ALLOWANCE-356 [page 751]	`The parameter "{parameterName}" is specified as a clause property of type "{typeInClauseProperty}" while its type is "{typeInAllowanceInterface}" in the Allowance Interface.`	Set the parameter to the correct type in the clause property. Verify your changes.
ALLOWANCE-357 [page 752]	`The counter "{counterName}" specified as a clause property does not exist in the Allowance Interface.`	Set the name of a counter that exists in the Allowance Interface. Verify your changes.
ALLOWANCE-359 [page 754]	`The counter "{counterName}" is specified as a clause property of type "{typeInClauseProperty}" while its type must be "number".`	Set the counter to the type "number" in the clause property. Verify your changes.
ALLOWANCE-360 [page 755]	`The clause property "{clausePropertyName}" is defined with an operator which is invalid or not compatible with the type "{typeOfClauseProperty}".`	Set a clause operator compatible with the type of the clause property. Verify your changes.
ALLOWANCE-361 [page 757]	`The clause property "{clausePropertyName}" is defined with the value "{valueOfClauseProperty}" which is not compatible with the type "{typeOfClauseProperty}".`	Set a clause value compatible with the type of the clause property. Verify your changes.
ALLOWANCE-363 [page 758]	`The parameter "{parameterName}" specified as the origin of the generated property "{generatedPropertyName}" does not exist in the Allowance Interface.`	Set the name of a parameter that exists in the Allowance Interface as the origin of the generated property. Verify your changes.

Error Code	Message	Action
ALLOWANCE-364 [page 760]	`The generated property "{generatedPropertyName}" defines its origin with the parameter "{parameterName}" of type "{typeInGeneratedProperty}" while its type is "{typeInAllowanceInterface}" in the Allowance Interface.`	Set the parameter to the correct type in the generated property. Verify your changes.
ALLOWANCE-365 [page 761]	`The counter "{counterName}" specified as the origin of the generated property "{generatedPropertyName}" does not exist in the Allowance Interface.`	Set the name of a counter that exists in the Allowance Interface as origin of the generated property. Verify your changes.
ALLOWANCE-366 [page 763]	`The generated property "{generatedPropertyName}" defines its origin with the counter "{counterName}" of type "{typeInGeneratedProperty}" while its type must be "number".`	Set the counter to the type "number" in the generated property. Verify your changes.
ALLOWANCE-367 [page 764]	`The generated property "{generatedPropertyName}" defines its origin with the unknown property "{generatedOriginName}".`	Set a valid origin in a generated property: a parameter or a counter defined in the Allowance Interface or a default Allowance property (unique identifier, activation date or expiration date). Verify your changes.
ALLOWANCE-368 [page 766]	`The parameter "{parameterName}" specified as the origin of the generated property "{generatedPropertyName}" is of type "string" which is not allowed.`	Set an origin of type "date" or "number" in a generated property. Verify your changes.
ALLOWANCE-369 [page 767]	`The generated property "{generatedPropertyName}" defines its origin with the default property "{generatedOriginName}" and the type "{typeOfGeneratedProperty}" instead of "{typeOfDefaultAllowanceProperty}".`	Set the right type of the origin in a generated property: "number" for the unique identifier, "date" for the allowance activation and allowance expiration. Verify your changes.

Error Code	Message	Action
ALLOWANCE-370 [page 769]	`The clause property "{clausePropertyName}" is defined with the type "{typeOfClauseProperty}" instead of "{typeOfDefaultAllowanceProperty}".`	Set the right type in the clause property: "number" for the unique identifier, "date" for the allowance activation and allowance expiration. Verify your changes.
ALLOWANCE-371 [page 771]	`The clause property "{clausePropertyName}" of type "{clausePropertyType}" is defined with the referenced value "{ratingContextPropertyName}" which is not part of the rating context.`	Set a clause value with a valid rating context property name. Verify your changes.
ALLOWANCE-372 [page 772]	`The name of the generated allowance count property is not set.`	Set a name for the generated allowance count property. Verify your changes.
ALLOWANCE-373 [page 774]	`The Counter "{counterName}" cannot be added because it is already used by one or more Allowance Plans.`	Set a name not already used by an Allowance Plan. Verify your changes.
ALLOWANCE-374 [page 775]	`The Parameter "{parameterName}" cannot be added because it is already used by one or more Allowance Plans.`	Set a name not already used by an Allowance Plan. Verify your changes.
ALLOWANCE-375 [page 777]	`One or more clause properties are invalid. A clause must have a name, a type, an operator, an isReferenceValue flag and a value.`	Check the clause properties have a name, a type, an operator, an `isReferenceValue` flag and a value Verify your changes.
ALLOWANCE-376 [page 778]	`One or more generated properties are invalid. A generated property must have a name, a type, an operator and an origin.`	Check the generated properties have a name, a type, an operator, and an origin. Verify your changes.
ALLOWANCE-377 [page 780]	`The generated property "{generatedPropertyName}" is specified more than once.`	Specify the generated property only once. Verify your changes.

Error Code	Message	Action
ALLOWANCE-378 [page 781]	`The default allowance property "{defaultAllowancePropertyName}" is specified more than once as a sorting criterion.`	Set the counter as a sorting criterion only once. Verify your changes.
ALLOWANCE-379 [page 783]	`The allowance search filter is missing in the search operation.`	Add an allowance search filter to the search operation. Verify your changes.
ALLOWANCE-380 [page 784]	`The attribute description "id" is missing in the allowance search filter.`	Add the attribute description "id" to the allowance search filter. Verify your changes.
ALLOWANCE-381 [page 785]	`The attribute description "id" of the allowance search filter is invalid.`	Set the attribute description "id" with either a format constraint or an enumerated constraint with a single value of type string. Verify your changes.
ALLOWANCE-382 [page 787]	`The identifier of the charging contract is empty.`	Set a charging contract identifier that is not empty. Verify your changes.
ALLOWANCE-387 [page 788]	`The start date property "{ratingContextPropertyName}" is unknown in the rating context.`	Set a valid rating context property name to define the start date. Verify your changes.
ALLOWANCE-386 [page 790]	`The end date cannot be modified after the creation of the Allowance.`	Keep the previous end date but extends the end date with the `extendedToEndDateProperty` attribute. Verify your changes.
ALLOWANCE-384 [page 791]	`The end date cannot be extended if the Allowance is not active.`	Keep the previous end date. Verify your changes.
ALLOWANCE-385 [page 793]	`The start date cannot be modified after the creation of the Allowance.`	Keep the previous start date. Verify your changes.
ALLOWANCE-388 [page 794]	`The end date property "{ratingContextPropertyName}" is unknown in the rating context.`	Set a valid rating context property name to define the end date. Verify your changes.

Error Code	Message	Action
ALLOWANCE-389 [page 796]	`The extended to end date property "{ratingContextPropertyName}" is unknown in the rating context.`	Set a valid rating context property name to define the extended to end date. Verify your changes.
ALLOWANCE-390 [page 797]	`The start date property is empty or null.`	Set a rating context property name to define the start date. Verify your changes.
ALLOWANCE-391 [page 799]	`The end date property is empty or null.`	Set a rating context property name to define the end date. Verify your changes.
ALLOWANCE-392 [page 800]	`The generated property "{generatedPropertyName}" is defined with the operator "{operatorOfGeneratedProperty}" which is not compatible with the type "{typeOfGeneratedProperty}".`	Verify your changes.
ALLOWANCE-393 (Revoked) [page 802]	`The Charged Item Mapping contains the entry "{entryName}". This entry is already defined in the Charged Item Class "{chargedItemClassName}".`	Remove the entry from the Charged Item Mapping. Verify your changes.
ALLOWANCE-394 [page 803]	`The property "{propertyName}" specified in the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is not allowed in an Allowance Plan.`	Set the name of a property allowed in Allowance Plans. Verify your changes.
ALLOWANCE-395 (Revoked) [page 805]	`The Charged Item Mapping does not contain the entry "{entryName}". This entry has no value or the value is not applicable in this context in the Charged Item Class "{chargedItemClassName}".`	Add the missing entry in the Charged Item Mapping. Verify your changes.
ALLOWANCE-396 [page 806]	`The output property at index {outputPropertyIndex} does not have a name.`	Specify a property name. Verify your changes.

Error Code	Message	Action
ALLOWANCE-397 [page 808]	`The output property "{outputPropertyName}" is specified more than once.`	Specify the output property only once. Verify your changes.
ALLOWANCE-398 [page 809]	`An output property cannot be defined for the unknown property "{outputPropertyName}" of the Allowance Event Class "{allowanceEventClassId}".`	Specify a property name that exists in the Allowance Event Class. Verify your changes.
ALLOWANCE-399 [page 811]	`The monitored property "{monitoredPropertyName}" does not exist in the Allowance Event Class "{allowanceEventClassId}".`	Specify a monitored property name that exists in the Allowance Event Class. Verify your changes.
ALLOWANCE-400 [page 813]	`The value of the output property "{outputPropertyName}" is missing.`	Specify a property name. Verify your changes.
ALLOWANCE-401 [page 814]	`The allowance event property at index {propertyIndex} does not have a name.`	Specify a property name. Verify your changes.
ALLOWANCE-402 [page 816]	`The allowance event property "{propertyName}" is specified more than once.`	Specify the allowance event property only once. Verify your changes.
ALLOWANCE-403 [page 817]	`The property "{propertyName}" does not exist in the Allowance Event Class "{allowanceEventClassId}".`	Specify a property name that exists in the Allowance Event Class. Verify your changes.
ALLOWANCE-404 [page 819]	`The property "{propertyName}" does not have the same type as in the Allowance Event Class "{allowanceEventClassId}".`	Specify the same property type as in the Allowance Event Class. Verify your changes.
ALLOWANCE-405 [page 820]	`The property "{propertyName}" does not have a value.`	Specify a value for the property. Verify your changes.
ALLOWANCE-406 [page 822]	`The property "{propertyName}" does not have a context property value.`	Specify a context property value for the property. Verify your changes.

Error Code	Message	Action
ALLOWANCE-407 [page 823]	`The context property name "{contextPropertyName}" specified in the property "{propertyName}" is not valid.`	Specify a valid context property name for the property. Verify your changes.
ALLOWANCE-408 [page 825]	`The output property name "{outputPropertyValue}" is specified more than once.`	Specify the output property name only once. Verify your changes.
ALLOWANCE-409 [page 826]	`The unit of time of the date shift is missing.`	Add a unit of time to the date shift if missing or set a valid unit of time otherwise. Verify your changes.
ALLOWANCE-410 [page 828]	`The shift of a one-shot rate triggered on the allowance creation is not supported.`	Remove the date shift of the one-shot rate. Verify your changes.
ALLOWANCE-411 [page 829]	`The brought forward triggering of one-shot rates related to the allowance activation is not supported (date shift is {dateShift}).`	Remove the date shift of the one-shot rate or set a positive quantity to delay the one-shot triggering. Verify your changes.
ALLOWANCE-412 [page 831]	`The delayed triggering of one-shot rates related to the allowance expiration is not supported (date shift is {dateShift}).`	Remove the date shift of the one-shot rate or set a negative quantity to bring forward the one-shot triggering. Verify your changes.
ALLOWANCE-413 [page 832]	`The property "{propertyName}" specified in the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is invalid.`	Set the name of a valid property. Verify your changes.
ALLOWANCE-414 [page 834]	`The type "{propertyType}" of the property "{propertyName}" specified in the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is invalid. The expected type is: "{chargedItemMappingEntryType}".`	Change the type of the Charged Item Mapping Entry or set another property with the expected type. Verify your changes.

Error Code	Message	Action
ALLOWANCE-415 [page 835]	`The reporting scope "session" cannot be used in an allowance plan item.`	Remove the reporting scope "session" from the allowance plan item. Verify your changes.
ALLOWANCE-416 [page 837]	`Unexpected error during the initialization of the Allowance Logic "{allowanceLogicId}".`	Contact the support. Verify your changes.
ALLOWANCE-417 [page 838]	`The Allowance Event Class "{allowanceEventClassId}" cannot be modified because it does not exist.`	Check the ID of the Allowance Event Class. Verify your changes.
ALLOWANCE-418 [page 840]	`The ID of the Allowance Event Class is missing in the DeleteAllowanceEventClassOp operation.`	Specify the ID of the Allowance Event Class in the `DeleteAllowanceEventClassOp` operation. Verify your changes.
ALLOWANCE-419 [page 841]	`The Allowance Logic specified in the operation has no ID.`	Specify the ID of the Allowance Logic. Verify your changes.
ALLOWANCE-420 [page 843]	`The data type additional information is missing in the parameter {parameterName}.`	Specify the data type additional information for the parameter. Verify your changes.
ALLOWANCE-421 [page 844]	`Invalid structure of the clause properties.`	Check the number and the order of the clause properties. Verify your changes.
ALLOWANCE-432 [page 846]	`The creation of allowances performed by an allowance logic is not allowed in the one-shot rate [{allowance_oneshot_name}] because it is not configured with the expiration event.`	Check that the one-shot rate used in your allowance logic for renewing allowances is configured with the expiration event. Verify your changes.
ALLOWANCE-433 [page 847]	`The creation of allowances performed by the allowance logic is not allowed in the one-shot rate [{allowance_oneshot_name}] because a shifted delay is used.`	Check that the one-shot rate used in your allowance logic for renewing allowances is configured with a zero-shifted delay. Verify your changes.

Error Code	Message	Action
ALLOWANCE-434 [page 849]	`You cannot set a validity start date property in this allowance rate context.`	Remove this property. Verify your changes.
ALLOWANCE-435 [page 850]	`The Allowance Plan [{allowancePlanId}] cannot be deleted because it is referred by the following Allowance Logic objects: [{allowanceLogicIds}].`	First delete the Allowance Logic objects. Verify your changes.
ALLOWANCE-436 [page 852]	`The allowance logic {allowanceLogicId} cannot be modified because the attribute shareable has been changed from "{allowanceLogicShareableAttribute}" to "{operationShareableAttribute}".`	Set the attribute shareable to "{1}" in the modification operation. Verify your changes.
ALLOWANCE-437 [page 853]	`The allowance plan {allowancePlanId} cannot be modified because the attribute shareable cannot be changed from "{allowancePlanShareableAttribute}" to "{operationShareableAttribute}" if the allowance plan is released.`	Set the attribute shareable to "{1}" in the operation. Verify your changes.
ALLOWANCE-438 [page 855]	`A shareable allowance plan must only contain shareable allowance logic components.`	Remove any allowance logic that is not shareable or make sure that the allowance plan is not shareable. Verify your changes.
ALLOWANCE-439 [page 856]	`Because the allowance logic is shareable, you cannot use the allowance event sender component in any trigger.`	Remove the allowance event sender component. Verify your changes.
ALLOWANCE-440 [page 858]	`Because the allowance logic {allowanceLogicId} is shareable, you cannot use a recurring trigger in this allowance logic.`	Remove the recurring trigger component from the allowance logic or make sure that the allowance logic is not shareable. Verify your changes.

Error Code	Message	Action
ALLOWANCE-441 [page 859]	`Because the allowance logic {allowanceLogicId} is shareable, you cannot use an activation one-shot trigger in this allowance.`	Remove the activation one-shot from the allowance logic. Verify your changes.
ALLOWANCE-442 [page 861]	`Because the allowance logic {allowanceLogicId} is shareable, you cannot shift the expiration of a one-shot trigger component.`	Set to 0 the time shift of the activation one-shot of the allowance logic. Verify your changes.
ALLOWANCE-443 [page 862]	`Because the allowance logic is shareable, you cannot use the persistent counters in the component {componentName} of the allowance logic.`	Remove the counter property from the allowance logic. Verify your changes.
ALLOWANCE-444 [page 864]	`The share identifier "{shareIdPropertyName}" of the allowance event sender component is invalid because only parameter properties are allowed.`	Set a property of parameter type for the share identifier. Verify your changes.
ALLOWANCE-445 [page 865]	`The share identifier "{shareIdPropertyName}" of the allowance event sender component does not refer to an existing parameter property.`	Set a property of parameter type that exists in the rating context for the share identifier. Verify your changes.
ALLOWANCE-446 [page 867]	`The share identifier "{shareIdPropertyName}" of the create allowance component does not refer to an existing rating context property.`	Set a property name that exists in the rating context for the share identifier. Verify your changes.
ALLOWANCE-447 [page 868]	`The counter property "{propertyName}" that is used in the charged item mapping entry "{chargedItemMappingEntryName}" is not allowed in a shareable allowance plan.`	Set a property that is allowed in allowance plans. Verify your changes.

Error Code	Message	Action
ALLOWANCE-448 [page 870]	`Because the allowance logic is not shareable, you can only use the allowance event sender component in the event-based trigger to send events to shared allowances.`	Remove the allowance event sender component from the event-based trigger or set a share identifier to send events to shared allowances. Verify your changes.
ALLOWANCE-449 [page 871]	`The allowance event sender component {allowanceEventSender} with a share identifier can only be used in the allowance logic that is not shareable.`	Remove the allowance event sender component or deselect the share identifier. Verify your changes.
ALLOWANCE-450 [page 873]	`The counterName "{counterPropertyName}" of a debit counter component must refer to a valid persistent or transient counter.`	Change the property name of the counter. Verify your changes.
ALLOWANCE-451 [page 874]	`The allowance validity period updater component is not allowed in the event-base trigger of the shareable allowance logic.`	Remove the allowance validity period updater component from the event-based trigger. Verify your changes.
ALLOWANCE-452 [page 876]	`The debitValueName "{debitValueName}" of a debit Counter component must refer to a valid persistent or transient counter.`	Change the property name of the debit value. Verify your changes.
ALLOWANCE-453 [page 877]	`The allowance property introducer component cannot be used in a shareable allowance logic.`	Remove the allowance property introducer component. Verify your changes.
ALLOWANCE-454 [page 879]	`The counter "{counterName}" that is defined as a clause property cannot be used to select shared allowances.`	Remove the clause properties of counter type if they are used for shared allowances. Verify your changes.
ALLOWANCE-455 [page 880]	`The counter "{counterName}" that is defined as a sorting criterion cannot be used to sort shared allowances.`	Remove the sorting criteria of counter type if they are used for shared allowances. Verify your changes.

Error Code	Message	Action
ALLOWANCE-456 [page 882]	`The value of debit "{negativeDebitValue}" must be equal to 0 or greater than 0.`	Set the value of debit to a positive value. Verify your changes.
ALLOWANCE-457 [page 883]	`The counter "{counterName}" that is used as the origin of the generated property "{generatedPropertyName}" is not allowed with shared allowances.`	Remove the counter that is used as the origin of the generated property. Verify your changes.
ALLOWANCE-458 [page 885]	`The share identifier property name "{shareIdPropertyName}" of the component allowance property introducer does not refer to an existing rating context property.`	Set a property that exists in the rating context for the share identifier. Verify your changes.
ALLOWANCE-459 [page 886]	`The name of the debited value output is mandatory.`	Set the name of the debited value output. Verify your changes.
ALLOWANCE-460 [page 888]	`The name of the non debited value output is mandatory.`	Set the name of the non debited value output. Verify your changes.
ALLOWANCE-461 [page 889]	`In the expiration one-shot rate of the allowance logic, the renewal of allowances is only allowed for allowances that are not shared.`	Check that the create allowance component is configured to renew allowances that are not shared. Verify your changes.
ALLOWANCE-462 [page 890]	`The create allowance component cannot be used in a shareable allowance logic.`	Remove the create allowance component from the shareable allowance logic. Verify your changes.
ALLOWANCE-463 [page 892]	`The create allowance component cannot be used with a share identifier if the allowance plan is not shareable.`	Remove the share identifier or set a shareable allowance plan. Verify your changes.
ALLOWANCE-464 [page 893]	`The debit counter component must contain a debit value.`	Set a debit value in the debit counter component. Verify your changes.

Error Code	Message	Action
ALLOWANCE-465 [page 895]	`The allowances of the charging contract "{chargingContractId}" cannot be retrieved. Message: {message}`	Read the message for more details. Verify your changes.
ALLOWANCE-466 [page 896]	`The allowance event sender component {allowanceEventSender} with a share identifier can only be used in the event-based trigger of the allowance logic that is not shareable.`	Remove the allowance event sender component or move it in an event-based trigger. Verify your changes.
ALLOWANCE-470 [page 898]	`The property "{propertyName}" specified in the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is not available in the context of the Allowance Plan Item.`	Set the name of a property available in the context of the Allowance Plan Item. Verify your changes.
ALLOWANCE-471 [page 899]	`The parameter "{parameterName}" cannot reference the mapping table "{mappingTableId}" because this mapping table has an agreement ID.`	Select a mapping table without agreement ID. Verify your changes.
ALLOWANCE-472 [page 901]	`The parameter of the allowance plan item cannot reference the mapping table "{parameterValue}" because this mapping table has an agreement ID.`	Select a mapping table without agreement ID. Verify your changes.
ALLOWANCE-473 [page 902]	`The parameter "{parameterName}" cannot reference the range table "{rangeTableId}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.
ALLOWANCE-474 [page 904]	`The parameter of the allowance plan item cannot reference the range table "{parameterValue}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.

Error Code	Message	Action
ALLOWANCE-475 [page 905]	`Recurring trigger "{recurringTriggerName}" is configured for a 4-4-5 calendar. The only supported frequency type is month.`	Set the frequency type to month. Verify your changes.
ALLOWANCE-476 [page 907]	`Recurring trigger "{recurringTriggerName}" is configured for a 4-4-5 calendar. The only supported frequency periods are 1, 3, 6 and 12.`	Set the frequency period to 1, 3, 6 or 12. Verify your changes.
ALLOWANCE-477 [page 908]	`The property "{propertyName}" specified in the charged item mapping entry "{chargedItemMappingEntryName}" is invalid because the Prepaid Accounts Management feature is disabled.`	Select a valid property. Verify your changes.
ALLOWANCE-478 [page 910]	`The frequency of the recurring trigger "{recurringAllowanceName}" is invalid.`	Set a valid frequency in the recurring trigger. Verify your changes.
ALLOWANCE-479 [page 911]	`The counterName "{counterPropertyName}" of a credit counter component must refer to a valid persistent or transient counter.`	Change the property name of the counter. Verify your changes.
ALLOWANCE-480 [page 913]	`The creditValueName "{creditValueName}" of a credit Counter component must refer to a valid persistent or transient counter.`	Change the property name of the credit value. Verify your changes.
ALLOWANCE-481 [page 914]	`The value of credit "{negativeCreditValue}" must be equal to 0 or greater than 0.`	Set the value of credit to a positive value. Verify your changes.
ALLOWANCE-482 [page 916]	`The credit counter component must contain a name for the result value output.`	Set the name of the result value output. Verify your changes.

Error Code	Message	Action
ALLOWANCE-483 [page 917]	`The credit counter component must contain a credit value or a credit value name.`	Set a credit value or a credit value name in the credit counter component. Verify your changes.
ALLOWANCE-484 [page 919]	`"{debitCounter}" is a counter of type debit. You cannot use a debit counter in the credit counter component "{creditCounterComponentName}".`	Set a counter of type credit in the credit counter component. Verify your changes.
ALLOWANCE-485 [page 920]	`"{creditCounter}" is a counter of type credit. You cannot use a credit counter in the debit counter component "{debitCounterComponentName}".`	Set a counter of type credit in the credit counter component. Verify your changes.
ALLOWANCE-486 [page 922]	`You cannot link the counter "{allowancePlanCounterName}" of type "{allowancePlanCounterType}" defined in the allowance plan to the counter "{allowancePlanItemCounterName}" of type "{allowancePlanItemCounterType}" defined in the allowance plan item.`	Change the type of the counter of the allowance plan or link the counter to a counter of the allowance plan item having the same type. Verify your changes.
ALLOWANCE-487 [page 923]	`"{counterName}" is a counter of type credit. You cannot use a credit counter in an allowance plan which is not shareable.`	Remove the counter. Verify your changes.
ALLOWANCE-488 [page 925]	`"{counterName}" is a counter of type credit. You cannot use a credit counter in an allowance logic which is not shareable.`	Remove the counter or remove the type credit. Verify your changes.
ALLOWANCE-489 [page 926]	`The operation of the counter "{counterName}" cannot be modified because the Allowance Plan "{allowancePlanId}" has been released.`	Create a new Allowance Plan. Verify your changes.

Error Code	Message	Action
ALLOWANCE-490 [page 928]	`You cannot create the allowance plan "{allowancePlanId}" with the flag ManagedByCockpit set to true with the create operation.`	Use the import operation. Verify your changes.
ALLOWANCE-491 [page 929]	`You cannot create the allowance logic "{allowanceLogicId}" with the flag ManagedByCockpit set to true with the create operation.`	Use the import operation. Verify your changes.
ALLOWANCE-492 [page 931]	`You cannot create the allowance event class "{allowanceEventClassId}" with the flag ManagedByCockpit set to true with the create operation.`	Use the import operation. Verify your changes.
ALLOWANCE-493 [page 932]	`The allowance logic "{allowanceLogicId}" referenced by the allowance plan item has the flag ManagedByCockpit set to "{isAllowanceLogicCockpitCompatible}" whereas the allowance plan has the flag ManagedByCockpit set to "{isAllowancePlanCockpitCompatible}".`	Check that the value of the attribute `ManagedByCockpit` of the allowance logic is the same as the one of the allowance plan.
ALLOWANCE-494 [page 934]	`The allowance event class "{allowanceEventClassId}" referenced by the allowance logic in trigger "{allowanceEventTriggerId}" has the flag ManagedByCockpit set to "{isAllowanceEventClassCockpitCompatible}" whereas the allowance logic has the flag ManagedByCockpit set to "{isAllowanceLogicCockpitCompatible}".`	Check that the value of the attribute `ManagedByCockpit` of the allowance event class is the same as the one of the allowance logic.

Error Code	Message	Action
ALLOWANCE-495 [page 936]	`You cannot create the allowance plan with the flag ManagedByCockpit set to true with the status OPEN. Use the status RELEASED.`	Change the status of the allowance plan. Verify your changes.
ALLOWANCE-496 [page 937]	`You cannot change the flag ManagedByCockpit to "{newManagedByCockpitFlag}" in the allowance plan.`	
ALLOWANCE-497 [page 939]	`You cannot change the flag ManagedByCockpit to "{newManagedByCockpitFlag}" in the allowance logic.`	
ALLOWANCE-498 [page 940]	`You cannot change the flag ManagedByCockpit to "{newManagedByCockpitFlag}" in the allowance event class.`	
ALLOWANCE-499 [page 942]	`You cannot change the content of an allowance logic with the flag ManagedByCockpit set to true.`	
ALLOWANCE-500 [page 943]	`You cannot change the content of an allowance event class with the flag ManagedByCockpit set to true.`	
ALLOWANCE-501 [page 944]	`The allowance logic or the charge component with the flag ManagedByCockpit set to true cannot reference the allowance plan "{allowancePlanId}" of which flag ManagedByCockpit is set to false.`	Change the allowance plan which is referenced to one of which attribute `ManagedByCockpit` is set to true. Verify your changes.
ALLOWANCE-502 [page 946]	`The allowance logic or the charge component with the flag ManagedByCockpit set to true cannot reference the allowance event class "{allowanceEventClassId}" of which flag ManagedByCockpit is set to false.`	Change the allowance event class which is referenced to one of which attribute `ManagedByCockpit` is set to true. Verify your changes.

Error Code	Message	Action
ALLOWANCE-503 [page 948]	`The allowance logic "{allowanceLogicId}" is already referenced by the allowance plan "{referencingAllowancePlanId}". You cannot reference twice an allowance logic with the flag ManagedByCockpit set to true.`	Choose another allowance logic or create a new one. Verify your changes.
ALLOWANCE-504 [page 949]	`The allowance event class "{allowanceEventClassId}" is already referenced by the allowance logic "{referencingAllowanceLogicId}". You cannot reference twice an allowance event class with the flag ManagedByCockpit set to true.`	Choose another allowance event class or create a new one. Verify your changes.
ALLOWANCE-505 [page 951]	`This allowance plan "{allowancePlanId}" is not managed by Cockpit. You cannot use the operation deleteAllowancePlanManagedByCockpit.`	Use the `deleteAllowancePlan` operation instead.
ALLOWANCE-506 [page 952]	`This allowance plan "{allowancePlanId}" is managed by Cockpit. You cannot use the operation deleteAllowancePlan.`	Use the `deleteAllowancePlanManagedByCockpit` operation instead.
ALLOWANCE-507 [page 954]	`The parameter "{parameterName}" specified as a sorting criterion does not exist in the allowance plan "{allowancePlanId}".`	In the sorting criterion, specify the name of a parameter that exists in the allowance plan. Verify your changes.
ALLOWANCE-508 [page 955]	`The parameter "{parameterName}" is specified as a sorting criterion of type "{typeInSortingCriterion}" while its type is "{typeInAllowancePlan}" in the allowance plan "{allowancePlanId}".`	In the sorting criterion, specify the correct type for the parameter. Verify your changes.

Error Code	Message	Action
ALLOWANCE-509 [page 957]	`The counter "{counterName}" specified as a sorting criterion does not exist in the allowance plan "{allowancePlanId}".`	In the sorting criterion, specify the name of a counter that exists in the allowance plan. Verify your changes.
CC-SEC-AUTH-2 [page 959]	`Authentication failure because no match found for user/password combination.`	Check your login or your password. Verify your changes.
CC-SEC-AUTH-3 [page 960]	`Authentication failure because no match found for user/password combination.`	Check your login or your password. Verify your changes.
CC-SEC-AUTH-4 [page 961]	`Authentication failure because the password has expired.`	Change your password. Verify your changes.
CC-SEC-AUTH-5 [page 963]	`The user profile ''{userLogin}'' is locked.`	Contact your system administrator to unlock your profile. Verify your changes.
CC-SEC-AUTH-6 [page 964]	`The user ''{userLogin}'' is not allowed to invoke the operation ''{operationName}''.`	Verify your changes.
CC-SEC-AUTH-7 [page 966]	`Authentication failure because the password needs to be changed.`	Change your password. Verify your changes.
CC-SEC-AUTH-8 [page 967]	`The user session with identifier ''{sessionId}'' does not exist.`	Open a new user session. Verify your changes.
CC-SEC-AUTH-9 [page 969]	`The user session ''{sessionId}'' is associated to another user.`	Open a new user session. Verify your changes.
CC-SEC-AUTH-10 [page 970]	`Authentication failure because the user and/or the authentication context is missing.`	Change your password. Verify your changes.

Error Code	Message	Action
CC-SEC-AUTH-11 [page 972]	`The user ''{userLogin}'' is not allowed to use this technical interface.`	Authenticate with another user which has the appropriate security profile for using this technical interface. Verify your changes.
CC-SEC-AUTH-1000 [page 973]	`Invalid user credential because the login is missing.`	Verify your changes.
CC-SEC-AUTH-1001 [page 974]	`Invalid user credential because the password is missing.`	Verify your changes.
CHANGEID-1 [page 976]	`The change id of the object [{objectId}] with type [{objectType}] is [{currentChangeId}]. It is different from the change id [{changeIdToCheck}] provided for checking.`	Cancel the modifications or overwrite the object. Verify your changes.
CHANGEID-2 [page 977]	`The id of the change id model is missing.`	Set a change ID. Verify your changes.
CHANGEID-3 [page 979]	`The object type is missing.`	Set an object type. Verify your changes.
CHANGEID-4 [page 980]	`The object id is missing.`	Set an object ID. Verify your changes.
CHANGEID-5 [page 982]	`The change id model is missing.`	Set a change ID model. Verify your changes.
CHANGEID-6 [page 983]	`The id of the change id model must be a positive number.`	Use a positive number as change ID. Verify your changes.
CHANGEID-7 [page 984]	`The catalog object identified by [{objectId}] with type [{objectType}] does not exist.`	Set a pair (object ID, object type) corresponding to an existing object. Verify your changes.
CHANGEID-8 [page 986]	`The id of the change id model must not be a negative number.`	Use a strictly positive number as change ID. Verify your changes.

Error Code	Message	Action
CHANGEID-9 [page 987]	`Cannot set the flag on the resource identified by the code "{code}". This flag was already set by user "{user}" during session "{session}" with another Core Tool.`	Unset the flag by asking this user to stop editing the resource or by asking the administrator to delete his/her session. Verify your changes.
CHANGEID-10 [page 989]	`This flag action is not supported.`	Use 'set' or 'unset' as valid action. Verify your changes.
CHANGEID-11 [page 990]	`The flag code is null or empty.`	Set a valid code. Verify your changes.
CHANGEID-12 [page 992]	`The owner cannot be empty.`	Set a valid owner. Verify your changes.
CHANGE-LIST-1 [page 993]	`The Change List is missing in the creation operation.`	Add a Change List to the creation operation. Verify your changes.
CHANGE-LIST-2 [page 994]	`The name of the Change List is missing.`	Specify a name for the Change List. Verify your changes.
CHANGE-LIST-3 [page 996]	`The Change List cannot be created because a Change List with the name "{changeListName}" already exists.`	Change the name of the Change List. Verify your changes.
CHANGE-LIST-4 [page 997]	`Error while validating the Change List "{changeListName}".`	Verify your changes.
CHANGE-LIST-5 [page 999]	`The Change List does not contain any object.`	Add at least one object to the Change List. Verify your changes.
CHANGE-LIST-6 [page 1000]	`Error while validating the object at index "{changeListObjectIndex}".`	Verify your changes.

Error Code	Message	Action
CHANGE-LIST-7 [page 1002]	`The code of the object is missing.`	Specify a code for the object. Verify your changes.
CHANGE-LIST-8 [page 1003]	`The type of the object is missing.`	Specify a type for the object. Verify your changes.
CHANGE-LIST-9 [page 1004]	`The object "{changeListObjectCode}" of type "{changeListObjectType}" does not exist.`	Modify the code or the type of the object to reference an existing object. Verify your changes.
CHANGE-LIST-10 [page 1006]	`The Change List "{changeListName}" cannot be deleted because it does not exist.`	Specify an existing name for the Change List. Verify your changes.
CHANGE-LIST-11 [page 1007]	`The mandatory filter in the Search Change List operation is missing.`	Specify a filter in the Search Change List operation. Verify your changes.
CHANGE-LIST-12 [page 1009]	`An error occurred during the execution of the search operation: {errorMessage}.`	Verify your changes.
CHANGE-LIST-13 [page 1010]	`The name of the Change List is missing in the operation.`	Specify the name of a Change List for the operation. Verify your changes.
CHANGE-LIST-14 [page 1012]	`The code of the object is missing in the operation.`	Specify the code of an object for the operation. Verify your changes.
CHANGE-LIST-15 [page 1013]	`The type of the object is missing in the operation.`	Specify the type of an object for the operation. Verify your changes.
CHANGE-LIST-16 [page 1014]	`The Change List "{changeListName}" does not exist.`	Modify the name of the Change List to reference an existing one. Verify your changes.

Error Code	Message	Action
CHANGE-LIST-17 [page 1016]	`The object "{changeListObjectCode}" of type "{changeListObjectType}" does not exist in the Change List "{changeListName}".`	Specify the code and type of an existing object to include in the Change List. Verify your changes.
CHANGE-LIST-18 [page 1017]	`The name of the Change List is missing in the delete operation.`	Specify the name of a Change List for the delete operation. Verify your changes.
CHANGE-LIST-19 [page 1019]	`The object "{changeListObjectCode}" of type "{changeListObjectType}" is specified more than once in the Change List.`	Remove the duplicate object from the Change List. Verify your changes.
CHANGE-LIST-20 (Revoked) [page 1020]	`The Change List cannot be created until Transport Destinations are configured.`	Add Transport Destination(s) to the system. Verify your changes.
CHANGE-LIST-22 [page 1022]	`The name of the change list is missing in the change list header of the create operation.`	Assign a name to the change list header of the create operation. Verify your changes.
CHANGE-LIST-23 [page 1023]	`The change list built from object references cannot be created because a change list with the name "{changeListName}" already exists.`	Change the name of the change list in the change list header of the create operation. Verify your changes.
CHANGE-LIST-24 [page 1025]	`Error while validating the object references of the change list "{changeListName}".`	Verify your changes.
CHANGE-LIST-25 [page 1026]	`The change list does not contain any object reference.`	Add at least one object reference to the create operation. Verify your changes.
CHANGE-LIST-26 [page 1028]	`Error while validating the object reference at index "{objectReferenceIndex}".`	Verify your changes.

Error Code	Message	Action
CHANGE-LIST-27 [page 1029]	`The identifier of the object reference is missing.`	Assign an identifier to the object reference. Verify your changes.
CHANGE-LIST-28 [page 1031]	`The type of the object reference is missing.`	Assign a type to the object reference. Verify your changes.
CHANGE-LIST-29 [page 1032]	`The object reference with the object identifier "{objectReferenceObjectId}" and the object type "{objectReferenceObjectType}" does not match any existing object in the SAP CC system.`	Change the object identifier or the object type in the object reference to match an existing object. Verify your changes.
CHANGE-LIST-30 [page 1034]	`The object reference with the object identifier "{objectReferenceObjectId}" and the object type "{objectReferenceObjectType}" already exists in the change list create operation.`	Remove the duplicate object reference from the change list create operation. Verify your changes.
CHARGE-COMPO-NENT-1 [page 1035]	`The code of the charge component is missing.`	Add an identification code to the charge component. Verify your changes.
CHARGE-COMPO-NENT-2 [page 1037]	`The owner of the charge component "{chargeComponentCode}" is missing.`	Add an owner to the charge component. It is the a pricing catalog of the service provider. Verify your changes.
CHARGE-COMPO-NENT-3 [page 1038]	`The price plan of the charge component "{chargeComponentCode}" is missing.`	Add a Price Plan to the Charge Component. Verify your changes.
CHARGE-COMPO-NENT-4 [page 1040]	`The charge component "{chargeComponentCode}" is set to manage multicurrencies but the currency "{currencyCode}" is set.`	Check whether the charge component is marked as multi-currencies or remove the set currency. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-5 [page 1041]	`The charge component "{chargeComponentCode}" is marked as monocurrency but no currency is set.`	Add a currency in the charge component or in the price plan. Verify your changes.
CHARGE-COMPO-NENT-6 [page 1043]	`The Charge Component "{chargeComponentCode}" is set with the currency "{chargeComponentCurrencyCode}" and Price Plan with currency "{pricePlanCurrencyCode}".`	Set the currency only in one of the two places. Verify your changes.
CHARGE-COMPO-NENT-7 [page 1044]	`The currency "{currencyCode}" of the charge component "{chargeComponentCode}" is not a valid currency.`	Set a valid currency. Verify your changes.
CHARGE-COMPO-NENT-8 [page 1046]	`The name of the price plan is missing.`	Add a name to the Price Plan. Verify your changes.
CHARGE-COMPO-NENT-9 [page 1047]	`The currency "{currencyCode}" of the Price Plan "{pricePlanName}" is not a valid currency.`	Set a valid currency. Verify your changes.
CHARGE-COMPO-NENT-10 [page 1049]	`The currency code of the Price Plan is not set.`	Check the presence of a currency code in the Price Plan. Verify your changes.
CHARGE-COMPO-NENT-11 [page 1050]	`The currency code "{invalidCurrencyCode}" of the Price Plan is not a valid currency code.`	Check the validity of the currency code in the Price Plan. Verify your changes.
CHARGE-COMPO-NENT-12 [page 1052]	`The rate component of type "{rateComponentType}" is invalid.`	Check the validity of the rate component. Verify your changes.
CHARGE-COMPO-NENT-13 [page 1053]	`The usage rate name is not set.`	Check the presence of a name in the usage rate. Verify your changes.
CHARGE-COMPO-NENT-14 [page 1055]	`The usage rate "{usageRateName}" does not contain any rate component.`	Check the presence of a rate component in the usage rate. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-15 [page 1056]	`The recurring rate name is not set.`	Check the presence of a name in the recurring rate. Verify your changes.
CHARGE-COMPO-NENT-16 [page 1058]	`The recurring rate "{recurringRateName}" does not contain any rate component.`	Check the presence of a rate component in the recurring rate. Verify your changes.
CHARGE-COMPO-NENT-17 [page 1059]	`The recurring rate "{recurringRateName}" is marked as proratable but does not contain any prorata.`	Check the presence of a prorata in the recurring rate. Verify your changes.
CHARGE-COMPO-NENT-18 [page 1061]	`The one-shot rate name is not set.`	Check the presence of a name in the one-shot rate. Verify your changes.
CHARGE-COMPO-NENT-19 [page 1062]	`The one-shot rate "{oneShotRateName}" does not contain any rate component.`	Check the presence of a rate component in the one-shot rate. Verify your changes.
CHARGE-COMPO-NENT-20 [page 1063]	`The counter description has no name.`	Check the presence of a name in the counter description. Verify your changes.
CHARGE-COMPO-NENT-21 [page 1065]	`The counter description "{counterDescriptionName}" has no initial value.`	Check the presence of an initial value in the counter description. Verify your changes.
CHARGE-COMPO-NENT-22 [page 1066]	`The counter description "{counterDescriptionName}" is duplicated.`	Check that the counter description name is unique. Verify your changes.
CHARGE-COMPO-NENT-23 [page 1068]	`The transient counter description has no name.`	Check the presence of a name in the transient counter description. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-24 [page 1069]	`The transient counter description "{counterDescriptionName}" has no initial value.`	Check the presence of an initial value in the transient counter description. Verify your changes.
CHARGE-COMPO-NENT-25 [page 1071]	`The transient counter description "{counterDescriptionName}" is duplicated.`	Check that the transient counter description name is unique. Verify your changes.
CHARGE-COMPO-NENT-26 [page 1072]	`One parameter does not have any name.`	Check that the parameter name is not empty. Verify your changes.
CHARGE-COMPO-NENT-27 [page 1074]	`The parameter "{parameterName}" has a null value.`	Check that the parameter value is not null. Verify your changes.
CHARGE-COMPO-NENT-28 [page 1075]	`The parameter "{parameterName}" is duplicated.`	Check that the parameter name is unique. Verify your changes.
CHARGE-COMPO-NENT-29 [page 1077]	`The charging plan name is not set.`	Check the presence of a name in the charging plan. Verify your changes.
CHARGE-COMPO-NENT-30 [page 1078]	`The usage charge name is not set.`	Check the presence of a name in the usage charge. Verify your changes.
CHARGE-COMPO-NENT-31 [page 1079]	`The chargeable item name is not set in the usage charge "{usageChargeName}".`	Check the presence of a chargeable item name in the usage charge. Verify your changes.
CHARGE-COMPO-NENT-32 [page 1081]	`There is no child in the usage charge "{usageChargeName}".`	Check the presence of a child in the usage charge. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-33 [page 1082]	`There are multiple children in the usage charge "{usageChargeName}".`	Check the presence of only one child in the usage charge. Verify your changes.
CHARGE-COMPO-NENT-34 [page 1084]	`The rate component of type "{rateComponentType}" is invalid in the charging plan.`	Check the validity of the rate component. Verify your changes.
CHARGE-COMPO-NENT-35 [page 1085]	`The recurring charge name is not set.`	Check the presence of a name in the recurring charge. Verify your changes.
CHARGE-COMPO-NENT-36 [page 1087]	`There is no child in the recurring charge "{recurringChargeName}".`	Check the presence of a child in the recurring charge. Verify your changes.
CHARGE-COMPO-NENT-37 [page 1088]	`There are multiple children in the recurring charge "{recurringChargeName}".`	Check the presence of only one child in the recurring charge. Verify your changes.
CHARGE-COMPO-NENT-38 [page 1090]	`The rate component of type "{rateComponentType}" is invalid in the usage charge "{usageChargeName}".`	Check the validity of the rate component. Verify your changes.
CHARGE-COMPO-NENT-39 [page 1091]	`The rate component of type "{rateComponentType}" is invalid in the recurring charge "{recurringChargeName}".`	Check the validity of the rate component. Verify your changes.
CHARGE-COMPO-NENT-40 [page 1093]	`The rate component of type "{rateComponentType}" is invalid in the one-shot charge "{oneShotChargeName}".`	Check the validity of the rate component. Verify your changes.
CHARGE-COMPO-NENT-41 [page 1094]	`The one-shot charge name is not set.`	Check the presence of a name in the one-shot charge. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-42 [page 1096]	`There is no child in the one-shot charge "{oneShotChargeName}".`	Check the presence of a child in the one-shot charge. Verify your changes.
CHARGE-COMPO-NENT-43 [page 1097]	`There are multiple children in the one-shot charge "{oneShotChargeName}".`	Check the presence of only one child in the one-shot charge. Verify your changes.
CHARGE-COMPO-NENT-44 [page 1099]	`The default charge name is not set.`	Check the presence of a name in the default charge. Verify your changes.
CHARGE-COMPO-NENT-45 [page 1100]	`There is no child in the default charge "{defaultChargeName}".`	Check the presence of a child in the default charge. Verify your changes.
CHARGE-COMPO-NENT-46 [page 1101]	`There are multiple children in the default charge "{defaultChargeName}".`	Check the presence of only one child in the default charge. Verify your changes.
CHARGE-COMPO-NENT-47 [page 1103]	`The rate component of type "{rateComponentType}" is invalid in the default charge "{defaultChargeName}".`	Check the validity of the rate component. Verify your changes.
CHARGE-COMPO-NENT-48 [page 1104]	`The usage charge "{usageChargeName}" already exists in the charging plan "{chargingPlanName}".`	Check the uniqueness of the usage charge name. Verify your changes.
CHARGE-COMPO-NENT-49 [page 1106]	`The charging plan "{chargingPlanName}" has several usage charges using the chargeable item class "{chargeableItemClassName}".`	Check the uniqueness of the chargeable item class in the charging plan. Verify your changes.
CHARGE-COMPO-NENT-50 [page 1107]	`The usage rate "{usageRateName}" already exists in the price plan "{pricePlanName}".`	Check the uniqueness of the usage rate name. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-51 [page 1109]	`The price plan "{pricePlanName}" has several usage rates using the chargeable item class "{chargeableItemClassName}".`	Check the uniqueness of the chargeable item class in the price plan. Verify your changes.
CHARGE-COMPO-NENT-52 [page 1110]	`The usage rate "{usageRateName}" is invalid because its component tree is invalid.`	Check the validity of the rate components in the usage rate. Verify your changes.
CHARGE-COMPO-NENT-53 [page 1112]	`The recurring rate "{recurringRateName}" is invalid because its component tree is invalid.`	Check the validity of the rate components in the recurring rate. Verify your changes.
CHARGE-COMPO-NENT-54 [page 1113]	`The one-shot rate "{oneshotRateName}" is invalid because its component tree is invalid.`	Check the validity of the rate components in the one-shot rate. Verify your changes.
CHARGE-COMPO-NENT-55 [page 1115]	`The rate component has an empty name.`	Check the presence of a name in the rate component. Verify your changes.
CHARGE-COMPO-NENT-56 [page 1116]	`The rate component "{rateComponentName}" must have exactly "{expectedChildrenCount}" children but has "{childrenCount}" children.`	Add or remove children. Verify your changes.
CHARGE-COMPO-NENT-57 [page 1118]	`The rate component "{rateComponentName}" has an undefined child at index "{childIndex}".`	Add or remove erroneous children. Verify your changes.
CHARGE-COMPO-NENT-58 [page 1119]	`The rate component "{rateComponentName}" is invalid.`	Check the validity of the rate component. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-59 [page 1121]	`The mapping table class "{mappingTableClassId}" defined in the parameter "{parameterName}" does not exist in the SAP CC system.`	Specify the identifier of an existing mapping table class for additional information value. Verify your changes.
CHARGE-COMPO-NENT-60 [page 1122]	`The mapping table "{mappingTableId}" defined in the parameter "{parameterName}" does not exist in the SAP CC system.`	Specify the identifier of an existing mapping table for additional information value. Verify your changes.
CHARGE-COMPO-NENT-61 [page 1124]	`The range table class "{rangeTableClassId}" defined in the parameter "{parameterName}" does not exist in the SAP CC system.`	Specify the identifier of an existing range table class for additional information value. Verify your changes.
CHARGE-COMPO-NENT-62 [page 1125]	`The range table "{rangeTableId}" defined in the parameter "{parameterName}" does not exist in the SAP CC system.`	Specify the identifier of an existing range table for additional information value. Verify your changes.
CHARGE-COMPO-NENT-63 [page 1127]	`The additional information named "{addInfoName}" defined in the parameter "{parameterName}" is not supported.`	Check the validity of the parameter. The supported values are: `dataType`, `mappingTableClass` and `rangeTableClass`. Verify your changes.
CHARGE-COMPO-NENT-64 [page 1128]	`The additional information value "{addInfoValue}" defined in the parameter "{parameterName}" is not a valid data type.`	Check the validity of the parameter additional information. Verify your changes.
CHARGE-COMPO-NENT-65 [page 1130]	`The additional information value "{addInfoValue}" requires that parameter "{parameterName}" is of type string.`	Most probably you defined the wrong type. Check the type and correct it to string. Verify your changes.
CHARGE-COMPO-NENT-66 [page 1131]	`The rate component "{rateComponentName}" defines no child but has "{childrenCount}" child(ren) defined.`	Remove all children. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-67 [page 1133]	`The rate "{rateName}" is invalid because it contains an allowance event sender component while the charging plan dictionary of the charge component is not typed.`	Remove the allowance event sender component from the rate. Verify your changes.
CHARGE-COMPO-NENT-68 [page 1134]	`The rate "{rateName}" is invalid because it contains an allowance property introducer component while the charging plan dictionary of the charge component is not typed.`	Remove the allowance property introducer component from the rate. Verify your changes.
CHARGE-COMPO-NENT-69 [page 1136]	`The rate "{rateName}" is invalid because it contains a create allowance component while the charging plan dictionary of the charge component is not typed.`	Remove the create allowance component from the rate. Verify your changes.
CHARGE-COMPO-NENT-70 [page 1138]	`The property at index {propertyIndex} does not have a name.`	Set a name for the property to introduce. Verify your changes.
CHARGE-COMPO-NENT-71 [page 1139]	`The property "{propertyName}" is configured as a context property but does not specify the name of a context property.`	Set the name of a context property in the property to introduce. Verify your changes.
CHARGE-COMPO-NENT-72 [page 1141]	`The property "{propertyName}" specifies an invalid context property: "{invalidContextPropertyName}" .`	Set the name of a valid context property in the property to introduce. Verify your changes.
CHARGE-COMPO-NENT-73 [page 1142]	`The property "{propertyName}" does not specify a value.`	Set a value in the property to introduce. Verify your changes.
CHARGE-COMPO-NENT-74 [page 1144]	`The property "{propertyName}" specifies an invalid type.`	Set a valid type in the property to introduce ("decimal", "string", or "date"). Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-75 [page 1145]	`The property "{duplicatePropertyName}" is specified more than once.`	Rename one of the duplicate properties. Verify your changes.
CHARGE-COMPO-NENT-76 [page 1147]	`The public holiday "{code}" does not exist.`	Use a valid public holiday. Verify your changes.
CHARGE-COMPO-NENT-77 [page 1148]	`The data type additional information is missing in the parameter {parameterName}.`	Specify the data type additional information for the parameter. Verify your changes.
CHARGE-COMPO-NENT-78 [page 1150]	`A no access function that contains a "bestEffortReservation" property is only allowed in a charge component, in a pricing macro or in an allowance logic.`	Remove the "bestEffortReservation" property from the no access function. Verify your changes.
CHARGE-COMPO-NENT-79 [page 1151]	`The property type of the source "{sourcePropertyType}" is unknown.`	Set the type as follows: 0 for a Number, 1 for a String, 2 for a Date, 4 for a Multi-valued String, or 5 for a Multi-valued NumberSet the type as follows: 0 for a Number, 1 for a String, 2 for a Date, 4 for a Multi-valued String, or 5 for a Multi-valued Number. Verify your changes.
CHARGE-COMPO-NENT-80 [page 1153]	`The property type of the target "{targetPropertyType}" is unknown.`	Set the type as follows: 0 for a Number, 1 for a String, 2 for a Date, 4 for a Multi-valued String, or 5 for a Multi-valued Number. Verify your changes.
CHARGE-COMPO-NENT-81 [page 1154]	`The conversion between the source property type "{sourcePropertyType}" and the target property type "{targetPropertyType}" is not allowed.`	Set a source type that can be converted into a target type. Verify your changes.
CHARGE-COMPO-NENT-82 [page 1156]	`The field separator "{fieldSeparator}" must exactly contain one character.`	Set the field separator to one character. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-83 [page 1157]	`The field separator is mandatory for converting source type "{sourcePropertyType}" into target type "{targetPropertyType}".`	Add the field separator, or change the source or the target type. Verify your changes.
CHARGE-COMPO-NENT-84 [page 1159]	`The decimal separator is mandatory for converting source type "{sourcePropertyType}" into target type "{targetPropertyType}".`	Add the decimal separator attribute, or change the source or the target type. Verify your changes.
CHARGE-COMPO-NENT-85 [page 1160]	`The decimal separator "{decimalSeparator}" must exactly contain one character.`	Set the decimal separator to one character. Verify your changes.
CHARGE-COMPO-NENT-86 [page 1162]	`The thousand separator is mandatory for converting source type "{sourcePropertyType}" into target type "{targetPropertyType}".`	Add the thousand separator, or change the source or the target type. Verify your changes.
CHARGE-COMPO-NENT-87 [page 1163]	`The thousand separator "{thousandSeparator}" must contain at least one character.`	Set the thousand separator to at least one character. Verify your changes.
CHARGE-COMPO-NENT-88 [page 1165]	`The field separator and the decimal separator must be different.`	Set the field separator and the decimal separator to different values. Verify your changes.
CHARGE-COMPO-NENT-89 [page 1166]	`The field separator and the thousand separator must be different.`	Set the field separator and the thousand separator to different values. Verify your changes.
CHARGE-COMPO-NENT-90 [page 1167]	`The decimal separator and the thousand separator must be different.`	Set the decimal separator and the thousand separator to different values. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-91 [page 1169]	`The date format pattern is mandatory for converting source type "{sourcePropertyType}" into target type "{targetPropertyType}".`	Add the date format pattern, or change the source or the target type. Verify your changes.
CHARGE-COMPO-NENT-92 [page 1170]	`The date format pattern "{dateFormatPattern}" is invalid.`	Set a valid date format pattern. Verify your changes.
CHARGE-COMPO-NENT-93 [page 1172]	`The field to use "{fieldToUse}" is not supported.`	Set a valid field to use between -1 and 16. Verify your changes.
CHARGE-COMPO-NENT-94 [page 1173]	`The start offset "{startOffset}" must be greater than 0.`	Set the start offset to a value greater than 0. Verify your changes.
CHARGE-COMPO-NENT-95 [page 1175]	`The start offset "{startOffset}" must be lower than or equal to the stop offset "{stopOffset}" plus one.`	Set the start offset to a value lower than or equal to the stop offset plus one. Verify your changes.
CHARGE-COMPO-NENT-96 [page 1176]	`The stop offset "{stopOffset}" must be greater than or equal to -1.`	Set the stop offset to a value greater than or equal to -1. Verify your changes.
CHARGE-COMPO-NENT-97 [page 1178]	`Property "{propertyName}" of type "{type}" is required by the component but does not exist in the context.`	Declare the missing property or remove the invalid reference from the logic component. Verify your changes.
CHARGE-COMPO-NENT-98 [page 1180]	`Property "{propertyName}" of type "{expectedType}" is required by the component but is declared in the context with a different type.`	Fix the logic component to reference a property of the expected type. Verify your changes.
CHARGE-COMPO-NENT-99 [page 1182]	`Property "{propertyName}" exists in the context but does not meet the constraints of the component.`	Change the logic component to reference an appropriate property (table ID, counter, etc.). Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-100 [page 1184]	`Property "{propertyName}" of type "{type}" is referenced by the component but has no valid category.`	Fix the XML envelope that contains the incorrect pricing logic. Verify your changes.
CHARGE-COMPO-NENT-101 [page 1186]	`The source property is mandatory.`	Set a source property. Verify your changes.
CHARGE-COMPO-NENT-102 [page 1187]	`The parameter "{parameterName}" cannot reference the mapping table "{mappingTableId}" because this mapping table has an agreement ID.`	Select a mapping table without agreement ID. Verify your changes.
CHARGE-COMPO-NENT-103 [page 1189]	`The parameter "{parameterName}" cannot reference the range table "{rangeTableId}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.
CHARGE-COMPO-NENT-104 [page 1190]	`Recurring rate "{recurringRateName}" is configured for a 4-4-5 calendar. The only supported frequency type is month.`	Set the frequency type to month. Verify your changes.
CHARGE-COMPO-NENT-105 [page 1192]	`Recurring rate "{recurringRateName}" is configured for a 4-4-5 calendar. T he only supported frequency periods are 1, 3, 6 and 12.`	Set the frequency period to 1, 3, 6 or 12. Verify your changes.
CHARGE-COMPO-NENT-106 [page 1193]	`The prorata component is configured for a 4-4-5 calendar. The only supported frequency type is month.`	Set the frequency type to month. Verify your changes.

Error Code	Message	Action
CHARGE-COMPO-NENT-107 [page 1195]	`The prorata component is configured for a 4-4-5 calendar. The only supported frequency periods are 1, 3, 6 and 12.`	Set the frequency period to 1, 3, 6 or 12. Verify your changes.
CHARGE-COMPO-NENT-108 [page 1196]	`The charge component "{chargeComponentCode}" must not contain any prepaid charging reference because the Prepaid Accounts Management feature is disabled.`	Remove all prepaid charging references from the charge component. Verify your changes.
CHARGE-COMPO-NENT-109 [page 1198]	`Overspending on prepaid account is not available because the Prepaid Accounts Management feature is disabled.`	Change the overspending parameters. Verify your changes.
CHARGE-COMPO-NENT-110 [page 1199]	`The Switching Comparator component is not available because the Prepaid Accounts Management feature is disabled.`	Remove the Switching Comparator component from the charge. Verify your changes.
CHARGE-COMPO-NENT-111 [page 1201]	`The Default Reference component is not available because the Prepaid Accounts Management feature is disabled.`	Remove the Default Reference component from the charge. Verify your changes.
CHARGE-COMPO-NENT-112 [page 1202]	`The frequency of recurring rate "{recurringRateName}" is not valid.`	Set a valid frequency in the recurring rate. Verify your changes.
CHARGE-COMPO-NENT-113 [page 1204]	`The frequency of prorata component "{componentName}" is not valid.`	Set a valid frequency in the prorata component. Verify your changes.
CHARGE-COMPO-NENT-114 [page 1205]	`The property is mandatory.`	Select a valid property from the rating context.

Error Code	Message	Action
CHARGE-COMPO-NENT-115 [page 1206]	`The recurring time slot is invalid.`	Check that the time slot is correctly defined (beginning of the slot before the end for example).
CHARGE-COMPO-NENT-116 [page 1208]	`The property "{propertyName}" is mandatory.`	Select a valid number property from the rating context.
CHARGE-COMPO-NENT-117 [page 1209]	`The property "{propertyName}" or the split value must be provided.`	Check that at least the number property or the split value is defined. Verify your changes.
CHARGE-PLAN-1 [page 1211]	`The charge plan is missing.`	Add a charge plan to the create operation. Verify your changes.
CHARGE-PLAN-2 [page 1212]	`The id of the charge plan is missing.`	Add an ID to the charge plan. Verify your changes.
CHARGE-PLAN-3 [page 1214]	`The owner of the charge plan "{chargePlanId}" is missing.`	Add an owner to the charge plan. Verify your changes.
CHARGE-PLAN-4 [page 1215]	`The description of the charge plan "{chargePlanId}" is missing.`	Add a description to the charge plan. Verify your changes.
CHARGE-PLAN-5 [page 1217]	`Error while validating the charge plan "{chargePlanId}".`	Verify your changes.
CHARGE-PLAN-6 (Revoked) [page 1218]	`The name of the Additional Information at index {additionalInformationIndex} is missing.`	Add a name to the Additional Information item. Verify your changes.
CHARGE-PLAN-7 (Revoked) [page 1220]	`The name "{additionalInformationName}" of the Additional Information at index {secondIndex} is already used by the Additional Information at index {firstIndex}.`	Change the name of the Additional Information. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-8 (Revoked) [page 1222]	`The description of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a description to the Additional Information. Verify your changes.
CHARGE-PLAN-9 (Revoked) [page 1223]	`The type of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing or unknown (supported types are string, number, date).`	Add a type to the Additional Information or change it to a supported one: string, number, date. Verify your changes.
CHARGE-PLAN-10 (Revoked) [page 1225]	`The date value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a date value to the Additional Information. Verify your changes.
CHARGE-PLAN-11 (Revoked) [page 1227]	`The number value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a number value to the Additional Information. Verify your changes.
CHARGE-PLAN-12 (Revoked) [page 1228]	`The string value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a string value to the Additional Information. Verify your changes.
CHARGE-PLAN-13 (Revoked) [page 1230]	`The type "{additionalInformationType}" of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is unsupported (supported types are string, number, date).`	Use a supported type (string, number, date) for the Additional Information. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-14 [page 1232]	`The name of the Parameter at index {parameterIndex} is missing.`	Add a name to the Parameter. Verify your changes.
CHARGE-PLAN-15 [page 1233]	`The name "{parameterName}" of the Parameter at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter. Verify your changes.
CHARGE-PLAN-16 [page 1235]	`The type of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown (supported types are string, number, date, currency).`	Add a type to the Parameter or change it to a supported one: string, number, date, currency. Verify your changes.
CHARGE-PLAN-17 [page 1236]	`The visibility of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown (supported visibilities are chargePlan, chargePlanClass).`	Add a visibility to the Parameter or change it to a supported one: chargePlan, chargePlanClass. Verify your changes.
CHARGE-PLAN-18 [page 1238]	`The description of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a description to the Parameter. Verify your changes.
CHARGE-PLAN-19 [page 1239]	`The date value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a date value to the Parameter. Verify your changes.
CHARGE-PLAN-20 [page 1241]	`The number value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a number value to the Parameter. Verify your changes.
CHARGE-PLAN-21 [page 1242]	`The string value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a string value to the Parameter. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-22 [page 1244]	`The type "{parameterType}" of the Parameter "{parameterName}" at index {parameterIndex} is unsupported (supported types are string, number, date, currency).`	Use a supported type (string, number, date, currency) for the Parameter. Verify your changes.
CHARGE-PLAN-23 [page 1245]	`The Parameter "{parameterName}" at index {parameterIndex} is not linked to a charge plan item Parameter Reference.`	Link the Parameter or remove it. Verify your changes.
CHARGE-PLAN-24 [page 1247]	`The name of the Counter at index {counterIndex} is missing.`	Add a name to the Counter. Verify your changes.
CHARGE-PLAN-25 [page 1248]	`The name "{counterName}" of the Counter at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter. Verify your changes.
CHARGE-PLAN-26 [page 1250]	`The initial value of the Counter "{counterName}" at index {counterIndex} is missing.`	Add an initial value to the Counter. Verify your changes.
CHARGE-PLAN-27 [page 1251]	`The visibility of the Counter "{counterName}" at index {counterIndex} is missing or unknown (supported visibilities are chargePlan, chargePlanClass).`	Add a visibility to the Counter or change it to a supported one: chargePlan, chargePlanClass. Verify your changes.
CHARGE-PLAN-28 [page 1253]	`The description of the Counter "{counterName}" at index {counterIndex} is missing.`	Add a description to the Counter. Verify your changes.
CHARGE-PLAN-29 [page 1254]	`The Counter "{counterName}" at index {counterIndex} is not linked to a charge plan item Counter Reference.`	Link the Counter or remove it. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-30 [page 1256]	`The name of the Account Assignment at index {accountAssignmentIndex} is missing.`	Add a name to the Account Assignment. Verify your changes.
CHARGE-PLAN-31 [page 1257]	`The name "{accountAssignmentName}" of the Account Assignment at index {secondIndex} is already used by the Account Assignment at index {firstIndex}.`	Change the name of the Account Assignment. Verify your changes.
CHARGE-PLAN-32 [page 1259]	`The type of the Account Assignment "{accountAssignmentName}" at index {accountAssignmentIndex} is missing or unknown (supported types are prepaid, postpaid).`	Add a type to the Account Assignment or change it to a supported one: prepaid, postpaid. Verify your changes.
CHARGE-PLAN-33 [page 1260]	`The description of the Account Assignment "{accountAssignmentName}" at index {accountAssignmentIndex} is missing.`	Add a description to the Account Assignment. Verify your changes.
CHARGE-PLAN-34 [page 1262]	`The Account Assignment "{accountAssignmentName}" at index {accountAssignmentIndex} is not linked to a charge plan item Account Assignment Reference.`	Link the Account Assignment or remove it. Verify your changes.
CHARGE-PLAN-35 [page 1263]	`The name of the User Technical Identifier at index {userTechIdIndex} is missing.`	Add a name to the User Technical Identifier. Verify your changes.
CHARGE-PLAN-36 [page 1265]	`The name "{userTechIdName}" of the User Technical Identifier at index {secondIndex} is already used by the User Technical Identifier at index {firstIndex}.`	Change the name of the User Technical Identifier. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-37 [page 1266]	`The description of the User Technical Identifier "{userTechIdName}" at index {userTechIdIndex} is missing.`	Add a description to the User Technical Identifier. Verify your changes.
CHARGE-PLAN-38 [page 1268]	`The User Technical Identifier "{userTechIdName}" at index {userTechIdIndex} is not linked to a charge plan item User Technical Identifier Reference.`	Link the User Technical Identifier or remove it. Verify your changes.
CHARGE-PLAN-39 [page 1269]	`The ID of the charge plan item at index {chargePlanItemIndex} is missing.`	Add an ID to the charge plan item. Verify your changes.
CHARGE-PLAN-40 [page 1271]	`The ID "{chargePlanItemId}" of the charge plan item at index {secondIndex} is already used by the charge plan item at index {firstIndex}.`	Change the ID of the charge plan item. Verify your changes.
CHARGE-PLAN-41 [page 1272]	`The operation type of the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is missing or unknown (supported types are debit, credit).`	Add an operation type to the charge plan item or change it to a supported one: debit, credit. Verify your changes.
CHARGE-PLAN-42 [page 1274]	`The relationship type of the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is missing or unknown (supported types are client, partner).`	Add a relationship type to the charge plan item or change it to a supported one: client, partner. Verify your changes.
CHARGE-PLAN-43 [page 1275]	`No charge component is referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex}.`	Add a charge component to the charge plan item. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-44 [page 1277]	`The ID of the master charge component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is missing.`	Add an ID to the master charge component within the charge plan item. Verify your changes.
CHARGE-PLAN-45 [page 1278]	`The ID of the dependent charge component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is missing.`	Add an ID to the dependent charge component within the charge plan item. Verify your changes.
CHARGE-PLAN-46 [page 1280]	`The role of the dependent charge component "{chargeComponentId}" referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is missing or unknown (supported roles are partnerCommission, commission, sponsorship, discount, other).`	Add a role to the dependent charge component within the charge plan item or change it to a supported one: partnerCommission, commission, sponsorship, discount, other. Verify your changes.
CHARGE-PLAN-47 [page 1281]	`The adjustment mode of the dependent charge component "{chargeComponentId}" referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is missing or unknown (supported modes are none, merging, splitting).`	Add an adjustment mode to the dependent charge component within the charge plan item or change it to a supported one: none, merging, splitting. Verify your changes.
CHARGE-PLAN-48 [page 1283]	`TheError while validating the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex}.`	Verify your changes.
CHARGE-PLAN-49 [page 1284]	`The name of the Parameter at index {parameterIndex} is missing.`	Add a name to the Parameter. Verify your changes.
CHARGE-PLAN-50 [page 1286]	`The name "{parameterName}" of the Parameter at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-51 [page 1287]	`The type of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown (supported types are string, number, date).`	Add a type to the Parameter or change it to a supported one: string, number, date. Verify your changes.
CHARGE-PLAN-52 [page 1289]	`The date value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a date value to the Parameter. Verify your changes.
CHARGE-PLAN-53 [page 1290]	`The number value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a number value to the Parameter. Verify your changes.
CHARGE-PLAN-54 [page 1292]	`The string value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a string value to the Parameter. Verify your changes.
CHARGE-PLAN-55 [page 1293]	`The type "{parameterType}" of the Parameter "{parameterName}" at index {parameterIndex} is unsupported (supported types are string, number, date).`	Use a supported type (string, number, date) for the Parameter. Verify your changes.
CHARGE-PLAN-56 [page 1295]	`The name of the Parameter Reference at index {parameterReferenceIndex} is missing.`	Add a name to the Parameter Reference. Verify your changes.
CHARGE-PLAN-57 [page 1297]	`The name "{parameterReferenceName}" of the Parameter Reference at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter Reference. Verify your changes.
CHARGE-PLAN-58 [page 1298]	`The target name of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is missing.`	Add a target name to the Parameter Reference. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-59 [page 1300]	`The Parameter "{targetName}" targeted by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} does not exist.`	Change the target name of the Parameter Reference to an existing one or create a new Parameter in the charge plan with this target name. Verify your changes.
CHARGE-PLAN-60 [page 1301]	`The type of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is missing or unknown (supported types are string, number, date).`	Add a type to the Parameter Reference or change it to a supported one: string, number, date. Verify your changes.
CHARGE-PLAN-61 [page 1303]	`The type "{parameterReferenceType}" of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not compatible with the type "{parameterType}" of the targeted Parameter.`	Link the Parameter Reference to a compatible Parameter. Verify your changes.
CHARGE-PLAN-62 [page 1304]	`The name of the Counter at index {counterIndex} is missing.`	Add a name to the Counter. Verify your changes.
CHARGE-PLAN-63 [page 1306]	`The name "{counterName}" of the Counter at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter. Verify your changes.
CHARGE-PLAN-64 [page 1307]	`The initial value of the Counter "{counterName}" at index {counterIndex} is missing.`	Add an initial value to the Counter. Verify your changes.
CHARGE-PLAN-65 [page 1309]	`The name of the Counter Reference at index {counterReferenceIndex} is missing.`	Add a name to the Counter Reference. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-66 [page 1310]	`The name "{counterName}" of the Counter Reference at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter Reference. Verify your changes.
CHARGE-PLAN-67 [page 1312]	`The target name of the Counter Reference "{counterReferenceName}" at index {counterReferenceIndex} is missing.`	Add a target name to the Counter Reference. Verify your changes.
CHARGE-PLAN-68 [page 1314]	`The Counter "{targetName}" targeted by the Counter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} does not exist.`	Change the target name of the Counter Reference to an existing one or create a new Counter in the charge plan with this target name. Verify your changes.
CHARGE-PLAN-69 [page 1315]	`The name of the Account Assignment Reference at index {accountAssignmentReferenceIndex} is missing.`	Add a name to the Account Assignment Reference. Verify your changes.
CHARGE-PLAN-70 [page 1317]	`The name "{accountAssignmentReferenceName}" of the Account Assignment Reference at index {secondIndex} is already used by the Account Assignment Reference at index {firstIndex}.`	Change the name of the Account Assignment Reference. Verify your changes.
CHARGE-PLAN-71 [page 1318]	`The target name of the Account Assignment Reference "{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex} is missing.`	Add a target name to the Account Assignment Reference. Verify your changes.
CHARGE-PLAN-72 [page 1320]	`The Account Assignment "{targetName}" targeted by the Account Assignment Reference "{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex} does not exist.`	Change the target name of the Account Assignment Reference to an existing one or create a new Account Assignment in the Charge Plan with this target name. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-73 [page 1321]	`The type of the Account Assignment Reference "{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex} is missing or unknown (supported types are prepaid, postpaid).`	Add a type to the Account Assignment Reference or change it to a supported one: prepaid, postpaid. Verify your changes.
CHARGE-PLAN-74 [page 1323]	`The type "{accountAssignmentReferenceType}" of the Account Assignment Reference "{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex} is not compatible with the type "{accountAssignmentType}" of the targeted Account Assignment.`	Link the Account Assignment Reference to a compatible Account Assignment. Verify your changes.
CHARGE-PLAN-75 [page 1325]	`The service name of the User Technical Identifier Reference at index {userTechnicalIdentifierReferenceIndex} is missing.`	Add a service name to the User Technical Identifier Reference. Verify your changes.
CHARGE-PLAN-76 [page 1326]	`The service "{userTechnicalIdentifierReferenceService}" of the User Technical Identifier Reference at index {secondIndex} is already used by the User Technical Identifier Reference at index {firstIndex}.`	Change the service of the User Technical Identifier Reference. Verify your changes.
CHARGE-PLAN-77 [page 1328]	`The target name of the User Technical Identifier Reference "{userTechnicalIdentifierReferenceName}" at index {userTechnicalIdentifierReferenceIndex} is missing.`	Add a target name to the User Technical Identifier Reference. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-78 [page 1329]	`The User Technical Identifier "{targetName}" targeted by the User Technical Identifier Reference "{userTechnicalIdentifierReferenceService}" at index {userTechnicalIdentifierReferenceIndex} does not exist.`	Change the target name of the User Technical Identifier Reference to an existing one or create a new User Technical Identifier in the charge plan with this target name. Verify your changes.
CHARGE-PLAN-79 [page 1331]	`The Charged Item Mapping is missing in the charge plan item.`	Add a Charged Item Mapping to the charge plan item. Verify your changes.
CHARGE-PLAN-80 [page 1332]	`The class of the Charged Item Mapping is missing.`	Add a class to the Charged Item Mapping. Verify your changes.
CHARGE-PLAN-81 [page 1334]	`Error while validating the Charged Item Mapping of class "{citcClass}".`	Verify your changes.
CHARGE-PLAN-82 [page 1335]	`The name of the Charged Item Mapping Entry at index {chargedItemMappingEntryIndex} is missing.`	Add a name to the Charged Item Mapping Entry. Verify your changes.
CHARGE-PLAN-83 [page 1337]	`The name "{chargedItemMappingEntryName}" of the Charged Item Mapping Entry at index {secondIndex} is already used by the Charged Item Mapping Entry at index {firstIndex}.`	Change the name of the Charged Item Mapping Entry. Verify your changes.
CHARGE-PLAN-84 [page 1338]	`The type of the Charged Item Mapping Entry "{chargedItemMappingEntryName}" at index {chargedItemMappingEntryIndex} is missing or unknown (supported types are string, number, date, boolean).`	Add a type to the Charged Item Mapping Entry or change it to a supported one: string, number, date, boolean. Verify your changes.
CHARGE-PLAN-85 [page 1340]	`The tax module of the Tax Parameter Set is missing or unknown (supported modules are vatTax, usTax).`	Add a tax module to the Tax Parameter Set or change it to a supported one: vatTax, usTax. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-86 [page 1341]	`The tax module "{taxParameterSetModule}" of the Tax Parameter Set at index {secondIndex} is already used by the Tax Parameter Set at index {firstIndex}.`	Change the tax module of the Tax Parameter Set. Verify your changes.
CHARGE-PLAN-87 [page 1343]	`Error while validating the Tax Parameter Set with tax module "{taxParameterSetModule}".`	Verify your changes.
CHARGE-PLAN-88 [page 1344]	`The name of the Tax Parameter at index {taxParameterIndex} is missing.`	Add a name to the Tax Parameter. Verify your changes.
CHARGE-PLAN-89 [page 1346]	`The name "{taxParameterName}" of the Tax Parameter at index {secondIndex} is already used by the Tax Parameter at index {firstIndex}.`	Change the name of the Tax Parameter. Verify your changes.
CHARGE-PLAN-90 [page 1347]	`The type of the Tax Parameter "{taxParameterName}" at index {taxParameterIndex} is missing or unknown (supported types are string, number, date).`	Add a type to the Tax Parameter or change it to a supported one: string, number, date. Verify your changes.
CHARGE-PLAN-91 [page 1349]	`Impossible to create the charge plan because its ID {chargePlanId} already exists.`	Change the ID of the charge plan. Verify your changes.
CHARGE-PLAN-92 [page 1350]	`The ID of the charge plan is missing in the delete charge plan operation.`	Add an ID in the operation. Verify your changes.
CHARGE-PLAN-93 [page 1352]	`Impossible to delete the charge plan because its ID {chargePlanId} does not exist.`	Change the ID of the charge plan. Verify your changes.
CHARGE-PLAN-94 [page 1353]	`Error while deleting the charge plan "{chargePlanId}". The charge plan is still activated in one provider contract.`	First delete all provider contract items referencing the charge plan. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-95 [page 1355]	`Impossible to modify the charge plan because its ID {chargePlanId} does not exist.`	Change the ID of the charge plan. Verify your changes.
CHARGE-PLAN-96 [page 1356]	`The Account Assignment at the index {accountAssignmentIndex} is empty.`	Replace it by a valid Account Assignment or remove it. Verify your changes.
CHARGE-PLAN-97 (Revoked) [page 1358]	`The Additional Info at the index {additionalInfoIndex} is empty.`	Replace it by a valid Additional Information item or remove it. Verify your changes.
CHARGE-PLAN-98 [page 1360]	`The Charge Dependency at the index {chargeDependencyIndex} is empty.`	Replace it by a valid Charge Dependency or remove it. Verify your changes.
CHARGE-PLAN-99 [page 1361]	`The masterCode of the Charge Dependency at index {chargeDependencyIndex} is missing.`	Add a masterCode to the Charge Dependency. Verify your changes.
CHARGE-PLAN-100 [page 1363]	`The dependentCode of the Charge Dependency at index {chargeDependencyIndex} is missing.`	Add a dependentCode to the Charge Dependency. Verify your changes.
CHARGE-PLAN-101 [page 1364]	`The Charge Dependency at index {firstIndex} having the masterCode "{masterCode}" and the dependentCode "{dependentCode}" is already used at index {secondIndex}.`	Remove one of the dependencies. Verify your changes.
CHARGE-PLAN-102 [page 1366]	`The masterCode "{masterCode}" of the Charge Dependency at index {chargeDependencyIndex} does not match the ID of an existing Master Charge Component.`	Link the masterCode to the ID of an existing Master Charge Component or remove the Charge Dependency. Verify your changes.
CHARGE-PLAN-103 [page 1367]	`The dependentCode "{dependentCode}" of the Charge Dependency at index {chargeDependencyIndex} does not match the ID of an existing Dependent Charge Component.`	Link the dependentCode to the ID of an existing Dependent Charge Component or remove the Charge Dependency. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-104 [page 1369]	`The Counter at the index {counterIndex} is empty.`	Replace it by a valid Counter or remove it. Verify your changes.
CHARGE-PLAN-105 [page 1370]	`The Visibility "{counterVisibility}" of the Counter "{counterName}" at index {counterIndex} is unsupported (supported visibilities are chargePlan, chargePlanClass).`	Use a supported visibility (chargePlan, chargePlanClass) for the Counter. Verify your changes.
CHARGE-PLAN-106 [page 1372]	`The Parameter at the index {parameterIndex} is empty.`	Replace it by a valid Parameter or remove it. Verify your changes.
CHARGE-PLAN-107 [page 1373]	`The Visibility "{parameterVisibility}" of the Parameter "{parameterName}" at index {parameterIndex} is unsupported (supported visibilities are chargePlan, chargePlanClass).`	Use a supported visibility (chargePlan, chargePlanClass) for the Parameter. Verify your changes.
CHARGE-PLAN-108 [page 1375]	`The User Technical Identifier at the index {userTechnicalIdentifierIndex} is empty.`	Replace it by a valid User Technical Identifier or remove it. Verify your changes.
CHARGE-PLAN-109 [page 1377]	`The charge plan item at the index {chargePlanItemIndex} is empty.`	Replace it by a valid charge plan item or remove it. Verify your changes.
CHARGE-PLAN-110 [page 1378]	`The ID of the charge component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} does not match any Charge Component.`	Set the ID of an existing Charge Component. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-111 [page 1380]	`The ID of the dependent charge component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} and the code "{retrievedChargeComponentCode}" of the Charge Component retrieved do not match.`	Contact the support. Verify your changes.
CHARGE-PLAN-112 [page 1381]	`The dependent charge component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} matches a master Charge Component instead of a dependent one.`	Set an ID matching a dependent Charge Component and not a master Charge Component. Verify your changes.
CHARGE-PLAN-113 [page 1383]	`The owner of the charge plan and the owner of the Charge Component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} do not match. The owner of the charge plan is "{chargePlanOwner}". The owner of the Charge Component is "{chargeComponentOwner}".`	Set an ID of dependent Charge Component that has the same owner as the charge plan. Verify your changes.
CHARGE-PLAN-114 [page 1384]	`The Charging Mapping "{chargingMappingName}" of the referred Charge Component "{chargeComponentId}" is not declared in the charge plan.`	Link the Charging Mapping in the charge plan. Verify your changes.
CHARGE-PLAN-115 [page 1386]	`The ID of the master charge component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} and the code "{retrievedChargeComponentCode}" of the Charge Component retrieved do not match.`	Contact the support. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-116 [page 1387]	`The master charge component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} matches a dependent Charge Component instead of a master one.`	Set an ID matching a master Charge Component and not a dependent Charge Component. Verify your changes.
CHARGE-PLAN-117 [page 1389]	`The owner of the charge plan and the owner of the Charge Component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} do not match. The owner of the charge plan is "{chargePlanOwner}". The owner of the Charge Component is "{chargeComponentOwner}".`	Set an ID of master Charge Component that has the same owner as the charge plan. Verify your changes.
CHARGE-PLAN-118 [page 1391]	`The mandatory filter in the Search charge plan operation is missing.`	Add a filter in the Search charge plan operation. Verify your changes.
CHARGE-PLAN-119 [page 1392]	`An error occurred during the execution of the search operation: {errorMessage}.`	Verify your changes.
CHARGE-PLAN-120 [page 1393]	`The mandatory filter in the Search charge plan Class operation is missing.`	Add a filter in the Search charge plan Class operation. Verify your changes.
CHARGE-PLAN-121 [page 1395]	`An error occurred during the execution of the search operation: {errorMessage}.`	Verify your changes.
CHARGE-PLAN-122 [page 1396]	`Only one charge component (master or dependent) must be declared in the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex}.`	Remove the extra charge component(s) from the charge plan item. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-123 [page 1398]	`The Account Assignment Reference "{accountAssignmentRefName}" at index {accountAssignmentRefIndex} does not exist in the Charging Mapping of the referred Charge Component "{chargeComponentId}".`	Remove this Account Assignment Reference. Verify your changes.
CHARGE-PLAN-124 [page 1399]	`The Charging Mapping "{chargingMappingName}" of the referred Charge Component "{chargeComponentId}" is not typed (this is mandatory).`	Set a type to the Charging Mapping in the Charge Component or choose another Charge Component with a typed Charging Mapping. Verify your changes.
CHARGE-PLAN-125 [page 1401]	`The type "{accountAssignmentRefType}" of the Account Assignment Reference "{accountAssignmentRefName}" at index {accountAssignmentRefIndex} is incompatible with the type of the Charging Mapping "{chargingMappingName}" in the referred Charge Component "{chargeComponentId}".`	Change the type of the Account Assignment Reference to the type of the Charging Mapping in the Charge Component. Verify your changes.
CHARGE-PLAN-126 [page 1402]	`The Counter "{counterName}" at index {counterIndex} does not exist in the referred Charge Component "{chargeComponentId}".`	Remove this Counter. Verify your changes.
CHARGE-PLAN-127 [page 1404]	`The Counter Reference "{counterRefName}" at index {counterRefIndex} does not exist in the referred Charge Component "{chargeComponentId}".`	Remove this Counter Reference. Verify your changes.
CHARGE-PLAN-128 [page 1406]	`The Parameter "{parameterName}" at index {parameterIndex} does not exist in the referred Charge Component "{chargeComponentId}".`	Remove this Parameter. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-129 [page 1407]	`The Parameter Reference "{parameterRefName}" at index {parameterRefIndex} does not exist in the referred Charge Component "{chargeComponentId}".`	Remove this Parameter Reference. Verify your changes.
CHARGE-PLAN-130 [page 1409]	`User Technical Identifiers are declared although the referred Charge Component "{chargeComponentId}" does not have usage rates.`	Remove User Technical Identifiers. Verify your changes.
CHARGE-PLAN-120 [page 1393]	`The mandatory filter in the Search charge plan Class operation is missing.`	Add a filter in the Search charge plan Class operation. Verify your changes.
CHARGE-PLAN-121 [page 1395]	`An error occurred during the execution of the search operation: {errorMessage}.`	Verify your changes.
CHARGE-PLAN-122 [page 1396]	`Only one charge component (master or dependent) must be declared in the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex}.`	Remove the extra charge component(s) from the charge plan item. Verify your changes.
CHARGE-PLAN-123 [page 1398]	`The Account Assignment Reference "{accountAssignmentRefName}" at index {accountAssignmentRefIndex} does not exist in the Charging Mapping of the referred Charge Component "{chargeComponentId}".`	Remove this Account Assignment Reference. Verify your changes.
CHARGE-PLAN-124 [page 1399]	`The Charging Mapping "{chargingMappingName}" of the referred Charge Component "{chargeComponentId}" is not typed (this is mandatory).`	Set a type to the Charging Mapping in the Charge Component or choose another Charge Component with a typed Charging Mapping. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-125 [page 1401]	`The type "{accountAssignmentRefType}" of the Account Assignment Reference "{accountAssignmentRefName}" at index {accountAssignmentRefIndex} is incompatible with the type of the Charging Mapping "{chargingMappingName}" in the referred Charge Component "{chargeComponentId}".`	Change the type of the Account Assignment Reference to the type of the Charging Mapping in the Charge Component. Verify your changes.
CHARGE-PLAN-126 [page 1402]	`The Counter "{counterName}" at index {counterIndex} does not exist in the referred Charge Component "{chargeComponentId}".`	Remove this Counter. Verify your changes.
CHARGE-PLAN-127 [page 1404]	`The Counter Reference "{counterRefName}" at index {counterRefIndex} does not exist in the referred Charge Component "{chargeComponentId}".`	Remove this Counter Reference. Verify your changes.
CHARGE-PLAN-128 [page 1406]	`The Parameter "{parameterName}" at index {parameterIndex} does not exist in the referred Charge Component "{chargeComponentId}".`	Remove this Parameter. Verify your changes.
CHARGE-PLAN-129 [page 1407]	`The Parameter Reference "{parameterRefName}" at index {parameterRefIndex} does not exist in the referred Charge Component "{chargeComponentId}".`	Remove this Parameter Reference. Verify your changes.
CHARGE-PLAN-130 [page 1409]	`User Technical Identifiers are declared although the referred Charge Component "{chargeComponentId}" does not have usage rates.`	Remove User Technical Identifiers. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-131 [page 1410]	`User Technical Identifiers are not declared although the referred Master Charge Component "{chargeComponentId}" has usage rates.`	Add User Technical Identifiers. Verify your changes.
CHARGE-PLAN-132 [page 1412]	`The charge plan is missing.`	Add a charge plan to the modify operation. Verify your changes.
CHARGE-PLAN-133 [page 1413]	`The charge plan with the ID {chargePlanId} does not exist.`	Change the ID of the charge plan to an existing one or create the charge plan first. Verify your changes.
CHARGE-PLAN-134 [page 1415]	`Impossible to modify the charge plan because the specified owner {specifiedOwner} does not correspond to the owner {realOwner} existing in the charge plan.`	Change the owner to the owner of the charge plan or create a new charge plan for the specified owner. Verify your changes.
CHARGE-PLAN-135 [page 1416]	`The Charge Component "{chargeComponentId}" referred by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is unknown.`	Change the chargeComponentId to an existing Charge Component identifier. Verify your changes.
CHARGE-PLAN-136 [page 1418]	`Internal server error. Impossible to modify the charge plan because the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} refers to an unknown Charge Component.`	Contact the support. Verify your changes.
CHARGE-PLAN-137 [page 1420]	`User Technical Identifiers are declared although the referred Charge Component "{chargeComponentId}" is dependent.`	Remove User Technical Identifiers. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-138 [page 1421]	`The charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is already referencing the Charge Component "{originalChargeComponentId}" and cannot reference the Charge Component "{newChargeComponentId}" at the same time.`	Use the Charge Component already referenced by the charge plan item or create a new charge plan item. Verify your changes.
CHARGE-PLAN-139 [page 1423]	`Internal server error. Impossible to modify the charge plan because the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} refers to an incompatible Charge Component "{chargeComponentId}". To be compatible, a Charge Component must have an Internal Reference Dictionary with typed references.`	Verify your changes.
CHARGE-PLAN-140 [page 1424]	`charge plan "{chargePlanId}" must at least declare one charge plan item.`	Add at least one charge plan item. Verify your changes.
CHARGE-PLAN-141 [page 1426]	`The mandatory modification date is missing in the modify charge plan operation.`	Add a modification date. Verify your changes.
CHARGE-PLAN-142 [page 1427]	`The status of the charge plan "{chargePlanId}" is missing.`	Add a status to the charge plan. Verify your changes.
CHARGE-PLAN-143 [page 1428]	`The status of new charge plan "{chargePlanId}" must be open.`	Set the status of this new charge plan to open. Verify your changes.
CHARGE-PLAN-144 [page 1430]	`The status of already released charge plan "{chargePlanId}" cannot be set back to open.`	Set the status of this new charge plan to released or obsolete. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-145 [page 1431]	`The status of already obsolete charge plan "{chargePlanId}" cannot be set back to open.`	Set the status of this new charge plan to released or obsolete. Verify your changes.
CHARGE-PLAN-146 [page 1433]	`The status of already obsolete charge plan "{chargePlanId}" cannot be set back to released.`	Set the status of this new charge plan to released or obsolete. Verify your changes.
CHARGE-PLAN-147 [page 1434]	`The parameter "{parameterName}" at index {parameterIndex} has a date type which is incompatible with the charge component parameter whose type is {chargeComponentParameterType}.`	Change the parameter type to the correct one. Verify your changes.
CHARGE-PLAN-148 [page 1436]	`The parameter "{parameterName}" at index {parameterIndex} has a number type which is incompatible with the charge component parameter whose type is {chargeComponentParameterType}.`	Change the parameter type to the correct one. Verify your changes.
CHARGE-PLAN-149 [page 1438]	`The parameter "{parameterName}" at index {parameterIndex} has a string type which is incompatible with the charge component parameter whose type is {chargeComponentParameterType}.`	Change the parameter type to the correct one. Verify your changes.
CHARGE-PLAN-150 [page 1439]	`The parameter reference "{parameterRefName}" at index {parameterRefIndex} has a date type which is incompatible with the charge component parameter whose type is {chargeComponentParameterType}.`	Change the parameter reference type to the correct one. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-151 [page 1441]	`The parameter reference "{parameterRefName}" at index {parameterRefIndex} has a number type which is incompatible with the charge component parameter whose type is {chargeComponentParameterType} .`	Change the parameter reference type to the correct one. Verify your changes.
CHARGE-PLAN-152 [page 1442]	`The parameter reference "{parameterRefName}" at index {parameterRefIndex} has a string type which is incompatible with the charge component parameter whose type is {chargeComponentParameterType} .`	Change the parameter reference type to the correct one. Verify your changes.
CHARGE-PLAN-153 [page 1444]	`The type "{parameterRefType}" of the Parameter Reference "{parameterRefName}" at index {parameterRefIndex} is unsupported (supported types are string, number, date).`	Use a supported type (string, number, date) for the Parameter. Verify your changes.
CHARGE-PLAN-154 [page 1446]	`The currency value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a currency value to the Parameter. Verify your changes.
CHARGE-PLAN-155 [page 1447]	`The currency Parameter "{parameterName}" at index {parameterIndex} is unnecessary because the referred Charge Component "{chargeComponentId}" has a fixed currency.`	Remove this Parameter. Verify your changes.
CHARGE-PLAN-156 [page 1449]	`The currency Parameter "{parameterName}" at index {secondIndex} is unnecessary because another one is already present in Parameter or Parameter Reference list.`	Remove this Parameter. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-157 [page 1450]	`The currency Parameter value "{parameterValue}" at index {parameterIndex} is unknown by the SAP Convergent Charging system.`	Find a valid currency value using `exportCurrencies` operation. Verify your changes.
CHARGE-PLAN-158 [page 1452]	`The currency value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a currency value to the Parameter. Verify your changes.
CHARGE-PLAN-159 [page 1453]	`A currency must be defined in the charge plan item "{chargePlanItemId}" because the referred charge Component "{chargeComponentId}" is multiCurrencies.`	Add a currency Parameter or Parameter Reference to the charge plan item. Verify your changes.
CHARGE-PLAN-160 [page 1455]	`The currency of the Dependent Charge "{dependentChargeId}" ({dependentCurrency}) must be the same as the Master Charge "{masterChargeComponentId}" ({masterCurrency}) because the adjustment mode of the dependent is merging or splitting.`	Change the adjustment mode or remove the dependency. Verify your changes.
CHARGE-PLAN-161 [page 1456]	`The Master charge plan item "{masterChargePlanItemId}" and the Dependent charge plan item "{dependentChargePlanItemId}" must define their currency at the same level and with the same value because the adjustment mode of the dependent is merging or splitting.`	Define the both charges currency at the charge plan item level and with the same value. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-162 [page 1458]	The Master charge plan item "{masterChargePlanItemId}" refers to the charge plan Currency parameter "{masterChargePlanCurrencyParam}" and the Dependent charge plan item "{dependentChargePlanItemId}" refers to the Charge Plan Currency parameter "{dependentChargePlanCurrencyParam}", but they must both refer to the same parameter because the adjustment mode of the dependent is merging or splitting.	Make both charge plan items currency parameter refer to the same charge plan currency parameter. Verify your changes.
CHARGE-PLAN-163 [page 1460]	The master Charge Component "{masterChargeComponentId}" is multiCurencies and the Dependent Charge Component "{dependentChargeComponentId}" is monoCurrency, but this case is not supported because the adjustment mode of the dependent is merging or splitting.	Change the adjustment mode or remove the dependency. Verify your changes.
CHARGE-PLAN-164 [page 1461]	The master Charge Component "{masterChargeComponentId}" is monoCurencies and the Dependent Charge Component "{dependentChargeComponentId}" is multiCurrency, but only Charge Plan Item currency definition is supported because the adjustment mode of the dependent is merging or splitting.	Change the adjustment mode or remove the dependency. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-165 [page 1463]	`The master charge plan item "{masterChargePlanItemId}" is defined with the currency "{masterChargeCurrency}" and the Dependent charge plan item "{dependentChargePlanItemId}" is defined with the currency "{dependentChargeCurrency}" but they must have the same currency because the adjustment mode of the dependent is merging or splitting.`	Change the adjustment mode or remove the dependency. Verify your changes.
CHARGE-PLAN-166 [page 1464]	`The service "{aUserTechnicalIdentifierReference}" of the User Technical Identifier Reference is already used by another charge plan item for the User Technical Identifier "{userTechnicalIdentifierTargetName}".`	Change the service of the User Technical Identifier Reference or the target name. Verify your changes.
CHARGE-PLAN-167 [page 1466]	`The counter name "{counterName}" at index {counterIndex} is unknown to the counter names dictionary whereas it is visible to the external system.`	Add the counter name to the counter names dictionary or change the counter name to a known one. Verify your changes.
CHARGE-PLAN-168 [page 1468]	`The service name "{serviceName}" of the User Technical Identifier Reference at index {userTechnicalIdentifierReferenceIndex} is missing is not ASCII. Invalid characters are "{invalidCharacters}".`	Replace the invalid characters of service name with ASCII characters. Verify your changes.
CHARGE-PLAN-169 [page 1469]	`The service name "{serviceName}" of the User Technical Identifier Reference at index {userTechnicalIdentifierReferenceIndex} has more than 128 characters.`	Shorten the service name to 128 ASCII characters. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-170 [page 1471]	`The parameter additional information "{additionalInformationName}" at index {additionalInformationIndex} is unknown.`	Remove this additional information or replace it with a known one. Verify your changes.
CHARGE-PLAN-171 [page 1472]	`The data type of the parameter is not defined.`	Add this additional information or remove all additional informations. Verify your changes.
CHARGE-PLAN-172 [page 1474]	`The parameter is a mapping table ID but no mapping table class is defined.`	Add the mapping table class additional information. Verify your changes.
CHARGE-PLAN-173 [page 1475]	`The parameter is a mapping table key and could not be linked to a mapping table class.`	Remove the mapping table class additional information. Verify your changes.
CHARGE-PLAN-174 [page 1476]	`The parameter cannot declare additional informations without a data type.`	Add a data type additional information or remove all additional informations. Verify your changes.
CHARGE-PLAN-175 [page 1478]	`Error while validating the Parameter "{parameterName}" at index {parameterIndex}.`	Verify your changes.
CHARGE-PLAN-176 [page 1479]	`The mapping table ID "{mappingTableIdName}" is not declared whereas it is used in the charge component.`	Add the corresponding mapping table ID parameter. Verify your changes.
CHARGE-PLAN-177 [page 1481]	`The mapping table key "{mappingTableKeyName}" of type "{mappingTableKeyType}" is not declared whereas it is used in the charge component.`	Add the corresponding mapping table ID parameter. Verify your changes.
CHARGE-PLAN-178 [page 1482]	`Error while validating the Parameter "{parameterName}" at index {parameterIndex}.`	Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-179 [page 1484]	`Error while validating the Parameter Reference "{parameterName}" at index {parameterIndex}.`	Verify your changes.
CHARGE-PLAN-180 [page 1485]	`The charge plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as a mapping table ID.`	Declare the mapping table ID data type and the mapping table class additional informations in the charge plan Parameter. Verify your changes.
CHARGE-PLAN-181 [page 1487]	`The charge plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declare an incompatible mapping table class "{cpParameterMappingTableClass}" while the Parameter Reference is of class "{parameterReferenceMappingTableClass}".`	Declare the mapping table ID data type and the mapping table class additional informations in the charge plan Parameter. Verify your changes.
CHARGE-PLAN-182 [page 1489]	`The charge plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as a mapping table key.`	Declare the mapping table key data type additional information in the charge plan Parameter. Verify your changes.
CHARGE-PLAN-183 [page 1490]	`The Parameter is declared as a mapping table ID while it does not exist in the Charge Component.`	Remove the mapping table ID data type additional information from the Parameter. Verify your changes.
CHARGE-PLAN-184 [page 1492]	`The Parameter is declared as a mapping table ID but it does not have a STRING type.`	Declare the parameter as a STRING. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-185 [page 1493]	`The mapping table class "{parameterMappingTableClass}" declared in the Parameter is incompatible with the one declared in the Charge Component "{chargeComponentMappingTableClass}".`	Declare the right mapping table class. Verify your changes.
CHARGE-PLAN-186 [page 1495]	`The Parameter is declared as a mapping table key while it does not exist in the Charge Component.`	Remove the mapping table key data type additional information from the Parameter. Verify your changes.
CHARGE-PLAN-187 [page 1496]	`The Parameter is declared with a mapping table key but has a wrong type "{parameterType}" while it should be "{chargeComponentType}".`	Declare the right type for the parameter. Verify your changes.
CHARGE-PLAN-188 [page 1498]	`The code of the charged item class ({chargedItemClassCode}) referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} does not match any Charged Item Class.`	Set the ID of an existing Charged Item Class. Verify your changes.
CHARGE-PLAN-189 [page 1499]	`The code of the charged item class ({chargedItemClassCode}) referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} does not match any Charged Item Class.`	Set the ID of an existing Charged Item Class. Verify your changes.
CHARGE-PLAN-190 [page 1501]	`Internal server error. Impossible to modify the charge plan because the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} refers to an unknown Charged Item Class.`	Contact the support. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-191 [page 1502]	`The code of the charged item class ({chargedItemClassCode}) referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} does not match any Charged Item Class.`	Set the ID of an existing Charged Item Class. Verify your changes.
CHARGE-PLAN-192 [page 1504]	`The description of the charge plan "{chargePlanId}" cannot be modified because the charge plan has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-193 [page 1506]	`The additional info "{additionalInformationName}" cannot be removed because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-194 [page 1507]	`The additional info "{additionalInformationName}" cannot be added because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-195 [page 1509]	`The description of the additional info "{additionalInformationName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-196 [page 1510]	`The type of the additional info "{additionalInformationName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-198 [page 1512]	`The date value of the additional info "{additionalInformationName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-199 [page 1513]	`The number value of the additional info "{additionalInformationName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-200 [page 1515]	`The string value of the additional info "{additionalInformationName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-201 [page 1516]	`The counter "{counterName}" cannot be removed because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-202 [page 1518]	`The counter "{counterName}" cannot be added because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-203 [page 1519]	`The description of the counter "{counterName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-204 [page 1521]	`The initial value of the counter "{counterName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-205 [page 1522]	`The account assignment "{accountAssignmentName}" cannot be removed because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-206 [page 1524]	`The account assignment "{accountAssignmentName}" cannot be added because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-207 [page 1525]	`The description of the account assignment "{accountAssignmentName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-208 [page 1527]	`The type of the account assignment "{accountAssignmentName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-209 [page 1528]	`The user technical identifier "{userTechIdName}" cannot be removed because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-210 [page 1530]	`The user technical identifier "{userTechIdName}" cannot be added because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-211 [page 1531]	`The description of the user technical identifier "{userTechIdName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-212 [page 1533]	`The charge plan item "{chargePlanItemId}" cannot be removed because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-213 [page 1534]	`The charge plan item "{chargePlanItemId}" cannot be added because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-214 [page 1536]	`The master charge component of the charge plan item "{chargePlanItemId}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-215 [page 1537]	`The parameter "{parameterName}" cannot be removed because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-216 [page 1539]	`The parameter "{parameterName}" cannot be added because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-217 [page 1540]	`The description of the parameter "{parameterName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-218 [page 1542]	`The type of the parameter "{parameterName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-219 [page 1543]	`The currency value of the parameter "{parameterName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-220 [page 1545]	`The date value of the parameter "{parameterName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-221 [page 1546]	`The number value of the parameter "{parameterName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-222 [page 1548]	`The string value of the parameter "{parameterName}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-223 [page 1549]	`The relationship type of the charge plan item "{chargePlanItemId}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-224 [page 1551]	`The operation type of the charge plan item "{chargePlanItemId}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-225 [page 1552]	`The dependent charge component of the charge plan item "{chargePlanItemId}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-226 [page 1554]	`The account assignment "{accountAssignmentName}" of the charge plan item "{chargePlanItemId}" cannot be added because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-227 [page 1555]	`The account assignment "{accountAssignmentName}" of the charge plan item "{chargePlanItemId}" cannot be removed because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-228 [page 1557]	`The user technical identifier "{userTechIdService}" of the charge plan item "{chargePlanItemId}" cannot be added because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-229 [page 1558]	`The user technical identifier "{userTechIdService}" of the charge plan item "{chargePlanItemId}" cannot be removed because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-230 (Revoked) [page 1560]	`The charged item mapping of the charge plan item "{chargePlanItemId}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-231 [page 1562]	`The account assignment "{accountAssignmentName}" of the charge plan item "{chargePlanItemId}" cannot be modified because the charge plan "{chargePlanId}" has been released.`	Create a new charge plan. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-232 [page 1563]	`The charge plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as an invoice text.`	Declare the invoice text data type additional information in the charge plan Parameter. Verify your changes.
CHARGE-PLAN-233 [page 1565]	`The charge plan Parameter "{parameterName}" at index {parameterIndex} points to an unknown mapping table "{parameterValue}".`	Change the value to a known mapping table. Verify your changes.
CHARGE-PLAN-234 [page 1566]	`The charge component Parameter "{parameterName}" points to an unknown mapping table "{parameterValue}".`	Change the value to a known mapping table. Verify your changes.
CHARGE-PLAN-235 [page 1568]	`The charge plan item Parameter "{parameterName}" at index {parameterIndex} points to an unknown mapping table "{parameterValue}".`	Change the value to a known mapping table. Verify your changes.
CHARGE-PLAN-236 [page 1569]	`The default value and property name of the Tax Parameter "{taxParameterName}" at index {taxParameterIndex} cannot be null.`	Add a default value or a property name to the Tax Parameter. Verify your changes.
CHARGE-PLAN-237 [page 1571]	`The default value of the Tax Parameter "{taxParameterName}" at index {taxParameterIndex} is empty.`	Add a default value to the Tax Parameter. Verify your changes.
CHARGE-PLAN-238 [page 1572]	`The property name of the Tax Parameter "{taxParameterName}" at index {taxParameterIndex} is empty.`	Add a property name to the Tax Parameter. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-239 [page 1574]	`The VAT rule "{vatRuleId}" referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} does not match any known VAT rule.`	Set the ID of an existing VAT rule. Verify your changes.
CHARGE-PLAN-240 [page 1575]	`The VAT rule referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} must not be set as a property, but as a fixed value matching an existing VAT rule ID.`	Set the ID of an existing VAT rule. Verify your changes.
CHARGE-PLAN-241 [page 1577]	`The tax module of the Tax Parameter Set has changed (the tax module cannot be changed).`	Set the original tax module of the Tax Parameter Set. Verify your changes.
CHARGE-PLAN-242 [page 1578]	`The parameter is a range table ID but no range table class is defined.`	Add the range table class additional information. Verify your changes.
CHARGE-PLAN-243 [page 1580]	`The range table ID "{rangeTableIdName}" is not declared whereas it is used in the charge component.`	Add the corresponding range table ID parameter. Verify your changes.
CHARGE-PLAN-244 [page 1581]	`The charge plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as a range table ID.`	Declare the range table ID data type and the range table class additional informations in the charge plan Parameter. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-245 [page 1583]	`The charge plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declare an incompatible range table class "{cpParameterRangeTableClass}" while the Parameter Reference is of class "{parameterReferenceRangeTableClass}".`	Declare the range table ID data type and the range table class additional informations in the charge plan Parameter. Verify your changes.
CHARGE-PLAN-246 [page 1585]	`The Parameter is declared as a range table ID while it does not exist in the Charge Component.`	Remove the range table ID data type additional information from the Parameter. Verify your changes.
CHARGE-PLAN-247 [page 1586]	`The Parameter is declared as a range table ID but it does not have a STRING type.`	Declare the parameter as a STRING. Verify your changes.
CHARGE-PLAN-248 [page 1588]	`The range table class "{parameterRangeTableClass}" declared in the Parameter is incompatible with the one declared in the Charge Component "{chargeComponentRangeTableClass}".`	Declare the right range table class. Verify your changes.
CHARGE-PLAN-249 [page 1589]	`The charge plan Parameter "{parameterName}" at index {parameterIndex} points to an unknown range table "{parameterValue}".`	Change the value to a known range table. Verify your changes.
CHARGE-PLAN-250 [page 1591]	`The charge component Parameter "{parameterName}" points to an unknown range table "{parameterValue}".`	Change the value to a known range table. Verify your changes.
CHARGE-PLAN-251 [page 1592]	`The charge plan item Parameter "{parameterName}" at index {parameterIndex} points to an unknown range table "{parameterValue}".`	Change the value to a known range table. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-252 [page 1594]	`The tax parameters of the dependent charge plan item "{dependentChargePlanItemId}" are different from the tax parameters of the master charge plan item "{masterChargePlanItemId}".`	Set axactlly the same tax parameters in both the master and dependent charge plan items. Verify your changes.
CHARGE-PLAN-253 [page 1595]	`The code of the Charged Item Aggregation Policy ({chargedItemAggregationPolicy Code}) referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} does not exist.`	Modify the Charge Plan Item with a code of an existing Charged Item Aggregation Policy. Verify your changes.
CHARGE-PLAN-254 [page 1597]	`The "{chargedItemAggregationPolicy Owner}" owner of the Charged Item Aggregation Policy is different from the "{chargePlanItemOwner}" of the Charge Plan.`	Specify a Charged Item Aggregation Policy which is owned by the same owner than the Charge Plan. Verify your changes.
CHARGE-PLAN-255 [page 1599]	`The "{chargedItemAggregationPolicy Code}" Charged Item Aggregation Policy and the "{chargePlanItemId}" Charge Plan Item must have same the "{chargedItemClassCode}" Charged Item Class.`	Select a Charged Item Aggregation Policy whose Charged Item Class corresponds to the Charged Item Class of the Charge Plan Item. Verify your changes.
CHARGE-PLAN-256 [page 1600]	`The name "{chargedItemMappingEntryName}" of the Charged Item Mapping Entry at index {index} does not exist in the Charged Item Class "{chargedItemClassCode}" of the Charge Plan Item "{chargePlanItemId}".`	Change the name of the Charged Item Mapping Entry or remove the entry. Verify your changes.
CHARGE-PLAN-257 [page 1602]	`The initial value of the Counter "{counterName}" at index {counterIndex} is forbidden.`	Remove the initial value of the Counter. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-258 (Revoked) [page 1603]	`The code of the charged item class ({chargedItemClassCode}) referred to by the charge plan item "{chargePlanItemId}" cannot be changed to ({newChargedItemClassCode}).`	Set the ID of the original charged item class. Verify your changes.
CHARGE-PLAN-259 [page 1605]	`Parameter "{parameterName}" at index {parameterIndex} points to the range table "{parameterValue}" which is not an instance of the previously defined range table class "{rangeTableClass}".`	Change the value to a known range table. Verify your changes.
CHARGE-PLAN-260 [page 1607]	`Error while validating the Response Charged Item Mapping Entry at index {chargedItemMappingEntryIndex} .`	Verify your changes.
CHARGE-PLAN-261 [page 1608]	`The Charged Item Class of the Response Charged Item Mapping is missing.`	Set the code of a Charged Item Class in the Response Charged Item Mapping. Verify your changes.
CHARGE-PLAN-262 [page 1610]	`The code of the Charged Item Class "{chargedItemClassCode}" referenced by the Response Charged Item Mapping does not match any existing Charged Item Class.`	Set the code of an existing Charged Item Class. Verify your changes.
CHARGE-PLAN-263 [page 1611]	`The owner of the Charged Item Class of the Response Charged Item Mapping does not match with the owner of the Charge Plan. The owner of the Charged Item Class is "{chargedItemClassOwner}". The owner of the Charge Plan is "{allowancePlanOwner}".`	Set the code of a Charged Item Class that has the same owner as the Charge Plan. Verify your changes.
CHARGE-PLAN-264 [page 1613]	`The name of the Charged Item Mapping Entry is missing.`	Set the name of the Charged Item Mapping Entry. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-265 [page 1614]	`The name "{chargedItemMappingEntryName}" of the Charged Item Mapping Entry is already used by the Charged Item Mapping Entry at index {firstOccurrenceIndex}.`	Change the name of the Charged Item Mapping Entry. Verify your changes.
CHARGE-PLAN-266 [page 1616]	`The type of the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is missing or unknown (the supported types are string, number, date, boolean).`	Add a type to the Charged Item Mapping Entry or change it into a supported one: string, number, date, boolean. Verify your changes.
CHARGE-PLAN-267 [page 1617]	`The Response Charged Item Mapping contains the entry "{chargedItemMappingEntryName}". This entry does not exist in the Charged Item Class "{chargedItemClassCode}".`	Remove the entry from the Response Charged Item Mapping or replace it by an existing property of the Charged Item Class. Verify your changes.
CHARGE-PLAN-269 [page 1619]	`The Response Charged Item Mapping contains the entry "{chargedItemMappingEntryName}" with the type "{chargedItemMappingEntryType}". This type is not compatible with the one defined in the Charged Item Class: "{chargedItemClassFieldType}".`	Change the type of the Charged Item Mapping Entry. Verify your changes.
CHARGE-PLAN-270 [page 1620]	`The value of the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is not set.`	Set either a value or a property name in the Charged Item Mapping Entry. Verify your changes.
CHARGE-PLAN-271 [page 1622]	`The property "{propertyName}" specified in the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is invalid.`	Set the name of a valid property. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-272 [page 1623]	`The type "{propertyType}" of the property "{propertyName}" specified in the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is invalid. The expected type is: "{chargedItemMappingEntryType}".`	Change the type of the Charged Item Mapping Entry or set another property with the expected type. Verify your changes.
CHARGE-PLAN-273 [page 1625]	`The property "{propertyName}" specified in the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is not allowed in a Charge Plan.`	Set the name of a property allowed in Charge Plans. Verify your changes.
CHARGE-PLAN-274 [page 1627]	`The Response Charged Item Mapping does not contain the entry "{missingChargedItemMappingEntryName}". This entry has no value or the value is not applicable in this context in the Charged Item Class "{chargedItemClassName}".`	Add the missing entry in the Charged Item Mapping. Verify your changes.
CHARGE-PLAN-275 [page 1628]	`The service name "{serviceName}" of the User Technical Identifier Reference at index {userTechnicalIdentifierReferenceIndex} is reserved for internal use.`	Change the service name to a value that is not reserved for internal use. Verify your changes.
CHARGE-PLAN-276 [page 1630]	`The reporting scope "session" cannot be used in a dependent charge plan item.`	Remove the reporting scope "session" from the charge plan item. Verify your changes.
CHARGE-PLAN-277 [page 1631]	`The currency Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not necessary because the related Charge Component "{chargeComponentId}" has a fixed currency.`	Remove this Parameter Reference. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-278 [page 1633]	`The currency Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not necessary because the currency is already specified in the list of Parameters or Parameter References.`	Remove this Parameter Reference. Verify your changes.
CHARGE-PLAN-279 [page 1634]	`The currency Parameter value "{parameterValue}" at index {parameterIndex} is unknown by the SAP Convergent Charging system.`	Specify a valid currency value in the Parameter. Verify your changes.
CHARGE-PLAN-280 [page 1636]	`The parameter of the charge plan item cannot reference the mapping table "{parameterValue}" because this mapping table has an agreement ID.`	Select a mapping table without agreement ID. Verify your changes.
CHARGE-PLAN-281 [page 1637]	`The parameter "{parameterName}" of the charge plan cannot reference the mapping table "{parameterValue}" because this mapping table has an agreement ID.`	Select a mapping table without agreement ID. Verify your changes.
CHARGE-PLAN-282 [page 1639]	`The parameter of the charge plan item cannot reference the range table "{parameterValue}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.
CHARGE-PLAN-283 [page 1640]	`The parameter "{parameterName}" of the charge plan cannot reference the range table "{parameterValue}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.

Error Code	Message	Action
CHARGE-PLAN-284 [page 1642]	`The type of the account assignment "{accountAssignmentName}" at index {accountAssignmentIndex} must not be prepaid because the Prepaid Accounts Management feature is disabled.`	Remove the account assignment. Verify your changes.
CHARGE-PLAN-285 [page 1643]	`The property "{propertyName}" specified in the charged item mapping entry "{chargedItemMappingEntryName}" is invalid because the Prepaid Accounts Management feature is disabled.`	Select a valid property. Verify your changes.
CHARGE-PLAN-286 [page 1645]	`You cannot set ManagedByCockpit to true in charge plan "{chargePlanId}".`	Create a new charge plan. Verify your changes.
CHARGE-PLAN-287 [page 1646]	`The charge component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} has the flag ManagedByCockpit set to "{isChargeComponentCockpitCompatible}" whereas the charge plan has the same flag set to "{isChargePlanCockpitCompatible}".`	Add charge components where ManagedByCockpit has the same value as the charge plan. Verify your changes.
CHARGE-PLAN-288 [page 1648]	`The charge component referenced by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is already referenced by the charge plan "referencingChargePlanId".`	Specify a charge component which is not already referenced by a charge plan item of another charge plan. Verify your changes.
CHARGE-PLAN-289 [page 1650]	`The parameter "{parameterName}" at index "{parameterIndex}" must be modifiable due to its charge plan visibility.`	Change the visibility level of the parameter. Save your changes.

Error Code	Message	Action
CHARGE-PLAN-290 [page 1651]	`The parameter "{parameterName}" at index "{parameterIndex}" must be modifiable because it has a value and a charge plan class visibility.`	Change the visibility level of the parameter. Save your changes.
CHARGE-PLAN-291 [page 1653]	`A charge plan managed by Cockpit cannot be converted to a charge plan managed by Core Tool because it references Pricing Functions.`	Use Cockpit user interface to edit the charge plan.
CHARGING-PLAN-1 [page 1654]	`Rate operation failed for usage rate "{usageRateName}".`	Fix the usage rate component, or one of its children. Verify your changes.
CHARGING-PLAN-2 [page 1655]	`Rate operation failed for recurring rate "{recurringRateName}".`	Fix the recurring rate component, or one of its children. Verify your changes.
CHARGING-PLAN-3 [page 1657]	`Rate operation failed for oneshot rate "{oneshotRateName}".`	Fix the oneshot rate component, or one of its children. Verify your changes.
CHARGING-PLAN-4 [page 1658]	`Charge operation failed for usage charge "{usageChargeName}".`	Fix the usage charge component, or one of its children. Verify your changes.
CHARGING-PLAN-5 [page 1660]	`Charge operation failed for recurring charge "{recurringChargeName}".`	Fix the recurring charge component, or one of its children. Verify your changes.
CHARGING-PLAN-6 [page 1661]	`Charge operation failed for oneshot charge "{oneshotChargeName}".`	Fix the oneshot charge component, or one of its children. Verify your changes.
CHARGING-PLAN-7 [page 1663]	`Rating failure in price plan "{pricePlanName}".`	Fix the price plan or one of its children. Verify your changes.

Error Code	Message	Action
CHARGING-PLAN-8 [page 1664]	`Rating failure in charge activation "{chargeActivationName}" in charging contract or subscription "{contractName}".`	Fix the price plan or one of its children. Verify your changes.
CHARGING-PLAN-9 [page 1666]	`Invalid delimitation ''{stringDelimitation}'' used for the conversion from type String to type Multi-Valued String in component ''{componentName}''.`	Define a delimitation character of exactly one character long. Verify your changes.
CHARGING-PLAN-10 [page 1667]	`Invalid delimitation ''{stringDelimitation}'' used for the conversion from type String to type Multi-Valued Number in component ''{componentName}''`	The string that you define as delimitation to convert String into Multi-Valued Number must respect the following constraints: • the delimitation string must be exactly one character long • the delimitation string must be different from the decimal separator • the delimitation string must be different from the thousand separator Verify your changes.
CHARGING-PLAN-11 [page 1669]	`Invalid decimal separator ''{decimalSeparator}'' used for the conversion from type String to type Multi-Valued Number in component ''{componentName}''.`	Define a decimal separator of exactly one character long. Verify your changes.
CHARGING-PLAN-12 [page 1671]	`Invalid thousand separator ''{thousandSeparator}'' used for the conversion from type String to type Multi-Valued Number in component ''{componentName}''.`	Define a thousand separator of exactly one character long. Verify your changes.
CHARGING-PLAN-13 [page 1672]	`Invalid conversion from type String to type Multi-Valued Number in component ''{componentName}'', the substring ''{subString}'' from the string ''{wholeString}'' cannot be converted to a number`	The part of the input string to convert must be a number. Verify your changes.

Error Code	Message	Action
CHAR-GING-PLAN-14 [page 1674]	`Invalid conversion from type String to type Multi-Valued Number in component ''{componentName}'', the substring ''{subString}'' from the string ''{wholeString}'' cannot be converted to a number`	The part of the input string to convert must be a number. Verify your changes.
CHAR-GING-PLAN-15 [page 1675]	`Invalid delimitation ''{stringDelimitation}'' used for the conversion from type Multi-Valued String to type String in component ''{componentName}''.`	Define a delimitation character of exactly one character long. Verify your changes.
CHAR-GING-PLAN-16 [page 1677]	`Invalid decimal separator ''{decimalSeparator}'' used for the conversion from type Multi-Valued String to type Multi-Valued Number in component ''{componentName}''.`	Define a decimal separator of exactly on character long. Verify your changes.
CHAR-GING-PLAN-17 [page 1678]	`Invalid thousand separator ''{thousandSeparator}'' used for the conversion from type Multi-Valued String to type Multi-Valued Number in component ''{componentName}''.`	Define a thousand separator of exactly one character long. Verify your changes.
CHAR-GING-PLAN-18 [page 1680]	`Invalid conversion from type Multi-Valued String to type Multi-Valued Number in component ''{componentName}'', the field ''{subString}'' cannot be converted to a number.`	Every field of the Multi-Valued String must be convertible to a number. Verify your changes.
CHAR-GING-PLAN-19 [page 1681]	`Invalid delimitation ''{stringDelimitation}'' used for the conversion from type Multi-Valued Number to type String in component ''{componentName}''.`	Define a delimitation character of exactly one character long. Verify your changes.

Error Code	Message	Action
CHAR-GING-PLAN-20 [page 1683]	`Invalid decimal separator ''{decimalSeparator}'' used for the conversion from type Multi-Valued Number to type String in component ''{componentName}''.`	Define a decimal separator of exactly one character long. Verify your changes.
CHAR-GING-PLAN-21 [page 1684]	`Invalid thousand separator ''{thousandSeparator}'' used for the conversion from type Multi-Valued Number to type String in component ''{componentName}''.`	Define a thousand separator of exactly one character long. Verify your changes.
CHAR-GING-PLAN-22 [page 1686]	`Invalid decimal separator ''{decimalSeparator}'' used for the conversion from type Multi-Valued Number to type Multi-Valued String in component ''{componentName}''.`	Define a decimal separator of exactly one character long. Verify your changes.
CHAR-GING-PLAN-23 [page 1687]	`Invalid thousand separator ''{thousandSeparator}'' used for the conversion from type Multi-Valued Number to type Multi-Valued String in component ''{componentName}''.`	Define a thousand separator of exactly one character long. Verify your changes.
CHAR-GING-PLAN-24 [page 1689]	`Invalid conversion in component ''{componentName}''. The start offset ''{startOffset}'' must be greater than 0. The start offset ''{startOffset}'' must be lower than or equal to the stop offset value ''{stopOffset}'' plus one, and the length ''{stringLength}'' of the input string plus one.`	Change the start offset or the stop offset according to those constraints. Verify your changes.
CHAR-GING-PLAN-25 [page 1691]	`Invalid decimal separator ''{decimalSeparator}'' used for the conversion from type String to type Number in component ''{componentName}''.`	Define a decimal separator of exactly one character long. Verify your changes.

Error Code	Message	Action
CHAR-GING-PLAN-26 [page 1692]	`Invalid thousand separator ''{thousandSeparator}'' used for the conversion from type String to type Number in component ''{componentName}''.`	Define a thousand separator of exactly one character long. Verify your changes.
CHAR-GING-PLAN-27 [page 1694]	`Invalid conversion from type String to type Number in component ''{componentName}'', the string ''{stringToConvert}'' cannot be converted to a number`	Verify your changes.
CHAR-GING-PLAN-28 [page 1695]	`Invalid conversion from type String to type Date in component ''{componentName}'', the string ''{stringToConvert}'' cannot be converted to a date`	Verify your changes.
CHAR-GING-PLAN-29 [page 1697]	`Invalid decimal separator ''{decimalSeparator}'' used for the conversion from type Number in component ''{componentName}''.`	Define a decimal separator of exactly one character long. Verify your changes.
CHAR-GING-PLAN-30 [page 1698]	`Invalid thousand separator ''{thousandSeparator}'' used for the conversion from type Number in component ''{componentName}''.`	Define a thousand separator of exactly one character long. Verify your changes.
CHAR-GING-PLAN-31 [page 1700]	`Invalid conversion from type Date to type String in component ''{componentName}'', the date ''{dateToConvert}'' cannot be converted to a string`	Verify your changes.

Error Code	Message	Action
CHARGING-PLAN-32 [page 1701]	`Invalid conversion from type Multi-Valued String in component ''{componentName}''. The start offset ''{startOffset}'' and the stop offset ''{stopOffset}'' must be greater than 0. The start offset ''{startOffset}'' must be lower than or equals to the stop offset value ''{stopOffset}'' plus one, and the length ''{stringLength}'' of the input sub-string plus one.`	Change the start offset or the stop offset according to those constraints. Verify your changes.
CHARGING-PLAN-33 [page 1703]	`Rating operation failed for Account Event Refill rate component "{accountEventRefillRateName}" .`	Fix the Account Event Refill rate component, or one of its children. Verify your changes.
CHARGING-PLAN-34 [page 1704]	`The date "{toDate}" specified for an activation or a charging operation is too far in the future considering the value of the parameter PERIOD_LIMIT_ACTIVATION ("{periodLimitActivation}") and the current system date.`	In the business operation requests, change the activation date or the consumption date to a date before the period limit. Verify if the value of the parameter PERIOD_LIMIT_ACTIVATION is correct depending on the business requirements. Verify your changes.
CHARGING-PLAN-35 [page 1706]	`The technical configuration of the shared allowances feature is not complete.`	Set a positive value for the following parameters: DISTRIBUTED_COUNTER_RESERVATION_POOL_SIZE, DISTRIBUTED_COUNTER_CLEANUP_POOL_SIZE and DISTRIBUTED_COUNTER_CHECK_POOL_SIZE Verify your changes.
CI-CLASS-1 [page 1707]	`The chargeable item class is missing in the create operation.`	Add a chargeable item class to the create operation. Verify your changes.
CI-CLASS-2 [page 1709]	`The product identifier of the chargeable item class must be null in the create operation.`	Remove the product identifier. Verify your changes.

Error Code	Message	Action
CI-CLASS-3 [page 1710]	`The id of the chargeable item class is missing in the create operation.`	Add an id to the chargeable item class. Verify your changes.
CI-CLASS-4 [page 1712]	`The service provider of the chargeable item class "{chargeableItemClassId}" is missing.`	Add the service provider to the chargeable item class. Verify your changes.
CI-CLASS-5 [page 1713]	`In the chargeable item class "{chargeableItemClassId}", the name of the property at index {propertyIndex} is missing.`	Add a name to the property. Verify your changes.
CI-CLASS-6 [page 1715]	`In the chargeable item class "{chargeableItemClassId}", the name "{counterName}" of the property at index {secondIndex} is already used at index {firstIndex}.`	Change the name of the property. Verify your changes.
CI-CLASS-7 [page 1716]	`Impossible to create the chargeable item class because its id {chargeableItemClassId} already exists.`	Change the ID of the chargeable item class. Verify your changes.
CI-CLASS-8 [page 1718]	`The id of the chargeable item class "{chargeableItemClassId}" and the service provider "{serviceProviderId}" are both provided, but they are mutually exclusive.`	Remove the ID or the service provider from the operation. Verify your changes.
CI-CLASS-9 [page 1719]	`The service provider "{serviceProviderId}" and the product ID "{productId}" of the chargeable item class are both provided, but they are mutually exclusive.`	Remove the product ID. Verify your changes.
CI-CLASS-10 [page 1721]	`The chargeable item class is missing in the modify operation.`	Add a chargeable item class to the modify operation. Verify your changes.

Error Code	Message	Action
CI-CLASS-11 [page 1722]	`The chargeable item class with the id {chargeableItemClassId} in the modify operation does not exist.`	Change the ID of the chargeable item class to an existing one or create the chargeable item class first. Verify your changes.
CI-CLASS-12 [page 1724]	`The chargeable item class with the id {chargeableItemClassId} and product id {productId} does not exist.`	Change the ID of the chargeable item class or the product ID to an existing one or remove the product ID. Verify your changes.
CI-CLASS-13 [page 1725]	`Impossible to modify the chargeable item class because the specified service provider {specifiedServiceProviderId} does not correspond to the service provider {realServiceProviderId} existing in the chargeable item class.`	Change the service provider to the one of the chargeable item class or create a new chargeable item class for the specified service provider. Verify your changes.
CI-CLASS-14 [page 1727]	`Impossible to modify the chargeable item class {chargeableItemClassId} because the type of the property {propertyName} is {specifiedPropertyType} in the database while the server has received the type {realPropertyType} in the operation.`	Change the type of the property. Verify your changes.
CI-CLASS-15 [page 1728]	`Impossible to modify the chargeable item class {chargeableItemClassId} because the following properties are missing: {missingPropertyName}.`	Add the missing properties to the operation. Verify your changes.
CI-CLASS-16 [page 1730]	`The id of chargeable item class is missing in the delete operation.`	Add an ID to the chargeable item class. Verify your changes.
CI-CLASS-17 [page 1731]	`The chargeable item class with the id {chargeableItemClassId} in the delete operation does not exist.`	Change the ID of the chargeable item class to an existing one. Verify your changes.

Error Code	Message	Action
CI-CLASS-18 [page 1733]	`The chargeable item class with the id {chargeableItemClassId} is still referenced in following charges: {referrencedChargeIds}.`	Delete the referenced charges first. Verify your changes.
CI-CLASS-19 [page 1734]	`The chargeable item class with the id {chargeableItemClassId} and product id {productId} in the delete operation does not exist.`	Change the ID or the product ID of the chargeable item class to an existing one. Verify your changes.
CI-CLASS-20 [page 1736]	`The chargeable item class with the id {chargeableItemClassId} and product id {productId} is still referenced in the following charges: {referredChargeIds}.`	Delete the referenced charges first. Verify your changes.
CI-CLASS-21 [page 1737]	`The chargeable item class with the id {chargeableItemClassId} is still referenced in the following exportable item mappings: {exportableItemMappingCodes}.`	Delete the referenced exportable item mappings first. Verify your changes.
CI-CLASS-22 [page 1739]	`The chargeable item class with the id {chargeableItemClassId} is still referenced by at least one data file.`	Trigger the processing of the data files by the bulk loader instances first. Verify your changes.
CI-CLASS-23 [page 1740]	`The bulk loader instances cannot be contacted to check if data files still reference the chargeable item class with the id {chargeableItemClassId}.`	Check that the bulkloader instances are running. Verify your changes.
CI-CLASS-24 [page 1742]	`The old product identifier of the chargeable item class must be null in the create and modify operations.`	Remove the old product identifier of the chargeable item class. Verify your changes.

Error Code	Message	Action
CI-CLASS-25 [page 1743]	`The old identifier of the chargeable item class must be null in the create and modify operations.`	Remove the old identifier of the chargeable item class. Verify your changes.
CI-CLASS-26 [page 1745]	`The chargeable item class identifier {chargeableItemClassId} is reserved for internal use.`	Modify the identifier of the chargeable item class. Verify your changes.
CON-TRACT-1 [page 1746]	`The date is missing in the create contract operation.`	Add a date in the operation request. Verify your changes.
CON-TRACT-2 [page 1748]	`The charging contract is missing in the create contract operation.`	Add a contract data object in the operation request. The charging contract is the charging view of a provider contract. Verify your changes.
CON-TRACT-3 [page 1749]	`The ID of the contract is missing.`	Add a contract identifier to the contract object in the operation request. Verify your changes.
CON-TRACT-4 [page 1751]	`The subscriber account ID of the contract is missing.`	Add a subscriber account identifier in the operation request. Verify your changes.
CON-TRACT-5 [page 1752]	`The name of the service provider who has delivered the provider contract is missing.`	Add the name of the service provider in the operation request. Verify your changes.
CON-TRACT-6 [page 1753]	`The subscriber ID "{subscriberId}" defined in the provider contract does not exist for the service provider "{serviceProvider}".`	Change the subscriber ID to an existing one or create the subscriber ID for the given service provider. Verify your changes.
CON-TRACT-7 [page 1755]	`Impossible to create the provider contract because its ID already exists: {chargingContractId}.`	Change the ID of the provider contract in the operation request. Verify your changes.

Error Code	Message	Action
CON-TRACT-8 [page 1756]	`The date is missing in the modify provider contract operation.`	Specify a date in the operation request. Verify your changes.
CON-TRACT-9 [page 1758]	`The provider contract is missing in the modify provider contract operation.`	Add a provider contract in the operation request. Verify your changes.
CON-TRACT-10 [page 1759]	`The charging contract with the ID {chargingContractId} does not exist.`	Change the identifier of the contract to an existing one or create the provider contract first. Verify your changes.
CON-TRACT-11 [page 1761]	`Internal SAP CC system error: Impossible to modify the contract because the related subscriber account is not found.`	Verify your changes.

CON-TRACT-12 [page 1762]	`Impossible to modify the contract because the subscriber ID {specifiedSubscriberAccountId}`
	
	`specified in the operation does not correspond to the subscriber ID {realSubscriberAccountId} which already exists in the provider contract.`
		Change the subscriber ID to the existing one {1} or create a new provider contract for the specified subscriber ID {0}.
		Verify your changes.

CON-TRACT-13 [page 1764]	`Impossible to modify the provider contract because the subscriber account service provider name {specifiedSubscriberAccountServiceProviderName} specified in the operation does not correspond to the subscriber account service provider name {realSubscriberAccountServiceProviderName} which already exists in the provider contract.`	Change the subscriber account service provider name to the existing one {1} or create a new provider contract for the specified subscriber account service provider name {0}. Verify your changes.
CON-TRACT-14 [page 1765]	`The ID is missing in the delete contract operation.`	Add a contract ID in the operation request. Verify your changes.

Error Code	Message	Action
CON-TRACT-15 [page 1767]	`The provider contract with the ID {chargingContractId} does not exist.`	Change the ID of the provider contract to an existing one or create the provider contract first. Verify your changes.
CON-TRACT-16 [page 1768]	`Internal SAP CC system error. Impossible to delete the contract because its subscriber account is not found.`	Verify your changes.
CON-TRACT-17 [page 1770]	`Error while validating the provider contract "{chargingContractId}".`	Verify your changes.
CON-TRACT-18 [page 1771]	`The ID of the contract item at index {chargingContractItemIndex} is missing.`	Add an ID to the contract item. Verify your changes.
CON-TRACT-19 [page 1773]	`The ID "{chargingContractItemId}" of the contract item at index {secondIndex} is already used by the contract item at index {firstIndex}. Two contract items cannot have the same identifier.`	Change the ID of the contract item. Verify your changes.
CON-TRACT-20 [page 1774]	`The chargePlanClassId, the refillPlanClassId or the monitoringPlanClassId of the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is missing.`	Add a chargePlanClassId, a refillPlanClassId or a monitoring-PlanClassId to the contract item. Verify your changes.
CON-TRACT-21 [page 1776]	`The charge plan class "{chargePlanClassId}" referred by the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.`	Specify another identifier of a charge plan class that exists. Verify your changes.

Error Code	Message	Action
CON-TRACT-22 [page 1777]	`The chargePlanClassId retrieved from the previous contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.`	Clearly set the chargePlanClassId in the contract item. Verify your changes.
CON-TRACT-23 [page 1779]	`The Charge Plan Class referred by the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.`	Change the chargePlanClassId to an existing Charge Plan Class identifier. Verify your changes.
CON-TRACT-24 [page 1780]	`Error while validating the contract item "{chargingContractItemId}" at index {chargingContractItemIndex}.`	Verify your changes.
CON-TRACT-25 [page 1782]	`The name of the User Technical Identifier at index {userTechIdIndex} is missing.`	Add a name to the User Technical Identifier. Verify your changes.
CON-TRACT-26 [page 1783]	`Impossible to create the linked contract because its parent contract "{chargingContractId}" does not exist.`	Change the ID of the parent contract or first create a new contract with this identifier. Verify your changes.
CON-TRACT-27 [page 1785]	`The User Technical Identifier "{userTechIdName}" at index {userTechIdIndex} does not exist in the referred charge plan class "{chargePlanClassId}".`	Remove the User Technical Identifier or change its name to a User Technical Identifier which exists in the charge plan class Verify your changes.

Error Code	Message	Action
CON-TRACT-28 [page 1786]	`Impossible to modify the linked contract because the parent contract ID {specifiedchargingContractId} specified in the operation request does not correspond to the parent contract ID {realchargingContractId} which already exists in the linked contract.`	Change the provider contract ID to the existing one {1}. Verify your changes.
CON-TRACT-29 [page 1788]	`The User Service Identifier (USID) of the user technical identifier "{userTechIdName}" at index {userTechIdIndex} is empty.`	Specify the user service identifier or remove this empty user technical identifier. Verify your changes.
CON-TRACT-30 (Revoked) [page 1790]	`The User Technical Identifier "{userTechIdName}" of the referred charge plan class "{chargePlanClassId}" is not declared in the contract item.`	Link the User Technical Identifier or remove it. Verify your changes.
CON-TRACT-31 [page 1791]	`The charge plan class "{chargePlanClassId}" referred by the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.`	Change the chargePlanClassId to an existing charge plan class identifier. Verify your changes.
CON-TRACT-32 [page 1793]	`Internal SAP CC system error. Impossible to modify the provider contract because the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is not found.`	Verify your changes.
CON-TRACT-33 [page 1794]	`The name of the Account Assignment at index {accountAssignmentIndex} is missing.`	Add a name to the Account Assignment. Verify your changes.

Error Code	Message	Action
CON-TRACT-34 [page 1796]	`The name "{accountAssignmentName}" of the Account Assignment at index {secondIndex} is already used by the Account Assignment at index {firstIndex}.`	Change the name of the Account Assignment. Verify your changes.
CON-TRACT-35 [page 1797]	`The Account Assignment "{accountAssignmentName}" at index {accountAssignmentIndex} does not exist in the referred charge plan class "{chargePlanClassId}".`	Remove the Account Assignment or give the name of an Account Assignment which already exists in the charge plan class. Verify your changes.
CON-TRACT-36 [page 1799]	`Internal server error. Impossible to delete the provider contract "{chargingContractId}" because it has, at least, one provider contract linked to it.`	Delete the linked provider contract(s) first. Verify your changes.
CON-TRACT-37 [page 1801]	`Impossible to create the linked contract because the parent contract ID {chargingContractId} specified in the operation request actually matches a linked contract.`	Specify another parent contract in the operation request. Verify your changes.
CON-TRACT-38 [page 1802]	`The account ID of the Account Assignment at index {accountAssignmentIndex} is missing.`	Add an account ID to the Account Assignment. Verify your changes.
CON-TRACT-39 [page 1804]	`The Account Assignment "{accountAssignmentName}" of the referred Charge Plan Class "{chargePlanClassId}" is not declared in the contract item.`	Link the Account Assignment or remove it. Verify your changes.
CON-TRACT-40 (Revoked) [page 1805]	`The name of the Additional Information at index {additionalInformationIndex} is missing.`	Add a name to the Additional Information. Verify your changes.

Error Code	Message	Action
CON-TRACT-41 (Revoked) [page 1807]	`The name "{additionalInformationName}" of the Additional Information at index {secondIndex} is already used by the Additional Information at index {firstIndex}.`	Change the name of the Additional Information. Verify your changes.
CON-TRACT-42 (Revoked) [page 1808]	`The type of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing or unknown. The supported types are: String, number, and date.`	Add a type to the Additional Information or change it to a valid type. Verify your changes.
CON-TRACT-43 (Revoked) [page 1810]	`The date value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a date value to the Additional Information. Verify your changes.
CON-TRACT-44 (Revoked) [page 1812]	`The number value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a number value to the Additional Information. Verify your changes.
CON-TRACT-45 (Revoked) [page 1813]	`The string value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a string value to the Additional Information. Verify your changes.
CON-TRACT-46 (Revoked) [page 1815]	`The type "{additionalInformationType}" of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is unsupported. The supported types are: String, number, and date.`	Use a valid type (string, number, date) for the Additional Information. Verify your changes.

Error Code	Message	Action
CON-TRACT-47 [page 1817]	`The name of the Parameter at index {parameterIndex} is missing.`	Add a name to the Parameter. Verify your changes.
CON-TRACT-48 [page 1818]	`The name "{parameterName}" of the Parameter at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter. Verify your changes.
CON-TRACT-49 [page 1820]	`The Parameter "{parameterName}" at index {parameterIndex} does not exist in the referred Charge Plan Class "{chargePlanClassId}".`	Remove the Parameter or change its name to a Parameter which exists in the Charge Plan Class. Verify your changes.
CON-TRACT-50 [page 1821]	`The type of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown. The supported types are: String, number, date, currency.`	Add a type to the Parameter or change it to a supported one: string, number, date, or currency. Verify your changes.
CON-TRACT-51 [page 1823]	`The type "{parameterType}" of the Parameter "{parameterName}" at index {parameterIndex} is incompatible with the type of the referred Parameter ({chargePlanClassParameterType}) in the Charge Plan Class "{chargePlanClassId}".`	Change the Parameter type to the type of the Parameter in the Charge Plan Class. Verify your changes.
CON-TRACT-52 [page 1824]	`The date value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a date value to the Parameter. Verify your changes.
CON-TRACT-53 [page 1826]	`The number value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a number value to the Parameter. Verify your changes.
CON-TRACT-54 [page 1827]	`The string value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a string value to the Parameter. Verify your changes.

Error Code	Message	Action
CONTRACT-55 [page 1829]	`The type "{parameterType}" of the Parameter "{parameterName}" at index {parameterIndex} is unsupported. The supported types are: String, number, date, and currency.`	Use a supported type (string, number, date, currency) for the parameter. Verify your changes.
CONTRACT-56 [page 1830]	`The mandatory parameter "{parameterName}" of the referred Charge Plan Class "{chargePlanClassId}" is not declared in the contract item.`	Add the missing mandatory Parameter. Verify your changes.
CONTRACT-57 [page 1832]	`The contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is already referencing the Charge Plan Class "{originalChargePlanClassId}" and cannot reference the Charge Plan Class "{newChargePlanClassId}" at the same time.`	Use the Charge Plan Class which is already referenced by the contract item or create a new contract item. Verify your changes.
CONTRACT-58 [page 1833]	`The access (user "{user}" / service "{service}") cannot be created because it already exists.`	Modify the access. Verify your changes.
CONTRACT-59 [page 1835]	`The end date {endDate} declared in the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is before or equal to the operation date {operationDate}.`	Modify the end date to a date strictly after the operation date. Verify your changes.
CONTRACT-60 [page 1836]	`The Refill Plan Class "{refillPlanClassId}" referred by the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.`	Change the refillPlanClassId to an existing Refill Plan Class identifier. Verify your changes.

Error Code	Message	Action
CON-TRACT-61 [page 1838]	`The Refill Plan Class "{refillPlanClassId}" referred by the contract item "{refillPlanClassId}" at index {chargingContractItemIndex} is unknown.`	Change the refillPlanClassId to an existing Refill Plan Class identifier. Verify your changes.
CON-TRACT-62 [page 1840]	`Internal server error. Impossible to modify the provider contract because the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is not found on the server.`	Verify your changes.
CON-TRACT-63 [page 1841]	`The contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is already referencing the Refill Plan Class "{originalRefillPlanClassId}" and cannot reference the Refill Plan Class "{newRefillPlanClassId}" at the same time.`	Use the Refill Plan Class which is already referenced by the contract item or create a new contract item. Verify your changes.
CON-TRACT-64 [page 1843]	`Only one of chargePlanClassId, refillPlanClassId and monitoringPlanClassId can be set in the contract item "{chargingContractItemId}" at index {chargingContractItemIndex}.`	Keep only one of the chargePlanClassId, the refillPlanClassId or the monitoringPlanClassId in the contract item. Verify your changes.
CON-TRACT-65 [page 1844]	`The name of the shared counter at index {sharedCounterIndex} is missing.`	Add a name to the shared counter. Verify your changes.
CON-TRACT-66 [page 1846]	`The name "{sharedCounterName}" of the shared counter at index {secondIndex} is already used by the shared counter at index {firstIndex}.`	Change the name of the shared counter. Verify your changes.

Error Code	Message	Action
CON-TRACT-67 [page 1847]	`The shared counter "{sharedCounterName}" at index {sharedCounterIndex} does not exist in the referred Charge Plan Class "{chargePlanClassId}".`	Remove the shared counter or change its name to a Counter which exists in the Charge Plan Class. Verify your changes.
CON-TRACT-68 [page 1849]	`The {accountType} account "{accountId}" is not found.`	Set an account identifier that referenced an existing account. Verify your changes.
CON-TRACT-69 [page 1851]	`The currency parameter value "{parameterValue}" at index {parameterIndex} is unknown by the SAP CC system.`	Find a valid currency value using the `exportCurrencies` operation. Verify your changes.
CON-TRACT-70 [page 1852]	`The CURRENCY value of the parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a currency value to the parameter. Verify your changes.
CON-TRACT-71 [page 1854]	`Duplicate access for service "{serviceAccess}" and user identifier "{identifierAccess}" is defined in provider contract "{chargingContractId}" in contract item "{firstChargingContractItemId}" linked to Charge Plan Item "{firstChargePlanItemId}" in Charge Plan "{firstChargePlanId}" and in contract item "{secondChargingContractItemId}" linked to Charge Plan Item "{secondChargePlanItemId}" in charge plan "{secondChargePlanId}".`	Change the contract configuration. Verify your changes.
CON-TRACT-72 [page 1855]	`The contract batch rating group assignment policy is not defined.`	Change the configuration of the updater BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS parameter. Verify your changes.

Error Code	Message	Action
CONTRACT-73 [page 1857]	`The batch rating group identifier returned by the implementation of the batch rating group assignment policy is null.`	Check the implementation of the batch rating group assignment policy. The batch rating group assignment policy is defined by the parameter BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS. Verify your changes.
CONTRACT-74 [page 1858]	`The code of the batch rating group identifier "{codeOfBatchRatingGroupIdentifier}" is unknown.`	Check the implementation of the batch rating group assignment policy and the configuration of the batch rating groups. The batch rating group assignment policy is defined by the parameter BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS. Verify your changes.
CONTRACT-75 [page 1860]	`The ID of the batch rating group identifier "{idOfBatchRatingGroupIdentifier}" is unknown.`	Check the implementation of the batch rating group assignment policy and the configuration of the batch rating groups. The batch rating group assignment policy is defined by the parameter BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS. Verify your changes.
CONTRACT-76 [page 1861]	`The batch rating group assignment policy cannot compute the batch rating group identifier for the provider contract "{chargingContractId}". The message of the exception is "{batchRatingGroupErrorMessage}".`	Check the implementation of the batch rating group assignment policy and the configuration of the batch rating groups. The batch rating group assignment policy is defined by the parameter BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS. Verify your changes.
CONTRACT-77 [page 1863]	`The User Service Identifier "{userServiceId}" of the User Technical Identifier Reference at index {userTechnicalIdentifierReferenceIndex} is missing is not ASCII. Invalid characters are "{invalidCharacters}".`	Replace the invalid characters of User Service Identifier with ASCII characters. Verify your changes.
CONTRACT-78 [page 1865]	`The User Service Identifier "{userServiceId}" of the User Technical Identifier Reference at index {userTechnicalIdentifierReferenceIndex} has more than 128 characters.`	Shorten the service name to 128 ASCII characters. Verify your changes.

Error Code	Message	Action
CON-TRACT-79 [page 1866]	`The Parameter "{parameterName}" at index {parameterIndex} points to an unknown mapping table "{parameterValue}".`	Change the value to a known mapping table. Verify your changes.
CON-TRACT-80 [page 1868]	`The Parameter "{parameterName}" at index {parameterIndex} points to a mapping table "{mappingTableId}" which has an invalid mapping table class "{mappingTableClass}". It should be "{parameterMappingTableClass}" .`	Change the parameter value to a mapping table with the correct mapping table class. Verify your changes.
CON-TRACT-81 [page 1869]	`The refill access (Service provider "{serviceProvider}" / Subscriber account code "{subAccountCode}" / Prepaid account code "{prepaidAccountCode}") cannot be created because it is already assigned between "{assignmentStartDate}" and "{assignmentEndDate}".`	Check the already assigned prepaid account. Verify your changes.
CON-TRACT-82 [page 1871]	`The access (User Service Identifier "{userServiceId}" / Service Identifier "{serviceId}") cannot be created because it is already assigned between "{assignmentStartDate}" and "{assignmentEndDate}".`	Check the already assigned access. Verify your changes.
CON-TRACT-83 [page 1873]	`The provider contract with the ID {chargingContractId} does not exist.`	Change the ID of the provider contract to an existing one or create the provider contract first. Verify your changes.

Error Code	Message	Action
CON-TRACT-84 [page 1874]	`The Account Assignment "{accountAssignmentName}" at index {firstIndex} of type postpaid is invalid for contract item pointing to a refill plan.`	Assign a Prepaid Account. Verify your changes.
CON-TRACT-85 [page 1876]	`The identification code of the prepaid account currency "{accountCurrencyCode}" differs from the one of the mono currency refill logic "{refillLogicCurrencyCode}" for the provider contract item of ID "{chargingContractItemId}" pointing to a Refill Plan.`	Check the currencies of the Prepaid Account and Refill Logic. Verify your changes.
CON-TRACT-86 [page 1877]	`The status of activated Charge Plan or Refill Plan "{chargePlanId}" is open. Only released or obsolete Charge Plans and Refill Plans can be activated.`	Change the status of activated Charge Plan or Refill Plan to release or obsolete. Verify your changes.
CON-TRACT-87 [page 1879]	`The currency "{currencyCode}" of the charge plan parameter "{parameterName}" is not compatible with any account currency declared in the account assignment list.`	Change the currency value of the charge plan parameter or add an account compatible with this currency. Verify your changes.
CON-TRACT-88 [page 1880]	`The currency "{currencyCode}" of the charge plan item parameter "{parameterName}" is not compatible with any account currency declared in the account assignment list.`	Change the currency value of the charge plan item parameter or add an account compatible with this currency. Verify your changes.
CON-TRACT-89 [page 1882]	`The currency "{currencyCode}" of the provider contract parameter "{parameterName}" is not compatible with any account currency declared in the account assignment list.`	Change the currency of the provider contract parameter or add an account compatible with this currency. Verify your changes.
CON-TRACT-90 [page 1883]	`The currency "{currencyCode}" of the charge component "{chargeComponentId}" is not compatible with any account currency declared in the account assignment list.`	Add an account compatible with this currency. Verify your changes.

Error Code	Message	Action
CON-TRACT-91 [page 1885]	`The taxation module "{chargePlanItemTaxationModule}" of the charge plan item "{chargePlanItemId}" is not compatible with the taxation module "{accountTaxationModule}" of the account declared in the account assignment list.`	Change the taxation module value of the charge plan item or add an account compatible with this taxation module. Verify your changes.
CON-TRACT-92 [page 1886]	`The Parameter "{parameterName}" at index {parameterIndex} points to an unknown range table "{parameterValue}".`	Change the value to a known range table. Verify your changes.
CON-TRACT-93 [page 1888]	`The Parameter "{parameterName}" at index {parameterIndex} points to a range table "{rangeTableId}" which has an invalid range table class "{rangeTableClass}". It should be "{parameterRangeTableClass}".`	Change the parameter value to a range table with the correct range table class. Verify your changes.
CON-TRACT-94 [page 1890]	`The name of the counter shared with other contracts at index {pooledCounterIndex} is missing.`	Add a name to the counter shared with other contracts. Verify your changes.
CON-TRACT-95 [page 1891]	`The name "{pooledCounterName}" of the counter shared with other contracts at index {secondIndex} is already used by the counter at index {firstIndex}.`	Change the name of the counter shared with other contracts. Verify your changes.
CON-TRACT-96 [page 1893]	`The shared counter "{pooledCounterName}" at index {pooledCounterIndex} does not exist in the referred Charge Plan Class "{chargePlanClassId}".`	Remove the counter shared with other contracts or change its name to a Counter which exists in the Charge Plan Class. Verify your changes.

Error Code	Message	Action
CON-TRACT-97 [page 1894]	`The name "{pooledCounterName}" of the counter at index {secondIndex} is already used by the shared counter at index {firstIndex}.`	Change the name of the counter. Verify your changes.
CON-TRACT-98 [page 1896]	`Impossible to change the provider contract "{chargingContractId}" into a linked provider contract.`	Remove the provider contract ID. Verify your changes.
CON-TRACT-99 [page 1897]	`The counter "{pooledCounterName}" at index {firstIndex} cannot be shared with other contracts because is not declared in the parent contract "{chargingContractId}".`	Change the name of the counter to an existing one or add the counter to the parent contract. Verify your changes.
CON-TRACT-101 [page 1899]	`The shared counter "{sharedCounterName}" is already declared as a counter shared with other contracts in another contract item.`	Change the name of the shared counter. Verify your changes.
CON-TRACT-102 [page 1900]	`The counter shared with other contracts "{pooledCounterName}" is already declared as a shared counter in another contract item.`	Change the name of the counter shared with other contracts. Verify your changes.
CON-TRACT-103 [page 1902]	`Impossible to change the linked provider contract "{linkedChargingContractId}" into a provider contract.`	Do not change the existing provider contract ID. Verify your changes.

Error Code	Message	Action
CONTRACT-104 [page 1903]	`Impossible to modify the provider contract because the counter shared with other contracts "{pooledCounterName}" is still referenced in the contract item "{linkedChargingContractItemId}" of the linked provider contract "{linkedChargingContractId}" during the period "{period}".`	Remove the counter shared with other contracts in the linked provider contract first. Verify your changes.
CONTRACT-105 [page 1905]	`The monitoring plan class "{monitoringPlanClassId}" referred by the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.`	Change the monitoringPlanClassId to an existing monitoring plan class identifier. Verify your changes.
CONTRACT-106 [page 1907]	`The contract item "{chargingContractItemId}" at index {chargingContractItemIndex} already refers to a plan class "{originalPlanClassId}" (type: {originalPlanClassType}) and cannot be changed to refer to the monitoring plan class "{newMonitoringPlanClassId}" at the same time.`	Verify your changes.
CONTRACT-107 [page 1908]	`The contract item "{chargingContractItemId}" at index {chargingContractItemIndex} already refers to the monitoring plan class "{originalMonitoringPlanClassId}" and cannot be changed to refer to "{newMonitoringPlanClassId}" at the same time.`	Change the ID of the monitoring plan class which is already referenced by the contract item or create a new contract item. Change the modify operation request. Verify your changes.
CONTRACT-108 [page 1910]	`The monitoring plan class "{monitoringPlanClassId}" referred to by the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.`	Change the monitoringPlanClassId to an existing monitoring plan class identifier. Verify your changes.

Error Code	Message	Action
CON-TRACT-109 [page 1912]	`The User Technical Identifier (UTI) "{userTechIdName}" at index {userTechIdIndex} does not exist in the referred monitoring plan class "{monitoringPlanClassId}".`	Remove the User Technical Identifier or change its name to a User Technical Identifier which exists in the monitoring plan class. Verify your changes.
CON-TRACT-110 [page 1913]	`The contract item "{chargingContractItemId}" referring to the monitoring plan class "{monitoringPlanClassId}" contains account assignments.`	Remove the Account Assignments from the contract item. Verify your changes.
CON-TRACT-111 [page 1915]	`The status of activated monitoring plan "{monitoringPlanId}" is open. Only released or obsolete monitoring plans can be activated.`	Change the status of activated monitoring plan to release or obsolete. Verify your changes.
CON-TRACT-112 [page 1916]	`The contract item "{chargingContractItemId}" referring to the monitoring plan class "{monitoringPlanClassId}" contains redefinition parameters.`	Remove the parameters from the contract item. Verify your changes.
CON-TRACT-113 [page 1918]	`The contract item "{chargingContractItemId}" referring to the monitoring plan class "{monitoringPlanClassId}" contains pooled counters.`	Remove the pooled counters from the contract item. Verify your changes.
CON-TRACT-114 [page 1919]	`Duplicate access for service "{serviceAccess}" and user identifier "{identifierAccess}" is defined in provider contract "{chargingContractId}" in contract item "{firstChargingContractItemId}" linked to monitoring plan "{firstMonitoringPlanId}" and in contract item "{secondChargingContractItemId}" linked to monitoring plan "{secondMonitoringPlanId}".`	Change the contract configuration. Verify your changes.

Error Code	Message	Action
CON-TRACT-115 [page 1921]	`The shared counter "{sharedCounterName}" at index {sharedCounterIndex} does not exist in the referred monitoring plan class "{monitoringPlanClassId}".`	Remove the shared counter or change its name to a Counter which exists in the monitoring plan class. Verify your changes.
CON-TRACT-116 [page 1922]	`At least one counter mapped in the monitoring plan class "{monitoringPlanClassId}" is not shared in the contract item "{chargingContractItemId}".`	Add the missing shared counters from the monitoring plan class. Verify your changes.
CON-TRACT-117 [page 1924]	`The spending status "{spendingStatusDescription}" referenced in the contract item "{chargingContractItemId}" has been already referenced in the contract item "{alreadyAssignedChargingContractItemId}".`	Refer to a spending status only once in a contract. Verify your changes.
CON-TRACT-118 [page 1926]	`The contract item "{chargingContractItemId}" at index {chargingContractItemIndex} already refers to a plan class "{originalPlanClassId}" (type: {originalPlanClassType}) and cannot be changed to refer to the charge plan class "{newChargePlanClassId}" at the same time.`	Verify your changes.
CON-TRACT-119 [page 1927]	`The contract item "{chargingContractItemId}" at index {chargingContractItemIndex} already refers to a plan class "{originalPlanClassId}" (type: {originalPlanClassType}) and cannot be changed to refer to the refill plan class "{newRefillPlanClassId}" at the same time.`	Verify your changes.

Error Code	Message	Action
CONTRACT-120 [page 1929]	`The status of the contract item "{chargingContractItemId}" is suspended with a suspension date/time {suspensionDate}. It is not possible to resume the contract item at the date/time {resumptionDate}. The given resumption date/time should be set after this suspension date/time.`	Specify the resumption date/time after this suspension date/time. Verify your changes.
CONTRACT-121 [page 1931]	`The contract item "{chargingContractItemId}" at index {chargingContractItemIndex} must not refer to a refill plan because the Prepaid Accounts Management feature is disabled.`	Remove the contract item from the provider contract. Verify your changes.
CONTRACT-122 [page 1932]	`The parameter "{parameterName}" in the contract item "{chargingContractItemId}" at index {chargingContractItemIndex} cannot be modified.`	Check the visibility level of the parameter.
CONTRACT-STATE-1 [page 1934]	`The shared counter "{sharedCounterName}" does not exist in the charging contract "{chargingContractId}".`	Change the name of the shared counter to an existing one. Verify your changes.
CONTRACT-STATE-2 [page 1935]	`The contract item "{chargingContractItemId}" specified in the contract item state does not exist in the charging contract "{chargingContractId}".`	Change the identifier of the contract item to an existing contract item (customer master data). Verify your changes.
CONTRACT-STATE-3 [page 1937]	`The counter "{counterName}" does not exist in the charge plan "{chargePlanId}" activated in the contract item "{chargingContractItemId}" specified in the operation request.`	Change the counter name to an existing one. Verify your changes.

Error Code	Message	Action
CONTRACT-STATE-4 [page 1938]	`The specified charge activation "{chargeActivationId}" does not exist in the contract item "{chargingContractItemId}" of the charging contract "{chargingContractId}".`	Change the identifier of the charge activation to an existing one. Verify your changes.
CONTRACT-STATE-5 [page 1940]	`The specified counter "{counterName}" of the charge activation "{chargeActivationId}" in the contract item "{chargingContractItemId}" does not exist in the customized charge "{chargeComponentId}" or is always redefined.`	Change the counter name to an existing one and check that the counter is not redefined. Verify your changes.
CONTRACT-STATE-6 [page 1942]	`The shared counter "{counterName}" specified in the operation request is referenced several times.`	Use the shared counter name only once in the operation request. Verify your changes.
CONTRACT-STATE-7 [page 1943]	`The specified counter "{counterName}" of the contract item "{chargingContractItemId}" is referenced several times.`	Specify the counter name only once in the operation request. Verify your changes.
CONTRACT-STATE-8 [page 1945]	`The specified counter "{counterName}" in the charge activation "{chargeActivationId}" of the contract item "{chargingContractItemId}" is referenced several times.`	Specify the counter name only once in this charge activation in the operation request. Verify your changes.
CONTRACT-STATE-9 [page 1946]	`The specified counter name "{counterName}" is reserved for internal use only.`	Do not use this counter name in the operation request. Verify your changes.
CONTRACT-STATE-10 [page 1948]	`Cannot change the charging contract "{chargingContractId}". This master data does not exist.`	Change the identifier of the charging contract to an existing contract. Verify your changes.

Error Code	Message	Action
CONTRACT-STATE-11 [page 1949]	`Cannot read the charging contract "{chargingContractId}". This master data does not exist.`	Change the identifier of the charging contract to an existing contract. Verify your changes.
CONTRACT-STATE-12 [page 1951]	`Cannot change the state of the charging contract. The contract item "{chargingContractItemId}" is referenced several times.`	Specify this contract item only once in the operation request. Verify your changes.
CONTRACT-STATE-13 [page 1952]	`Cannot change the state of the charging contract. The charge activation "{chargeActivationId}" in the contract item "{chargingContractItemId}" is referenced several times.`	Specify this charge activation only once in the operation request. Verify your changes.
CONTRACT-STATE-14 [page 1954]	`The specified LastActivationDate "{lastActivationDate}" in the charge activation "{chargeActivationId}" of the contract item "{chargingContractItemId}" is anterior to the validity start date of the contract item "{chargingContractItemValidity StartDate}".`	Specify a LastActivationDate posterior to the validity start date of the contract item. Verify your changes.
CUSTOMERDATA-1 [page 1955]	`Neither the subscriber account ID or the root charging contract ID is provided in the request.`	Add a subscriber account ID or at least one root charging contract ID to the export request. Verify your changes.
CUSTOMERDATA-2 [page 1957]	`The subscriber account with the ID "{subscriberAccountId}" does not exist in the SAP CC system.`	Change the subscriber account ID in the export request to an existing one. Verify your changes.
CUSTOMERDATA-3 [page 1958]	`The root charging contract with the ID "{rootChargingContractId}" does not exist in the SAP CC system.`	Change the root charging contract ID in the export request to an existing one. Verify your changes.

Error Code	Message	Action
CUSTOM-ERDATA-4 [page 1960]	`The contracts to be exported do not belong to the same subscriber account.`	To export several contracts at the same time, choose contracts having the same subscriber account. Verify your changes.
CUSTOM-ERDATA-5 [page 1961]	`The root charging contract ID "{rootChargingContractId}" is duplicated in the export request.`	Remove the duplicate ID from the export request. Verify your changes.
CUSTOM-ERDATA-6 [page 1963]	`The rootChargingContractId "{chargingContractId}" refers to a linked charging contract in the SAP CC system.`	Change the rootChargingContractId to a root charging contract ID. Verify your changes.
CUSTOM-ERDATA-7 [page 1964]	`The external account with the ID "{externalAccountId}" is duplicated in the import request.`	Remove the duplicate external account from the import request. Verify your changes.
CUSTOM-ERDATA-8 [page 1966]	`The external account with the ID "{externalAccountId}" does not reference the subscriber account with the ID "{subscriberAccountId}" specified in the request.`	Change the subscriber account ID or remove the external account from the import request. Verify your changes.
CUSTOM-ERDATA-9 [page 1967]	`The prepaid account with the ID "{prepaidAccountId}" is duplicated in the import request.`	Remove the duplicate prepaid account from the import request. Verify your changes.
CUSTOM-ER-DATA-10 [page 1969]	`The prepaid account with the ID "{prepaidAccountId}" does not reference the subscriber account with the ID "{subscriberAccountId}" specified in the request.`	Change the subscriber account ID or remove the prepaid account from the import request. Verify your changes.
CUSTOM-ERDATA-11 [page 1970]	`The subscriber mapping table with the ID "{subscriberMappingTableId}" is duplicated in the import request.`	Remove the duplicate subscriber mapping table from the import request. Verify your changes.

Error Code	Message	Action
CUSTOMER-DATA-12 [page 1972]	`The subscriber mapping table with the ID "{subscriberMappingTableId}" does not reference the subscriber account with the ID "{subscriberAccountId}" specified in the request.`	Change the subscriber account ID or remove the subscriber mapping table from the import request. Verify your changes.
CUSTOMER-DATA-13 [page 1973]	`The subscriber mapping table "{subscriberMappingTableId}" to be imported already exists in the SAP CC destination system.`	To keep the existing table, remove the table from the import request. To overwrite the existing table, set the onAlreadyExistingTable attribute to "overwrite". Verify your changes.
CUSTOMER-DATA-14 [page 1975]	`The subscriber range table with the ID "{subscriberRangeTableId}" is duplicated in the import request.`	Remove the duplicate subscriber range table from the import request. Verify your changes.
CUSTOMER-DATA-15 [page 1976]	`The subscriber range table with the ID "{subscriberRangeTableId}" does not reference the subscriber account with the ID "{subscriberAccountId}" specified in the request.`	Change the subscriber account ID or remove the subscriber range table from the import request. Verify your changes.
CUSTOMER-DATA-16 [page 1978]	`The subscriber range table "{subscriberRangeTableId}" to be imported already exists in the SAP CC destination system.`	To keep the existing table, remove the table from the import request. To overwrite the existing table, set the onAlreadyExistingTable attribute to "overwrite". Verify your changes.
CUSTOMER-DATA-17 [page 1979]	`The charging contract with the ID "{chargingContractId}" is duplicated in the import request.`	Remove the duplicate charging contract from the import request. Verify your changes.
CUSTOMER-DATA-18 [page 1981]	`The charging contract with the ID "{chargingContractId}" does not reference the subscriber account with the ID "{subscriberAccountId}" specified in the request.`	Change the subscriber account ID or remove the subscriber range table from the import request. Verify your changes.

Error Code	Message	Action
CUSTOMER-DATA-19 [page 1982]	`The object with the type "{objectType}" and the ID "{objectId}" does not reference the subscriber account with the ID "{subscriberAccountId}".`	Remove the object from the import request and check that all the objects to be imported belong to the same subscriber account. Verify your changes.
CUSTOMER-DATA-20 [page 1984]	`The linked charging contract "{linkedChargingContractId}" to be imported references the root charging contract "{rootChargingContractId}" which does not exist in the SAP CC destination system.`	Remove the linked charging contract from the import request or import the root charging contract first. Verify your changes.
CUSTOMER-DATA-21 [page 1986]	`The linked charging contract "{linkedChargingContractId}" to be imported reference the root charging contract "{rootChargingContractId}" having a different subscriber account in the SAP CC destination system.`	Remove the linked charging contract from the import request and check that all the objects to be imported belong to the same subscriber account. Verify your changes.
CUSTOMER-DATA-22 [page 1987]	`The subscriber account "{subscriberAccountId}" to be imported already exists in the SAP CC destination system.`	Remove the subscriber account from the import request or delete the existing one in the SAP CC destination system. Verify your changes.
CUSTOMER-DATA-23 [page 1989]	`The external account "{externalAccountId}" to be imported already exists in the SAP CC destination system.`	Remove the external account from the import request or delete the existing one in the SAP CC destination system. Verify your changes.
CUSTOMER-DATA-24 [page 1990]	`The prepaid account "{prepaidAccountId}" to be imported already exists in the SAP CC destination system.`	Remove the prepaid account from the import request or delete the existing one in the SAP CC destination system. Verify your changes.
CUSTOMER-DATA-25 [page 1992]	`The charging contract "{chargingContractId}" to be imported already exists in the SAP CC destination system.`	Remove the charging contract from the import request or delete the existing one in the SAP CC destination system. Verify your changes.

Error Code	Message	Action
CUSTOMER-DATA-26 [page 1993]	`The chargingContractOperationalStatusChangedTo cannot be set to "closed". Only "active" or "locked" are allowed in the import request.`	Remove the chargingContractOperationalStatusChangedTo or set it to an appropriate value: "active" or "locked" (default). Verify your changes.
CUSTOMER-DATA-27 [page 1995]	`You cannot provide both a subscriber account ID and root charging contract IDs in the export request.`	Set a subscriber account ID or one or more root charging contract IDs in the export request. Verify your changes.
CUSTOMER-DATA-28 [page 1996]	`The subscriber range table with the ID "{subscriberRangeTableId}" belongs to another subscriber account in the SAP CC destination system.`	Change the subscriber range table ID. Update the charging contract with the new subscriber range table ID and relaunch the import request. Verify your changes.
CUSTOMER-DATA-29 [page 1998]	`The subscriber mapping table with the ID "{subscriberMappingTableId}" belongs to another subscriber account in the SAP CC destination system.`	Change the subscriber mapping table ID. Update the charging contract with the new subscriber mapping table ID and relaunch the import request. Verify your changes.
CUSTOMER-DATA-30 [page 1999]	`The allowance ID "{allowanceId}" is duplicated in the import request.`	Remove the duplicate ID from the import request. Verify your changes.
CUSTOMERMANAGEMENTAREA-1 [page 2001]	`The name of the customer management area at index {customerManagementAreaIndex} is missing.`	Add a name to the customer management area. Verify your changes.
CUSTOMERMANAGEMENTAREA-2 [page 2002]	`The name of the customer management area at index {customerManagementAreaIndex} is empty.`	Set the name of the customer management area. Verify your changes.

Error Code	Message	Action
CUSTOM-ERMANA-GEMEN-TAREA-3 [page 2004]	`The name "{customerManagementAreaName}" of the customer management area at index {secondIndex} is already used by another customer management area at index {firstIndex}.`	Change the name of the customer management area. Verify your changes.
CUSTOM-ERMANA-GEMEN-TAREA-4 [page 2005]	`The name of the ERP JCo destination in the customer management area at index {sapSystemDefinitionIndex} is missing.`	Add a name of ERP JCo destination to the customer management area. Verify your changes.
CUSTOM-ERMANA-GEMEN-TAREA-5 [page 2007]	`The name of the ERP JCo destination in the customer management area at index {customerManagementAreaIndex} is empty.`	Set the name of the ERP JCo destination in the customer management area. Verify your changes.
CUSTOM-ERMANA-GEMEN-TAREA-6 [page 2008]	`The name "{erpJcoDestinationName}" of the ERP JCo destination in the customer management area at index {customerManagementAreaIndex} matches no existing ERP JCo destination.`	Set an existing ERP JCo destination name to the customer management area. Verify your changes.
CUSTOM-ERMANA-GEMEN-TAREA-7 [page 2010]	`The name of the CRM JCo destination in the customer management area at index {customerManagementAreaIndex} is empty.The name of the CRM JCo destination in the customer management area at index {customerManagementAreaIndex} is empty.`	Set the name of the CRM JCo destination in the customer management area. Verify your changes.
CUSTOM-ERMANA-GEMEN-TAREA-8 [page 2011]	`The name "{crmJcoDestinationName}" of the CRM JCo destination in the definition at index {customerManagementAreaDefinitionIndex} matches no existing CRM JCo destination.`	Set an existing CRM JCo destination name to the customer management area. Verify your changes.

Error Code	Message	Action
CUSTOMERMANAGEMENTAREA-9 [page 2013]	`The name of the default customer management area is empty in the customer management area list.`	Set the name of the default customer management area in the customer management area list. Verify your changes.
CUSTOMERMANAGEMENTAREA-10 [page 2014]	`The name "{defaultCustomerManagementAreaName}" of the default customer management area matches no customer management area name in the customer management area list.`	Set a valid default customer management area or change the name of a customer management area to the default customer management area name. Verify your changes.
CUSTOMERMANAGEMENTAREA-11 [page 2016]	`The customer management area list is missing in the maintain operation.`	Add the customer management area list to the maintain operation request. Verify your changes.
CUSTOMERMANAGEMENTAREA-12 [page 2017]	`The customer management area "{customerManagementAreaName}" cannot be removed because it is still used by at least one subscriber account.`	Delete all the subscriber accounts that use this customer management area. Verify your changes.
DICTIONARY-1 [page 2019]	`Counter name at index {counterNameIndex} is null.`	Set a value to that counter name. Verify your changes.
DICTIONARY-2 [page 2020]	`The name of the counter name at index {counterNameIndex} is missing.`	Add a name to the counter name. Verify your changes.
DICTIONARY-3 [page 2022]	`The description of the counter name "{counterName}" at index {counterNameIndex} is missing.`	Add a description to the counter name. Verify your changes.
DICTIONARY-4 [page 2023]	`The name "{counterName}" of the Counter name at index {secondIndex} is already used by the Counter name at index {firstIndex}.`	Change the name of the Counter name. Verify your changes.

Error Code	Message	Action
DICTIONARY-5 [page 2025]	`Error while validating the dictionary of counter names.`	Verify your changes.
DICTIONARY-6 [page 2026]	`The counter name entry "{counterName}" cannot be deleted from the dictionary because it is still used by charge plans.`	Do not remove this counter name entry or delete charge plans that are referencing it. Verify your changes.
DICTIONARY-7 [page 2028]	`The counter names dictionary is missing in the modification operation.`	Set a valid counter names dictionary in the modification operation. Verify your changes.
DICTIONARY-8 [page 2029]	`The counter name entry "{counterName}" cannot be deleted from the dictionary because it is still used by monitoring plans.`	Do not remove this counter name entry or delete monitoring plans that are referencing it. Verify your changes.
HCI-1 [page 2031]	`The name of the Additional Information at index {additionalInformationIndex} is missing.`	Add a name to the 'Additional Information' item. The message indicates the position of the invalid item: index 1 means first item. Verify your changes.
HCI-2 [page 2032]	`The name "{additionalInformationName}" of the Additional Information at index {secondIndex} is already used by the Additional Information at index {firstIndex}.`	Change the name of one Additional Information item or remove the duplicate item. Verify your changes.
HCI-3 [page 2034]	`The description of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a description to the 'Additional Information' item. Verify your changes.

Error Code	Message	Action
HCI-4 [page 2035]	`The type of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing or unknown (supported types are string, number, date).`	Add a type to the Additional Information item or change it to a supported one: string, number, or date. Verify your changes.
HCI-5 [page 2037]	`The date value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a date value to the Additional Information item. Verify your changes.
HCI-6 [page 2038]	`The number value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a number value to the Additional Information item. Verify your changes.
HCI-7 [page 2040]	`The string value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a string value to the Additional Information item. Verify your changes.
HCI-8 [page 2041]	`The type "{additionalInformationType}" of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is not supported (supported types are string, number, date).`	Specify a type that is supported (string, number, or date/time) for the Additional Information item. Verify your changes.
HCI-9 [page 2043]	`The Additional Information item at index {additionalInformationIndex} is empty.`	Replace it by a valid Additional Information item or remove it. Verify your changes.
HCI-10 [page 2044]	`You must provide at least one object reference for the search object dependencies operation.`	Add an object reference to the search object dependencies operation. Verify your changes.

Error Code	Message	Action
HCI-11 [page 2046]	`The object reference at index {objectReferenceIndex} has no object identifier.`	Add an object identifier to the object reference. Verify your changes.
HCI-12 [page 2047]	`The object reference "{objectReferenceObjectID}" at index {objectReferenceIndex} has no object type.`	Add an object type to the object reference. Verify your changes.
HCI-13 [page 2049]	`The object reference "{objectReferenceObjectID}" at index {objectReferenceIndex} has no object type.`	Add an object type to the object reference. Verify your changes.
HCI-14 [page 2050]	`You cannot concurrently set a modification date and a validity date range.`	Specify either the validity date range or the modification date but do not specify both at the same time. Verify your changes.
HCI-15 [page 2052]	`The end date {endDate} of the validity date range is before or equal to the start date {startDate}.`	Specify an end date/time after the start date/time. Verify your changes.
HCI-16 [page 2053]	`The mandatory filter in the search operation is missing.`	Add a filter to the search operation. Verify your changes.
HCI-17 [page 2055]	`The search filter {searchFilter} does not know the name of the attribute description {attributeDescriptionName}.`	Specify a known attribute description name. Verify your changes.
HCI-18 [page 2056]	`The attribute name {attributeName} cannot be present more than one time in the attribute result description.`	Remove the duplicated attribute name in the attribute result description. Verify your changes.
HCI-19 [page 2058]	`The search filter {searchFilter} does not know the name of the attribute result description {attributeName}.`	Specify a known attribute name in the attribute result description. Verify your changes.

Error Code	Message	Action
HCI-20 [page 2059]	`The attribute result description can only be used with the result type 'attributes'.`	Use the result type 'attributes' or remove the attribute result descriptions. Verify your changes.
HCI-21 [page 2061]	`The constraint of the attribute description {attributeDescriptionName} is null or invalid.`	Specify a not null and well formatted constraint according to the type of the attribute description. Verify your changes.
HCI-22 [page 2062]	`The object "{objectID}" of type "{objectType}" is invalid.`	First correct the object according to the other error messages, then perform the import operation again. Verify your changes.
HCI-23 [page 2064]	`The object of type "{objectType}" is invalid.`	First correct the object according to the other error messages, then perform the import operation again. Verify your changes.
HCI-24 [page 2065]	`The start date of the validity date range cannot be null while the end date {endDate} is defined in this context.`	Specify a start date or remove the end date. Specify a start date or remove the end date. Verify your changes.
HCI-25 [page 2067]	`The login of the user is missing.`	Specify a valid user name. Verify your changes.
HCI-26 [page 2068]	`The object access rule is missing.`	Specify a valid object access rule. Verify your changes.
HCI-27 [page 2069]	`The user {userName} does not exist in the SAP CC system.`	Check that the specified user exists, if not, create it. Verify your changes.
HCI-28 [page 2071]	`The object access rule cannot be created for {userName} because this user does not have the role Pricing Specialist - Price Data.`	Assign the role Pricig Specialist - Price Data to the user. Verify your changes.

Error Code	Message	Action
HCI-31 [page 2072]	`The object access rule with the additional info name {addInfoName} and the additional info value "{addInfoValue} cannot be created because both must be either null or not null.`	Ensure that de name of the additional information and its value are both defined or both null. Verify your changes.
MACRO-COMPONENT-1 [page 2074]	`The logic component defines the mapping between a mapping table ID property "{componentMappedPropertyName}" and a pricing macro "{pricingMacroId}" input property "{pricingMacroInputPropertyName}" that is not a mapping table ID property.`	Change the mapping to a standard string or change the input property of the pricing macro to a mapping table ID property. Verify your changes.
MACRO-COMPONENT-2 [page 2076]	`The component defines a mapping between a mapping table ID property "{componentMappedPropertyName}" and pricing macro "{pricingMacroId}" input property "{pricingMacroInputPropertyName}" that do not define the same mapping table class IDs: "{componentMappedPropertyMappingTableClassId}" /"{pricingMacroInputPropertyMappingTableClassId}".`	Modify the property mapping table class ID or change the pricing macro input property to the correct mapping table class ID. Verify your changes.
MACRO-COMPONENT-3 [page 2077]	`The component defines a mapping between a mapping table key property "{componentMappedPropertyName}" and a pricing macro "{pricingMacroId}" input property "{pricingMacroInputPropertyName}" that is not a mapping table key property.`	Modify the mapping to a standard string or change the pricing macro input property to a mapping table key property. Verify your changes.

Error Code	Message	Action
MACRO-COMPO-NENT-4 [page 2079]	`The component defines a mapping between a range table ID property "{componentMappedPropertyName}" and a pricing macro "{pricingMacroId}" input property "{pricingMacroInputPropertyName}" that is not a range table ID property.`	Modify the mapping to a standard string or change the pricing macro input property to a range table ID property. Verify your changes.
MACRO-COMPO-NENT-5 [page 2081]	`The component defines a mapping between a range table ID property "{componentMappedPropertyName}" and pricing macro "{pricingMacroId}" input property "{pricingMacroInputPropertyName}" that both do not define the same range table class IDs: "{componentMappedPropertyRangeTableClassId}"/"{pricingMacroInputPropertyRangeTableClassId}".`	Modify the property range table class ID or change the pricing macro input property to the correct range table class ID. Verify your changes.
MACRO-COMPO-NENT-6 [page 2082]	`The pricing macro "{pricingMacroId}" defines a string property "{pricingMacroInputPropertyName}" but component mapped property "{componentMappedPropertyName}" is a mapping table ID property.`	Modify the mapping to a mapping table ID or change the pricing macro input property to a string property. Verify your changes.
MACRO-COMPO-NENT-7 [page 2084]	`The pricing macro "{pricingMacroId}" defines a string property "{pricingMacroInputPropertyName}" but component mapped property "{componentMappedPropertyName}" is a mapping table key property.`	Modify the mapping to a mapping table key or change the pricing macro input property to a string property. Verify your changes.

Error Code	Message	Action
MACRO-COMPO-NENT-8 [page 2086]	`The pricing macro "{pricingMacroId}" defines a string property "{pricingMacroInputPropertyName}" but component mapped property "{componentMappedPropertyName}" is a range table ID property.`	Modify the mapping to a range table ID or change the pricing macro input property to a string property. Verify your changes.
MACRO-COMPO-NENT-9 [page 2087]	`Component "{macroComponent}" calls pricing macro "{pricingMacroId}" with {actualParameterCount} parameter(s) instead of {expectedParameterCount}.`	Modify the component to pass in the right number of parameters to the macro. Verify your changes.
MACRO-COMPO-NENT-10 [page 2089]	`Pricing macro "{pricingMacroId}" is called by component "{macroComponentName}" but is not defined.`	Modify the component to call a known macro or create the macro first. Verify your changes.
MACRO-COMPO-NENT-11 [page 2091]	`Component "{macroComponent}" calls pricing macro "{pricingMacroId}" with {actualParameterCount} output parameter(s) instead of {expectedParameterCount}.`	Modify the component to generate the right number of parameters by the macro. Verify your changes.
MACRO-COMPO-NENT-12 [page 2093]	`Pricing macro "{pricingMacroId}" called by component "{macroComponent}" has the flag ManagedByCockpit set to "{isPricingMacroCockpitCompatible}" which is not compatible.`	Use the correct user interface.
MAP-PINGTA-BLE-1 [page 2094]	`The mapping table class to create is missing.`	Add a mapping table class to the create operation. Verify your changes.
MAP-PINGTA-BLE-2 [page 2096]	`The ID of the mapping table class is missing.`	Add an identifier to the mapping table class. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-3 [page 2097]	`The owner of the mapping table class "{mappingTableClassId}" is missing.`	Add an owner to the mapping table class. Verify your changes.
MAP-PINGTA-BLE-4 [page 2099]	`The description of the mapping table class "{mappingTableClassId}" is missing.`	Add a description to the mapping table class. Verify your changes.
MAP-PINGTA-BLE-5 [page 2101]	`The mapping table class "{mappingTableClassId}" must at least declare one input column.`	Add at least one input column. Verify your changes.
MAP-PINGTA-BLE-6 (Revoked) [page 2102]	`The mapping table class "{mappingTableClassId}" must have less than four input columns.`	Delete an input column to have 4 input columns maximum. Verify your changes.
MAP-PINGTA-BLE-7 [page 2104]	`The mapping table class "{mappingTableClassId}" must at least declare one output column.`	Add at least one output column. Verify your changes.
MAP-PINGTA-BLE-8 (Revoked) [page 2105]	`The mapping table class "{mappingTableClassId}" must have less than 15 output columns.`	Delete output column(s) to have 15 output columns maximum. Verify your changes.
MAP-PINGTA-BLE-9 [page 2107]	`The name of the input column at index {inColumnIndex} is missing.`	Add a name to the input column. Verify your changes.
MAP-PINGTA-BLE-10 [page 2109]	`The type of the input column at index {inColumnIndex} is missing.`	Add a type to the input column. Verify your changes.
MAP-PINGTA-BLE-11 [page 2110]	`The column name "{columnName}" already exists in the mapping table class.`	Change the name of the column. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-12 [page 2112]	`The name of the output column at index {outColumnIndex} is missing.`	Add a name to the output column. Verify your changes.
MAP-PINGTA-BLE-13 [page 2114]	`The type of the output column at index {outColumnIndex} is missing.`	Add a type to the output column. Verify your changes.
MAP-PINGTA-BLE-15 [page 2116]	`Error while validating the mapping table class "{mappingTableClassId}".`	See the caused-by information. Verify your changes.
MAP-PINGTA-BLE-16 [page 2117]	`Impossible to create the mapping table class because its ID {mappingTableClassId} already exists.`	Change the identifier of the mapping table class. Verify your changes.
MAP-PINGTA-BLE-17 [page 2119]	`The description of the input column at index {inColumnIndex} is missing.`	Add a description to the input column. Verify your changes.
MAP-PINGTA-BLE-18 [page 2121]	`The description of the output column at index {outColumnIndex} is missing.`	Add a description to the output column. Verify your changes.
MAP-PINGTA-BLE-19 [page 2123]	`The ID of the mapping table class is missing.`	Add the identifier of the mapping table class to the delete operation. Verify your changes.
MAP-PINGTA-BLE-20 [page 2124]	`Impossible to remove the mapping table class because its ID "{mappingTableClassId}" does not exist.`	Change the identifier of the mapping table class. Verify your changes.
MAP-PINGTA-BLE-21 [page 2126]	`Impossible to remove the mapping table class "{mappingTableClassId}" because it is still used by a mapping table.`	Determine and delete all the mapping tables that reference the specified mapping table class. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-22 [page 2127]	`The filter is missing in the search mapping table class operation.`	Add a filter to the operation. Verify your changes.
MAP-PINGTA-BLE-23 [page 2129]	`An error occurred when processing the search mapping table class operation: {errorMessage}.`	Verify your changes.
MAP-PINGTA-BLE-24 [page 2130]	`Impossible to remove the mapping table class "{mappingTableClassId}" because it is still used by a subscriber mapping table.`	Determine and delete all the subscriber mapping tables that reference the specified mapping table class. Verify your changes.
MAP-PINGTA-BLE-101 [page 2132]	`The ID of the mapping table is missing.`	Add an ID to the mapping table. Verify your changes.
MAP-PINGTA-BLE-102 [page 2133]	`The ID of the mapping table class used by the mapping table "{mappingTableId}" is missing.`	Add the ID of the mapping table class used by the mapping table. Verify your changes.
MAP-PINGTA-BLE-103 [page 2135]	`The mapping table is missing.`	Add a mapping table to the create operation. Verify your changes.
MAP-PINGTA-BLE-104 [page 2136]	`The ID "{mappingTableId}" is already used by another mapping table.`	Change the identifier of the mapping table. Verify your changes.
MAP-PINGTA-BLE-105 [page 2138]	`The ID "{mappingTableClassId}" of the mapping table class used by the mapping table does not exist.`	Change the mapping table class identifier. Verify your changes.
MAP-PINGTA-BLE-107 [page 2139]	`The ID of the mapping table to delete is missing.`	Add the mapping table identifier to the delete operation. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-108 [page 2141]	`The mapping table "{mappingTableId}" does not exist.`	Change the identifier of the mapping table. Verify your changes.
MAP-PINGTA-BLE-109 [page 2142]	`The filter is missing in the search mapping table operation.`	Add a filter to the operation request. Verify your changes.
MAP-PINGTA-BLE-110 [page 2144]	`An error occurred when processing the search mapping table operation: {errorMessage}.`	Verify your changes.
MAP-PINGTA-BLE-111 [page 2145]	`The subscriber account ID of the subscriber mapping table "{subscriberMappingTableID}" is missing.`	Add a subscriber account identifier to the subscriber mapping table. Verify your changes.
MAP-PINGTA-BLE-112 [page 2147]	`The service provider name of the subscriber mapping table "{subscriberMappingTableId}" is missing.`	Add a service provider name to the subscriber mapping table. Verify your changes.
MAP-PINGTA-BLE-113 [page 2148]	`The subscriber account "{subscriberAccountId}", with service provider "{subscriberAccountServiceProviderName}", does not exist. These identifiers are provided by the subscriber mapping table "{subscriberMappingTableId}".`	Change the identifier of the subscriber account and/or the service provider. Verify your changes.
MAP-PINGTA-BLE-114 [page 2150]	`Unable to create a subscriber mapping table with an ID already used by an existing mapping table "{mappingTableId}".`	Change the subscriber mapping table identifier. Verify your changes.
MAP-PINGTA-BLE-115 [page 2151]	`Unable to create a mapping table with the same ID "{subscriberMappingTableId}" of a subscriber mapping table that already exists.`	Change the mapping table identifier. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-116 [page 2153]	`The owner "{owner}" of the mapping table class used by the subscriber mapping table does not match the subscriber account service provider name "{subscriberAccountServiceProviderName}" of the subscriber mapping table.`	Change the subscriber mapping table subscriber account service provider name. Verify your changes.
MAP-PINGTA-BLE-117 [page 2154]	`The filter is missing in the search subscriber mapping table operation.`	Add a filter to the operation. Verify your changes.
MAP-PINGTA-BLE-118 [page 2156]	`An error occurred when processing the search subscriber mapping table operation: {errorMessage}.`	Verify your changes.
MAP-PINGTA-BLE-201 [page 2157]	`The ID of the row is missing.`	Add an identifier to the row. Verify your changes.
MAP-PINGTA-BLE-202 [page 2159]	`The start date of the row "{rowId}" is missing.`	Add a start date to the row. Verify your changes.
MAP-PINGTA-BLE-203 [page 2160]	`The end date of the row "{rowId}" is missing.`	Add an end date to the row. Verify your changes.
MAP-PINGTA-BLE-204 [page 2162]	`The row "{rowId}" is empty.`	Fill in the column of the row. Verify your changes.
MAP-PINGTA-BLE-205 [page 2163]	`The column of the row "{rowId}" at index {columnIndex} has no name.`	Add a name to the column. Verify your changes.
MAP-PINGTA-BLE-206 [page 2165]	`The column "{columnName}" of the row "{rowId}" has no type.`	Add a type to the column. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-207 [page 2166]	`The column "{columnName}" of the row "{rowId}" has no string value.`	Add a string value to the column. Verify your changes.
MAP-PINGTA-BLE-208 [page 2168]	`The column "{columnName}" of the row "{rowId}" has no currency value.`	Add a currency value to the column. Verify your changes.
MAP-PINGTA-BLE-209 [page 2169]	`The column "{columnName}" of the row "{rowId}" has no number value.`	Add a number value to the column. Verify your changes.
MAP-PINGTA-BLE-210 [page 2171]	`The number of columns for the row "{rowId}" does not match with the number of columns specified in the related mapping table class.`	Modify the row to have the same number of columns than the mapping table class. Verify your changes.
MAP-PINGTA-BLE-211 [page 2172]	`The column with name "{columnName}" in the row "{rowId}" is missing.`	Add the column in the row. Verify your changes.
MAP-PINGTA-BLE-212 [page 2174]	`The column of the row "{rowId}" at index {columnIndex} has no type.`	Add a type to the column. Verify your changes.
MAP-PINGTA-BLE-213 [page 2175]	`The type of the column in the row "{rowId}" does not match with the type of the input column of the mapping table class "{inColumnName}".`	Change the type of the column. Verify your changes.
MAP-PINGTA-BLE-215 [page 2177]	`The type of the column in the row "{rowId}" does not match with the type of the output column "{outColumnName}" of the mapping table class.`	Change the type of the column. Verify your changes.
MAP-PINGTA-BLE-217 (Revoked) [page 2178]	`The list of rows is empty.`	Add at least one row in the list of the operation. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-218 [page 2180]	`The mapping table ID is null or empty.`	Add the identifier of the mapping table that owns the rows. Verify your changes.
MAP-PINGTA-BLE-219 [page 2181]	`The mapping table "{mappingTableId}" does not exist.`	Change the mapping table that owns the rows. Verify your changes.
MAP-PINGTA-BLE-220 [page 2183]	`The ID "{rowId}" of the row already exists.`	Change the identifier of the row. Verify your changes.
MAP-PINGTA-BLE-221 [page 2184]	`The list of row identifiers is null.`	Add a list of row identifiers to the operation. Verify your changes.
MAP-PINGTA-BLE-222 [page 2186]	`The list of row identifiers is empty.`	Add at least one row ID in the list of the operation. Verify your changes.
MAP-PINGTA-BLE-224 [page 2187]	`The start date and the end date of the row "{rowId}" are the same.`	Change the start date or the end date of the row. Verify your changes.
MAP-PINGTA-BLE-225 [page 2189]	`The row ID "{rowId}" is already used.`	Change the identifier of the row. Verify your changes.
MAP-PINGTA-BLE-226 [page 2190]	`The row "{rowId1}" is duplicated with the row "{rowId2}".`	Change the input values or the validity dates of the row. Verify your changes.
MAP-PINGTA-BLE-227 [page 2192]	`The mapping table row "{mappingTableRowId}" does not exist.`	Change the identifier of the row. Verify your changes.
MAP-PINGTA-BLE-228 [page 2193]	`The start date of mapping table row "{mappingTableRowId}" is after its end date.`	Change the dates of the row. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-229 [page 2195]	`The mapping table class "{mappingTableClassId}" cannot be deleted because it is referenced by at least one charge or refill logic object or pricing macro or allowance logic.`	Delete the charge(s) and/or refill logic object(s) and/or pricing macro(s) referencing the mapping table class. Verify your changes.
MAP-PINGTA-BLE-230 [page 2196]	`The mapping table "{mappingTableId}" cannot be deleted because it is referenced by at least one of the following components: charge component, refill logic, allowance logic, charge plan, refill plan, pricing macro, or provider contract.`	Delete the charge(s), refill logic object(s), allowance logic object(s), charge plan(s), refill plan(s), pricing macro(s) and/or provider contract(s) referencing the mapping table. Verify your changes.
MAP-PINGTA-BLE-231 [page 2198]	`The new row "{rowId1}" is duplicated with the existing row "{rowId2}".`	Change the input values or the validity dates of the row. Verify your changes.
MAP-PINGTA-BLE-232 [page 2199]	`The mapping table class "{mappingTableClassId}" cannot have more than 20 input columns.`	Split the existing mapping table class into several mapping table classes to respect the above limitation. Verify your changes.
MAP-PINGTA-BLE-233 [page 2201]	`The mapping table class "{mappingTableClassId}" cannot have more than 30 output columns.`	Split the existing mapping table class into several mapping table classes to respect the above limitation. Verify your changes.
MAP-PINGTA-BLE-234 [page 2202]	`The mapping table code is missing in the search mapping table row operation.`	Add the code of the mapping table to the operation request. Verify your changes.
MAP-PINGTA-BLE-235 [page 2204]	`The mapping table "{mappingTableId}" does not exist.`	Change the identifier of the mapping table. Verify your changes.
MAP-PINGTA-BLE-236 [page 2205]	`The identifier of the mapping table is missing.`	Add the code of the mapping table to the operation request. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-237 [page 2207]	`The mapping table "{mappingTableId}" does not exist.`	Change the identifier of the mapping table. Verify your changes.
MAP-PINGTA-BLE-238 [page 2208]	`The identifier of the subscriber mapping table is missing.`	Add the code of the subscriber mapping table to the operation request. Verify your changes.
MAP-PINGTA-BLE-239 [page 2210]	`The subscriber mapping table "{subscriberMappingTableId}" does not exist.`	Change the identifier of the subscriber mapping table. Verify your changes.
MAP-PINGTA-BLE-240 [page 2211]	`The CSV field delimiter must be a single character, except a double quote.`	Change the **CSV** field delimiter. Verify your changes.
MAP-PINGTA-BLE-241 [page 2213]	`The decimal separator must be a dot or a comma.`	Change the decimal separator. Verify your changes.
MAP-PINGTA-BLE-242 [page 2214]	`The thousand separator must be a dot, a comma, a single quote, a space, or empty.`	Change the separator for thousands. Verify your changes.
MAP-PINGTA-BLE-243 [page 2215]	`The decimal and thousand separators must be different.`	Change the thousand or the decimal separator. Verify your changes.
MAP-PINGTA-BLE-244 [page 2217]	`The value "{value}" cannot be formatted as a number.`	Contact your SAP Support Team. Verify your changes.
MAP-PINGTA-BLE-245 [page 2218]	`The mapping table class to modify is missing.`	Add a mapping table class to the modify operation request. Verify your changes.
MAP-PINGTA-BLE-246 [page 2220]	`Impossible to modify the mapping table class because its ID {mappingTableClassId} does not exist.`	In the operation request, change the ID of the mapping table class or determine why the mapping table class does not exist in the pricing catalog (in master data). Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-247 [page 2221]	`Impossible to modify the mapping table class "{mappingTableClassId}" because it is still used by a mapping table. Only restricted modifications are possible.`	Delete all the mapping tables that are based on and refer to this mapping table class. See the other error messages about the detailed reason. Verify your changes.
MAP-PINGTA-BLE-248 [page 2223]	`Impossible to modify the mapping table class "{mappingTableClassId}" because it is referenced by at least one charge, refill logic object, pricing macro, or allowance logic object. Only restricted modifications are possible.`	Delete all the charges, refill logic objects, pricing macros, or allowance logic objects that refer to this mapping table class. See the other error messages about the detailed reason. Verify your changes.
MAP-PINGTA-BLE-249 [page 2224]	`Impossible to modify the mapping table class "{mappingTableClassId}" because it is still used by a subscriber mapping table. Only restricted modifications are possible.`	Delete all the subscriber mapping tables that are based on and refer to this mapping table class. See the other error messages about the detailed reason. Verify your changes.
MAP-PINGTA-BLE-250 [page 2226]	`Impossible to modify the mapping table class "{mappingTableClassId}" because the specified owner {specifiedOwner} does not correspond to the owner {realOwner} already configured in the existing mapping table class.`	In the operation request, change the owner to the owner of the mapping table class or create a new mapping table class for the specified owner. Verify your changes.
MAP-PINGTA-BLE-251 [page 2227]	`In the current context of use, you cannot modify the number of input columns {specifiedInColumns}. It must equal the number of input columns {realInColumns} already configured in the existing mapping table class.`	In the operation request, correct the number of input columns or create a new mapping table class for the specified number of input columns. See the other error messages to determine your use context. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-252 [page 2229]	`In the current context of use, you cannot replace the name of the input column "{existingInColumnName}" at index {inColumnIndex} by "{operationInColumnName}".`	In the operation request, correct the name of the input column or create a new mapping table class with an input column having the specified name. See the other error messages to determine your use context. Verify your changes.
MAP-PINGTA-BLE-253 [page 2231]	`In the current context of use, you cannot modify the type of the input column at index {specifiedInColumnIndex}. It must equal the type of the input column at index {realInColumnIndex} that is already configured in the mapping table class.`	In the operation request, correct the type of the input column or create a new mapping table class for the specified input column type. See the other error messages to determine your use context. Verify your changes.
MAP-PINGTA-BLE-254 [page 2232]	`In the current context of use, you cannot modify the number of output columns {specifiedOutColumns}. It must equal the number of output columns {realOutColumns} already configured in the existing mapping table class.`	In the operation request, correct the number of output columns or create a new mapping table class for the specified number of output columns. See the other error messages to determine your use context. Verify your changes.
MAP-PINGTA-BLE-255 [page 2234]	`In the current context of use, you cannot replace the name of the output column "{existingOutColumnName}" at index {outColumnIndex} by "{operationOutColumnName}".`	In the operation request, correct the name of the output column or create a new mapping table class with an output column having the specified name. See the other error messages to determine your use context. Verify your changes.
MAP-PINGTA-BLE-256 [page 2235]	`In the current context of use, you cannot modify the type of the output column at index {specifiedOutColumnIndex}. It must equal the type of the output column at index {realOutColumnIndex} that is already configured in the mapping table class.`	In the operation request, correct the type of the output column or create a new mapping table class for the specified output column type. See the other error messages to determine your use context. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-257 [page 2237]	`You cannot modify the agreement ID "{operationAgreementId}". The agreement ID of the mapping table is "{mappingTableAgreementId}".`	Set the agreement ID to "{1}" in the operation. Verify your changes.
MAP-PINGTA-BLE-258 [page 2239]	`The agreement ID cannot be filled only with spaces.`	Change the value of the agreement ID. Verify your changes.
MAP-PINGTA-BLE-259 [page 2240]	`The version of the mapping table is null or empty.`	Add the version of the mapping table you want to search from. Verify your changes.
MAP-PINGTA-BLE-260 [page 2242]	`The mapping table class cannot contain more than one input column of type currency.`	Remove the second column of type currency or change the column type of the input column. Verify your changes.
MAP-PINGTA-BLE-262 [page 2243]	`Impossible to import the mapping table rows because the CSV contains two rows with identifier equal to "{duplicatedIdentifier}".`	1. Check the CSV content. 2. Check why two rows have the same row identifier. Several reasons are possible: the row is duplicated, one row identifier must be different. 3. Change the data to import. 4. Verify your changes.
MAP-PINGTA-BLE-263 [page 2245]	`Cannot parse the token "{csvFieldIndex}" of the mapping table row "{csvRowLine}". {errorMessageDetails}`	1. Carefully read the part of the message that details the error. This information is added by the system to the error message for troubleshooting purpose. 2. Check the CSV content. 3. Check the line indicated in the error message. In this line, check the data at the position indicated. 4. Change the CSV content. 5. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLE-264 [page 2247]	`The comment line mark must be a hash, a dollar, or empty.`	1. Check the settings of the operation request. Some information is required and was not specified. When you work with a comment line at the beginning, specify a hash ('#') or a dollar (`'$'`) character as the comment line mark. 2. Change the API call or SOAP Web Services operation consumption. 3. Verify your changes.
MAP-PINGTA-BLE-265 [page 2248]	`The value of the element "csvImportMode" must be "Merge" or "ClearAndReplace".`	1. In the operation request, check the option that was specified as a setting of the operation request. 2. Change the value of the XML element `csvImportMode`: • Use `<csvImportMode>Merge</csvImportMode>` to merge alreay-existing data with the imported data. • Use `<csvImportMode>ClearAndReplace</csvImportMode>` to erase alreay-existing data and replace it with the imported data. 3. Verify your changes.
MAP-PINGTA-BLE-266 [page 2250]	`Failed to read the CSV content representing the mapping table rows. {errorMessageDetails}`	1. Carefully read the part of the message that details the error. This information is added by the system to the error message for troubleshooting purpose. 2. Check and change the CSV content. 3. Verify your changes.
MAP-PINGTA-BLECOM-PONENT-1 [page 2252]	`The mapping table class ID is missing.`	Set the mapping table class ID. Verify your changes.
MAP-PINGTA-BLECOM-PO-NENT-2 [page 2253]	`Both mapping table ID and mapping table ID property name are missing. At least one of them must be defined.`	Set a mapping table ID or a mapping table ID property name. Verify your changes.
MAP-PINGTA-BLECOM-PO-NENT-3 [page 2255]	`Both mapping table ID and mapping table ID property name are defined. Only one of them must be defined.`	Set a mapping table ID or a mapping table ID property name. Verify your changes.

Error Code	Message	Action
MAP-PINGTA-BLECOM-PO-NENT-4 [page 2256]	`The mapping table class "{mappingTableClassId}" does not exist.`	Change the identifier of the mapping table class. Verify your changes.
MAP-PINGTA-BLECOM-PO-NENT-5 [page 2258]	`The mapping table ID defined by a charge component parameter named "{mappingTableIdPropertyName}" does not exist.`	Add a parameter in the charge component or define a mapping table ID. Verify your changes.
MAP-PINGTA-BLECOM-PO-NENT-6 [page 2259]	`The mapping table "{mappingTableId}" does not exist.`	Change the identifier of the mapping table. Verify your changes.
MAP-PINGTA-BLECOM-PONENT-7 [page 2261]	`The mapping table class "{mappingTableClassIdFromParameter}" referenced in the parameter "{parameterName}" does not correspond to the mapping table class "{mappingTableClassIdFromRateComponent}" defined in the rate component.`	Set up the same mapping table class in the parameter and in the component. Verify your changes.
MAP-PINGTA-BLECOM-PO-NENT-8 [page 2262]	`The mapping table class "{mappingTableClassIdFromParameter}" from range table "{parameterName}" does not correspond to the mapping table class "{mappingTableClassIdFromRateComponent}" defined in the rate component.`	Set up the same mapping table class in the parameter and in the component. Verify your changes.
MAP-PINGTA-BLECOM-PO-NENT-9 [page 2264]	`The rating context property "{mappingTableIdPropertyName}" defining a mapping table ID does not include the mandatory additional information "{addInfoName}".`	Add the additional information to this property specified in the logic component. Verify your changes.

Error Code	Message	Action
MAPPINGTABLECOMPONENT-10 [page 2265]	`The index of the input column that represents the prefix is lower than 0 or greater than the number of input columns minus 1.`	Select an index that ranges from 0 to the number of input columns minus 1. Verify your changes.
MAPPINGTABLECOMPONENT-11 [page 2267]	`Component "{component}" invokes a mapping table of class "{mappingTableClass}" with {actualKeyCount} keys instead of {expectedKeyCount}.`	Match the number of input columns of the mapping table class and the number of key(s) provided by the component. Verify your changes.
MAPPINGTABLECOMPONENT-12 [page 2269]	`Component "{component}" references a mapping table of class "{mappingTableClass}" and expects {mappedValueCount} output value(s) instead of {generatedValueCount}.`	Match the number of outputs columns of the mapping table and the number of values expected by the component. Verify your changes.
MAPPINGTABLECOMPONENT-13 [page 2271]	`The component cannot reference the mapping table "{mappingTable}" because this mapping table has an agreement ID.`	Select a mapping table without agreement ID. Verify your changes.
MONITORING-PLAN-1 [page 2272]	`The ID of the monitoring plan is missing.`	Add an ID to the monitoring plan. Verify your changes.
MONITORING-PLAN-2 [page 2274]	`The owner of the monitoring plan "{monitoringPlanId}" is missing.`	Add an owner to the monitoring plan. Verify your changes.
MONITORING-PLAN-3 [page 2275]	`The description of the monitoring plan "{monitoringPlanId}" is missing.`	Add a description to the monitoring plan. Verify your changes.
MONITORING-PLAN-4 [page 2277]	`The status of the monitoring plan "{monitoringPlanId}" is missing.`	Add a status to the monitoring plan. Verify your changes.

Error Code	Message	Action
MONITORING-PLAN-5 [page 2278]	`The monitoring plan "{monitoringPlanId}" must at least declare one spending status mapping.`	Add at least one spending status mapping that configures the generation of a spending status. Verify your changes.
MONITORING-PLAN-6 [page 2280]	`The ID of the spending status description in the spending status mapping at index {spendingStatusMappingIndex} is missing.`	Add a spending status description ID to the spending status mapping. Verify your changes.
MONITORING-PLAN-7 [page 2281]	`The ID "{spendingStatusDescriptionId}" of the spending status description in the spending status mapping at index {spendingStatusMappingIndex} is unknown.`	Specify the ID of an existing spending status description to the spending status mapping. Verify your changes.
MONITORING-PLAN-8 [page 2283]	`The ID "{spendingStatusDescriptionId}" of the spending status description in the spending status mapping at index {secondIndex} is already used by the spending status mapping at index {firstIndex}.`	Specify another ID of the spending status description in the spending status mapping. Verify your changes.
MONITORING-PLAN-9 [page 2284]	`The name of the counter in the spending status mapping at index {spendingStatusMappingIndex} is missing.`	Specify a counter name from the counter name dictionary to the spending status mapping. Verify your changes.
MONITORING-PLAN-10 [page 2286]	`The name "{counterName}" of the counter in the spending status mapping at index {spendingStatusMappingIndex} is unknown in the counter name dictionary.`	Specify an existing counter name to the spending status mapping. Verify your changes.
MONITORING-PLAN-11 [page 2287]	`The name of the parameter in the spending status mapping at index {spendingStatusMappingIndex} is missing.`	Specify the relevant parameter name to the spending status mapping. Verify your changes.

Error Code	Message	Action
MONITORING-PLAN-12 [page 2289]	`The parameter name "{parameterTargetName}" in the spending status mapping at index {spendingStatusMappingIndex} is unknown.`	Specify the name of an existing parameter to the spending status mapping. Verify your changes.
MONITORING-PLAN-13 [page 2290]	`The parameter "{parameterName}" at index {parameterIndex} in the monitoring plan is not used in a spending status mapping.`	Link the parameter or remove it from the monitoring plan. Verify your changes.
MONITORING-PLAN-14 [page 2292]	`The monitoring plan is missing in the create operation.`	Specify a monitoring plan in the create operation request. Verify your changes.
MONITORING-PLAN-15 [page 2293]	`Cannot create the monitoring plan: The monitoring plan "{monitoringPlanId}" already exists.`	Specify another monitoring plan in the create operation request. Verify your changes.
MONITORING-PLAN-16 [page 2295]	`The monitoring plan is missing in the modify operation.`	Specify a monitoring plan to the modify operation request. Verify your changes.
MONITORING-PLAN-17 [page 2296]	`The monitoring plan "{monitoringPlanId}" does not exist.`	Specify another monitoring plan to the modify operation request. Verify your changes.
MONITORING-PLAN-18 [page 2298]	`The mandatory filter is missing in the search operation.`	Specify a filter in the search operation request. Verify your changes.

Error Code	Message	Action
MONITORING-PLAN-19 [page 2299]	`An unknown error occurred during the execution of the monitoring plan search operation: {reasonInformation}`	Check the reason information recorded in your error message. The reason is based on the Java Technology. It details the exception raised in the connected SAP CC system. Typical reasons are: Invalid search filter, Back-end database failure. Refer to the Java/XML API Reference (Core Library) documentation for more information about the com.highdeal.filter.hci.InvalidSearchException. Verify your changes.
MONITORING-PLAN-20 [page 2301]	`The ID of the monitoring plan is missing in the delete operation.`	Specify the relevant monitoring plan ID in the delete operation request. Verify your changes.
MONITORING-PLAN-21 [page 2302]	`Cannot delete the monitoring plan: The monitoring plan "{monitoringPlanId}" does not exist.`	Specify another ID of monitoring plan to the delete operation request. Verify your changes.
MONITORING-PLAN-22 [page 2304]	`Error while deleting the monitoring plan "{monitoringPlanId}". The monitoring plan is still activated in one provider contract.`	First delete all contract items referencing the monitoring plan. Verify your changes.
MONITORING-PLAN-23 [page 2305]	`The monitoring plan "{monitoringPlanId}" cannot be modified because the specified owner {specifiedOwner} does not correspond to the owner {realOwner} existing in the monitoring plan.`	Change the owner to the owner of the monitoring plan or create a new monitoring plan for the specified owner. Verify your changes.
MONITORING-PLAN-24 [page 2307]	`The status of already released monitoring plan "{monitoringPlanId}" cannot be set back to open.`	Set the status of this new monitoring plan to released or obsolete. Verify your changes.
MONITORING-PLAN-25 [page 2308]	`The status of already obsolete monitoring plan "{monitoringPlanId}" cannot be set back to open.`	Set the status of this new monitoring plan to released or obsolete. Verify your changes.

Error Code	Message	Action
MONITORING-PLAN-26 [page 2310]	`The status of already obsolete monitoring plan "{monitoringPlanId}" cannot be set back to released.`	Set the status of this new monitoring plan to released or obsolete. Verify your changes.
MONITORING-PLAN-27 [page 2311]	`The text description of the monitoring plan "{monitoringPlanId}" cannot be modified because the monitoring plan has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-28 [page 2313]	`The additional information "{additionalInformationName}" cannot be removed because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-29 [page 2314]	`The additional information "{additionalInformationName}" cannot be added because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-30 [page 2316]	`The description of the additional information "{additionalInformationName}" cannot be modified because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-31 [page 2317]	`The type of the additional information "{additionalInformationName}" cannot be modified because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.

Error Code	Message	Action
MONITORING-PLAN-32 [page 2319]	`The date value of the additional information "{additionalInformationName}" cannot be modified because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-33 [page 2321]	`The number value of the additional information "{additionalInformationName}" cannot be modified because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-34 [page 2322]	`The string value of the additional information "{additionalInformationName}" cannot be modified because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-35 [page 2324]	`The user technical identifier "{userTechIdName}" cannot be removed because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-36 [page 2325]	`The user technical identifier "{userTechIdName}" cannot be added because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-37 [page 2327]	`The description of the user technical identifier "{userTechIdName}" cannot be modified because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.

Error Code	Message	Action
MONITORING-PLAN-38 [page 2328]	`The parameter "{parameterName}" cannot be removed because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-39 [page 2330]	`The parameter "{parameterName}" cannot be added because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-40 [page 2331]	`The description of the parameter "{parameterName}" cannot be modified because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-41 [page 2333]	`The string value of the parameter "{parameterName}" cannot be modified because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-42 [page 2335]	`The spending status mapping "{spendingStatusDescriptionId}" cannot be removed because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-43 [page 2336]	`The spending status mapping "{spendingStatusDescriptionId}" cannot be added because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-44 [page 2338]	`The name of the counter in the spending status mapping "{spendingStatusDescriptionId}" cannot be changed because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.

Error Code	Message	Action
MONITORING-PLAN-45 [page 2339]	`The parameter name in the spending status mapping "{spendingStatusDescriptionId}" cannot be changed because the monitoring plan "{monitoringPlanId}" has been released or is obsolete.`	Create a new monitoring plan. Verify your changes.
MONITORING-PLAN-46 [page 2341]	`The status of new monitoring plan "{monitoringPlanId}" must be open.`	Set the status of this new monitoring plan to open. Verify your changes.
MONITORING-PLAN-47 [page 2343]	`Error(s) while validating the monitoring plan "{monitoringPlanId}".`	Check the nested errors in the error stack. Verify your changes.
MONITORING-PLAN-48 [page 2344]	`The name "{counterName}" of the counter in the spending status mapping at index {secondIndex} is already used by the spending status mapping at index {firstIndex}.`	Change the name of the counter in the relevant spending status mapping. Verify your changes.
MONITORING-PLAN-49 [page 2346]	`The parameter name "{parameterTargetName}" in the spending status mapping at index {secondIndex} is already used by the spending status mapping at index {firstIndex}.`	Change the parameter name in the spending status mapping. Verify your changes.
MONITORING-PLAN-50 [page 2347]	`The Parameter at index {parameterIndex} is empty.`	Replace it by a valid Parameter or remove it. Verify your changes.
MONITORING-PLAN-51 [page 2349]	`The name of the Parameter at index {parameterIndex} is missing.`	Add a name to the Parameter. Verify your changes.
MONITORING-PLAN-52 [page 2350]	`The name "{parameterName}" of the Parameter at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter. Verify your changes.

Error Code	Message	Action
MONITORING-PLAN-53 [page 2352]	`The type of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown (the only supported type is string).`	Add a type to the Parameter or change it to the only supported one: string. Verify your changes.
MONITORING-PLAN-54 [page 2353]	`The description of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a description to the Parameter. Verify your changes.
MONITORING-PLAN-55 [page 2355]	`The value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a value to the Parameter. Verify your changes.
MONITORING-PLAN-56 [page 2356]	`Error while validating the Parameter "{parameterName}" at index {parameterIndex}.`	Verify your changes.
MONITORING-PLAN-57 [page 2358]	`The Parameter additional information "{additionalInformationName}" at index {additionalInformationIndex} is unknown.`	Remove this additional information or replace it with a known one. Verify your changes.
MONITORING-PLAN-58 [page 2359]	`The data type of the Parameter is missing or unknown (the only supported type is rangeTableId).`	Add a data type to the Parameter or change it to the only supported one: rangeTableId. Verify your changes.
MONITORING-PLAN-59 [page 2361]	`The Parameter is a Range Table ID but no Range Table Class is defined.`	Add the Range Table Class additional information. Verify your changes.
MONITORING-PLAN-60 [page 2362]	`The Parameter points to an unknown Range Table Class "{rangeTableClassId}".`	Change the value to a known Range Table Class. Verify your changes.

Error Code	Message	Action
MONITORING-PLAN-61 [page 2364]	`The Parameter points to the Range Table Class "{rangeTableClassId}" which does not have a single output column of type string.`	Change the value to a Range Table Class with a single output column of type string. Verify your changes.
MONITORING-PLAN-62 [page 2365]	`The Parameter points to an unknown Range Table "{rangeTableId}".`	Change the value to a known Range Table. Verify your changes.
MONITORING-PLAN-63 [page 2367]	`The Parameter points to the Range Table "{rangeTableId}" which is not an instance of the previously defined Range Table Class "{rangeTableClassId}".`	Change the value to a Range Table which is an instance of the previously defined Range Table Class. Verify your changes.
MONITORING-PLAN-64 [page 2368]	`The parameter cannot reference the range table "{parameterValue}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.
OPERATIONAL-STATUS-1 [page 2370]	`The process cannot access the contract with the ID "{chargingContractId}" because the operational status of the contract is not set to active.`	If the contract is locked, set its operational status to active and launch the process again. If the contract is closed, the process cannot access it. Verify your changes.
OPERATIONAL-STATUS-2 [page 2371]	`The string entered as rootChargingContractId is empty.`	Enter a string that is not empty. Verify your changes.
OPERATIONAL-STATUS-3 [page 2373]	`The contract does not exist.`	Enter a rootChargingContractId corresponding to an existing contract. Verify your changes.
OPERATIONAL-STATUS-4 [page 2374]	`The operational status of the contract cannot be modified because the contract is a linked charging contract.`	Modify the operational status of the root charging contract corresponding to this linked charging contract. Verify your changes.

Error Code	Message	Action
OPERATIONAL-STATUS-5 [page 2376]	`The operational status of the contract is empty.`	Contact your SAP Support Team. Verify your changes.
OPERATIONAL-STATUS-6 [page 2377]	`The operational status of the contract cannot be changed because it is used for a rerating or a recharging session.`	Wait until the rerating session is completed. Verify your changes.
OPERATIONAL-STATUS-7 [page 2379]	`The contract cannot be closed because its operational status is set to active.`	Set the operational status of the contract to locked first, and then set it to closed. Verify your changes.
OPERATIONAL-STATUS-8 [page 2380]	`The linked contract with the ID "{chargingContractId}" cannot be modified because its root contract is locked or closed.`	Set the operational status of the root contract to active first, and then perform the modification. Verify your changes.
OPERATIONAL-STATUS-9 [page 2382]	`The root charging contract with the ID "{chargingContractId}" cannot be modified because its operational status is set to locked or closed.`	Set the operational status of the root charging contract to active first, and then modify the root charging contract. Verify your changes.
OPERATIONAL-STATUS-10 [page 2383]	`The charging contract with the ID "{chargingContractId}" cannot be deleted because its operational status is set to locked.`	Set the operational status of the corresponding root charging contract to active or closed first, and then delete the charging contract. Verify your changes.
OPERATIONAL-STATUS-11 [page 2385]	`The linked charging contract cannot be created because the operational status of the root charging contract with the ID "{chargingContractId}" is not set to active.`	Set the operational status of the root charging contract to active first, and then create the linked charging contract. Verify your changes.
OPERATIONAL-STATUS-12 [page 2386]	`The operational status of the root charging contract with the ID "{chargingContractId}" cannot be changed because it is set to closed.`	Create a new root charging contract or export it and re-create it. Verify your changes.

Error Code	Message	Action
PREPAI-DAC-COUNT-STATE-1 [page 2388]	`The prepaid account ID is missing in the prepaid account reference specified in the operation request.`	Specify a prepaid account identifier in the prepaid account reference. Verify your changes.
PREPAI-DAC-COUNT-STATE-2 [page 2389]	`The subscriber account ID is missing in the prepaid account reference specified in the operation request.`	Specify a prepaid account identifier in the prepaid account reference. Verify your changes.
PREPAI-DAC-COUNT-STATE-3 [page 2391]	`The amount is missing in the operation request.`	Specify the amount in the operation operation. Verify your changes.
PREPAI-DAC-COUNT-STATE-4 [page 2392]	`The amount value is missing in the operation request.`	Specify the amount value in the operation request. Verify your changes.
PREPAI-DAC-COUNT-STATE-5 [page 2394]	`The subscriber account "{subscriberAccountId}" specified in the operation request does not exist.`	Change the subscriber account ID to an existing subscriber account. Verify your changes.
PREPAI-DAC-COUNT-STATE-6 [page 2395]	`The prepaid account "{prepaidAccountId}" does not exist in the subscriber account "{subscriberAccountId}".`	Check that the prepaid account ID belongs to this subscriber account or determine another prepaid account or another subscriber account. Verify your changes.
PREPAI-DAC-COUNT-STATE-7 [page 2397]	`The currency code "{prepaidAccountStateCurrencyCode}" specified in the operation request does not correspond to the currency code "{prepaidAccountCurrencyCode}" of the balance of the prepaid account.`	Change the currency in the operation request to the currency of the balance of the prepaid acccount. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-1 [page 2398]	`The ID of the range table class is missing.`	Add an ID to the range table class. Verify your changes.
RANGET-ABLE-2 [page 2400]	`The owner of the range table class is missing.`	Add an owner to the range table class. Verify your changes.
RANGET-ABLE-3 [page 2401]	`The description of the range table class is missing.`	Add a description to the range table class. Verify your changes.
RANGET-ABLE-4 [page 2403]	`The range table class must declare the range upper bound.`	Set the range upper bound. Verify your changes.
RANGET-ABLE-5 [page 2404]	`The range table class must at least declare one output column.`	Add at least one output column. Verify your changes.
RANGET-ABLE-6 [page 2406]	`The range table class must have less than {outColumnMax} output columns.`	Delete output columns to have a count of output column underneath the maximum. Verify your changes.
RANGET-ABLE-7 [page 2407]	`Error while validating the range table class "{rangeTableClassId}".`	Verify your changes.
RANGET-ABLE-8 [page 2409]	`The name of the output column at index {outColumnIndex} is missing.`	Add a name to the output column. Verify your changes.
RANGET-ABLE-9 [page 2410]	`The description of output column at index {outColumnIndex} is missing.`	Add a description to the output column. Verify your changes.
RANGET-ABLE-10 [page 2412]	`The type of the output column at index {outColumnIndex} is missing.`	Add a type to the output column.Add a type to the output column. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-11 [page 2413]	`The column name "{columnName}" is duplicated in the range table class.`	Change the name of the column. Verify your changes.
RANGET-ABLE-12 [page 2415]	`The ID of the range table class is missing.`	Add the ID of the range table class to delete operation. Verify your changes.
RANGET-ABLE-13 [page 2416]	`Impossible to remove the range table class because its ID "{rangeTableClassId}" does not exist.`	Change the ID of the range table class. Verify your changes.
RANGET-ABLE-14 [page 2418]	`The filter is missing in the search range table class operation.`	Add a filter to the operation. Verify your changes.
RANGET-ABLE-15 [page 2419]	`An error occurred during the search range table class execution: {errorMessage}.`	Verify your changes.
RANGET-ABLE-16 [page 2420]	`Impossible to create the range table class because its ID {rangeTableClassId} already exists.`	Change the ID of the range table class. Verify your changes.
RANGET-ABLE-17 [page 2422]	`The range table class to create is missing.`	Add a range table class to the create operation. Verify your changes.
RANGET-ABLE-18 [page 2423]	`The range table class to modify is missing.`	Add a range table class to the modify operation. Verify your changes.
RANGET-ABLE-19 [page 2425]	`Impossible to modify the range table class because its ID {rangeTableClassId} does not exist.`	Change the ID of the range table class. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-20 [page 2426]	`Impossible to modify the range table class "{rangeTableClassId}" because the specified owner {specifiedOwner} does not correspond to the owner {realOwner} existing in the range table class.`	Change the owner to the owner of the range table class or create a new range table class for the specified owner. Verify your changes.
RANGET-ABLE-21 [page 2428]	`Impossible to remove the range table class "{rangeTableClassId}" because it is still used by a range table.`	Delete all the subscriber range tables and all the range tables that relate to this range table class. Verify your changes.
RANGET-ABLE-22 [page 2429]	`Impossible to modify the range table class because the specified range upper bound value "{specifiedRangeUpperBound}" does not correspond to the range upper bound value "{realRangeUpperBound}" existing in the range table class.`	Change the range upper bound value to the range upper bound value of the range table class or create a new range table class for the specified range upper bound value. Verify your changes.
RANGET-ABLE-23 [page 2431]	`Impossible to modify the range table class because the number of output column(s) {specifiedOutColumns} does not correspond to the number of output column(s) {realOutColumns} existing in the range table class.`	Change the number of output column(s) to the number of output column(s) of the range table class or create a new range table class for the specified output column(s). Verify your changes.
RANGET-ABLE-24 [page 2432]	`Impossible to remove the range table class "{rangeTableClassId}" because it is still used by a subscriber range table.`	Delete all the subscriber range tables and all the range tables that relate to this range table class. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-25 [page 2434]	`Impossible to modify the range table class because the name of the output column at index {specifiedOutColumnIndex} does not correspond to the name of the output column at index {realOutColumnIndex} existing in the range table class.`	Change the name of the output column to the name of the output column of the range table class or create a new range table class for the specified output column name. Verify your changes.
RANGET-ABLE-26 [page 2435]	`Impossible to modify the range table class because the type of the output column at index {specifiedOutColumnIndex} does not correspond to the type of the output column at index {realOutColumnIndex} existing in the range table class.`	Change the type of the output column to the type of the output column of the range table class or create a new range table class for the specified output column type. Verify your changes.
RANGET-ABLE-27 [page 2437]	`The range table class has an owner "{rangeTableClassOwner}" with no catalog.`	Change the owner of the range table class to a catalog owner or create the catalog owner. Verify your changes.
RANGET-ABLE-28 [page 2439]	`The range table class must declare the last range type.`	Set the last range type. Verify your changes.
RANGET-ABLE-29 [page 2440]	`Impossible to modify the range table class because the specified last range type "{specifiedLastRangeType}" does not correspond to the last range type "{realLastRangeType}" existing in the range table class.`	Change the last range type to the last range type of the range table class or create a new range table class for the specified last range type. Verify your changes.
RANGET-ABLE-30 [page 2442]	`Impossible to modify the range table class "{rangeTableClassId}" because it is referenced by a range table, a charge, a refill logic, an allowance logic object or a pricing macro.`	Create a new range table class of remove all the objects that refer to this class. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-107 [page 2443]	`The ID of the range table to delete is missing.`	Add the identifier of the range table to the delete operation. Verify your changes.
RANGET-ABLE-108 [page 2445]	`The range table "{rangeTableId}" does not exist.`	Change the identifier of the range table. Verify your changes.
RANGET-ABLE-109 [page 2446]	`The filter is missing in the search range table operation.`	Add a filter to the operation. Verify your changes.
RANGET-ABLE-110 [page 2448]	`An error occurred when processing the search range table operation: {errorMessage}`	Check the error stack and the linked errors. Verify your changes.
RANGET-ABLE-111 [page 2449]	`The filter is missing in the search subscriber range table operation.`	Add a filter to the operation. Verify your changes.
RANGET-ABLE-112 [page 2451]	`An error occurred during the search subscriber range table execution: {errorMessage}.`	Verify your changes.
RANGET-ABLE-120 [page 2452]	`The range table revision is missing.`	Add a range table revision in the create operation. Verify your changes.
RANGET-ABLE-121 [page 2454]	`The revision for range table "{rangeTableId}" is not valid.`	Add a valid range table revision in the create operation. Verify your changes.
RANGET-ABLE-122 [page 2455]	`The range table ID is missing.`	Set the range table identifier in the range table revision. Verify your changes.
RANGET-ABLE-123 [page 2457]	`The range table rows or range sets are missing.`	Add at least one row or range set to the range table revision. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-126 [page 2458]	`The range table row #{rangeTableRowIndex} is not valid.`	Check the linked error. Verify your changes.
RANGET-ABLE-128 [page 2460]	`The range table "{rangeTableId}" already exists in the SAP CC system.` `The creation with this ID is not possible.`	In the range table revision of the create operation, set a new range table ID. Verify your changes.
RANGET-ABLE-129 [page 2461]	`The subscriber range table "{subscriberRangeTableId}" already exists in the SAP CC system. The creation with this ID is not possible.`	In the range table revision of the create operation, set a new range table ID. Verify your changes.
RANGET-ABLE-130 [page 2463]	`The range table class ID is missing.`	Set the range table class ID. Verify your changes.
RANGET-ABLE-131 [page 2464]	`The range table class ID "{rangeTableClassId}" is not valid. It does not correspond to a range table class.`	Set the ID of an existing range table class. Verify your changes.
RANGET-ABLE-132 [page 2466]	`The rows or the ranges at indexes #{firstIndexWoUpperBound} and #{secondIndexWoUpperBound} have no upper bound.`	Set an upper bound in one of the rows or the ranges. Verify your changes.
RANGET-ABLE-133 [page 2467]	`The rows or the ranges at indexes #{firstIndexSameUpperBound} and #{secondIndexSameUpperBound} must not have the same upper bound "{upperBound}".`	Change the upper bound for one of the rows or the ranges. Verify your changes.
RANGET-ABLE-134 [page 2469]	`The upper bound value is not valid. It must be strictly positive.`	Change the upper bound to a positive value. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-135 [page 2470]	`Require {columnCountRequired} range table columns. See the range table class "{rangeTableClassId}".`	Add or remove a column. Verify your changes.
RANGET-ABLE-136 [page 2472]	`The range table column #{rangeTableColumnIndex} is not valid.`	Check the linked error. Verify your changes.
RANGET-ABLE-137 [page 2473]	`The column name "{rangeTableColumnName}" is not a column name of the range table class "{rangeTableClassId}".`	Choose a column name from the corresponding range table class. Verify your changes.
RANGET-ABLE-138 [page 2475]	`The type of the column is not valid. Replace it with "{expectedRangeTableColumnType}".`	Change the type of the column. Set the type that is defined in the range table class. Verify your changes.
RANGET-ABLE-139 [page 2476]	`The type of the column is not valid. Replace it with "{expectedRangeTableColumnType}".`	Change the type of the column. Set the type that is defined in the range table class. Verify your changes.
RANGET-ABLE-140 [page 2478]	`The column name is missing.`	Add a name to the column. Verify your changes.
RANGET-ABLE-141 [page 2479]	`The column type is missing.`	Add a type to the column. Verify your changes.
RANGET-ABLE-142 [page 2481]	`The number value of the column is missing.`	Add a number value to the column. Verify your changes.
RANGET-ABLE-143 [page 2482]	`The string value of the column is missing.`	Add a string value to the column. Verify your changes.
RANGET-ABLE-146 [page 2485]	`The modification date is missing.`	Add a modification date in the modify operation. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-147 [page 2487]	`Unable to modify the subscriber range table "{subscriberRangeTableId}" with an operation that modifies a range table from a pricing catalog.`	Implement the appropriate operation that modifies subscriber range tables. Verify your changes.
RANGET-ABLE-148 [page 2488]	`Unable to modify the range table "{rangeTableId}" because it does not exist.`	Use an ID of an existing range table to modify it. Verify your changes.
RANGET-ABLE-149 [page 2490]	`In the modify operation, the range table class ID "{rangeTableClassIdFromRevision}" from the revision "{rangeTableId}" does not correspond to the range table class ID from the SAP CC system "{rangeTableClassIdFromSystem}".`	Set the correct ID of the range table class or let it empty. Verify your changes.
RANGET-ABLE-150 [page 2491]	`The columns #{firstColumnIndex} and #{secondColumnIndex} have the same name "{columnName}".`	Change the name of one of both or remove one. Verify your changes.
RANGET-ABLE-151 [page 2493]	`The create operation of a range table is not valid.`	Check the linked error. Verify your changes.
RANGET-ABLE-152 [page 2494]	`The modify operation of range table is not valid.`	Check the linked error. Verify your changes.
RANGET-ABLE-153 [page 2496]	`Unable to modify the range table "{catalogRangeTableId}" from pricing catalog with an operation that modifies subscriber range tables.`	Implement the appropriate operation that modifies a range table of a pricing catalog. Verify your changes.
RANGET-ABLE-154 [page 2497]	`The subscriber range table "{subscriberRangeTableId}" does not exist.`	Use an ID of an existing subscriber range table to modify it. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-155 [page 2499]	`The create operation of subscriber range table is not valid.`	Check the linked error. Verify your changes.
RANGET-ABLE-156 [page 2500]	`The subscriber account ID is missing.`	Set the identifier of the subscriber account. Verify your changes.
RANGET-ABLE-157 [page 2502]	`The service provider name is missing.`	Set the name of the service provider. Verify your changes.
RANGET-ABLE-158 [page 2503]	`The couple subscriber account ID "{subscriberAccountId}" and service provider "{serviceProviderName}" does not correspond to a subscriber account.`	Check the identifier of the subscriber account. Verify your changes.
RANGET-ABLE-159 [page 2505]	`The modify operation of subscriber range table is not valid.`	Check the linked error. Verify your changes.
RANGET-ABLE-160 [page 2506]	`The subscriber account ID "{subscriberAccountId}" is not valid. It should be "{initialSubscriberAccountId}" .`	Change the identifier of the subscriber account. Verify your changes.
RANGET-ABLE-161 [page 2508]	`The service provider name "{subscriberAccountServiceProviderName}" is not valid. It should be "{initialSubscriberAccountServiceProviderName}".`	Change the service provider name. Verify your changes.
RANGET-ABLE-162 [page 2509]	`The range table row or the range #{unboundedIndex} has no upper bound. The range table class requires a bounded last range.`	Add an upper bound to the row or to the range. Verify your changes.
RANGET-ABLE-163 [page 2511]	`The range table is not unbounded. The range table class requires unbounded only tables.`	Set a row or a range without upper bound value. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-229 [page 2512]	`The range table class "{rangeTableClassId}" cannot be deleted because it is referenced by at least one charge or refill logic, an allowance logic object or pricing macro.`	Delete the charge(s) and/or refill logic object(s) and/or pricing macro(s) referencing the range table class. Verify your changes.
RANGET-ABLE-230 [page 2514]	`The range table "{rangeTableId}" cannot be deleted because it is referenced by at least one of the following components: charge component, refill logic, allowance logic, charge plan, refill plan, pricing macro, or provider contract.`	Delete the charge(s), refill logic object(s), allowance logic object(s), charge plan(s), refill plan(s), pricing macro(s) and/or provider contract(s) referencing the range table. Verify your changes.
RANGET-ABLE-231 [page 2515]	`The range table class must have less than {inColumnMax} input columns.`	Delete the additional input columns. Verify your changes.
RANGET-ABLE-232 [page 2517]	`The name of the input column at index {inColumnIndex} is missing.`	Add a name to the input column. Verify your changes.
RANGET-ABLE-233 [page 2518]	`The description of the input column at index {inColumnIndex} is missing.`	Add a description to the input column. Verify your changes.
RANGET-ABLE-234 [page 2520]	`Impossible to modify the range table class because the number of input columns {specifiedInColumns} does not correspond to the number of input columns {realInColumns} existing in the range table class.`	Change the number of input columns to the number of input columns of the range table class or create a new range table class for the specified input columns. Verify your changes.
RANGET-ABLE-235 [page 2521]	`You cannot replace the name of the input column "{existingInColumnName}" at index {inColumnIndex} by "{operationInColumnName}".`	Change the name of the input column in the operation or create a new range table class with an input column having the specified name. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-236 [page 2523]	`The type of the input column is not valid. Only the type "{expectedRangeTableColumnType}" is allowed.`	Change the type of the column. Verify your changes.
RANGET-ABLE-237 [page 2524]	`All the rows or range sets with the input values {rangeTableInputValues} have an upper bound. Because the range table class is unbounded, one row or range set for those input values must be unbounded.`	Set a row or range set without upper bound. Verify your changes.
RANGET-ABLE-238 [page 2526]	`The ID of the range table is missing in the maintain range set operation.`	Add the ID of the range table to the maintain operation. Verify your changes.
RANGET-ABLE-239 [page 2527]	`The range table with the ID "{rangeTableId}" given in the maintain operation does not exist.`	Use the ID of an existing range table in the maintain operation. Verify your changes.
RANGET-ABLE-240 [page 2529]	`The ID of the range table is missing in the delete range set operation.`	Add the ID of the range table to the delete operation. Verify your changes.
RANGET-ABLE-241 [page 2530]	`The range table with the ID "{rangeTableId}" given in the delete operation does not exist.`	Use the ID of an existing range table in the delete operation. Verify your changes.
RANGET-ABLE-242 [page 2532]	`The range sets are missing.`	Add at least one range set to the operation. Verify your changes.
RANGET-ABLE-243 [page 2533]	`The number of input columns {inputColumnNbOp} does not correspond to the number of input columns {inputColumnNbClass} declared in the range table class.`	Change the number of input columns. Verify your changes.
RANGET-ABLE-244 [page 2535]	`The range set #{rangeSetIndex} is not valid.`	Check the linked error. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-245 [page 2536]	`The input column "{inputColumnName}" is missing.`	Check the name of the input columns declared in the range table class. Verify your changes.
RANGET-ABLE-246 [page 2538]	`The range #{rangeIndex} is not valid.`	Check the linked error. Verify your changes.
RANGET-ABLE-247 [page 2539]	`The ranges are missing in the range set.`	Add at least one range to the range set. Verify your changes.
RANGET-ABLE-248 [page 2541]	`The range set key #{rangeSetKeyIndex} is not valid.`	Check the linked error. Verify your changes.
RANGET-ABLE-249 [page 2542]	`The range set key is missing in the range set.`	Add a key to the range set. Verify your changes.
RANGET-ABLE-250 [page 2544]	`The value of the input column #{inputColumnName} is missing.`	Add a value to the input column. Verify your changes.
RANGET-ABLE-251 [page 2545]	`The range sets #{firstRangeSetIndex} and #{secondRangeSetIndex} must not have the same range set key "{rangeSetKey}".`	Change the range set key for one of both. Verify your changes.
RANGET-ABLE-252 [page 2547]	`The range set keys are missing.`	Add at least one range set key to the operation. Verify your changes.
RANGET-ABLE-253 [page 2548]	`You cannot delete all the range sets of a period.`	Consider modifying the range table. Verify your changes.
RANGET-ABLE-254 [page 2549]	`You cannot modify the agreement ID "{operationAgreementId}". The agreement ID of the range table is "{rangeTableAgreementId}".`	1. In the operation request, change the agreement ID to the value "{rangeTableAgreementId}" that is indicated in the error message. 2. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-255 [page 2551]	`The agreement ID cannot be filled only with spaces.`	Change the value of the agreement ID. Verify your changes.
RANGET-ABLE-256 [page 2553]	`You cannot set rows and range sets simultaneously in the range table revision.`	Set rows or range sets in the range table revision. Verify your changes.
RANGET-ABLE-257 [page 2554]	`Impossible to modify the range table "{rangeTableId}" because the specified owner {specifiedOwner} does not correspond to the owner {actualOwner} already configured in the existing range table.`	In the operation request, change the owner to the owner of the range table or create a new range table for the specified owner. Verify your changes.
RANGET-ABLE-258 [page 2556]	`The range table identifier is missing.`	1. Check the settings of the operation request. Some information is required and was not specified. 2. Change the API call or SOAP Web Services operation consumption. 3. Verify your changes.
RANGET-ABLE-259 [page 2557]	`The comment line mark must be a hash, a dollar, or empty.`	1. Check the settings of the operation request. Some information is required and was not specified. When you work with a comment line at the beginning, specify a hash ('#') or a dollar (`'$'`) character as the comment line mark. 2. Change the API call or SOAP Web Services operation consumption. 3. Verify your changes.
RANGET-ABLE-260 [page 2559]	`The field delimiter must be a single character, except a double quote.`	1. Check the settings of the operation request. Some required information is wrong. The field delimiter must be a single character. **Note** In the operation request, you cannot specify a double quote as a field delimiter. 2. Change the API call or SOAP Web Services operation consumption. 3. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-261 [page 2561]	`The decimal separator must be a dot or a comma.`	1. Check the settings of the operation request. Some required information is wrong. The decimal separator must be a dot ('.') or a comma (',') character. **Note** In the operation request, specify a valid decimal separator. 2. Change the API call or SOAP Web Services operation consumption. 3. Verify your changes.
RANGET-ABLE-262 [page 2562]	`The field separator must not be the same as the decimal separator.`	1. In the operation request, the CSV field separator and the decimal separator cannot be the same. The specified separators must be different to be able to process the CSV content. 2. Check the CSV field separator and the decimal separator that are specified in the operation request. Compare with the data in the CSV content. 3. Change one of these separators in the operation request. 4. Verify your changes.
RANGET-ABLE-263 [page 2564]	`The thousand separator must be a dot, a comma, a single quote, a space, or empty.`	1. Check the settings of the operation request. Some required information is wrong. The thousand separator must be one of the following: • A dot ('.') • A comma (',') • A single quote ('') • A space character (' ') • Empty In the operation request, specify a valid thousand separator. 2. Change the API call or SOAP Web Services operation consumption. 3. Verify your changes.

Error Code	Message	Action
RANGET-ABLE-264 [page 2566]	`The decimal separator must not be the same as the thousand separator.`	1. In the operation request, the decimal separator and the thousand separator cannot be the same. The specified separators must be different to be able to process the CSV content. 2. Check the decimal separator and the thousand separator that are specified in the operation request. Compare with the data in the CSV content. 3. Change one of these separators in the operation request. 4. Verify your changes.
RANGET-ABLE-265 [page 2567]	`The field separator must not be the same as the thousand separator.`	1. In the operation request, the CSV field separator and the thousand separator cannot be the same. The specified separators must be different to be able to process the CSV content. 2. Check the CSV field separator and the thousand separator that are specified in the operation request. Compare with the data in the CSV content. 3. Change one of these separators in the operation request. 4. Verify your changes.
RANGET-ABLE-266 [page 2569]	`The CSV content representing the range table rows is missing.`	1. Check the CSV content in the operation request. 2. Check why it is empty. 3. Change the CSV content or the implementation. 4. Verify your changes.
RANGET-ABLE-267 [page 2571]	`Cannot parse the token "{csvFieldIndex}" of the range table row "{csvRowLine}". {errorMessageDetails}`	1. Carefully read the part of the message that details the error. This information is added by the system to the error message for troubleshooting purpose. 2. Check the CSV content. 3. Check the line indicated in the error message. In this line, check the data at the position indicated. 4. Change the CSV content. 5. Verify your changes.
RANGET-ABLE-268 [page 2573]	`The value "{value}" cannot be formatted as a number.`	1. Check the CSV content in the operation request. 2. Check the settings of the request: decimal separator, thousand separator. 3. Change the CSV content or the implementation. 4. Verify your changes.

Error Code	Message	Action
RANGETABLE-269 [page 2574]	`Failed to read the CSV content representing the range table rows. {errorMessageDetails}`	1. Carefully read the part of the message that details the error. This information is added to the error message for troubleshooting purpose. 2. Check and change the CSV content. 3. Verify your changes.
RANGE-TABLE-COMPONENT-1 [page 2576]	`The ID of the range table class is missing.`	Set up the identifier of the range table class. Verify your changes.
RANGE-TABLE-COMPONENT-2 [page 2577]	`Both range table ID and range table ID property name are missing. At least one of them must be defined.`	Set up a range table ID or a range table ID property name. Verify your changes.
RANGE-TABLE-COMPONENT-3 [page 2579]	`Both range table ID and range table ID property name are defined. Only one of them must be defined.`	Set up a range table ID or a range table ID property name. Verify your changes.
RANGE-TABLE-COMPONENT-4 [page 2580]	`The range table class "{rangeTableClassId}" does not exist.`	Change the identifier of the range table class. Verify your changes.
RANGE-TABLE-COMPONENT-5 [page 2582]	`The range table ID defined by a charge component parameter named "{rangeTableIdPropertyName}" does not exist.`	Add a parameter in the charge component or define a range table ID. Verify your changes.
RANGE-TABLE-COMPONENT-6 [page 2583]	`The range table "{rangeTableId}" does not exist.`	Change the identifier of the range table. Verify your changes.
RANGE-TABLE-COMPONENT-7 [page 2585]	`The reference date property name is not defined.`	Set up the reference date property name. Verify your changes.

Error Code	Message	Action
RANGE-TABLE-COMPO-NENT-8 [page 2586]	`The reference date property name "{referenceDatePropertyName}" does not reference an existing rating context property.`	Set up the reference date property name to an existing rating context property. Verify your changes.
RANGE-TABLE-COMPO-NENT-9 [page 2588]	`The input property name is not defined.`	Set up the input property name. Verify your changes.
RANGE-TABLE-COMPO-NENT-10 [page 2589]	`The input property name "{inputPropertyName}" does not reference an existing rating context property.`	Set up the input property name to an existing rating context property. Verify your changes.
RANGE-TABLE-COMPO-NENT-11 [page 2591]	`The default output mapping property name "{defaultOutputMappingName}" at index "{defaultOutputMappingIndex}" is not defined.`	Set up the default output property name. Verify your changes.
RANGE-TABLE-COMPO-NENT-12 [page 2592]	`The default output mapping property name "{defaultOutputMappingName}" at index "{defaultOutputMappingIndex}" is already defined as a number rating context property.`	Set up the default output property name. Verify your changes.
RANGE-TABLE-COMPO-NENT-13 [page 2594]	`The output mapping is mandatory and must contain rating context property names that match range table class: "{outputMappingCount}".`	Set up a rating context property name for each string or single number range table class column. Add the mapping for each column that is cumulative or range size cumulative. Verify your changes.
RANGE-TABLE-COMPO-NENT-14 [page 2595]	`The output mapping property name "{outputMappingName}" at index "{outputMappingIndex}" is not defined.`	Set up the output property name. Verify your changes.

Error Code	Message	Action
RANGE-TABLE-COMPO-NENT-15 [page 2597]	`The output mapping property name "{outputMappingName}" at index "{outputMappingIndex}" of range table class column name "{rangeTableClassColumnName}" is already defined as a string rating context property.`	Set up the output property name. Verify your changes.
RANGE-TABLE-COMPO-NENT-16 [page 2598]	`The output mapping property name "{outputMappingName}" at index "{outputMappingIndex}" of range table class column name "{rangeTableClassColumnName}" is already defined as a number rating context property.`	Set up the output property name. Verify your changes.
RANGE-TABLE-COMPO-NENT-17 [page 2600]	`The output mapping for cumulative or range-size cumulative number property name "{outputMappingName}" at index "{outputMappingIndex}" is not defined.`	Set up the output property name. Verify your changes.
RANGE-TABLE-COMPO-NENT-18 [page 2601]	`The output mapping for cumulative or range-size cumulative number property name "{outputMappingName}" at index "{outputMappingIndex}" of range table class column name "{rangeTableClassColumnName}" is already defined as a number rating context property.`	Set up the output property name. Verify your changes.
RANGE-TABLE-COMPO-NENT-19 [page 2603]	`The mapping "{outputMappingName}" defined for default output mapping property "{defaultOutputMappingName}" is already used by the default output mapping property "{duplicatedDefaultOutputMappingName}".`	Change the name of the Parameter Reference. Verify your changes.

Error Code	Message	Action
RANGE-TABLE-COMPO-NENT-20 [page 2605]	`The mapping "{outputMappingName}" defined for output mapping property at index "{outputMappingIndex}" of range table class column name "{rangeTableClassColumnName}" is already used by the default output mapping property "{duplicatedDefaultOutputMappingName}".`	Change the name of the Parameter Reference. Verify your changes.
RANGE-TABLE-COMPO-NENT-21 [page 2606]	`The mapping "{outputMappingName}" defined for output mapping property at index "{outputMappingIndex}" of range table class column name "{rangeTableClassColumnName}" is already used by the output mapping property at index "{duplicatedOutputMappingName}".`	Change the name of the Parameter Reference. Verify your changes.
RANGE-TABLE-COMPO-NENT-22 [page 2608]	`The range table class "{rangeTableClassIdFromParameter}" referenced in the parameter "{parameterName}" does not correspond to the range table class "{rangeTableClassIdFromRateComponent}" defined in the rate component.`	Set up the same range table class in the parameter and in the component. Verify your changes.
RANGE-TABLE-COMPO-NENT-23 [page 2610]	`The range table class "{rangeTableClassIdFromParameter}" from range table "{parameterName}" does not correspond to the range table class "{rangeTableClassIdFromRateComponent}" defined in the rate component.`	Set up the same range table class in the parameter and in the component. Verify your changes.
RANGE-TABLE-COMPO-NENT-24 [page 2611]	`The rating context property "{rangeTableIdPropertyName}" defining a range table ID does not include the mandatory additional information "{addInfoName}".`	Add the additional information to this property specified in the logic component. Verify your changes.

Error Code	Message	Action
RANGE-TABLE-COMPO-NENT-25 [page 2613]	`The input mapping is mandatory and must contain rating context property names that match range table class: "{inputMappingCount}".`	Set up a rating context property name for each input column of the range table class. Verify your changes.
RANGE-TABLE-COMPO-NENT-26 [page 2614]	`The property name "{inputMappingPropertyName}" defined for the input mapping does not reference an existing rating context property of type String.`	Set up an existing property name of type String that exist in the rating context for the input mapping. Verify your changes.
RANGE-TABLE-COMPO-NENT-27 [page 2616]	`You cannot set input mapping when the range table class does not have input columns.`	Remove the input mapping properties. Verify your changes.
RANGE-TABLE-COMPO-NENT-28 [page 2617]	`The component cannot reference the range table "{rangeTable}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.
REFILL-PLAN-1 [page 2619]	`The Refill Plan is missing in the CreateRefillPlanOp. The Refill Plan is missing in the CreateRefillPlanOp.`	Add the Refill Plan to the CreateRefillPlanOp. Verify your changes.
REFILL-PLAN-2 [page 2620]	`The id of the Refill Plan is missing.`	Add the ID of the Refill Plan. Verify your changes.
REFILL-PLAN-3 [page 2622]	`The owner of the Refill Plan "{refillPlanId}" is missing.`	Add the owner of the Refill Plan. Verify your changes.
REFILL-PLAN-4 [page 2623]	`The description of the Refill Plan "{refillPlanId}" is missing.`	Add a description to the Refill Plan. Verify your changes.
REFILL-PLAN-5 [page 2625]	`Error while validating the Refill Plan "{refillPlanId}".`	Verify your changes.

Error Code	Message	Action
REFILL-PLAN-6 (Revoked) [page 2626]	`The name of the Additional Information at index {additionalInformationIndex} is missing.`	Add a name to the Additional Information item. Verify your changes.
REFILL-PLAN-7 (Revoked) [page 2628]	`The name "{additionalInformationName}" of the Additional Information at index {secondIndex} is already used by the Additional Information at index {firstIndex}.`	Change the name of the Additional Information. Verify your changes.
REFILL-PLAN-8 (Revoked) [page 2630]	`The description of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a description to the Additional Information. Verify your changes.
REFILL-PLAN-9 (Revoked) [page 2631]	`The type of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing or unknown (the supported types are string, number, date).`	Add a type to the Additional Information or change it into a supported one: string, number, date. Verify your changes.
REFILL-PLAN-10 (Revoked) [page 2633]	`The date value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a date value to the Additional Information. Verify your changes.
REFILL-PLAN-11 (Revoked) [page 2635]	`The number value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a number value to the Additional Information. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-12 (Revoked) [page 2636]	`The string value of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is missing.`	Add a string value to the Additional Information. Verify your changes.
REFILL-PLAN-13 (Revoked) [page 2638]	`The type "{additionalInformationType}" of the Additional Information "{additionalInformationName}" at index {additionalInformationIndex} is unsupported (the supported types are string, number, date).`	Use a supported type (string, number, date) for the Additional Information. Verify your changes.
REFILL-PLAN-14 [page 2640]	`The name of the Parameter at index {parameterIndex} is missing.`	Add a name to the Parameter. Verify your changes.
REFILL-PLAN-15 [page 2641]	`The name "{parameterName}" of the Parameter at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter. Verify your changes.
REFILL-PLAN-16 [page 2643]	`The type of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown (the supported types are string, number, date, currency).`	Add a type to the Parameter or change it into a supported one: string, number, date, currency. Verify your changes.
REFILL-PLAN-18 [page 2644]	`The description of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a description to the Parameter. Verify your changes.
REFILL-PLAN-22 [page 2646]	`The type "{parameterType}" of the Parameter "{parameterName}" at index {parameterIndex} is unsupported (the supported types are string, number, date, currency).`	Use a supported type (string, number, date, currency) for the Parameter. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-23 [page 2647]	`Parameter "{parameterName}" at index {parameterIndex} is not linked to a Parameter Reference of the Refill Plan Item.`	Link the Parameter or remove it. Verify your changes.
REFILL-PLAN-24 [page 2649]	`The name of the Counter at index {counterIndex} is missing.`	Add a name to the Counter. Verify your changes.
REFILL-PLAN-25 [page 2650]	`The name "{counterName}" of the Counter at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter. Verify your changes.
REFILL-PLAN-26 [page 2652]	`The initial value of the Counter "{counterName}" at index {counterIndex} is missing.`	Add an initial value to the Counter. Verify your changes.
REFILL-PLAN-28 [page 2653]	`The description of the Counter "{counterName}" at index {counterIndex} is missing.`	Add a description to the Counter. Verify your changes.
REFILL-PLAN-29 [page 2655]	`The Counter "{counterName}" at index {counterIndex} does not refer to a Counter Reference of the Refill Plan Item.`	Link the Counter or remove it. Verify your changes.
REFILL-PLAN-30 [page 2656]	`The name of the Account Assignment at index {accountAssignmentIndex} is missing.`	Add a name to the Account Assignment. Verify your changes.
REFILL-PLAN-31 [page 2658]	`The name "{accountAssignmentName}" of the Account Assignment at index {secondIndex} is already used by the Account Assignment at index {firstIndex}.`	Change the name of the Account Assignment. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-32 [page 2659]	`The type of the Account Assignment "{accountAssignmentName}" at index {accountAssignmentIndex} is invalid, missing or unknown (the supported type is prepaid).`	Add a type to the Account Assignment or set it to prepaid. Verify your changes.
REFILL-PLAN-33 [page 2661]	`The description of the Account Assignment "{accountAssignmentName}" at index {accountAssignmentIndex} is missing.`	Add a description to the Account Assignment. Verify your changes.
REFILL-PLAN-34 [page 2662]	`The Account Assignment "{accountAssignmentName}" at index {accountAssignmentIndex} does not refer to an Account Assignment Reference of the Refill Plan Item.`	Link the Account Assignment or remove it. Verify your changes.
REFILL-PLAN-35 [page 2664]	`The name of the User Technical Identifier at index {userTechIdIndex} is missing.`	Add a name to the User Technical Identifier. Verify your changes.
REFILL-PLAN-36 [page 2665]	`The name "{userTechIdName}" of the User Technical Identifier at index {secondIndex} is already used by the User Technical Identifier at index {firstIndex}.`	Change the name of the User Technical Identifier. Verify your changes.
REFILL-PLAN-37 [page 2667]	`The description of the User Technical Identifier "{userTechIdName}" at index {userTechIdIndex} is missing.`	Add a description to the User Technical Identifier. Verify your changes.
REFILL-PLAN-38 [page 2669]	`The User Technical Identifier "{userTechIdName}" at index {userTechIdIndex} does not refer to a User Technical Identifier Reference of the Refill Plan Item.`	Link the User Technical Identifier or remove it. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-39 [page 2670]	`The id of the Refill Plan Item at index {refillPlanItemIndex} is missing.`	Add an id to the Refill Plan Item. Verify your changes.
REFILL-PLAN-40 [page 2672]	`The id "{refillPlanItemId}" of the Refill Plan Item at index {secondIndex} is already used by the Refill Plan Item at index {firstIndex}.`	Change the ID of the Refill Plan Item. Verify your changes.
REFILL-PLAN-43 [page 2673]	`No Refill Logic is referred to by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex}.`	Add the Refill Logic to the Refill Plan Item. Verify your changes.
REFILL-PLAN-44 [page 2675]	`The id of the master Refill Logic referred to by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} is missing.`	Add an ID to the master Refill Logic in the Refill Plan Item. Verify your changes.
REFILL-PLAN-45 [page 2676]	`The Refill Plan Item "{refillPlanItemId}" must define one and only one Account Assignment Reference.`	Define one Account Assignment Reference for the Refill Plan Item. Verify your changes.
REFILL-PLAN-48 [page 2678]	`Error while validating the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex}.`	Verify your changes.
REFILL-PLAN-49 [page 2679]	`The name of the Parameter at index {parameterIndex} is missing.`	Add a name to the Parameter. Verify your changes.
REFILL-PLAN-50 [page 2681]	`The name "{parameterName}" of the Parameter at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-51 [page 2682]	`The type of the Parameter "{parameterName}" at index {parameterIndex} is missing or unknown (the supported types are string, number, date).`	Add a type to the Parameter or change it into a supported one: string, number, date. Verify your changes.
REFILL-PLAN-52 [page 2684]	`The date value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a date value to the Parameter. Verify your changes.
REFILL-PLAN-53 [page 2685]	`The number value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a number value to the Parameter. Verify your changes.
REFILL-PLAN-54 [page 2687]	`The string value of the Parameter "{parameterName}" at index {parameterIndex} is missing.`	Add a string value to the Parameter. Verify your changes.
REFILL-PLAN-55 [page 2688]	`The type "{parameterType}" of the Parameter "{parameterName}" at index {parameterIndex} is unsupported (the supported types are string, number, date).`	Use a supported type (string, number, date) for the Parameter. Verify your changes.
REFILL-PLAN-56 [page 2690]	`The name of the Parameter Reference at index {parameterIndex} is missing.`	Add a name to the Parameter Reference. Verify your changes.
REFILL-PLAN-57 [page 2691]	`The name "{parameterReferenceName}" of the Parameter Reference at index {secondIndex} is already used by the Parameter at index {firstIndex}.`	Change the name of the Parameter Reference. Verify your changes.
REFILL-PLAN-58 [page 2693]	`The target name of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is missing.`	Add a target name to the Parameter Reference. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-59 [page 2694]	`The Parameter "{targetName}" targeted by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} does not exist.`	Change the target name of the Parameter Reference into an existing one or create a new Parameter in the Refill Plan with this target name. Verify your changes.
REFILL-PLAN-60 [page 2696]	`The type of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is missing or unknown (the supported types are string, number, date).`	Add a type to the Parameter Reference or change it into a supported one: string, number, date. Verify your changes.
REFILL-PLAN-61 [page 2697]	`The type "{parameterReferenceType}" of the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not compatible with the type "{parameterType}" of the targeted Parameter.`	Link the Parameter Reference to a compatible Parameter. Verify your changes.
REFILL-PLAN-62 [page 2699]	`The name of the Counter at index {counterIndex} is missing.`	Add a name to the Counter. Verify your changes.
REFILL-PLAN-63 [page 2701]	`The name "{counterName}" of the Counter at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter. Verify your changes.
REFILL-PLAN-64 [page 2702]	`The initial value of the Counter "{counterName}" at index {counterIndex} is missing.`	Add an initial value to the Counter. Verify your changes.
REFILL-PLAN-65 [page 2704]	`The name of the Counter Reference at index {counterReferenceIndex} is missing.`	Add a name to the Counter Reference. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-66 [page 2705]	`The name "{counterName}" of the Counter Reference at index {secondIndex} is already used by the Counter at index {firstIndex}.`	Change the name of the Counter Reference. Verify your changes.
REFILL-PLAN-67 [page 2707]	`The target name of the Counter Reference "{counterReferenceName}" at index {counterReferenceIndex} is missing.`	Add a target name to the Counter Reference. Verify your changes.
REFILL-PLAN-68 [page 2708]	`The Counter "{targetName}" targeted by the Counter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} does not exist.`	Change the target name of the Counter Reference into an existing one or create a new Counter in the Refill Plan with this target name. Verify your changes.
REFILL-PLAN-69 [page 2710]	`The name of the Account Assignment Reference at index {accountAssignmentReferenceIndex} is missing.`	Add a name to the Account Assignment Reference. Verify your changes.
REFILL-PLAN-70 [page 2711]	`The name "{accountAssignmentReferenceName}" of the Account Assignment Reference at index {secondIndex} is already used by the Account Assignment Reference at index {firstIndex}.`	Change the name of the Account Assignment Reference. Verify your changes.
REFILL-PLAN-71 [page 2713]	`The target name of the Account Assignment Reference "{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex} is missing.`	Add a target name to the Account Assignment Reference. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-72 [page 2715]	`The Account Assignment "{targetName}" targeted by the Account Assignment Reference "{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex} does not exist.`	Change the target name of the Account Assignment Reference into an existing one or create a new Account Assignment in the Refill Plan with this target name. Verify your changes.
REFILL-PLAN-73 [page 2716]	`The type of the Account Assignment Reference "{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex} is missing, invalid or unknown (the supported type is prepaid).`	Add a type to the Account Assignment Reference or change it into prepaid. Verify your changes.
REFILL-PLAN-74 [page 2718]	`The type "{accountAssignmentReferenceType}" of the Account Assignment Reference "{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex} is not compatible with the type "{accountAssignmentType}" of the targeted Account Assignment.`	Link the Account Assignment Reference to a compatible Account Assignment. Verify your changes.
REFILL-PLAN-75 [page 2719]	`The service name of the User Technical Identifier Reference at index {userTechnicalIdentifierReferenceIndex} is missing.`	Add a service name to the User Technical Identifier Reference. Verify your changes.
REFILL-PLAN-76 [page 2721]	`The service "{userTechnicalIdentifierReferenceService}" of the User Technical Identifier Reference at index {secondIndex} is already used by the User Technical Identifier Reference at index {firstIndex}.`	Change the service of the User Technical Identifier Reference. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-77 [page 2722]	`The target name of the User Technical Identifier Reference "{userTechnicalIdentifierReferenceName}" at index {userTechnicalIdentifierReferenceIndex} is missing.`	Add a target name to the User Technical Identifier Reference. Verify your changes.
REFILL-PLAN-78 [page 2724]	`The User Technical Identifier "{targetName}" targeted by the User Technical Identifier Reference "{userTechnicalIdentifierReferenceService}" at index {userTechnicalIdentifierReferenceIndex} does not exist.`	Change the target name of the User Technical Identifier Reference into an existing one or create a new User Technical Identifier in the Refill Plan with this target name. Verify your changes.
REFILL-PLAN-79 [page 2726]	`The Refill Record Mapping is missing in the Refill Plan Item.`	Set the Refill Record Mapping of the Refill Plan Item. Verify your changes.
REFILL-PLAN-80 [page 2727]	`The class of the Refill Record Mapping is missing.`	Add a class to the Refill Record Mapping. Verify your changes.
REFILL-PLAN-81 [page 2729]	`Error while validating the Refill Record Mapping of class "{citcClass}".`	Verify your changes.
REFILL-PLAN-82 [page 2730]	`The name of the Refill Record Mapping Entry at index {chargedItemMappingEntryIndex} is missing.`	Add a name to the Refill Record Mapping Entry. Verify your changes.
REFILL-PLAN-83 [page 2732]	`The name "{chargedItemMappingEntryName}" of the Refill Record Mapping Entry at index {secondIndex} is already used by the Refill Record Mapping Entry at index {firstIndex}.`	Change the name of the Refill Record Mapping Entry. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-84 [page 2733]	`The type of the Refill Record Mapping Entry "{chargedItemMappingEntryName}" at index {chargedItemMappingEntryIndex} is missing or unknown (the supported types are string, number, date, boolean).`	Add a type to the Refill Record Mapping Entry or change it into a supported one: string, number, date, boolean. Verify your changes.
REFILL-PLAN-91 [page 2735]	`The Refill Plan "{refillPlanId}" already exists.`	Use another ID or use the ModifyRefillPlanOp to modify the Refill Plan. Verify your changes.
REFILL-PLAN-92 [page 2736]	`The id of the Refill Plan is missing in the DeleteRefillPlanOp.`	Set the ID of the Refill Plan to the DeleteRefillPlanOp. Verify your changes.
REFILL-PLAN-93 [page 2738]	`The Refill Plan "{refillPlanId}" cannot be deleted because it does not exist.`	Use an existing ID for the Refill Plan. Verify your changes.
REFILL-PLAN-94 [page 2739]	`Error while deleting the Refill Plan "{refillPlanId}". The Refill Plan is still linked to one or more Charging Contract Items.`	First delete all Charging Contract Items referring to the Refill Plan. Verify your changes.
REFILL-PLAN-96 [page 2741]	`The Account Assignment at the index {accountAssignmentIndex} is empty.`	Replace it by a valid Account Assignment or remove it. Verify your changes.
REFILL-PLAN-97 (Revoked) [page 2742]	`The Additional Info at the index {additionalInfoIndex} is empty.`	Replace it by a valid Additional Information item or remove it. Verify your changes.
REFILL-PLAN-104 [page 2744]	`The Counter at the index {counterIndex} is empty.`	Replace it by a valid Counter or remove it. Verify your changes.
REFILL-PLAN-106 [page 2745]	`The Parameter at the index {parameterIndex} is empty.`	Replace it by a valid Parameter or remove it. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-108 [page 2747]	`The User Technical Identifier at the index {userTechnicalIdentifierIndex} is empty.`	Replace it by a valid User Technical Identifier or remove it. Verify your changes.
REFILL-PLAN-109 [page 2748]	`The Refill Plan Item at the index {refillPlanItemIndex} is empty.`	Replace it by a valid Refill Plan Item or remove it. Verify your changes.
REFILL-PLAN-110 [page 2750]	`The id of the Refill Logic referred to by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} does not match any Refill Logic.`	Set the ID of the existing Refill Logic. Verify your changes.
REFILL-PLAN-115 [page 2751]	`The id of the master Refill Logic referred to by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} and the code "{retrievedRefillLogicCode}" of the retrieved Refill Logic do not match.`	Contact the support. Verify your changes.
REFILL-PLAN-117 [page 2753]	`The owner of the Refill Plan and the owner of the Refill Logic referred to by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} do not match. The owner of the Refill Plan is "{refillPlanOwner}". The owner of the Refill Logic is "{refillLogicOwner}".`	Set the id the master Refill Logic that has the same owner as the Refill Plan. Verify your changes.
REFILL-PLAN-118 [page 2755]	`The mandatory filter in the SearchRefillPlanOp is missing.`	Add the filter to the SearchRefillPlanOp. Verify your changes.
REFILL-PLAN-119 [page 2756]	`An error occurred during the execution of the SearchRefillPlanOp: {errorMessage}.`	Verify your changes.

Error Code	Message	Action
REFILL-PLAN-120 [page 2757]	`The mandatory filter in the SearchRefillPlanClassOp is missing.`	Add the filter to the SearchRefillPlanClassOp. Verify your changes.
REFILL-PLAN-121 [page 2759]	`An error occurred during the execution of the SearchRefillPlanClassOp: {errorMessage}.`	Verify your changes.
REFILL-PLAN-126 [page 2760]	`The Counter "{counterName}" at index {counterIndex} does not exist in the Refill Logic "{refillLogicId}".`	Remove this Counter. Verify your changes.
REFILL-PLAN-127 [page 2762]	`The Counter Reference "{counterRefName}" at index {counterRefIndex} does not exist in the Refill Logic "{refillLogicId}".`	Remove this Counter Reference. Verify your changes.
REFILL-PLAN-128 [page 2763]	`The Parameter "{parameterName}" at index {parameterIndex} does not exist in the Refill Logic "{refillLogicId}".`	Remove this Parameter. Verify your changes.
REFILL-PLAN-129 [page 2765]	`The Parameter Reference "{parameterRefName}" at index {parameterRefIndex} does not exist in the Refill Logic "{refillLogicId}".`	Remove this Parameter Reference. Verify your changes.
REFILL-PLAN-130 [page 2767]	`User Technical Identifiers are defined while no usage refill is assigned to the Refill Logic "{refillLogicId}".`	Remove the User Technical Identifiers. Verify your changes.
REFILL-PLAN-132 [page 2768]	`The Refill Plan is missing in the ModifyRefillPlanOp.`	Add the Refill Plan to the ModifyRefillPlanOp. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-133 [page 2770]	`The Refill Plan with the id {refillPlanId} does not exist.`	Change the ID of the Refill Plan into an existing one or first create the Refill Plan. Verify your changes.
REFILL-PLAN-134 [page 2771]	`Impossible to modify the Refill Plan because the specified owner {specifiedOwner} does not correspond to the owner {realOwner} existing in the Refill Plan.`	Change the owner into the owner of the Refill Plan or create a new Refill Plan for the specified owner. Verify your changes.
REFILL-PLAN-135 [page 2773]	`The Refill Logic "{refillLogicId}" referred to by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} is unknown.`	Change the refillLogicId into an existing Refill Logic identifier. Verify your changes.
REFILL-PLAN-136 [page 2774]	`Internal server error. Impossible to modify the Refill Plan because the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} refers to no known Refill Logic.`	Contact the support. Verify your changes.
REFILL-PLAN-138 [page 2776]	`The Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} already refers to the Refill Logic "{originalRefillLogicId}" and cannot refer to the Refill Logic "{newRefillLogicId}" at the same time.`	Use the Refill Logic already referred to by the Refill Plan Item or create a new Refill Plan Item. Verify your changes.
REFILL-PLAN-140 [page 2777]	`Refill Plan "{refillPlanId}" must define one and only one Refill Plan Item.`	Add a Refill Plan Item. Verify your changes.
REFILL-PLAN-142 [page 2779]	`The status of the Refill Plan "{refillPlanId}" is missing.`	Add a status to the Refill Plan. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-143 [page 2780]	`The status of new Refill Plan "{refillPlanId}" must be set to open.`	Set the status of this new Refill Plan to open. Verify your changes.
REFILL-PLAN-144 [page 2782]	`The Refill Plan "{refillPlanId}" whose status is already set to released cannot be set back to open.`	Set the status of this new Refill Plan to released or obsolete. Verify your changes.
REFILL-PLAN-145 [page 2783]	`The Refill Plan "{refillPlanId}" whose status is already set to obsolete cannot be set back to open.`	Set the status of this new Refill Plan to released or obsolete. Verify your changes.
REFILL-PLAN-146 [page 2785]	`The Refill Plan "{refillPlanId}" whose status is already set to obsolete cannot be set back to released.`	Set the status of this new Refill Plan to released or obsolete. Verify your changes.
REFILL-PLAN-147 [page 2786]	`The name of the Account Assignment Reference at index {accountAssignmentReferenceIndex} differs from the only one ({defaultReference}) available in the Refill Logic.`	Add a valid name to the Account Assignment Reference. Verify your changes.
REFILL-PLAN-170 [page 2788]	`The parameter additional information "{additionalInformationName}" at index {additionalInformationIndex} is unknown.`	Remove this additional information or replace it with a known one. Verify your changes.
REFILL-PLAN-171 [page 2790]	`The data type of the parameter is not defined.`	Add this additional information or remove all additional informations. Verify your changes.
REFILL-PLAN-172 [page 2791]	`The parameter is a mapping table ID but no mapping table class is defined.`	Add the mapping table class additional information. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-173 [page 2793]	`The parameter is a mapping table key and could not be linked to a mapping table class.`	Remove the mapping table class additional information. Verify your changes.
REFILL-PLAN-174 [page 2794]	`The parameter cannot declare additional informations without a data type.`	Add a data type additional information or remove all additional informations. Verify your changes.
REFILL-PLAN-175 [page 2796]	`Error while validating the Parameter "{parameterName}" at index {parameterIndex}.`	Verify your changes.
REFILL-PLAN-176 [page 2797]	`The mapping table ID "{mappingTableIdName}" is not declared whereas it is used in the charge component.`	Add the corresponding mapping table ID parameter. Verify your changes.
REFILL-PLAN-177 [page 2799]	`The mapping table key "{mappingTableKeyName}" of type "{mappingTableKeyType}" is not declared whereas it is used in the charge component.`	Add the corresponding mapping table ID parameter. Verify your changes.
REFILL-PLAN-178 [page 2800]	`Error while validating the Parameter "{parameterName}" at index {parameterIndex}.`	Verify your changes.
REFILL-PLAN-179 [page 2802]	`Error while validating the Parameter Reference "{parameterName}" at index {parameterIndex}.`	Verify your changes.
REFILL-PLAN-180 [page 2803]	`The refill plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as a mapping table ID.`	Declare the mapping table ID data type and the mapping table class additional informations in the refill plan Parameter. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-181 [page 2805]	`The refill plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declare an incompatible mapping table class "{cpParameterMappingTableClass}" while the Parameter Reference is of class "{parameterReferenceMappingTableClass}".`	Declare the mapping table ID data type and the mapping table class additional informations in the refill plan Parameter. Verify your changes.
REFILL-PLAN-182 [page 2806]	`The charge plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as a mapping table key.`	Declare the mapping table key data type additional information in the charge plan Parameter. Verify your changes.
REFILL-PLAN-183 [page 2808]	`The Parameter is declared as a mapping table ID while it does not exist in the Charge Component.`	Remove the mapping table ID data type additional information from the Parameter. Verify your changes.
REFILL-PLAN-184 [page 2809]	`The Parameter is declared as a mapping table ID but it does not have a STRING type.`	Declare the parameter as a STRING. Verify your changes.
REFILL-PLAN-185 [page 2811]	`The mapping table class "{parameterMappingTableClass}" declared in the Parameter is incompatible with the one declared in the Charge Component "{chargeComponentMappingTableClass}".`	Declare the right mapping table class. Verify your changes.
REFILL-PLAN-186 [page 2812]	`The Parameter is declared as a mapping table key while it does not exist in the Charge Component.`	Remove the mapping table key data type additional information from the Parameter. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-187 [page 2814]	`The Parameter is declared with a mapping table key but has a wrong type "{parameterType}" while it should be "{chargeComponentType}".`	Declare the right type for the parameter. Verify your changes.
REFILL-PLAN-188 [page 2815]	`The code of the refill record class ({refillRecordClassCode}) referred to by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} does not match any Refill Record Class.`	Set the ID of an existing Refill Record Class. Verify your changes.
REFILL-PLAN-189 [page 2817]	`The code of the refill record class ({refillRecordClassCode}) referred to by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} does not match any Refill Record Class.`	Set the ID of an existing Refill Record Class. Verify your changes.
REFILL-PLAN-190 [page 2819]	`Internal server error. Impossible to modify the Refill Plan because the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} refers to an unknown Refill Record Class.`	Contact the support. Verify your changes.
REFILL-PLAN-191 [page 2820]	`The code of the refill record class ({refillRecordClassCode}) referred to by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} does not match any Refill Record Class.`	Add the ID of an existing Refill Record Class. Verify your changes.
REFILL-PLAN-201 [page 2822]	`The Refill Item Class is missing in the CreateRefillItemClassOp.`	Add the Refill Item Class to the CreateRefillItemClassOp. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-202 [page 2823]	`The ID of the Refill Item Class is missing in the CreateRefillItemClassOp.`	Add the id of the Refill Item Class to the CreateRefillItemClassOp. Verify your changes.
REFILL-PLAN-203 [page 2825]	`The service provider of the Refill Item Class "{refillItemClassId}" is missing in the CreateRefillItemClassOp.`	Add the service provider of the Refill Item Class to the CreateRefillItemClassOp. Verify your changes.
REFILL-PLAN-204 [page 2826]	`The name is missing in the Refill Item Class property at index {propertyIndex}.`	Add a name to the Refill Item Class property. Verify your changes.
REFILL-PLAN-205 (Revoked) [page 2828]	`The Refill Item Class "{refillItemClassId}" has not been saved in the database due to "{sqlErrorMessage}".`	Check that the database is online. Verify your changes.
REFILL-PLAN-206 [page 2829]	`The Refill Item Class "{refillItemClassId}" already exists.`	Use another ID or use the ModifyRefillItemClassOp to modify the Refill Item Class. Verify your changes.
REFILL-PLAN-207 [page 2831]	`The Refill Item Class "{refillItemClassId}" cannot be modified because it does not exist.`	Use an existing id for the Refill Item Class. Verify your changes.
REFILL-PLAN-208 [page 2832]	`Unable to change the service provider from "{oldServiceProvider}" to "{newServiceProvider}" in the Refill Item Class "{refillItemClassId}". The service provider is not modifiable.`	Check the service provider of the Refill Item Class. Verify your changes.
REFILL-PLAN-209 [page 2834]	`Unable to modify the type from "{oldPropertyType}" to "{newPropertyType}" for the property "{propertyName}" in the Refill Item Class "{refillItemClassId}". The property type is not modifiable.`	Check the property type of the Refill Item Class. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-210 [page 2836]	`The Refill Item Class is missing in the ModifyRefillItemClassOp.`	Add the Refill Item Class to the ModifyRefillItemClassOp. Verify your changes.
REFILL-PLAN-211 [page 2837]	`The id of the Refill Item Class is missing in the ModifyRefillItemClassOp.`	Add the ID of the Refill Item Class to the ModifyRefillItemClassOp. Verify your changes.
REFILL-PLAN-212 [page 2838]	`The service provider of the Refill Item Class "{refillItemClassId}" is missing in the ModifyRefillItemClassOp.`	Add the service provider of the Refill Item Class to the ModifyRefillItemClassOp. Verify your changes.
REFILL-PLAN-213 [page 2840]	`The id of the Refill Item Class is missing in the DeleteRefillItemClassOp.`	Add the ID of the Refill Item Class to the DeleteRefillItemClassOp. Verify your changes.
REFILL-PLAN-214 [page 2841]	`The Refill Item Class "{refillItemClassId}" cannot be deleted because it does not exist.`	Use an existing ID for the Refill Item Class. Verify your changes.
REFILL-PLAN-215 [page 2843]	`The Refill Item Class "{refillItemClassId}" cannot be deleted because it is referred to by one or more Refill Logic objects.`	First delete the Refill Logic object(s). Verify your changes.
REFILL-PLAN-216 (Revoked) [page 2844]	`The Refill Item Class "{refillItemClassId}" has not been deleted in the database due to "{sqlErrorMessage}".`	Check that the database is online. Verify your changes.
REFILL-PLAN-217 (Revoked) [page 2846]	`Unable to get the catalog entries related to the Refill Item Class "{refillItemClassId}" due to "{sqlErrorMessage}".`	Check that the database is online. Verify your changes.
REFILL-PLAN-218 (Revoked) [page 2848]	`Unable to delete the catalog entry related to the Refill Item Class "{refillItemClassId}" due to "{sqlErrorMessage}".`	Check that the database is online. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-219 [page 2849]	`Unable to remove the property "{propertyName}" in the Refill Item Class "{refillItemClassId}". Properties are not removable.`	Check that the Refill Item Class contains properties. Verify your changes.
REFILL-PLAN-232 [page 2851]	`The refill plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as an invoice text.`	Declare the invoice text data type additional information in the refill plan Parameter. Verify your changes.
REFILL-PLAN-233 [page 2852]	`The refill plan Parameter "{parameterName}" at index {parameterIndex} points to an unknown mapping table "{parameterValue}".`	Change the value to a known mapping table. Verify your changes.
REFILL-PLAN-234 [page 2854]	`The refill logic Parameter "{parameterName}" points to an unknown mapping table "{parameterValue}".`	Change the value to a known mapping table. Verify your changes.
REFILL-PLAN-235 [page 2856]	`The refill plan item Parameter "{parameterName}" at index {parameterIndex} points to an unknown mapping table "{parameterValue}".`	Change the value to a known mapping table. Verify your changes.
REFILL-PLAN-236 [page 2857]	`The {mappingTableClassName} Mapping Table Class associated with the {parameterName} parameter in the Refill Logic does not exist.`	Change the name of the Mapping Table Class to an existing one. Verify your changes.
REFILL-PLAN-237 [page 2859]	`The {parameterName} parameter of the Refill Plan declares the {mappingTableName} Mapping Table with the {actualMappingTableClass} Mapping Table Class while this table is of class "{expectedMappingTableClass}".`	Change the name of the Mapping Table to a Mapping Table having the expected Mapping Table Class. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-239 [page 2860]	`The parameter is a range table ID but no range table class is defined.`	Add the range table class additional information. Verify your changes.
REFILL-PLAN-240 [page 2862]	`The range table ID "{rangeTableIdName}" is not declared whereas it is used in the charge component.`	Add the corresponding range table ID parameter. Verify your changes.
REFILL-PLAN-241 [page 2863]	`The refill plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not declared as a range table ID.`	Declare the range table ID data type and the range table class additional informations in the refill plan Parameter. Verify your changes.
REFILL-PLAN-242 [page 2865]	`The refill plan Parameter "{cpParameterName}" referenced by the Parameter Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declare an incompatible range table class "{cpParameterRangeTableClass}" while the Parameter Reference is of class "{parameterReferenceRangeTableClass}".`	Declare the range table ID data type and the range table class additional informations in the refill plan Parameter. Verify your changes.
REFILL-PLAN-243 [page 2867]	`The Parameter is declared as a range table ID while it does not exist in the Charge Component.`	Remove the range table ID data type additional information from the Parameter. Verify your changes.
REFILL-PLAN-244 [page 2868]	`The Parameter is declared as a range table ID but it does not have a STRING type.`	Declare the parameter as a STRING. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-245 [page 2870]	`The range table class "{parameterRangeTableClass}" declared in the Parameter is incompatible with the one declared in the Charge Component "{chargeComponentRangeTableClass}".`	Declare the right range table class. Verify your changes.
REFILL-PLAN-246 [page 2871]	`The refill plan Parameter "{parameterName}" at index {parameterIndex} points to an unknown range table "{parameterValue}".`	Change the value to a known range table. Verify your changes.
REFILL-PLAN-247 [page 2873]	`The refill logic Parameter "{parameterName}" points to an unknown range table "{parameterValue}".`	Change the value to a known range table. Verify your changes.
REFILL-PLAN-248 [page 2874]	`The refill plan item Parameter "{parameterName}" at index {parameterIndex} points to an unknown range table "{parameterValue}".`	Change the value to a known range table. Verify your changes.
REFILL-PLAN-302 [page 2876]	`The currency code "{invalidCurrencyCode}" of the Refill Logic is not a valid currency code.`	Check that the currency code of the Refill Logic is valid. Verify your changes.
REFILL-PLAN-304 [page 2877]	`The name of the usage refill is not set.`	Set the name of the usage refill. Verify your changes.
REFILL-PLAN-305 [page 2879]	`The usage refill "{usageRefillName}" does not contain any refill component.`	Add a refill component to the usage refill. Verify your changes.
REFILL-PLAN-306 [page 2880]	`The name of the recurring refill is not set.`	Set the name of the recurring refill. Verify your changes.
REFILL-PLAN-307 [page 2882]	`The recurring refill "{recurringRefillName}" does not contain any refill component.`	Add a refill component to the recurring refill. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-309 [page 2883]	`The name of the one-shot refill is not set.`	Set the name of the one-shot refill. Verify your changes.
REFILL-PLAN-310 [page 2885]	`The one-shot refill "{oneShotRefillName}" does not contain any refill component.`	Add a refill component to the one-shot refill. Verify your changes.
REFILL-PLAN-311 [page 2886]	`The counter has no name.`	Set the counter name. Verify your changes.
REFILL-PLAN-312 [page 2888]	`The counter "{counterDescriptionName}" has no initial value.`	Set the initial value of the counter has. Verify your changes.
REFILL-PLAN-313 [page 2889]	`The counter "{counterDescriptionName}" is duplicated.`	Set a unique name to the counter. Verify your changes.
REFILL-PLAN-314 [page 2891]	`The parameter "{parameterName}" is duplicated.`	Set a unique name to the parameter. Verify your changes.
REFILL-PLAN-315 [page 2892]	`The Refill Logic has no code.`	Set the code of the Refill Logic. Verify your changes.
REFILL-PLAN-316 [page 2894]	`The Refill Logic "{refillLogicId}" has no owner.`	Set the owner of the Refill Logic. Verify your changes.
REFILL-PLAN-317 [page 2895]	`The Refill Logic "{refillLogicId}" has no refill logic tree.`	Add the refill logic tree to the Refill Logic. Verify your changes.
REFILL-PLAN-318 [page 2897]	`The Refill Item Class "{refillItemClassName}" referred to in the usage refill "{usageRefillName}" does not exist.`	Use an existing Refill Item Class in the usage refill. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-319 [page 2898]	`The Refill Logic "{refillLogicId}" already exists.`	Use another ID or use the ModifyRefillLogicOp to modify the Refill Logic. Verify your changes.
REFILL-PLAN-320 [page 2900]	`The Refill Logic "{refillLogicId}" has not been initialized for an unknown reason.`	Check that the Refill logic is unique. Verify your changes.
REFILL-PLAN-321 [page 2901]	`The Refill Logic is missing in the CreateRefillLogicOp.`	Add the Refill Logic to the CreateRefillLogicOp. Verify your changes.
REFILL-PLAN-322 [page 2903]	`The Refill Logic is missing in the ModifyRefillLogicOp.`	Add the Refill Logic to the ModifyRefillLogicOp. Verify your changes.
REFILL-PLAN-323 [page 2904]	`The Refill Logic "{refillLogicCode}" cannot be modified because it does not exist.`	Check the ID of the Refill Logic. Verify your changes.
REFILL-PLAN-324 [page 2906]	`The Refill Logic owner "{refillLogicOwner}" is not modifiable in the Refill Logic "{refillLogicId}".`	Check the owner of the Refill Logic. Verify your changes.
REFILL-PLAN-325 [page 2907]	`The id of the Refill Logic is missing in the DeleteRefillLogicOp.`	Add the ID of the Refill Logic to the DeleteRefillLogicOp. Verify your changes.
REFILL-PLAN-326 [page 2909]	`The Refill Logic "{refillLogicId}" cannot be deleted because it is referred to by one or more Refill Plans.`	First delete the Refill Plan(s). Verify your changes.
REFILL-PLAN-327 [page 2910]	`The Refill Logic "{refillLogicId}" cannot be deleted because it does not exist.`	Check the code of the Refill Logic. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-333 [page 2912]	`The Refill Logic "{refillLogicId}" is set to manage multicurrency but the currency "{currencyCode}" is already set.`	Mark the Refill Logic as multicurrency or remove the currency that has been set. Verify your changes.
REFILL-PLAN-334 [page 2913]	`The Refill Logic "{refillLogicId}" is marked as monocurrency but no currency is set.`	Add a currency in the refill logic. Verify your changes.
REFILL-PLAN-335 [page 2915]	`The counter name "{counterName}" at index {counterIndex} is unknown to the counter name dictionary whereas it is visible to the external system.`	Add the counter name to the counter name dictionary or change the counter name into a known one. Verify your changes.
REFILL-PLAN-336 [page 2916]	`The usage refill usageId is not set.`	Check that a usageId exists in the usage refill. Verify your changes.
REFILL-PLAN-337 [page 2918]	`The usage refill usageId "{usageId}" is used at least twice in the refill logic.`	Check that each usageId in the usage refill is unique. Verify your changes.
REFILL-PLAN-400 [page 2919]	`The Refill Record Class is missing in the CreateRefillRecordClassOp.`	Add the Refill Record Class to the CreateRefillRecordClassOp. Verify your changes.
REFILL-PLAN-401 [page 2921]	`The code of the Refill Record Class is missing in the CreateRefillRecordClassOp.`	Add the code of the Refill Record Class to the CreateRefillRecordClassOp. Verify your changes.
REFILL-PLAN-402 [page 2922]	`The owner of the Refill Record Class "{refillRecordClassCode}" is missing in the CreateRefillRecordClassOp.`	Add the owner of the Refill Record Class to the CreateRefillRecordClassOp. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-403 [page 2924]	`The Refill Record Class of code "{refillRecordClassCode}" already exists.`	Use another code or use the ModifyRefillRecordClassOp to modify the Refill Record Class. Verify your changes.
REFILL-PLAN-404 [page 2925]	`The Exportable Item Mapping of the Refill Record Class "{refillRecordClassCode}" is invalid due to: {errorMessage}.`	Check that the Refill Record Class is valid. Verify your changes.
REFILL-PLAN-405 [page 2927]	`The name of the Refill Record Class Field is missing in the CreateRefillRecordClassOp.`	Add the name of the Refill Record Class Field to the CreateRefillRecordClassOp. Verify your changes.
REFILL-PLAN-406 [page 2928]	`The type of the Refill Record Class Field "{refillRecordClassFieldName}" is missing in the CreateRefillRecordClassOp.`	Add the type of the Refill Record Class Field to the CreateRefillRecordClassOp. Verify your changes.
REFILL-PLAN-407 [page 2930]	`The Refill Record Class Field "{refillRecordClassFieldName}" is duplicated.`	Remove the duplicated Refill Record Class Field. Verify your changes.
REFILL-PLAN-408 [page 2931]	`The property name "{propertyName}" does not exists for the Refill Record Class Field "{refillRecordClassFieldName}".`	Set a valid property name for the Refill Record Class Field. Verify your changes.
REFILL-PLAN-409 [page 2933]	`Impossible to map the property name "{propertyName}" of type "{propertyType}" onto the Refill Record Class Field "{refillRecordClassFieldName}" of type "{refillRecordClassFieldType}".`	Set a valid property type for the Refill Record Class Field. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-410 [page 2934]	`The property name "{propertyName}" does not exists for the Refill Record Class Field "{refillRecordClassFieldName}" .`	Set a valid property name for the Refill Record Class Field. Verify your changes.
REFILL-PLAN-411 [page 2936]	`A Charged Item Class with the code "{refillRecordClassCode}" exists.`	Use another code or delete the Charged Item Class. Verify your changes.
REFILL-PLAN-450 [page 2937]	`The Refill Record Class is missing in the ModifyRefillRecordClassOp.`	Add the Refill Record Class to the ModifyRefillRecordClassOp. Verify your changes.
REFILL-PLAN-451 [page 2939]	`The Refill Record Class "{refillRecordClassCode}" cannot be modified because it does not exist.`	Use an existing code for the Refill Record Class. Verify your changes.
REFILL-PLAN-452 [page 2940]	`The owner "{owner}" of the Refill Record Class "{refillRecordClassCode}" cannot be changed to "{newOwner}".`	Use the original owner of the Refill Record Class. Verify your changes.
REFILL-PLAN-453 [page 2942]	`The Exportable Item Mapping of the Refill Record Class "{refillRecordClassCode}" is invalid due to: {errorMessage}.`	Check the validity of the Refill Record Class. Verify your changes.
REFILL-PLAN-454 [page 2943]	`The name of the Refill Record Class Field is missing in the ModifyRefillRecordClassOp.`	Add the name of the Refill Record Class Field to the ModifyRefillRecordClassOp. Verify your changes.
REFILL-PLAN-455 [page 2945]	`The type of the Refill Record Class Field "{refillRecordClassFieldName}" is missing in the ModifyRefillRecordClassOp.`	Add a type to the Refill Record Class Field to the ModifyRefillRecordClassOp. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-456 [page 2946]	`The Refill Record Class Field "{refillRecordClassFieldName}" is duplicated.`	Remove the duplicated Refill Record Class Field. Verify your changes.
REFILL-PLAN-457 [page 2948]	`The property name "{propertyName}" does not exists for the Refill Record Class Field "{refillRecordClassFieldName}" .`	Set a valid property name for the Refill Record Class Field. Verify your changes.
REFILL-PLAN-458 [page 2949]	`Impossible to map the property name "{propertyName}" of type "{propertyType}" onto the Refill Record Class Field "{refillRecordClassFieldName}" of type "{refillRecordClassFieldType}" .`	Set a valid property type for the Refill Record Class Field. Verify your changes.
REFILL-PLAN-459 [page 2951]	`The property name "{propertyName}" does not exists for the Refill Record Class Field "{refillRecordClassFieldName}" .`	Set a valid property name for the Refill Record Class Field. Verify your changes.
REFILL-PLAN-460 [page 2952]	`The Refill Record Class Field "{refillRecordClassFieldName}" is missing in the ModifyRefillRecordClassOp.`	Add the Refill Record Class Field to the ModifyRefillRecord-ClassOp. Verify your changes.
REFILL-PLAN-461 [page 2954]	`The type "{refillRecordClassFieldType}" of the Refill Record Class Field "{refillRecordClassFieldName}" cannot be modified to "{newRefillRecordClassFieldTyp e}".`	Use the original type of the Refill Record Class Field. Verify your changes.
REFILL-PLAN-462 (Revoked) [page 2955]	`The Refill Record Class Field "{refillRecordClassFieldName}" cannot be modified if no property value or property name is set.`	Set the property name and the property value of the Refill Record Class Field. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-475 [page 2957]	`The Refill Record Class "{refillRecordClassCode}" cannot be deleted because it does not exist.`	Use an existing code for the Refill Record Class. Verify your changes.
REFILL-PLAN-476 [page 2958]	`The Refill Record Class referred to as "{refillRecordClassRef}" cannot be deleted because it does not exist.`	Use an existing reference for the Refill Record Class. Verify your changes.
REFILL-PLAN-477 [page 2960]	`The Refill Record Class "{refillRecordClassCode}" cannot be deleted because it is referred to by {refillPlanCount} Refill Plan(s). Codes: {refillPlanCodes}.`	First delete the Refill Plan(s). Verify your changes.
REFILL-PLAN-478 [page 2961]	`The Refill Record Class "{refillRecordClassCode}" cannot be deleted because it is referred to by one or more Exportable Item Mappings. Codes: {exportableItemMappingCodes}.`	First delete the Exportable Item Mapping(s). Verify your changes.
REFILL-PLAN-479 [page 2963]	`The Refill Record Class "{refillRecordClassCode}" cannot be deleted because it is referred to by one or more data files.`	First delete the data file(s). Verify your changes.
REFILL-PLAN-480 [page 2965]	`The code of the Refill Record Class is missing in the DeleteRefillRecordClassOp.`	Add the code of Refill Record Class to the DeleteRefillRecordClassOp. Verify your changes.
REFILL-PLAN-481 [page 2966]	`The Refill Record Class referred to by "{refillRecordClassRef}" cannot be deleted because the reference is not a number.`	Check the reference of the Refill Record Class. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-482 [page 2968]	`The description of the Refill Plan "{refillPlanId}" cannot be modified because the Refill Plan has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-483 [page 2969]	`The additional info "{additionalInformationName}" cannot be removed because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-484 [page 2971]	`The additional info "{additionalInformationName}" cannot be added because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-485 [page 2972]	`The description of the additional info "{additionalInformationName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-486 [page 2974]	`The type of the additional info "{additionalInformationName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-488 [page 2975]	`The date value of the additional info "{additionalInformationName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-489 [page 2977]	`The number value of the additional info "{additionalInformationName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-490 [page 2978]	`The string value of the additional info "{additionalInformationName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-491 [page 2980]	`The counter "{counterName}" cannot be removed because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-492 [page 2981]	`The counter "{counterName}" cannot be added because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-493 [page 2983]	`The description of the counter "{counterName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-494 [page 2984]	`The initial value of the counter "{counterName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-495 [page 2986]	`The account assignment "{accountAssignmentName}" cannot be removed because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-496 [page 2987]	`The account assignment "{accountAssignmentName}" cannot be added because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-497 [page 2989]	`The description of the account assignment "{accountAssignmentName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-498 [page 2990]	`The type of the account assignment "{accountAssignmentName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-499 [page 2992]	`The user technical identifier "{userTechIdName}" cannot be removed because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-500 [page 2993]	`The user technical identifier "{userTechIdName}" cannot be added because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-501 [page 2995]	`The description of the user technical identifier "{userTechIdName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-502 [page 2996]	`The refill plan item "{refillPlanItemId}" cannot be removed because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-503 [page 2998]	`The refill plan item "{refillPlanItemId}" cannot be added because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-504 [page 2999]	`The refill plan item "{refillPlanItemId}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-505 [page 3001]	`The parameter "{parameterName}" cannot be removed because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-506 [page 3002]	`The parameter "{parameterName}" cannot be added because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-507 [page 3004]	`The description of the parameter "{parameterName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-508 [page 3005]	`The type of the parameter "{parameterName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-510 [page 3007]	`The date value of the parameter "{parameterName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-511 [page 3008]	`The number value of the parameter "{parameterName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-512 [page 3010]	`The string value of the parameter "{parameterName}" cannot be modified because the Refill Plan "{refillPlanId}" has been released.`	Create a new Refill Plan. Verify your changes.
REFILL-PLAN-513 [page 3011]	`The Refill Logic fails to initialize because the Refill Component "{refillComponentName}" of type "{refillComponentType}" is not valid.`	Check the Refill Component. Verify your changes.
REFILL-PLAN-514 [page 3013]	`The account assignment "{accountAssignmentName}" of the refill plan item "{refillPlanItemId}" cannot be added because the refill plan "{refillPlanId}" has been released.`	Create a new refill plan. Verify your changes.
REFILL-PLAN-515 [page 3014]	`The account assignment "{accountAssignmentName}" of the refill plan item "{refillPlanItemId}" cannot be removed because the refill plan "{refillPlanId}" has been released.`	Create a new refill plan. Verify your changes.
REFILL-PLAN-516 [page 3016]	`The user technical identifier "{userTechIdService}" of the refill plan item "{refillPlanItemId}" cannot be added because the refill plan "{refillPlanId}" has been released.`	Create a new refill plan. Verify your changes.
REFILL-PLAN-517 [page 3017]	`The user technical identifier "{userTechIdService}" of the refill plan item "{refillPlanItemId}" cannot be removed because the refill plan "{refillPlanId}" has been released.`	Create a new refill plan. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-518 [page 3019]	`The usage refill "{usageRateName}" is invalid because its component tree is invalid.`	Check the validity of the components in the usage refill. Verify your changes.
REFILL-PLAN-519 [page 3021]	`The recurring refill "{recurringRateName}" is invalid because its component tree is invalid.`	Check the validity of the rate components in the recurring refill. Verify your changes.
REFILL-PLAN-520 [page 3022]	`The one-shot refill "{oneshotRateName}" is invalid because its component tree is invalid.`	Check the validity of the components in the one-shot refill. Verify your changes.
REFILL-PLAN-521 [page 3024]	`The Refill Record Mapping of "{refillPlanItemId}" Refill Plan Item contains the "{entryName}" entry. This entry does not exist in the "{refillRecordClassId}" Refill Record Class.`	Remove the entry from the Refill Record Mapping or replace it by an existing property of the Refill Record Class. Verify your changes.
REFILL-PLAN-522 [page 3025]	`The Refill Record Mapping of "{refillPlanItemId}" Refill Plan Item contains the "{entryName}" entry with the type: {entryType}. This type is not compatible with the one defined in the "{refillRecordClassId}" Refill Record Class: {propertyType}.`	Check the validity of the components in the one-shot refill. Verify your changes.
REFILL-PLAN-523 (Revoked) [page 3027]	`The code of the refill record class ({refillRecordClassCode}) referred to by the Refill Plan Item "{refillPlanItemId}" cannot be changed to ({newRefillRecordClassCode}).`	Set the ID of the original refill record class. Verify your changes.
REFILL-PLAN-525 [page 3029]	`The name of the account event refill is not set.`	Set the name of the account event refill. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-526 [page 3030]	`The account event refill "{accountEventRefillName}" does not contain any refill component.`	Add a refill component to the account event refill. Verify your changes.
REFILL-PLAN-527 [page 3032]	`The account event refill "{accountEventRefillName}" is invalid because the component tree is invalid.`	Check the validity of the components in the account event refill. Verify your changes.
REFILL-PLAN-528 [page 3033]	`The service name "{serviceName}" of the User Technical Identifier Reference at index {userTechnicalIdentifierReferenceIndex} is reserved for internal use.`	Change the service name to a value that is not reserved for internal use. Verify your changes.
REFILL-PLAN-529 [page 3035]	`The parameter reference "{parameterRefName}" at index {parameterRefIndex} has a date type which is incompatible with the refill logic parameter whose type is {refillLogicParameterType}.`	Change the parameter reference type to the correct one. Verify your changes.
REFILL-PLAN-530 [page 3036]	`The parameter reference "{parameterRefName}" at index {parameterRefIndex} has a number type which is incompatible with the refill logic parameter whose type is {refillLogicParameterType}.`	Change the parameter reference type to the correct one. Verify your changes.
REFILL-PLAN-531 [page 3038]	`The parameter reference "{parameterRefName}" at index {parameterRefIndex} has a string type which is incompatible with the refill logic parameter whose type is {refillLogicParameterType}.`	Change the parameter reference type to the correct one. Verify your changes.
REFILL-PLAN-532 [page 3039]	`The type "{parameterRefType}" of the Parameter Reference "{parameterRefName}" at index {parameterRefIndex} is unsupported (supported types are string, number, date).`	Use a supported type (string, number, date) for the Parameter. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-533 [page 3041]	`The parameter "{parameterName}" at index {parameterIndex} has a date type which is incompatible with the refill logic parameter whose type is {refillLogicParameterType}.`	Change the parameter type to the correct one. Verify your changes.
REFILL-PLAN-534 [page 3043]	`The parameter "{parameterName}" at index {parameterIndex} has a number type which is incompatible with the refill logic parameter whose type is {refillLogicParameterType}.`	Change the parameter type to the correct one. Verify your changes.
REFILL-PLAN-535 [page 3044]	`The parameter "{parameterName}" at index {parameterIndex} has a string type which is incompatible with the refill logic parameter whose type is {refillLogicParameterType}.`	Change the parameter type to the correct one. Verify your changes.
REFILL-PLAN-536 [page 3046]	`The parameter "{parameterName}" cannot reference the mapping table "{mappingTableId}" because this mapping table has an agreement ID.`	Select a mapping table without agreement ID. Verify your changes.
REFILL-PLAN-537 [page 3047]	`The parameter of the refill plan item cannot reference the mapping table "{parameterValue}" because this mapping table has an agreement ID.`	Select a mapping table without agreement ID. Verify your changes.
REFILL-PLAN-538 [page 3049]	`The parameter "{parameterName}" of the refill plan cannot reference the mapping table "{parameterValue}" because this mapping table has an agreement ID.`	Select a mapping table without agreement ID. Verify your changes.

Error Code	Message	Action
REFILL-PLAN-539 [page 3050]	`The parameter "{parameterName}" cannot reference the range table "{rangeTableId}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.
REFILL-PLAN-540 [page 3052]	`The parameter of the refill plan item cannot reference the range table "{parameterValue}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.
REFILL-PLAN-541 [page 3053]	`The parameter "{parameterName}" of the refill plan cannot reference the range table "{parameterValue}" because this range table has an agreement ID.`	Select a range table without agreement ID. Verify your changes.
REFILL-PLAN-542 [page 3055]	`Recurring refill "{recurringRefillName}" is configured for a 4-4-5 calendar. The only supported frequency type is month.`	Set the frequency type to month. Verify your changes.
REFILL-PLAN-543 [page 3056]	`Recurring refill "{recurringRefillName}" is configured for a 4-4-5 calendar. The only supported frequency periods are 1, 3, 6 and 12.`	Set the frequency period to 1, 3, 6 or 12. Verify your changes.
REFILL-PLAN-544 [page 3058]	`Operations on Refill Item Classes are not available because the Prepaid Accounts Management feature is disabled.`	Verify your changes.
REFILL-PLAN-545 [page 3059]	`Operations on Refill Record Classes are not available because the Prepaid Accounts Management feature is disabled.`	Verify your changes.

Error Code	Message	Action
REFILL-PLAN-546 [page 3061]	`Operations on Refill Logic objects are not available because the Prepaid Accounts Management feature is disabled.`	Verify your changes.
REFILL-PLAN-547 [page 3062]	`Operations on Refill Plans are not available because the Prepaid Accounts Management feature is disabled.`	Verify your changes.
REFILL-PLAN-548 [page 3063]	`The frequency of the recurring refill "{recurringRefillName}" is invalid.`	Set a valid frequency in the recurring refill. Verify your changes.
REST-CHARG-ING-1 [page 3065]	`The charging session with the ID "{sessionID}" does not exist in the SAP CC system.`	Check if the session has not been automatically removed or closed. Add a valid session ID.
REST-CHARG-ING-2 [page 3066]	`The charging session with the ID "{sessionID}" already exists in the SAP CC system.`	Set a new session ID and send a new request.
RFC-1 [page 3068]	`One or more billable items or consumption items could not be loaded into SAP Convergent Invoicing because they are invalid.`	Check the related error messages and correct the pricing configuration.
RFC-2 [page 3070]	`One or more billable items or consumption items could not be loaded into SAP Convergent Invoicing because of a communication error.`	Execute the operation again later.
SPEN-DINGSTA-TUS-1 [page 3072]	`The label "{label}" is not valid because it does not verify the regular expression "{regex}".`	Set up another value of label verifying the regexp syntax. Verify your changes.

Error Code	Message	Action
SPENDINGSTATUS-2 [page 3073]	`The code ID of the spending status description "{spendingStatusDescriptionId}" is not valid because it does not verify the regular expression "{regex}".`	Set up another ID of the spending status description verifying the regexp syntax. Verify your changes.
SPENDINGSTATUS-3 [page 3075]	`The text description of the spending status description "{spendingStatusDescriptionDescription}" is not valid because it does not verify the regular expression "{regex}".`	Set up another text description of the spending status description verifying the regexp syntax. Verify your changes.
SPENDINGSTATUS-4 [page 3076]	`The label "{label}" at the index "{index}" is not valid.`	Check the previous error messages in the error stack. Verify your changes.
SPENDINGSTATUS-5 [page 3078]	`The label "{label}" is duplicated at the index "{index1}" and "{index2}".`	Remove a label in the spending status description specified in the operation request. Verify your changes.
SPENDINGSTATUS-6 [page 3079]	`The spending status description needs at least a label.`	Add at least a label in the spending status description. Verify your changes.
SPENDINGSTATUS-100 [page 3081]	`The spending status description is missing in the create operation.`	Specify a spending status description in the create operation request. Verify your changes.
SPENDINGSTATUS-101 [page 3082]	`The spending status description "{spendingStatusDescriptionId}" already exists.`	Specify another spending status description in the create operation request. Verify your changes.
SPENDINGSTATUS-200 [page 3084]	`The spending status description is missing in the modify operation.`	Specify a spending status description in the modify operation request. Verify your changes.

Error Code	Message	Action
SPENDINGSTATUS-201 [page 3085]	`The spending status description "{spendingStatusDescriptionId}" does not exist.`	Specify another spending status description to the modify operation request. Verify your changes.
SPENDINGSTATUS-202 [page 3086]	`Cannot modify the spending status description "{spendingStatusDescriptionId}". Its label "{missingSpendingStatusLabel}" is still used.`	Add the missing label back in the spending status description to modify or check why the label is still used. Verify your changes.
SPENDINGSTATUS-203 [page 3088]	`Cannot modify the spending status description "{spendingStatusDescriptionId}"; Its description "{spendingStatusDescriptionDescription}" cannot be changed.`	Create a new spending status description. Verify your changes.
SPENDINGSTATUS-300 [page 3090]	`The mandatory filter is missing in the search operation.`	Specify a filter in the search operation request. Verify your changes.
SPENDINGSTATUS-301 [page 3091]	`Cannot search for spending status descriptions. The search operation or the specified filter is invalid. Reason: {reasonInformation}.`	Check the reason information recorded in your error message; The reason is based on the Java Technology. It details the exception raised in the connected SAP CC system. Typical reasons are: Invalid search filter, Back-end database failure. Refer to the Java/XML API Reference (Core Library) technical documentation for more information about the `com.highdeal.filter.hci.InvalidSearchException`. Verify your changes.
SPENDINGSTATUS-400 [page 3093]	`The ID of the spending status description is missing in the delete operation.`	Specify the ID of the relevant spending status description in the operation request. Verify your changes.
SPENDINGSTATUS-401 [page 3094]	`The spending status description "{spendingStatusDescriptionId}" does not exist.`	Specify another ID of spending status description in the delete operation request. Verify your changes.

Error Code	Message	Action
SPENDINGSTATUS-402 [page 3095]	`Error while deleting the spending status description "{spendingStatusDescriptionId}". The spending status description is still used in one monitoring plan.`	First delete all monitoring plans referencing the spending status description. Verify your changes.
SQL-1 [page 3097]	`Incompatible database version ({version}).`	Upgrade database to a compatible version. Verify your changes.
SQL-2 [page 3098]	`Cannot find JDBC driver ({driverName}).`	Check your classpath. Verify your changes.
SQL-3 [page 3100]	`Bad URL syntax : {URL}. Expected format: {URLSample}.`	URL must have the format {1}. Verify your changes.
SQL-4 [page 3101]	`Unable to finish the SQL IResultSet {method} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.
SQL-5 [page 3103]	`The SQLServer database is not in read committed snapshot mode.`	Set the Microsoft SQL Server database in read committed snapshot mode. As a dba, execute the command script: `ALTER DATABASE <DB_NAME> SET READ_COMMITTED_SNAPSHOT ON` Verify your changes.
SQL-6 [page 3105]	`The SQL Exception due to {SQLState} SQL state is not fatal and can be retried.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-7 [page 3106]	`Cannot add statement to batch due to {SQLState} SQL State.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-8 [page 3108]	`Cannot set statement batch size due to {SQLState} SQL State.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.

Error Code	Message	Action
SQL-9 [page 3109]	`Cannot execute statement batch due to {SQLState} SQL State.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-10 [page 3111]	`Cannot set timestamp on prepareStatement due to {SQLState} SQL State.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-11 [page 3112]	`A failover is required by the SQL Exception due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-12 [page 3114]	`The database is not ready to accept SQL query. SQL state {SQLState}.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-13 [page 3115]	`Unable to change transaction isolation level to {isolationLevel} due to SQL state {SQLState}.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-14 [page 3117]	`Unable to reserve ID range for ids generation due to SQL state {SQLState}.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-15 [page 3118]	`Unable to get BigDecimal value from resultSet due to SQL state {SQLState}.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-16 [page 3120]	`The backup JDBC URI ({jdbcBackupUri}) must begin by {jdbcDriverUriSample} like the primary JDBC URI ({jdbcUri}).`	Consult your JDBC driver documentation to get information about the URI format. Verify your changes.

Error Code	Message	Action
SQL-17 [page 3121]	`Invalid JDBC URI ({jdbcUri}) or related JDBC driver not found.`	Refer to the documentation of the SQLHELPER_JDBC_URI system parameter to check the syntax of the specified URI. In case your URI corresponds to an Oracle RDBMS, check that the corresponding JDBC driver is available within your landscape and matches the minimum required version. Verify your changes.
SQL-18 [page 3123]	`There is no SQL transaction opened for the current process.`	An SQL transaction must be opened to use the database, please contact support. Verify your changes.
SQL-19 [page 3124]	`The SQL Manager is closed and cannot be used anymore.`	Verify that your process is not shutting down. Verify your changes.
SQL-20 [page 3126]	`A shutdown has been called on this SQL connection pool. SQL connection cannot be delivered.`	Verify that your process is not shutting down. Verify your changes.
SQL-21 [page 3127]	`This SQL transaction has been canceled and cannot be used anymore.`	Open a new transaction for your process. Verify your changes.
SQL-22 [page 3129]	`Unable to execute the SQL operation due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-23 [page 3130]	`Unable to commit the SQL transaction due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-24 [page 3132]	`Unable to rollback the SQL transaction due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-25 [page 3133]	`Unable to close the SQL prepared statement due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.

Error Code	Message	Action
SQL-26 [page 3135]	`Unable to close the SQL statement due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-27 [page 3136]	`Unable to close the SQL prepared statement due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-28 [page 3138]	`Unable to close the ResultSet for Big Query statement due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-29 [page 3139]	`Unable to commit the database connection for Big Query statement due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-30 [page 3141]	`Unable to close the database connection for Big Query statement due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-31 [page 3142]	`Unable to get the value of Microsoft SQLServer is_read_committed_snapshot_on parameters due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-32 [page 3144]	`Unable to close the ResultSet used to get the value of Microsoft SQLServer is_read_committed_snapshot_on parameters due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-33 [page 3145]	`Unable to create the {preparedStatement} prepared statement due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.
SQL-34 [page 3147]	`Unable to close the prepared statement used by this query {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.

Error Code	Message	Action
SQL-35 [page 3148]	`Unable to prepare statement for {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.
SQL-36 [page 3150]	`Unable to execute prepared statement {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.
SQL-37 [page 3151]	`The driver and SQLServer database are not in sync regarding date management. {SQLState} SQL state.`	Consult your database or your driver documentation to get information about the {0} SQL state. Verify your changes.
SQL-38 [page 3153]	`Unable to execute the addBatch() method of the prepared statement using the Oracle JDBC driver due to {SQLState} SQL state.`	Consult your database or your driver documentation to get information about the {0} SQL state. Verify your changes.
SQL-39 [page 3154]	`Unable to use the SQL Connection pool as it has been shutdown.`	Verify that the server instance is not shutting down. Verify your changes.
SQL-40 [page 3156]	`Unable to close prepared statement {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.
SQL-41 [page 3157]	`Unable to execute the prepared statement {SQLStatement} and build a ResultSet due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.
SQL-42 [page 3159]	`Unable to execute the DML prepared statement {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.
SQL-43 [page 3160]	`Unable to cancel the prepared statement {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.

Error Code	Message	Action
SQL-44 [page 3162]	`Unable to set object {ObjectAsString} of type {ObjectType} at position {ObjectPosition} in the prepared statement {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {4} SQL state. Verify your changes.
SQL-45 [page 3163]	`Unable to reserve ID range for ids generation because there is no line in ID_TABLE.`	Check your database scripts to see if the original line has been inserted in `ID_TABLE`. Verify your changes.
SQL-46 [page 3165]	`Unable to add the current batch to the prepared statement {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-47 [page 3166]	`Unable to execute the batch of DML prepared statement {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {1} SQL state. Verify your changes.
SQL-48 [page 3168]	`Unable to use the embedded ResultSet due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-49 [page 3169]	`Unable to make a checkpoint on the SQL transaction due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-50 [page 3171]	`Unable to revert the last checkpoint on the SQL transaction due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-51 [page 3172]	`Unable to add batch on the prepared statement {SQLStatement} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-52 [page 3174]	`Unable to execute the prepared statement {SQLStatement} on a close SQL connection.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.

Error Code	Message	Action
SQL-53 [page 3175]	`Unable to execute an update to the prepared statement {SQLStatement} on a close SQL connection.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-54 [page 3177]	`Unable to execute a batch to the prepared statement {SQLStatement} on a close SQL connection.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-55 [page 3178]	`Unable to set object to the prepared statement {SQLStatement} on a close SQL connection.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-56 [page 3180]	`Unable to add batch on the prepared statement {SQLStatement} on a close SQL connection.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-57 [page 3181]	`Unable to cancel the prepared statement {SQLStatement} on a close SQL connection.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-58 [page 3183]	`Unable to reconnect ID generation connection due to SQL state {SQLStatement}.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SQL-59 [page 3184]	`This database does not support to store strings which end with a space character ({invalidString}).`	Sanitize the data so that strings do not end with a space character. Verify your changes.
SQL-60 [page 3186]	`Unable to retrieve the size of the column {columnName} of the table {tableName} due to {SQLState} SQL state.`	Consult your database documentation to get information about the {2} SQL state. Verify your changes.
SQL-61 [page 3187]	`The server is not connected to the database using the URL {URL}.`	The database with the URL {0} is offline or it is not possible to connect to it. Check the status of the database and reconnect the server to the database using the adequate Admin+ command. Verify your changes.

Error Code	Message	Action
SQL-62 [page 3189]	`Cannot process statement because a Server failure exception occurred.`	Contact your SAP Support Team. Verify your changes.
SQL-63 [page 3190]	`Cannot process statement because the database update pool for the database {URL} is not enabled.`	Enable the database update pool. Verify your changes.
SQL-64 [page 3192]	`Unable to change the transaction isolation level due to {SQLState} SQL state.`	Consult your database documentation to get information about the {0} SQL state. Verify your changes.
SUBSCRIBER-DATA-1 [page 3193]	`The Subscriber Data type is missing or invalid.`	Fill the Subscriber Data type with a correct value. Verify your changes.
SUBSCRIBER-DATA-2 [page 3195]	`The Subscriber Data id is missing.`	Fill the Subscriber Data ID. Verify your changes.
SUBSCRIBER-DATA-3 [page 3196]	`No Subscriber Data found for id ''{id}'' and type ''{type}''.`	Fill the Subscriber Data ID and type with a correct value. Verify your changes.
SUBSCRIBER-DATA-4 [page 3198]	`Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because it does not exist.`	Correct the Subscription ID of the Counter Snapshot to import. Verify your changes.
SUBSCRIBER-DATA-5 [page 3199]	`Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because it is not of type offline.`	None. Verify your changes.
SUBSCRIBER-DATA-6 [page 3201]	`Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because no Subscription is defined in the Snapshot for date ''{snapshotDate}''.`	None. Verify your changes.

Error Code	Message	Action
SUBSCRIBER-DATA-7 [page 3202]	`Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because the Sub-Subscription ''{subSubscriptionCode}'' does not exist.`	Correct the ID of the Sub-Subscription with an valid name, or remove the invalid Sub-Subscription. Verify your changes.
SUBSCRIBER-DATA-8 [page 3204]	`Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because the Charge ''{chargeCode}'' does not exist.`	Correct the ID of the Charge with an valid name, or remove the invalid Charge. Verify your changes.
SUBSCRIBER-DATA-9 [page 3205]	`Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because the Counter name ''{counterName}'' is not valid.`	Correct the name of the invalid Counter. Verify your changes.
SUBSCRIBER-DATA-10 [page 3207]	`Cannot import Access ''{serviceId}''/''{userServideId}'' for Subscription ''{subscriptionCode}'' because there are overlapped periods.`	Correct the Access chronology. Verify your changes.
SUBSCRIBER-DATA-11 [page 3208]	`Cannot import Access ''{serviceId}''/''{userServideId}'' for Subscription ''{subscriptionCode}'' because a period overlaps the existing Access.`	Correct the Access chronology. Verify your changes.
SUBSCRIBER-DATA-12 [page 3210]	`Cannot import Subscription ''{subscriptionCode}'' because the chronology is invalid.`	None. Verify your changes.
SUBSCRIBER-DATA-13 [page 3211]	`The Subscriber Data owner is missing.`	Fill the Subscriber Data owner. Verify your changes.

Error Code	Message	Action
SUBSCRIBER-DATA-14 [page 3213]	`Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because the dates ''{snapshotDate1}'' and ''{snapshotDate2}'' are not consecutive.`	Correct the dates of the Counter Snapshots. Verify your changes.
SUBSCRIBERAC-COUNT-1 [page 3214]	`The subscriber account "{subscriberAccountId}" (with "{serviceProvider}" as service provider) is not valid.`	Fix the data model that is provided. Verify your changes.
SUBSCRIBERAC-COUNT-2 [page 3216]	`The expected type of the additional info "{additionalInfoName}" must be "{additionalInfoExpectedType}" but not "{additionalInfoInvalidType}".`	Change the additional info type to the expected type. Verify your changes.
SUBSCRIBERAC-COUNT-3 [page 3217]	`The value of the additional info "{additionalInfoName}" must not be empty.`	Fix the additional info value. Verify your changes.
SUBSCRIBERAC-COUNT-4 [page 3219]	`The Customer Management Area name "{additionalInfoValue}" provided as a value of the additional info "{additionalInfoName}" is not defined.`	Choose a name of Customer Management Area coming from the configured list of Customer Management Areas. Verify your changes.
SUBSCRIBERAC-COUNT-5 [page 3220]	`The subscriber account "{subscriberAccountId}" (with "{serviceProvider}" as service provider) must not contain any prepaid account because the Prepaid Accounts Management feature is disabled.`	Remove all prepaid accounts from the subscriber account. Verify your changes.
SUBSCRIBERAC-COUNT-6 [page 3222]	`The reset frequency of the credit limit balance "{creditLimitBalanceName}" is invalid.`	Set a valid reset frequency in the credit limit balance. Verify your changes.

Error Code	Message	Action
TRANSPORTREQUEST-1 [page 3223]	`The mandatory filter in the Search Transport Request operation is missing.`	Add a filter in the Search Transport Request operation. Verify your changes.
TRANSPORTREQUEST-2 [page 3225]	`An error occurred during the execution of the search operation: {errorMessage}.`	Verify your changes.
TRANSPORTREQUEST-3 [page 3226]	`The Web services of the updater are not available for receiving responses.`	Enable the Web services of the updater. Verify your changes.
TRANSPORTREQUEST-4 [page 3228]	`The execution of transport requests is already running.`	Wait for the end of current transport requests execution before attempting a new one. Verify your changes.
TRANSPORTREQUEST-5 [page 3229]	`The mandatory filter in the Execute Transport Request operation is missing.`	Add a filter in the Execute Transport Request operation. Verify your changes.
TRANSPORTREQUEST-6 [page 3230]	`An error occurred during the transport request execution: {errorMessage}.`	Verify your changes.
TRANSPORTREQUEST-7 [page 3232]	`The name of the associated Change List is missing.`	Add a change list name in the Create Transport Request operation. Verify your changes.
TRANSPORTREQUEST-8 [page 3233]	`The Transport Request cannot be created because the change list {changeListName} does not exist.`	Create first the associated change list with the given name. Verify your changes.
TRANSPORTREQUEST-9 [page 3235]	`The mandatory filter in the Delete Transport Request operation is missing.`	Add a filter in the Delete Transport Request operation. Verify your changes.
TRANSPORTREQUEST-10 [page 3236]	`An error occurred during the execution of the delete operation: {errorMessage}.`	Verify your changes.

Error Code	Message	Action
TRANS-PORTRE-QUEST-11 [page 3238]	`The Transport Request is missing in the creation operation.`	Add a Transport Request to the creation operation. Verify your changes.

4.1 AGGREGATIONPOLICY-1

Message

```
The code of the Aggregation Policy is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a code to the Aggregation Policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.2 AGGREGATIONPOLICY-2

Message

```
The owner of the "{aggregationPolicyCode}" Aggregation Policy is missing.
```

Legend

- `{aggregationPolicyCode}`: The code of the Aggregation Policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an owner to the Aggregation Policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.3 AGGREGATIONPOLICY-3

Message

```
The code of the Charged Item Class for the "{aggregationPolicyCode}" Aggregation
Policy is missing.
```

Legend

- `{aggregationPolicyCode}`: The code of the Aggregation Policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the code of the Charged Item Class for the Aggregation Policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.4 AGGREGATIONPOLICY-4

Message

```
The "{itemClassCode}" Charged Item Class of the "{aggregationPolicyCode}"
Aggregation Policy does not exist.
```

Legend

- `{itemClassCode}`: The code of the Aggregation Policy
- `{aggregationPolicyCode}`: The code of the Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an existing code for the Charged Item Class or create a new Charged Item Class with this code.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.5 AGGREGATIONPOLICY-5

Message

```
Rule #{ruleIndex} has no field name.
```

Legend

- `{ruleIndex}`: The index of the current rule

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a field name to the rule or delete this rule.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.6 AGGREGATIONPOLICY-6

Message

```
The "{fieldName}" field name used by Rule #{ruleIndex} is already used by
Rule #{previousRuleIndex}.
```

Legend

- `{fieldName}`: The name of the field used by the rule
- `{ruleIndex}`: The index of the current rule
- `{previousRuleIndex}`: The index of the another rule which uses the same field name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set another field name to the rule or delete this rule.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.7 AGGREGATIONPOLICY-7

Message

```
The "{fieldName}" field name used by Rule #{ruleIndex} does not exist in the
"{itemClassCode}" Charged Item Class.
```

Legend

- `{fieldName}`: The name of the field used by the rule
- `{ruleIndex}`: The index of the current rule
- `{itemClassCode}`: The code of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

The field name must exist in the specified Charged Item Class. Specify an existing field name for the rule, or add a new field in the Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.8 AGGREGATIONPOLICY-8

Message

```
Rule #{ruleIndex} using the "{fieldName}" field name has no aggregation operator.
```

Legend

- `{ruleIndex}`: The index of the current rule
- `{fieldName}`: The name of the field used by the rule

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an aggregation operator for the rule or delete this rule.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.9 AGGREGATIONPOLICY-9

Message

```
Rule #{ruleIndex} uses an aggregation operator which is not compatible with
the "{fieldType}" type of the "{fieldName}" field. Compatible types are:
{expectedTypes}.
```

Legend

- `{ruleIndex}`: The index of the current rule
- `{fieldType}`: The type of the field used by the rule
- `{fieldName}`: The name of the field used by the rule
- `{expectedTypes}`: A `CSV` string contening the list of types compatible with the operator

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an aggregation operator which is compatible with the type of the specified field name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.10 AGGREGATIONPOLICY-10

Message

```
The Aggregation Policy is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an Aggregation Policy in the creation operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.11 AGGREGATIONPOLICY-11

Message

```
Unable to create the Aggregation Policy. "{aggregationPolicyCode}" code already
exists.
```

Legend

- `{aggregationPolicyCode}`: The code of the Aggregation Policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another code for the Aggregation Policy to create.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.12 AGGREGATIONPOLICY-12

Message

```
Unable to modify the Aggregation Policy. "{aggregationPolicyCode}" Aggregation
Policy does not exist.
```

Legend

- `{aggregationPolicyCode}`: The code of the Aggregation Policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an existing code for the Aggregation Policy to modify.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.13 AGGREGATIONPOLICY-13

Message

```
Unable to modify the "{aggregationPolicyCode}" Aggregation Policy. Modification
of the Charged Item Class is not allowed.
```

Legend

- `{aggregationPolicyCode}`: The code of the Aggregation Policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the Charged Item Class which is already specified in the Aggregation Policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.14 AGGREGATIONPOLICY-14

Message

```
Unable to delete the Aggregation Policy. "{aggregationPolicyCode}" Aggregation
Policy does not exist.
```

Legend

- `{aggregationPolicyCode}`: The code of the Aggregation Policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an existing code for the Aggregation Policy to delete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.15 AGGREGATIONPOLICY-15

Message

```
The owner of the Aggregation Policy ({aggregationPolicyOwner}) is different
from the owner of Charged Item Class ({itemClassOwner}).
```

Legend

- `{aggregationPolicyOwner}`: The owner of the Aggregation Policy
- `{itemClassOwner}`: The owner of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another owner for the Aggregation Policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.16 AGGREGATIONPOLICY-16

Message

```
Unable to delete the Aggregation Policy. "{aggregationPolicyCode}" Aggregation
Policy is used by the following Charge Plan(s): {chargePlanCodes}.
```

Legend

- `{aggregationPolicyCode}`: The code of the Aggregation Policy
- `{chargePlanCodes}`: A `CSV` string containing the list of Charge Plan codes

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the Charge Plan(s) to remove the reference to this Aggregation Policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.17 AGGREGATIONPOLICY-18

Message

```
Missing value for the field name of Number Report Condition
#{numberReportConditionIndex}.
```

Legend

- `{numberReportConditionIndex}`: The index of the current Number Report condition

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a field name to the Number Report Condition or delete this Number Report Condition.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.18 AGGREGATIONPOLICY-19

Message

```
The "{fieldName}" field name used by Number Report Condition
#{numberReportConditionIndex}
does not exist in the "{itemClassCode}" Charged Item Class.
```

Legend

- `{fieldName}`: The name of the field used by the Number Report Condition
- `{numberReportConditionIndex}`: The index of the current Number Report condition
- `{itemClassCode}`: The code of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

The field name must exist in the specified Charged Item Class. Specify an existing field name for the Number Report Condition, or add a new field in the Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.19 AGGREGATIONPOLICY-20

Message

```
Missing value for Number Report Condition #{numberReportConditionIndex} using
the "{fieldName}" field name.
```

Legend

- `{numberReportConditionIndex}`: The index of the current Number Report condition
- `{fieldName}`: The name of the field used by the Number Report Condition

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a value to the Number Report Condition.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.20 AGGREGATIONPOLICY-22

Message

```
Incorrect "{value}" value for the Duration-based Report Condition.
```

Legend

- `{value}`: The value of the Duration-based Report Condition

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a value greater than 0 in the Duration-based Report Condition.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.21 AGGREGATIONPOLICY-23

Message

```
Invalid unit for the Duration-based Report Condition.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid unit in the Duration-based Report Condition.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.22 AGGREGATIONPOLICY-24

Message

```
The Aggregation Policy can contain a maximum of one Duration-based Report
Condition.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set only one Duration-based Report Condition in the Aggregation Policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP11 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.23 AGGREGATIONPOLICY-25

Message

```
Unable to delete the Aggregation Policy. "{aggregationPolicyCode}" Aggregation
Policy is used by the following Allowance Plan(s): {allowancePlanCodes}.
```

Legend

- `{aggregationPolicyCode}`: The code of the Aggregation Policy
- `{allowancePlanCodes}`: A `CSV` string containing the list of Allowance Plan codes

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the Allowance Plan(s) to remove the reference to this Aggregation Policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.24 AGGREGATIONPOLICY-26

Message

```
The Aggregation Policy is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an Aggregation Policy in the modification operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.25 ALLOWANCE-1

Message

```
The ID of the Allowance Plan is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.26 ALLOWANCE-2

Message

```
The owner of the Allowance Plan "{allowancePlanId}" is missing.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the owner of the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.27 ALLOWANCE-3

Message

```
The description of the Allowance Plan "{allowancePlanId}" is missing.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.28 ALLOWANCE-4

Message

```
The status of the Allowance Plan "{allowancePlanId}" is missing.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a status to the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.29 ALLOWANCE-6

Message

```
Error while validating the Allowance Plan "{allowancePlanId}".
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.30 ALLOWANCE-10

Message

```
The Counter at the index {counterIndex} is empty.
```

Legend

- `{counterIndex}`: The index of the empty Counter that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Counter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.31 ALLOWANCE-11

Message

```
The name of the Counter at index {counterIndex} is missing.
```

Legend

- `{counterIndex}`: The index of the Counter in the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.32 ALLOWANCE-12

Message

```
The name "{counterName}" of the Counter at index {secondIndex} is already
used by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Counters
- `{firstIndex}`: The index of the first occurrence of the name in Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.33 ALLOWANCE-13

Message

```
The Counter "{counterName}" at index {counterIndex} does not refer to a Counter
of
the Allowance Plan Item.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Counter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.34 ALLOWANCE-14

Message

```
The description of the Counter "{counterName}" at index {counterIndex} is
missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.35 ALLOWANCE-15

Message

```
The initial value of the Counter "{counterName}" at index {counterIndex} is
missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an initial value to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.36 ALLOWANCE-16

Message

```
The Parameter at the index {parameterIndex} is empty.
```

Legend

- `{parameterIndex}`: The index of the empty Parameter that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Parameter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.37 ALLOWANCE-17

Message

```
The name of the Parameter at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter in the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.38 ALLOWANCE-18

Message

```
The name "{parameterName}" of the Parameter at index {secondIndex} is already
used
by the Parameter at index {firstIndex}.
```

Legend

- `{parameterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Parameters
- `{firstIndex}`: The index of the first occurrence of the name in Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.39 ALLOWANCE-20

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex} is missing
or
unknown (the supported types are string, number, date).
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter or change it into a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.40 ALLOWANCE-21

Message

```
The description of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.41 ALLOWANCE-22

Message

```
Error while validating the Parameter "{parameterName}" at index {parameterIndex}.
```

Legend

- `{parameterName}`: The name of the allowance plan Parameter
- `{parameterIndex}`: The index of the allowance plan Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.42 ALLOWANCE-25

Message

```
The parameter additional information "{additionalInformationName}" at index
{additionalInformationIndex} is unknown.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this additional information or replace it with a known one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.43 ALLOWANCE-26

Message

```
The data type of the parameter is not defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add this additional information or remove any additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.44 ALLOWANCE-27

Message

```
The parameter is a mapping table ID but no mapping table class is defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the additional information of the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.45 ALLOWANCE-28

Message

```
The parameter is a range table ID but no range table class is defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the additional information of the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.46 ALLOWANCE-29

Message

```
The parameter is a mapping table key and could not be linked to a mapping table
class.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the additional information of the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.47 ALLOWANCE-30

Message

```
The parameter cannot declare additional information without a data type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the additional information of a data type or remove any additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.48 ALLOWANCE-36

Message

```
The Allowance Plan Item at index {allowancePlanItemIndex} is empty.
```

Legend

- `{allowancePlanItemIndex}`: The index of the Allowance Plan Item in the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Allowance Plan Item or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.49 ALLOWANCE-37

Message

```
The ID of the Allowance Plan Item at index {allowancePlanItemIndex} is missing.
```

Legend

- `{allowancePlanItemIndex}`: The index of the Allowance Plan Item in the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the Allowance Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.50 ALLOWANCE-38

Message

```
The ID "{allowancePlanItemId}" of the Allowance Plan Item at index {secondIndex}
is already used by the Allowance Plan Item at index {firstIndex}.
```

Legend

- `{allowancePlanItemId}`: The duplicated ID
- `{secondIndex}`: The index of the second occurrence of the name in Allowance Plan Items
- `{firstIndex}`: The index of the first occurrence of the name in Allowance Plan Items

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the Allowance Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.51 ALLOWANCE-39

Message

```
No Allowance Logic is specified.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Allowance Logic to the Allowance Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.52 ALLOWANCE-40

Message

```
Error while validating the Allowance Plan Item "{allowancePlanItemId}" at index
{allowancePlanItemIndex}.
```

Legend

- `{allowancePlanItemId}`: The ID of the Allowance Plan Item
- `{allowancePlanItemIndex}`: The index of the Allowance Plan Item in the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.53 ALLOWANCE-41

Message

```
The ID of the master Allowance Logic referred to by the Allowance Plan Item is
missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the master Allowance Logic in the Allowance Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.54 ALLOWANCE-42

Message

```
The ID of the master Allowance Logic referred to by the Allowance Plan Item and
the
code "{retrievedAllowanceLogicCode}" of the retrieved Allowance Logic do not
match.
```

Legend

- `{retrievedAllowanceLogicCode}`: The code of the retrieved Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.55 ALLOWANCE-43

Message

```
The owner of the Allowance Plan and the owner of the Allowance Logic. The owner
of the Allowance Plan is "{allowancePlanOwner}". The owner of the Allowance
Logic is
"{allowanceLogicOwner}".
```

Legend

- `{allowancePlanOwner}`: The owner of the Allowance Plan
- `{allowanceLogicOwner}`: The owner of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID the master Allowance Logic that has the same owner as the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.56 ALLOWANCE-44

Message

```
The name of the Counter at index {counterIndex} is missing.
```

Legend

- `{counterIndex}`: The index of the Counter in the Allowance Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.57 ALLOWANCE-45

Message

```
The name "{counterName}" of the Counter at index {secondIndex} is already
used by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Counters
- `{firstIndex}`: The index of the first occurrence of the name in Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.58 ALLOWANCE-46

Message

```
The name of the Counter Reference at index {counterReferenceIndex} is missing.
```

Legend

- `{counterReferenceIndex}`: The index of the Counter Reference in the Allowance Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.59 ALLOWANCE-47

Message

```
The name "{counterName}" of the Counter Reference at index {secondIndex} is
already used by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Counters
- `{firstIndex}`: The index of the first occurrence of the name in Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.60 ALLOWANCE-48

Message

```
The initial value of the Counter "{counterName}" at index {counterIndex}
is missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an initial value to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.61 ALLOWANCE-49

Message

```
The Counter "{counterName}" at index {counterIndex} does not exist in the
Allowance Logic "{allowanceLogicId}".
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter
- `{allowanceLogicId}`: The id of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.62 ALLOWANCE-50

Message

```
The target name of the Counter Reference "{counterReferenceName}" at index
{counterReferenceIndex} is missing.
```

Legend

- `{counterReferenceName}`: The name of the Counter Reference
- `{counterReferenceIndex}`: The index of the Counter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.63 ALLOWANCE-51

Message

```
The Counter "{targetName}" targeted by the Counter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} does not exist.
```

Legend

- `{targetName}`: The target name of the Counter Reference
- `{parameterReferenceName}`: The name of the Counter Reference
- `{parameterReferenceIndex}`: The index of the Counter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the Counter Reference into an existing one or create a new Counter in the Allowance Plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.64 ALLOWANCE-52

Message

```
The Counter Reference "{counterRefName}" at index {counterRefIndex} does not
exist in the Allowance Logic "{allowanceLogicId}".
```

Legend

- `{counterRefName}`: The name of the Counter Reference
- `{counterRefIndex}`: The index of the Counter Reference
- `{allowanceLogicId}`: The ID of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.65 ALLOWANCE-58

Message

```
The name of the Parameter at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter in the Allowance Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.66 ALLOWANCE-59

Message

```
The name "{parameterName}" of the Parameter at index {secondIndex} is already
used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Parameters
- `{firstIndex}`: The index of the first occurrence of the name in Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.67 ALLOWANCE-60

Message

```
The name of the Parameter Reference at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter Reference in the Allowance Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.68 ALLOWANCE-61

Message

```
The name "{parameterReferenceName}" of the Parameter Reference at index
{secondIndex}
is already used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterReferenceName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Parameters
- `{firstIndex}`: The index of the first occurrence of the name in Parametersc

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.69 ALLOWANCE-62

Message

```
The Parameter "{parameterName}" of the Allowance Logic points to an unknown
mapping table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.70 ALLOWANCE-63

Message

```
The Parameter "{parameterName}" of the Allowance Logic points to an unknown
range table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.71 ALLOWANCE-64

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex} is missing
or unknown (the supported types are string, number, date).
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter or change it into a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.72 ALLOWANCE-65

Message

```
The date value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.73 ALLOWANCE-66

Message

```
The number value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.74 ALLOWANCE-67

Message

```
The string value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.75 ALLOWANCE-68

Message

```
The type "{parameterType}" of the Parameter "{parameterName}" at index
{parameterIndex}
is unsupported (the supported types are string, number, date).
```

Legend

- `{parameterType}`: The unsupported type of the Parameter
- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date) for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.76 ALLOWANCE-69

Message

```
The Parameter "{parameterName}" at index {parameterIndex} does not exist in the
Allowance Logic "{allowanceLogicId}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{allowanceLogicId}`: The ID of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.77 ALLOWANCE-70

Message

```
Error while validating the Parameter "{parameterName}" at index {parameterIndex}.
```

Legend

- `{parameterName}`: The name of the allowance plan item Parameter
- `{parameterIndex}`: The index of the allowance plan item Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.78 ALLOWANCE-71

Message

```
The target name of the Parameter Reference "{parameterReferenceName}" at index
{parameterReferenceIndex} is missing.
```

Legend

- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.79 ALLOWANCE-72

Message

```
The Parameter "{targetName}" targeted by the Parameter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} does not exist.
```

Legend

- `{targetName}`: The target name of the Parameter Reference
- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the Parameter Reference into an existing one or create a new Parameter in the Allowance Plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.80 ALLOWANCE-73

Message

```
The type of the Parameter Reference "{parameterReferenceName}" at index
{parameterReferenceIndex}
is missing or unknown (the supported types are string, number, date).
```

Legend

- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter Reference or change it into a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.81 ALLOWANCE-74

Message

```
The type "{parameterReferenceType}" of the Parameter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} is not compatible with the type
"{parameterType}" of
the targeted Parameter.
```

Legend

- `{parameterReferenceType}`: The type of the Parameter Reference
- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference
- `{parameterType}`: The type of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Parameter Reference to a compatible Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.82 ALLOWANCE-75

Message

```
Error while validating the Parameter Reference "{parameterName}" at index
{parameterIndex}.
```

Legend

- `{parameterName}`: The name of the allowance plan item Parameter Reference
- `{parameterIndex}`: The index of the allowance plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.83 ALLOWANCE-76

Message

```
The Parameter Reference "{parameterRefName}" at index {parameterRefIndex} does
not
exist in the Allowance Logic "{allowanceLogicId}".
```

Legend

- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference
- `{allowanceLogicId}`: The ID of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.84 ALLOWANCE-77

Message

```
The Parameter "{cpParameterName}" of the Allowance Plan referenced by the
Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
```

```
declared as
a mapping table ID.
```

Legend

- `{cpParameterName}`: The name of the allowance plan Parameter
- `{parameterReferenceName}`: The name of the allowance plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the allowance plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the data type of the mapping table ID and the additional information of the mapping table class in the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.85 ALLOWANCE-78

Message

```
The Parameter "{cpParameterName}" of the Allowance Plan referenced by the
Parameter Reference
"{parameterReferenceName}" at index {parameterReferenceIndex} declares an
incompatible mapping
table class "{cpParameterMappingTableClass}" while the Parameter Reference is of
class
"{parameterReferenceMappingTableClass}".
```

Legend

- `{cpParameterName}`: The name of the allowance plan Parameter
- `{parameterReferenceName}`: The name of the allowance plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the allowance plan item Parameter Reference
- `{cpParameterMappingTableClass}`: The mapping table class of the allowance plan Parameter
- `{parameterReferenceMappingTableClass}`: The mapping table class of the allowance plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the data type of the mapping table ID and the additional information of the mapping table class in the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.86 ALLOWANCE-79

Message

```
The Parameter "{cpParameterName}" of the Allowance Plan referenced by the
Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared
as a range table ID.
```

Legend

- `{cpParameterName}`: The name of the allowance plan Parameter
- `{parameterReferenceName}`: The name of the allowance plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the allowance plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the data type of the range table ID and the additional information of the range table class in the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.87 ALLOWANCE-80

Message

```
The Parameter "{cpParameterName}" of the Allowance Plan referenced by the
Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declares
an incompatible
range table class "{cpParameterRangeTableClass}" while the Parameter Reference
is of class
"{parameterReferenceRangeTableClass}".
```

Legend

- `{cpParameterName}`: The name of the allowance plan Parameter
- `{parameterReferenceName}`: The name of the allowance plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the allowance plan item Parameter Reference
- `{cpParameterRangeTableClass}`: The range table class of the allowance plan Parameter
- `{parameterReferenceRangeTableClass}`: The range table class of the allowance plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the data type of the range table ID and the additional information of the range table class in the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.88 ALLOWANCE-81

Message

```
The Parameter "{cpParameterName}" of the Allowance Plan referenced by the
Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared as
a mapping table key.
```

Legend

- `{cpParameterName}`: The name of the charge class Parameter
- `{parameterReferenceName}`: The name of the charge class item Parameter Reference
- `{parameterReferenceIndex}`: The index of the charge class item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the additional information of the data type of the mapping table key in the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.89 ALLOWANCE-83

Message

```
The Parameter is declared as a mapping table ID while it does not exist in
the Allowance Logic.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the additional information of the data type of the mapping table ID from the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.90 ALLOWANCE-84

Message

```
The Parameter is declared as a mapping table ID but it does not have a STRING
type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the parameter as a STRING.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.91 ALLOWANCE-85

Message

```
The mapping table class "{parameterMappingTableClass}" declared in the Parameter
is incompatible with the one declared in the Allowance Logic
"{allowanceLogicMappingTableClass}".
```

Legend

- `{parameterMappingTableClass}`: The mapping table class of the Parameter
- `{allowanceLogicMappingTableClass}`: The mapping table class declared in the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the right mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.92 ALLOWANCE-86

Message

```
The Parameter "{parameterName}" at index {parameterIndex} points to an unknown
mapping table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.93 ALLOWANCE-87

Message

```
The Parameter is declared as a range table ID while it does not exist in the
Allowance Logic.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the additional information of the data type of the range table ID from the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.94 ALLOWANCE-88

Message

```
The Parameter is declared as a range table ID but it does not have a STRING type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the parameter as a STRING.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.95 ALLOWANCE-89

Message

```
The range table class "{parameterRangeTableClass}" declared in the Parameter is
incompatible with the one declared in the Allowance Logic
"{allowanceLogicRangeTableClass}".
```

Legend

- `{parameterRangeTableClass}`: The range table class of the Parameter
- `{allowanceLogicRangeTableClass}`: The range table class declared in the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the right range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.96 ALLOWANCE-90

Message

```
The Parameter "{parameterName}" at index {parameterIndex} points to an unknown
range table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.97 ALLOWANCE-91

Message

```
The Parameter is declared as a mapping table key while it does not exist in the
Allowance Logic.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the additional information of the data type of the mapping table key from the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.98 ALLOWANCE-92

Message

```
The Parameter is declared with a mapping table key but has a wrong type
"{parameterType}"
while it should be "{allowanceLogicType}".
```

Legend

- `{parameterType}`: The type of the Parameter
- `{allowanceLogicType}`: The type declared in the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the right type for the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.99 ALLOWANCE-93

Message

```
The mapping table ID "{mappingTableIdName}" is not declared whereas it is used
in the Allowance Logic.
```

Legend

- `{mappingTableIdNamemappingTableIdName}`: The name of the Parameter which is a mapping table ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the corresponding mapping table ID parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.100 ALLOWANCE-94

Message

```
The range table ID "{rangeTableIdName}" is not declared whereas it is used in
the
Allowance Logic.
```

Legend

- `{rangeTableIdName}`: The name of the Parameter which is a range table ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the corresponding range table ID parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.101 ALLOWANCE-95

Message

```
The mapping table key "{mappingTableKeyName}" of type "{mappingTableKeyType}" is
not
declared whereas it is used in the Allowance Logic.
```

Legend

- `{mappingTableKeyName}`: The name of the Parameter which is a mapping table key
- `{mappingTableKeyType}`: The type of the mapping table key

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the corresponding mapping table ID parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.102 ALLOWANCE-96 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The Charged Item Mapping is missing in the Allowance Plan Item.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the Charged Item Mapping of the Allowance Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to 2021 FPS 1. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.103 ALLOWANCE-97

Message

```
The class of the Charged Item Mapping is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a class to the Charged Item Mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.104 ALLOWANCE-98

Message

```
Error while validating the Charged Item Mapping of class "{citcClass}".
```

Legend

- `{citcClass}`: The class of the Charged Item Mapping

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.105 ALLOWANCE-99

Message

```
The name of the Charged Item Mapping Entry at index
{chargedItemMappingEntryIndex}
is missing.
```

Legend

- `{chargedItemMappingEntryIndex}`: The index of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Charged Item Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.106 ALLOWANCE-100

Message

```
The name "{chargedItemMappingEntryName}" of the Charged Item Mapping Entry at
index {secondIndex} is already used by the Charged Item Mapping Entry at index
{firstIndex}.
```

Legend

- `{chargedItemMappingEntryName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Charged Item Mapping Entries
- `{firstIndex}`: The index of the first occurrence of the name in Charged Item Mapping Entries

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Charged Item Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.107 ALLOWANCE-101

Message

```
The type of the Charged Item Mapping Entry "{chargedItemMappingEntryName}" at
index
{chargedItemMappingEntryIndex} is missing or unknown (the supported types are
string,
number, date, boolean).
```

Legend

- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry
- `{chargedItemMappingEntryIndex}`: The index of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Charged Item Mapping Entry or change it into a supported one: string, number, date, boolean.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.108 ALLOWANCE-102

Message

```
The Charged Item Mapping contains the "{entryName}" entry. This entry does
not exist in the "{chargedItemClassId}" Charged Item Class.
```

Legend

- `{entryName}`: The entry name in the Charged Item Mapping
- `{chargedItemClassId}`: The ID of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the entry from the Charged Item Mapping or replace it by an existing property of the Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.109 ALLOWANCE-103

Message

```
The Charged Item Mapping contains the entry "{entryName}" with the type:
{entryType}.
This type is not compatible with the one defined in the Charged Item Class
"{chargedItemClassId}":
{propertyType}.
```

Legend

- `{entryName}`: The entry name in the Charged Item Mapping
- `{entryType}`: The entry type in the Charged Item Mapping

- `{chargedItemClassId}`: The ID of the Charged Item Class
- `{propertyType}`: The property type in the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the Charged Item Mapping entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.110 ALLOWANCE-104

Message

```
The Allowance Plan is missing in the CreateAllowancePlanOp operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Allowance Plan to the CreateAllowancePlanOp operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.111 ALLOWANCE-105

Message

```
The Allowance Plan "{allowancePlanId}" already exists.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan that already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use another ID or use the `ModifyAllowancePlanOp` operation to modify the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.112 ALLOWANCE-106

Message

```
The status of the new Allowance Plan "{allowancePlanId}" must be set to open.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new Allowance Plan to open.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.113 ALLOWANCE-107

Message

```
The ID of the Allowance Logic "{allowanceLogicId}" does not match any Allowance
Logic.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing Allowance Logic object.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.114 ALLOWANCE-108

Message

```
The code of the charged item class "{chargedItemClassCode}" does not match
any charged item class.
```

Legend

- `{chargedItemClassCode}`: The code of the charged item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of an existing charged item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.115 ALLOWANCE-109

Message

```
The Allowance Plan is missing in the ModifyAllowancePlanOp operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Allowance Plan to the `ModifyAllowancePlanOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.116 ALLOWANCE-110

Message

```
The Allowance Plan with the ID {allowancePlanId} does not exist.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the Allowance Plan into an existing one or first create the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.117 ALLOWANCE-111

Message

```
Impossible to modify the Allowance Plan because the specified owner
{specifiedOwner}
does not correspond to the owner {realOwner} existing in the Allowance Plan.
```

Legend

- `{specifiedOwner}`: The specified owner in the operation
- `{realOwner}`: The owner existing in the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the owner into the owner of the Allowance Plan or create a new Allowance Plan for the specified owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.118 ALLOWANCE-112

Message

```
The description of the Allowance Plan "{allowancePlanId}" cannot be modified
because the Allowance Plan has been released.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.119 ALLOWANCE-120

Message

```
The parameter "{parameterName}" cannot be removed because the Allowance Plan
"{allowancePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.120 ALLOWANCE-121

Message

```
The parameter "{parameterName}" cannot be added because the Allowance Plan
"{allowancePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.121 ALLOWANCE-122

Message

```
The description of the parameter "{parameterName}" cannot be modified because
the Allowance Plan "{allowancePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.122 ALLOWANCE-123

Message

```
The type of the parameter "{parameterName}" cannot be modified because the
Allowance
Plan "{allowancePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.123 ALLOWANCE-127

Message

```
The counter "{counterName}" cannot be removed because the Allowance Plan
"{allowancePlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.124 ALLOWANCE-128

Message

```
The counter "{counterName}" cannot be added because the Allowance Plan
"{allowancePlanId}"
has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.125 ALLOWANCE-129

Message

```
The description of the counter "{counterName}" cannot be modified because the
Allowance Plan "{allowancePlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.126 ALLOWANCE-133

Message

```
The allowance plan item "{allowancePlanItemId}" cannot be removed because the
Allowance Plan "{allowancePlanId}" has been released.
```

Legend

- `{allowancePlanItemId}`: The ID of the Allowance Plan Item
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.127 ALLOWANCE-134

Message

```
The allowance plan item "{allowancePlanItemId}" cannot be added because the
Allowance
Plan "{allowancePlanId}" has been released.
```

Legend

- `{allowancePlanItemId}`: The ID of the Allowance Plan Item
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.128 ALLOWANCE-135

Message

```
The allowance plan item "{allowancePlanItemId}" cannot be modified because the
Allowance Plan "{allowancePlanId}" has been released.
```

Legend

- `{allowancePlanItemId}`: The ID of the Allowance Plan Item
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.129 ALLOWANCE-138

Message

```
The Allowance Plan "{allowancePlanId}" whose status is already set to released
cannot be set to open.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new Allowance Plan to released.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.130 ALLOWANCE-141

Message

```
The Allowance Logic "{allowanceLogicId}" is unknown.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the allowanceLogicId into an existing Allowance Logic identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.131 ALLOWANCE-142

Message

```
The code of the charged item class "{chargedItemClassCode}" does not match
any charged item class.
```

Legend

- `{chargedItemClassCode}`: The code of the charged item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of an existing charged item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.132 ALLOWANCE-143

Message

```
Internal server error. The Allowance Plan Item refers to no known Allowance
Logic.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.133 ALLOWANCE-144

Message

```
The Allowance Plan Item already refers to the Allowance Logic
"{originalAllowanceLogicId}"
and cannot refer to the Allowance Logic "{newAllowanceLogicId}" at the same time.
```

Legend

- `{originalAllowanceLogicId}`: The original ID of the Allowance Logic
- `{newAllowanceLogicId}`: The new ID of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the Allowance Logic already referred to by the Allowance Plan Item or create a new Allowance Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.134 ALLOWANCE-145

Message

```
Internal server error. The Allowance Plan Item refers to an unknown charged item
class.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.135 ALLOWANCE-146

Message

```
The code of the charged item class "{chargedItemClassCode}" does not match any
charged item class.
```

Legend

- `{chargedItemClassCode}`: The code of the charged item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the code of an existing charged item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.136 ALLOWANCE-147

Message

```
The ID of the Allowance Plan is missing in the DeleteAllowancePlanOp operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of the Allowance Plan to the `DeleteAllowancePlanOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.137 ALLOWANCE-148

Message

```
The Allowance Plan "{allowancePlanId}" cannot be deleted because it does not
exist.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan that needs to be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing ID for the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.138 ALLOWANCE-149

Message

```
Error while deleting the Allowance Plan "{allowancePlanId}". The Allowance Plan
is still linked to one or more Charging Contract Items.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan that needs to be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete all Charging Contract Items referring to the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.139 ALLOWANCE-150

Message

```
The mandatory filter in the SearchAllowancePlanOp operation is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the filter to the `SearchAllowancePlanOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.140 ALLOWANCE-151

Message

```
An error occurred during the execution of the SearchAllowancePlanOp operation:
{errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.141 ALLOWANCE-152

Message

```
The code of the charged item class is empty or null.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of an existing charged item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.142 ALLOWANCE-153

Message

```
The owner of the Allowance Plan and the owner of the Charged Item Class do not
match.
The owner of the Allowance Plan is "{allowancePlanOwner}". The owner of the
Charged Item Class
is "{chargedItemClassOwner}".
```

Legend

- `{allowancePlanOwner}`: The owner of the Allowance Plan
- `{chargedItemClassOwner}`: The owner of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of a Charged Item Class that has the same owner as the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.143 ALLOWANCE-200

Message

```
The Allowance Logic has no ID.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.144 ALLOWANCE-201

Message

```
The Allowance Logic "{allowanceLogicId}" has no owner.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic with no owner

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the owner of the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.145 ALLOWANCE-202

Message

```
The Allowance Logic "{allowanceLogicId}" has no allowance logic tree.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic with no allowance logic tree

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the allowance logic tree to the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.146 ALLOWANCE-209

Message

```
The name of the recurring trigger is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the recurring trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.147 ALLOWANCE-210

Message

```
The recurring trigger "{recurringAllowanceName}" does not contain any allowance
component.
```

Legend

- `{recurringAllowanceName}`: The name of the recurring trigger with no allowance component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an allowance component to the recurring trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.148 ALLOWANCE-211

Message

```
The recurring trigger "{recurringRateName}" is invalid because the component
tree is invalid.
```

Legend

- `{recurringRateName}`: The name of the recurring trigger with invalid component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate components in the recurring trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.149 ALLOWANCE-212

Message

```
The name of the one-shot trigger is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the one-shot trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.150 ALLOWANCE-213

Message

```
The one-shot trigger "{oneShotAllowanceName}" does not contain any allowance
component.
```

Legend

- `{oneShotAllowanceName}`: The name of the one-shot trigger with no allowance component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an allowance component to the one-shot trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.151 ALLOWANCE-214

Message

```
The one-shot trigger "{oneshotRateName}" is invalid because the component tree
is invalid.
```

Legend

- `{oneshotRateName}`: The name of the oneshot allowance with invalid component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the components in oneshot allowance.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.152 ALLOWANCE-216

Message

```
The counter has no name.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the counter name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.153 ALLOWANCE-217

Message

```
The counter "{counterDescriptionName}" has no initial value.
```

Legend

- `{counterDescriptionName}`: The name of the counter with no initial value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the initial value of the counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.154 ALLOWANCE-218

Message

```
The counter "{counterDescriptionName}" is duplicated.
```

Legend

- `{counterDescriptionName}`: The name of the duplicated counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the counter to a unique name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.155 ALLOWANCE-219

Message

```
The parameter "{parameterName}" is duplicated.
```

Legend

- `{parameterName}`: The name of the duplicated parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the parameter to a unique name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.156 ALLOWANCE-220

Message

```
The Allowance Logic is missing in the CreateAllowanceLogicOp operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Allowance Logic to the `CreateAllowanceLogicOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.157 ALLOWANCE-221

Message

```
The Allowance Logic "{allowanceLogicId}" already exists.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic that already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use another ID or use the `ModifyAllowanceLogicOp` operation to modify the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.158 ALLOWANCE-222

Message

```
The Allowance Logic is missing in the ModifyAllowanceLogicOp operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Allowance Logic to the `ModifyAllowanceLogicOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.159 ALLOWANCE-223

Message

```
The Allowance Logic "{allowanceLogicCode}" cannot be modified because it does
not exist.
```

Legend

- `{allowanceLogicCode}`: The ID of the Allowance Logic that does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the ID of the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.160 ALLOWANCE-224

Message

```
The Allowance Logic owner "{allowanceLogicOwner}" is not modifiable in the
Allowance
Logic "{allowanceLogicId}".
```

Legend

- `{allowanceLogicOwner}`: The owner of the Allowance Logic
- `{allowanceLogicId}`: The ID of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the owner of the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.161 ALLOWANCE-225

Message

```
The ID of the Allowance Logic is missing in the DeleteAllowanceLogicOp operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the Allowance Logic to the `DeleteAllowanceLogicOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.162 ALLOWANCE-226

Message

```
The Allowance Logic "{allowanceLogicId}" cannot be deleted because it is
referred
to by the following Allowance Plans: {allowancePlanIds}.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic that is referred to by a Allowance Plan
- `{allowancePlanIds}`: A `CSV` string containing the list of Allowance Plan ID which refer to the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the Allowance Plan(s).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.163 ALLOWANCE-227

Message

```
The Allowance Logic "{allowanceLogicId}" cannot be deleted because it does not
exist.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic that does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the code of the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.164 ALLOWANCE-229

Message

```
The one-shot trigger "{oneShotAllowanceName}" event is not set.
```

Legend

- `{oneShotAllowanceName}`: The name of the one-shot trigger with no event name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid event in the one-shot trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.165 ALLOWANCE-230

Message

```
The event "{oneShotEventName}" of the one-shot trigger "{oneShotAllowanceName}"
is not a valid event.
```

Legend

- `{oneShotEventName}`: The name of the invalid event
- `{oneShotAllowanceName}`: The name of the one-shot trigger with invalid event name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid event in the one-shot trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.166 ALLOWANCE-232

Message

```
The Allowance Plan "{allowancePlanId}" cannot be deleted because it is referred
to by the following Refill Logic objects: {refillLogicIds}.
```

Legend

- `{allowancePlanId}`: The ID of the allowance plan
- `{refillLogicIds}`: A `CSV` string containing the list of Refill Logic ID which refer to the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the Refill Logic object(s).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.167 ALLOWANCE-233

Message

```
The Allowance Plan "{allowancePlanId}" cannot be deleted because it is referred
to by the following Charge Components: {chargeComponentIds}.
```

Legend

- `{allowancePlanId}`: The ID of the allowance plan
- `{chargeComponentIds}`: A `CSV` string containing the list of Charge Component ID which refer to the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the Charge Component(s).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.168 ALLOWANCE-234

Message

```
The parameter has no name.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the parameter name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.169 ALLOWANCE-235

Message

```
The parameter "{parameterName}" has no value.
```

Legend

- `{parameterName}`: The name of the parameter with no value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the parameter value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.170 ALLOWANCE-236

Message

```
The mapping table class "{mappingTableClassId}" defined in the parameter
"{parameterName}"
does not exist in the SAP CC system.
```

Legend

- `{mappingTableClassId}`: The identifier of the mapping table class specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid ID of mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing mapping table class for the additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.171 ALLOWANCE-237

Message

```
The mapping table "{mappingTableId}" defined in the parameter "{parameterName}"
does not exist in the SAP CC system.
```

Legend

- `{mappingTableId}`: The identifier of the mapping table specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid ID of mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing mapping table for the additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.172 ALLOWANCE-238

Message

```
The range table class "{rangeTableClassId}" defined in the parameter
"{parameterName}"
does not exist in the SAP CC system.
```

Legend

- `{rangeTableClassId}`: The identifier of the range table class specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid ID of range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing range table class for the additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.173 ALLOWANCE-239

Message

```
The range table "{rangeTableId}" defined in the parameter "{parameterName}"
does not exist in the SAP CC system.
```

Legend

- `{rangeTableId}`: The identifier of the range table specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid ID of range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing range table for the additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.174 ALLOWANCE-240

Message

```
The additional information named "{addInfoName}" defined in the parameter
"{parameterName}" is not supported.
```

Legend

- `{addInfoName}`: The name of the additional information specified in the parameter
- `{parameterName}`: The name of the parameter containing an unsupported additional information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the parameter. The supported values are: dataType, mappingTableClass and rangeTableClass.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.175 ALLOWANCE-241

Message

```
The additional information value "{addInfoValue}" defined in the parameter
"{parameterName}" is not a valid data type.
```

Legend

- `{addInfoValue}`: The value of the additional information specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid data type

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the parameter additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.176 ALLOWANCE-242

Message

```
The additional information value "{addInfoValue}" requires that the parameter
"{parameterName}" is of type string.
```

Legend

- `{addInfoValue}`: The value of the additional information specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid data type

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

The type is wrong. Check the type and change it into string.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.177 ALLOWANCE-243

Message

```
The parameter "{parameterName}" does not define a mapping table class.
```

Legend

- `{parameterName}`: The name of the parameter containing an invalid ID of mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing mapping table class for the additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.178 ALLOWANCE-244

Message

```
The parameter "{parameterName}" does not define a range table class.
```

Legend

- `{parameterName}`: The name of the parameter containing an invalid data type

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing range table class for the additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.179 ALLOWANCE-245

Message

```
The recurring trigger "{recurringAllowanceName}" frequency is not set.
```

Legend

- `{recurringAllowanceName}`: The name of the recurring trigger with no frequency

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid frequency in the recurring trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.180 ALLOWANCE-246

Message

```
The chargeable item class ID of the usage allowance "{usageAllowanceName}" is
not set.
```

Legend

- `{usageAllowanceName}`: The name of the usage allowance with no chargeable item class ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid chargeable item class ID in the usage allowance.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.181 ALLOWANCE-248

Message

```
No allowance plan is specified.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an allowance plan in the create allowance component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.182 ALLOWANCE-249

Message

```
The allowance plan "{allowancePlanId}" does not exist.
```

Legend

- `{allowancePlanId}`: The identifier of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing allowance plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.183 ALLOWANCE-250

Message

```
The allowance plan "{allowancePlanId}" is not released.
```

Legend

- `{allowancePlanId}`: The identifier of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of a released allowance plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.184 ALLOWANCE-251

Message

```
The parameter "{parameterName}" does not exist in the allowance plan
"{allowancePlanId}".
```

Legend

- `{parameterName}`: The name of the parameter
- `{allowancePlanId}`: The identifier of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a parameter name that exists in the allowance plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.185 ALLOWANCE-252

Message

```
The parameter "{parameterName}" does not have the same type as in the allowance
plan "{allowancePlanId}".
```

Legend

- `{parameterName}`: The name of the parameter
- `{allowancePlanId}`: The identifier of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the same parameter type as in the allowance plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.186 ALLOWANCE-253

Message

```
The parameter "{parameterName}" of the allowance plan "{allowancePlanId}" is not
defined in the create allowance component.
```

Legend

- `{parameterName}`: The name of the parameter
- `{allowancePlanId}`: The identifier of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a value for the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.187 ALLOWANCE-254

Message

```
The mapping table "{mappingTableId}" referenced by the parameter
"{parameterName}"
does not exist.
```

Legend

- `{mappingTableId}`: The identifier of the mapping table
- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.188 ALLOWANCE-255

Message

```
The mapping table "{mappingTableId}" referenced by the parameter
"{parameterName}"
is not related to the mapping table class "{mappingTableClassId}".
```

Legend

- `{mappingTableId}`: The identifier of the mapping table
- `{parameterName}`: The name of the parameter
- `{mappingTableClassId}`: The identifier of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an mapping table related to the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.189 ALLOWANCE-256

Message

```
The range table "{rangeTableId}" referenced by the parameter "{parameterName}"
does not exist.
```

Legend

- `{rangeTableId}`: The identifier of the range table
- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.190 ALLOWANCE-257

Message

```
The range table "{rangeTableId}" referenced by the parameter "{parameterName}"
is not related to the range table class "{rangeTableClassId}".
```

Legend

- `{rangeTableId}`: The identifier of the range table
- `{parameterName}`: The name of the parameter
- `{rangeTableClassId}`: The identifier of the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of a range table related to the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.191 ALLOWANCE-258

Message

```
The counter "{counterName}" does not exist in the allowance plan
"{allowancePlanId}".
```

Legend

- `{counterName}`: The name of the counter
- `{allowancePlanId}`: The identifier of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a counter name that exists in the allowance plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.192 ALLOWANCE-259

Message

```
The counter "{counterName}" of the allowance plan "{allowancePlanId}" is not
defined in the create allowance component.
```

Legend

- `{counterName}`: The name of the counter
- `{allowancePlanId}`: The identifier of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a value for the counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.193 ALLOWANCE-260

Message

```
The context property name "{contextPropertyName}" specified in the start date
is not valid.
```

Legend

- `{contextPropertyName}`: The name of the context property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a valid context property name in the start date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.194 ALLOWANCE-261

Message

```
The context property name "{contextPropertyName}" specified in the end date
is not valid.
```

Legend

- `{contextPropertyName}`: The name of the context property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a valid context property name in the end date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.195 ALLOWANCE-262

Message

```
The context property name "{contextPropertyName}" specified in the parameter
"{parameterName}" is not valid.
```

Legend

- `{contextPropertyName}`: The name of the context property
- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a valid context property name for the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.196 ALLOWANCE-263

Message

```
The context property name "{contextPropertyName}" specified in the counter
"{counterName}" is not valid.
```

Legend

- `{contextPropertyName}`: The name of the context property
- `{counterName}`: The name of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a valid context property name for the counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.197 ALLOWANCE-264

Message

```
The code of the charged item class is empty or null.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of an existing charged item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.198 ALLOWANCE-265

Message

```
The code of the charged item class is empty or null.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of an existing charged item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.199 ALLOWANCE-266

Message

```
The code of the charged item aggregation policy
"{chargedItemAggregationPolicyCode}"
does not match any charged item aggregation policy.
```

Legend

- `{chargedItemAggregationPolicyCode}`: The code of the charged item aggregation policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of an existing charged item aggregation policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.200 ALLOWANCE-267

Message

```
The code of the charged item aggregation policy
"{chargedItemAggregationPolicyCode}"
does not match any charged item aggregation policy.
```

Legend

- `{chargedItemAggregationPolicyCode}`: The code of the charged item aggregation policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of an existing charged item aggregation policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.201 ALLOWANCE-268

Message

```
The code of the charged item aggregation policy
"{chargedItemAggregationPolicyCode}"
does not match any charged item aggregation policy.
```

Legend

- `{chargedItemAggregationPolicyCode}`: The code of the charged item aggregation policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of an existing charged item aggregation policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.202 ALLOWANCE-269

Message

```
The Allowance Plan "{allowancePlanId}" does not contain any Allowance Plan
Item.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an Allowance Plan Item to the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.203 ALLOWANCE-270

Message

```
The logic tree of the Allowance Logic "{allowanceLogicId}" does not contain
any allowance component.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an allowance component to the logic tree of the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.204 ALLOWANCE-271

Message

```
The type "{parameterType}" of the Parameter "{parameterName}" at index
{parameterIndex}
is not compatible with the type "{logicParameterType}" of the corresponding
Allowance Logic
Parameter.
```

Legend

- `{parameterType}`: The type of the Parameter
- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{logicParameterType}`: The type of the Allowance Logic Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the correct type for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.205 ALLOWANCE-272

Message

```
The type "{parameterReferenceType}" of the Parameter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} is not compatible with the type
"{logicParameterType}"
of the corresponding Allowance Logic Parameter.
```

Legend

- `{parameterReferenceType}`: The type of the Parameter Reference
- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference
- `{logicParameterType}`: The type of the Allowance Logic Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the correct type for the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.206 ALLOWANCE-273

Message

```
The value of the Charged Item Mapping Entry "{chargedItemMappingEntryName}"
at index {chargedItemMappingEntryIndex} is not set.
```

Legend

- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry
- `{chargedItemMappingEntryIndex}`: The index of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set either a value or a property name in the Charged Item Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.207 ALLOWANCE-274

Message

```
The allowance plan "{allowancePlanId}" does not belong to the same owner
as the charge component or refill logic.
```

Legend

- `{allowancePlanId}`: The identifier of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an allowance plan with the same owner as the charge component or refill logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.208 ALLOWANCE-276

Message

```
The Allowance Interface is missing in the modify operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an Allowance Interface to the modify operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.209 ALLOWANCE-277

Message

```
Error while validating the Allowance Interface.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.210 ALLOWANCE-278

Message

```
The name of the Parameter at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a name for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.211 ALLOWANCE-279

Message

```
The name "{parameterName}" of the Parameter at index {secondIndex} is already
used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterName}`: The duplicated Parameter name
- `{secondIndex}`: The index of the second occurrence of the name in the Parameters in the Allowance Interface
- `{firstIndex}`: The index of the first occurrence of the name in the Parameters in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.212 ALLOWANCE-280

Message

```
The description of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a description for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.213 ALLOWANCE-281

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex} is
missing or unknown (the supported types are string, number, date).
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a type for the Parameter or change it into a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.214 ALLOWANCE-282

Message

```
The default value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a default value for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.215 ALLOWANCE-283

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex} cannot
be changed from {previousParameterType} to {newParameterType}.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter in the Allowance Interface
- `{previousParameterType}`: The previous type of the Parameter
- `{newParameterType}`: The new type of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the same type for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.216 ALLOWANCE-284

Message

```
The Parameter "{parameterName}" cannot be removed.
```

Legend

- `{parameterName}`: The name of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.217 ALLOWANCE-285

Message

```
The name of the Counter at index {counterIndex} is missing.
```

Legend

- `{counterIndex}`: The index of the Counter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a name for the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.218 ALLOWANCE-286

Message

```
The name "{counterName}" of the Counter at index {secondIndex} is already used
by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated Counter name
- `{secondIndex}`: The index of the second occurrence of the name in the Counters in the Allowance Interface
- `{firstIndex}`: The index of the first occurrence of the name in the Counters in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.219 ALLOWANCE-287

Message

```
The description of the Counter "{counterName}" at index {counterIndex} is
missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a description for the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.220 ALLOWANCE-288

Message

```
The default value of the Counter "{counterName}" at index {counterIndex} is
missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a default value for the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.221 ALLOWANCE-289

Message

```
The Counter "{counterName}" cannot be removed.
```

Legend

- `{counterName}`: The name of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.222 ALLOWANCE-290

Message

```
The context property name "{contextPropertyName}" specified in the parameter
"{parameterName}" does not correspond to a parameter of type mapping table
identifier.
```

Legend

- `{contextPropertyName}`: The name of the context property
- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a context property name that corresponds to a parameter of type mapping table identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.223 ALLOWANCE-291

Message

```
The context property name "{contextPropertyName}" specified in the parameter
"{parameterName}" does not correspond to a parameter of type range table
identifier.
```

Legend

- `{contextPropertyName}`: The name of the context property
- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a context property name that corresponds to a parameter of type range table identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.224 ALLOWANCE-300

Message

```
The Allowance Event Class is missing in the CreateAllowanceEventClassOp
operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Allowance Event Class to the `CreateAllowanceEventClassOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.225 ALLOWANCE-301

Message

```
The Allowance Event Class has no ID.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.226 ALLOWANCE-302

Message

```
The owner of the Allowance Event Class "{allowanceEventClassId}" is missing
in the CreateAllowanceEventClassOp operation.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the owner of the Allowance Event Class to the `CreateAllowanceEventClassOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.227 ALLOWANCE-303

Message

```
The Allowance Event Class "{allowanceEventClassId}" already exists.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class that already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use another ID or use the `ModifyAllowanceEventClassOp` operation to modify the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.228 ALLOWANCE-304

Message

```
The name is missing in one of the Allowance Event Class properties.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Allowance Event Class property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.229 ALLOWANCE-305

Message

```
The property "{allowanceEventClassPropertyName}" of type
"{allowanceEventClassPropertyType}"
cannot be removed or changed from the Allowance Event Class
"{allowanceEventClassId}"
because it is referenced by the following Allowance Logic object(s):
{allowanceLogicIds}.
```

Legend

- `{allowanceEventClassPropertyName}`: The name of the original property
- `{allowanceEventClassPropertyType}`: The type of the original property
- `{allowanceEventClassId}`: The ID of the Allowance Event Class that is referred by an Allowance Logic
- `{allowanceLogicIds}`: The `CSV` string containing the list of Allowance Logic codes which reference the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Keep the property as it was created initially in the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.230 ALLOWANCE-306

Message

```
The name "{allowanceEventClassPropertyName}" of the Allowance Event Class
property is already used.
```

Legend

- `{allowanceEventClassPropertyName}`: The duplicated name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Allowance Event Class property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.231 ALLOWANCE-307

Message

```
The Allowance Event Class is missing in the ModifyAllowanceEventClassOp
operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Allowance Event Class to the `ModifyAllowanceEventClassOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.232 ALLOWANCE-308

Message

```
The Allowance Event Class has no ID.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.233 ALLOWANCE-309

Message

```
The owner of the Allowance Event Class "{allowanceEventClassId}" cannot be
modified.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the owner of the Allowance Event Class

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.234 ALLOWANCE-310

Message

```
The Allowance Event Class "{allowanceEventClassId}" cannot be deleted because
it does not exist.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class that does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the ID of the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.235 ALLOWANCE-311

Message

```
The parameter "{parameterName}" specified as a sorting criterion does not
exist in the Allowance Interface.
```

Legend

- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a parameter that exists in the Allowance Interface in the sorting criterion.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.236 ALLOWANCE-312

Message

```
The parameter "{parameterName}" is specified more than once as a sorting
criterion.
```

Legend

- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the parameter as a sorting criterion only once.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.237 ALLOWANCE-313

Message

```
The parameter "{parameterName}" is specified as a sorting criterion of type
"{typeInSortingCriterion}" while its type is "{typeInAllowanceInterface}" in the
Allowance
Interface.
```

Legend

- `{parameterName}`: The name of the parameter
- `{typeInSortingCriterion}`: The type of the parameter in the sorting criterion
- `{typeInAllowanceInterface}`: The type of the parameter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the correct type for the parameter in the sorting criterion.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.238 ALLOWANCE-314

Message

```
The parameter "{parameterName}" cannot be used as a sorting criterion because
it is of type "string".
```

Legend

- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the name of another parameter as a sorting criterion.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.239 ALLOWANCE-315

Message

```
The counter "{counterName}" specified as a sorting criterion does not exist
in the Allowance Interface.
```

Legend

- `{counterName}`: The name of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a counter that exists in the Allowance Interface in the sorting criterion.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.240 ALLOWANCE-316

Message

```
The counter "{counterName}" is specified more than once as a sorting criterion.
```

Legend

- `{counterName}`: The name of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the counter as a sorting criterion only once.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.241 ALLOWANCE-317

Message

```
The counter "{counterName}" is specified as a sorting criterion of type
"{typeInSortingCriterion}" while its type must be "number".
```

Legend

- `{counterName}`: The name of the counter
- `{typeInSortingCriterion}`: The type of the counter in the sorting criterion

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the counter to the type "number" in the sorting criterion.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.242 ALLOWANCE-318

Message

```
The sorting criterion "{sortingCriterion}" is unknown.
```

Legend

- `{sortingCriterion}`: The sorting criterion

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid sorting criterion.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.243 ALLOWANCE-319

Message

```
The name of the event-based trigger is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the event-based trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.244 ALLOWANCE-320

Message

```
The allowance event class ID of the event-based trigger "{eventAllowanceName}"
is not set.
```

Legend

- `{eventAllowanceName}`: The name of the event-based trigger with no allowance event class ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid allowance event class ID in the usage allowance.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.245 ALLOWANCE-321

Message

```
The Allowance Event Class "{allowanceEventClassName}" referred to in the
event-based trigger "{eventAllowanceName}" is already used.
```

Legend

- `{allowanceEventClassName}`: The name of the Allowance Event Class that is already used
- `{eventAllowanceName}`: The name of the event-based trigger

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing but not already used Allowance Event Class in the event-based trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.246 ALLOWANCE-322

Message

```
The Allowance Event Class "{allowanceEventClassName}" referred to in the event-
based
trigger "{eventAllowanceName}" does not exist.
```

Legend

- `{allowanceEventClassName}`: The name of the Allowance Event Class that does not exist
- `{eventAllowanceName}`: The name of the event-based trigger

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing Allowance Event Class in the event-based trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.247 ALLOWANCE-323

Message

```
The owner of the allowance logic and the owner of the Allowance Event Class
referenced by the event-based trigger "{eventAllowanceName}" do not match. The
owner of the
allowance logic is "{allowanceLogicOwner}". The owner of the Allowance Event
Class is
"{allowanceEventClassOwner}".
```

Legend

- `{eventAllowanceName}`: The name of the event-based trigger
- `{allowanceLogicOwner}`: The owner of the allowance logic
- `{allowanceEventClassOwner}`: The owner of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a chargeable item class that has the same owner as the allowance logic in the usage allowance.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.248 ALLOWANCE-324

Message

```
The event-based trigger "{eventAllowanceName}" cannot be added because the
Allowance Logic is referenced more than once in the Allowance Plan
"{allowancePlanId}".
```

Legend

- `{eventAllowanceName}`: The name of the event-based trigger
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Do not add an event-based trigger to the Allowance Logic or remove the duplicate Allowance Logic from the Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.249 ALLOWANCE-325

Message

```
The Allowance Event Class "{allowanceEventClassName}" referenced by the event-
based
trigger "{eventAllowanceName}" is already used in the Allowance Plan
"{allowancePlanId}" by
the Allowance Logic "{allowanceLogicId}".
```

Legend

- `{allowanceEventClassName}`: The name of the Allowance Event Class already referenced
- `{eventAllowanceName}`: The name of the event-based trigger
- `{allowancePlanId}`: The ID of the Allowance Plan
- `{allowanceLogicId}`: The ID of the other Allowance Logic referencing the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select another Allowance Event Class in the event-based trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.250 ALLOWANCE-326

Message

```
The event-based trigger "{eventAllowanceName}" does not contain any allowance
component.
```

Legend

- `{eventAllowanceName}`: The name of the event-based trigger with no allowance component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an allowance component to the event-based trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.251 ALLOWANCE-327

Message

```
The event-based trigger "{eventAllowanceName}" is invalid because the component
tree is invalid.
```

Legend

- `{eventAllowanceName}`: The name of the event-based trigger with invalid component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the components in the event-based trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.252 ALLOWANCE-328

Message

```
Rating failure of the charge activation "{chargeActivationName}" in the
allowance "{allowanceUniqueIdentifier}".
```

Legend

- `{chargeActivationName}`: The name of the charge activation
- `{allowanceUniqueIdentifier}`: The unique identifier of the allowance

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the logic tree of the allowance logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.253 ALLOWANCE-329

Message

```
Rating event failure of the charge activation "{chargeActivationName}" in the
allowance "{allowanceUniqueIdentifier}".
```

Legend

- `{chargeActivationName}`: The name of the charge activation
- `{allowanceUniqueIdentifier}`: The unique identifier of the allowance

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the logic tree of the allowance logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.254 ALLOWANCE-330

Message

```
The Allowance Event Class "{allowanceEventItemClassName}" referred to in the
allowance logic "{allowanceLogicName}" is already used by another allowance
logic.
```

Legend

- `{allowanceEventItemClassName}`: The name of the Allowance Event Class that is already used
- `{allowanceLogicName}`: The name of the allowance logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the allowance logic with the Allowance Event Class not already used in another allowance logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.255 ALLOWANCE-336

Message

```
The Allowance Event Class "{allowanceEventClassId}" cannot be deleted because
it is referenced at least by one Allowance Event Sender operator or Event-Based
Trigger Rate
in the following: - Charge(s): {chargeIds}. - Refill Logic object(s):
{refillLogicIds}.
- Allowance Logic object(s): {allowanceLogicIds}.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class that is referred by an Allowance Logic
- `{chargeIds}`: The `CSV` string containing the list of Charge codes which reference the Allowance Event Class

- `{refillLogicIds}`: The `CSV` string containing the list of Refill Logic codes which reference the Allowance Event Class
- `{allowanceLogicIds}`: The `CSV` string containing the list of Allowance Logic codes which reference the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.256 ALLOWANCE-337

Message

```
No Allowance Event Class is specified.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.257 ALLOWANCE-338

Message

```
The Allowance Event Class "{allowanceEventClassId}" does not exist.
```

Legend

- `{allowanceEventClassId}`: The identifier of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.258 ALLOWANCE-339

Message

```
The owner of the Allowance Logic and the owner of the Allowance Event Class
referenced by the component do not match. The owner of the Allowance Logic is
"{allowanceLogicOwner}".
The owner of the Allowance Event Class is "{allowanceEventClassOwner}".
```

Legend

- `{allowanceLogicOwner}`: The owner of the Allowance Logic
- `{allowanceEventClassOwner}`: The owner of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an Allowance Event Class that has the same owner as the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.259 ALLOWANCE-340

Message

```
The property at index {propertyIndex} does not have a name.
```

Legend

- `{propertyIndex}`: The index of the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.260 ALLOWANCE-341

Message

```
The property "{propertyName}" is specified more than once.
```

Legend

- `{propertyName}`: The name of the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the property only once.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.261 ALLOWANCE-342

Message

```
The property "{propertyName}" does not exist in the Allowance Event Class
"{allowanceEventClassId}".
```

Legend

- `{propertyName}`: The name of the property
- `{allowanceEventClassId}`: The identifier of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a property name which exists in the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.262 ALLOWANCE-343

Message

```
The property "{propertyName}" does not have the same type as in the Allowance
Event
Class "{allowanceEventClassId}".
```

Legend

- `{propertyName}`: The name of the property
- `{allowanceEventClassId}`: The identifier of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the same property type as in the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.263 ALLOWANCE-344

Message

```
The property "{propertyName}" does not have a value.
```

Legend

- `{propertyName}`: The name of the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a value for the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.264 ALLOWANCE-345

Message

```
The property "{propertyName}" does not have a context property value.
```

Legend

- `{propertyName}`: The name of the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a context property value for the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.265 ALLOWANCE-346

Message

```
The context property name "{contextPropertyName}" specified in the property
"{propertyName}" is not valid.
```

Legend

- `{contextPropertyName}`: The name of the invalid context property
- `{propertyName}`: The name of the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a valid context property name for the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.266 ALLOWANCE-347

Message

```
No properties can be added to the Allowance Event Class
"{allowanceEventClassId}"
because it is referenced at least by one Allowance Event operator in the
following:
- Charge(s): {chargeIds}. - Refill Logic object(s): {refillLogicIds}.
- Allowance Logic object(s): {allowanceLogicIds}.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class that is referred by an Allowance Logic
- `{chargeIds}`: The `CSV` string containing the list of Charge codes which reference the Allowance Event Class
- `{refillLogicIds}`: The `CSV` string containing the list of Refill Logic codes which reference the Allowance Event Class
- `{allowanceLogicIds}`: The `CSV` string containing the list of Allowance Logic codes which reference the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a value for the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.267 ALLOWANCE-348

Message

```
The type "{parameterType}" of the parameter "{parameterName}" at index
{parameterIndex}
is not equal to the type "{parameterTypeInterface}" of the parameter in the
Allowance Interface.
```

Legend

- `{parameterType}`: The type of the Parameter
- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterTypeInterface}`: The type of the Parameter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Parameter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.268 ALLOWANCE-350 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The code of the Charged Item Class of the Allowance Plan Item
"{allowancePlanItemId}"
cannot be changed from "{chargedItemClassCode}" to "{newChargedItemClassCode}"
because the
Allowance Plan "{allowancePlanId}" has been released.
```

Legend

- `{allowancePlanItemId}`: The identifier of the Allowance Plan Item
- `{chargedItemClassCode}`: The original code of the Charged Item Class
- `{newChargedItemClassCode}`: The new code of the Charged Item Class
- `{allowancePlanId}`: The identifier of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of the original Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to 4.0 SP09. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.269 ALLOWANCE-352

Message

```
The parameter additional information "{additionalInformationName}" at index
{additionalInformationIndex} does not have a value.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set of a value for this additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.270 ALLOWANCE-353

Message

```
The clause property "{clausePropertyName}" is unknown.
```

Legend

- `{clausePropertyName}`: The name of the unknown clause property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid clause property: A parameter or a counter defined in the Allowance Interface or a default Allowance property (unique identifier, activation date or expiration date).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.271 ALLOWANCE-354

Message

```
The parameter "{parameterName}" specified as a clause property does not
exist in the Allowance Interface.
```

Legend

- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a parameter that exists in the Allowance Interface.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.272 ALLOWANCE-356

Message

```
The parameter "{parameterName}" is specified as a clause property of type
"{typeInClauseProperty}" while its type is "{typeInAllowanceInterface}" in the
Allowance
Interface.
```

Legend

- `{parameterName}`: The name of the parameter
- `{typeInClauseProperty}`: The type of the parameter in the clause property
- `{typeInAllowanceInterface}`: The type of the parameter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the parameter to the correct type in the clause property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.273 ALLOWANCE-357

Message

```
The counter "{counterName}" specified as a clause property does not exist
in the Allowance Interface.
```

Legend

- `{counterName}`: The name of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a counter that exists in the Allowance Interface.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.274 ALLOWANCE-359

Message

```
The counter "{counterName}" is specified as a clause property of type
"{typeInClauseProperty}" while its type must be "number".
```

Legend

- `{counterName}`: The name of the counter
- `{typeInClauseProperty}`: The type of the counter in the clause property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the counter to the type "number" in the clause property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.275 ALLOWANCE-360

Message

```
The clause property "{clausePropertyName}" is defined with an operator
which is invalid or not compatible with the type "{typeOfClauseProperty}".
```

Legend

- `{clausePropertyName}`: The name of the clause property
- `{typeOfClauseProperty}`: The type of the clause property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a clause operator compatible with the type of the clause property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.276 ALLOWANCE-361

Message

```
The clause property "{clausePropertyName}" is defined with the value
"{valueOfClauseProperty}"
which is not compatible with the type "{typeOfClauseProperty}".
```

Legend

- `{clausePropertyName}`: The name of the clause property
- `{valueOfClauseProperty}`: The value of the clause property
- `{typeOfClauseProperty}`: The type of the clause property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a clause value compatible with the type of the clause property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.277 ALLOWANCE-363

Message

```
The parameter "{parameterName}" specified as the origin of the generated
property "{generatedPropertyName}" does not exist in the Allowance Interface.
```

Legend

- `{parameterName}`: The name of the parameter
- `{generatedPropertyName}`: The name of the generated property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a parameter that exists in the Allowance Interface as the origin of the generated property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.278 ALLOWANCE-364

Message

```
The generated property "{generatedPropertyName}" defines its origin with
the parameter "{parameterName}" of type "{typeInGeneratedProperty}" while its
type is
"{typeInAllowanceInterface}" in the Allowance Interface.
```

Legend

- `{generatedPropertyName}`: The name of the generated property
- `{parameterName}`: The name of the parameter
- `{typeInGeneratedProperty}`: The type of the parameter in the generated property
- `{typeInAllowanceInterface}`: The type of the parameter in the Allowance Interface

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the parameter to the correct type in the generated property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.279 ALLOWANCE-365

Message

```
The counter "{counterName}" specified as the origin of the generated property
"{generatedPropertyName}" does not exist in the Allowance Interface.
```

Legend

- `{counterName}`: The name of the counter
- `{generatedPropertyName}`: The name of the generated property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a counter that exists in the Allowance Interface as origin of the generated property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.280 ALLOWANCE-366

Message

```
The generated property "{generatedPropertyName}" defines its origin with the
counter "{counterName}" of type "{typeInGeneratedProperty}" while its type must
be "number".
```

Legend

- `{generatedPropertyName}`: The name of the generated property
- `{counterName}`: The name of the counter
- `{typeInGeneratedProperty}`: The type of the counter in the generated property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the counter to the type "number" in the generated property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.281 ALLOWANCE-367

Message

```
The generated property "{generatedPropertyName}" defines its origin with
the unknown property "{generatedOriginName}".
```

Legend

- `{generatedPropertyName}`: The name of the generated property
- `{generatedOriginName}`: The name of the origin of the generated property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid origin in a generated property: a parameter or a counter defined in the Allowance Interface or a default Allowance property (unique identifier, activation date or expiration date).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.282 ALLOWANCE-368

Message

```
The parameter "{parameterName}" specified as the origin of the generated
property
"{generatedPropertyName}" is of type "string" which is not allowed.
```

Legend

- `{parameterName}`: The name of the generated property
- `{generatedPropertyName}`: The name of the origin of the generated property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an origin of type "date" or "number" in a generated property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.283 ALLOWANCE-369

Message

```
The generated property "{generatedPropertyName}" defines its origin with the
default property "{generatedOriginName}" and the type
"{typeOfGeneratedProperty}" instead of "{typeOfDefaultAllowanceProperty}".
```

Legend

- `{generatedPropertyName}`: The name of the generated property

- `{generatedOriginName}`: The name of the origin of the generated property
- `{typeOfGeneratedProperty}`: The type of the generated property
- `{typeOfDefaultAllowanceProperty}`: The type of the default Allowance property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the right type of the origin in a generated property: "number" for the unique identifier, "date" for the allowance activation and allowance expiration.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.284 ALLOWANCE-370

Message

```
The clause property "{clausePropertyName}" is defined with the type
"{typeOfClauseProperty}" instead of "{typeOfDefaultAllowanceProperty}".
```

Legend

- `{clausePropertyName}`: The name of the clause property
- `{typeOfClauseProperty}`: The type of the clause property
- `{typeOfDefaultAllowanceProperty}`: The type of the default Allowance property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the right type in the clause property: "number" for the unique identifier, "date" for the allowance activation and allowance expiration.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.285 ALLOWANCE-371

Message

```
The clause property "{clausePropertyName}" of type "{clausePropertyType}"
is defined with the referenced value "{ratingContextPropertyName}" which is not
part of
the rating context.
```

Legend

- `{clausePropertyName}`: The name of the clause property
- `{clausePropertyType}`: The type of the clause property
- `{ratingContextPropertyName}`: The name of the rating context property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a clause value with a valid rating context property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.286 ALLOWANCE-372

Message

```
The name of the generated allowance count property is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a name for the generated allowance count property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.287 ALLOWANCE-373

Message

```
The Counter "{counterName}" cannot be added because it is already used by
one or more Allowance Plans.
```

Legend

- `{counterName}`: The name of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a name not already used by an Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.288 ALLOWANCE-374

Message

```
The Parameter "{parameterName}" cannot be added because it is already used
by one or more Allowance Plans.
```

Legend

- `{parameterName}`: The name of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a name not already used by an Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.289 ALLOWANCE-375

Message

```
One or more clause properties are invalid. A clause must have a name, a type,
an operator, an isReferenceValue flag and a value.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the clause properties have a name, a type, an operator, an `isReferenceValue` flag and a value

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.290 ALLOWANCE-376

Message

```
One or more generated properties are invalid. A generated property must
have a name, a type, an operator and an origin.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the generated properties have a name, a type, an operator, and an origin.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.291 ALLOWANCE-377

Message

```
The generated property "{generatedPropertyName}" is specified more than once.
```

Legend

- `{generatedPropertyName}`: The name of the generated property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the generated property only once.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.292 ALLOWANCE-378

Message

```
The default allowance property "{defaultAllowancePropertyName}" is specified
more than once as a sorting criterion.
```

Legend

- `{defaultAllowancePropertyName}`: The name of the default allowance property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the counter as a sorting criterion only once.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.293 ALLOWANCE-379

Message

```
The allowance search filter is missing in the search operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an allowance search filter to the search operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.294 ALLOWANCE-380

Message

```
The attribute description "id" is missing in the allowance search filter.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the attribute description "id" to the allowance search filter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.295 ALLOWANCE-381

Message

```
The attribute description "id" of the allowance search filter is invalid.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the attribute description "id" with either a format constraint or an enumerated constraint with a single value of type string.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.296 ALLOWANCE-382

Message

```
The identifier of the charging contract is empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a charging contract identifier that is not empty.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.297 ALLOWANCE-387

Message

```
The start date property "{ratingContextPropertyName}" is unknown in the
rating context.
```

Legend

- `{ratingContextPropertyName}`: The name of the rating context property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid rating context property name to define the start date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.298 ALLOWANCE-386

Message

```
The end date cannot be modified after the creation of the Allowance.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Keep the previous end date but extends the end date with the `extendedToEndDateProperty` attribute.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.299 ALLOWANCE-384

Message

```
The end date cannot be extended if the Allowance is not active.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Keep the previous end date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.300 ALLOWANCE-385

Message

```
The start date cannot be modified after the creation of the Allowance.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Keep the previous start date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.301 ALLOWANCE-388

Message

```
The end date property "{ratingContextPropertyName}" is unknown in the rating
context.
```

Legend

- `{ratingContextPropertyName}`: The name of the rating context property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid rating context property name to define the end date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.302 ALLOWANCE-389

Message

```
The extended to end date property "{ratingContextPropertyName}" is unknown
in the rating context.
```

Legend

- `{ratingContextPropertyName}`: The name of the rating context property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid rating context property name to define the extended to end date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.303 ALLOWANCE-390

Message

```
The start date property is empty or null.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a rating context property name to define the start date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.304 ALLOWANCE-391

Message

```
The end date property is empty or null.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a rating context property name to define the end date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.305 ALLOWANCE-392

Message

```
The generated property "{generatedPropertyName}" is defined with the operator
"{operatorOfGeneratedProperty}" which is not compatible with the type
"{typeOfGeneratedProperty}".
```

Legend

- `{generatedPropertyName}`: The name of the generated property
- `{operatorOfGeneratedProperty}`: The operator of the generated property
- `{typeOfGeneratedProperty}`: The type of the generated property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.306 ALLOWANCE-393 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The Charged Item Mapping contains the entry "{entryName}". This entry is
already defined in the Charged Item Class "{chargedItemClassName}".
```

Legend

- `{entryName}`: The name of the entry in the Charged Item Mapping
- `{chargedItemClassName}`: The name of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the entry from the Charged Item Mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to 4.0 SP06. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.307 ALLOWANCE-394

Message

```
The property "{propertyName}" specified in the Charged Item Mapping Entry
"{chargedItemMappingEntryName}" is not allowed in an Allowance Plan.
```

Legend

- `{propertyName}`: The name of the forbidden property
- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a property allowed in Allowance Plans.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.308 ALLOWANCE-395 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The Charged Item Mapping does not contain the entry "{entryName}". This entry
has no value or the value is not applicable in this context in the Charged Item
Class
"{chargedItemClassName}".
```

Legend

- `{entryName}`: The name of the entry in the Charged Item Mapping
- `{chargedItemClassName}`: The name of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the missing entry in the Charged Item Mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to 4.0 SP09. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.309 ALLOWANCE-396

Message

```
The output property at index {outputPropertyIndex} does not have a name.
```

Legend

- `{outputPropertyIndex}`: The index of the output property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.310 ALLOWANCE-397

Message

```
The output property "{outputPropertyName}" is specified more than once.
```

Legend

- `{outputPropertyName}`: The name of the output property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the output property only once.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.311 ALLOWANCE-398

Message

```
An output property cannot be defined for the unknown property
"{outputPropertyName}"
of the Allowance Event Class "{allowanceEventClassId}".
```

Legend

- `{outputPropertyName}`: The name of the output property
- `{allowanceEventClassId}`: The identifier of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a property name that exists in the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.312 ALLOWANCE-399

Message

```
The monitored property "{monitoredPropertyName}" does not exist in the
Allowance Event Class "{allowanceEventClassId}".
```

Legend

- `{monitoredPropertyName}`: The name of the monitored property
- `{allowanceEventClassId}`: The identifier of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a monitored property name that exists in the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.313 ALLOWANCE-400

Message

```
The value of the output property "{outputPropertyName}" is missing.
```

Legend

- `{outputPropertyName}`: The name of the output property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.314 ALLOWANCE-401

Message

```
The allowance event property at index {propertyIndex} does not have a name.
```

Legend

- `{propertyIndex}`: The index of the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.315 ALLOWANCE-402

Message

```
The allowance event property "{propertyName}" is specified more than once.
```

Legend

- `{propertyName}`: The name of the allowance event property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the allowance event property only once.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.316 ALLOWANCE-403

Message

```
The property "{propertyName}" does not exist in the Allowance Event Class
"{allowanceEventClassId}".
```

Legend

- `{propertyName}`: The name of the property
- `{allowanceEventClassId}`: The identifier of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a property name that exists in the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.317 ALLOWANCE-404

Message

```
The property "{propertyName}" does not have the same type as in the Allowance
Event Class "{allowanceEventClassId}".
```

Legend

- `{propertyName}`: The name of the property
- `{allowanceEventClassId}`: The identifier of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the same property type as in the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.318 ALLOWANCE-405

Message

```
The property "{propertyName}" does not have a value.
```

Legend

- `{propertyName}`: The name of the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a value for the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.319 ALLOWANCE-406

Message

```
The property "{propertyName}" does not have a context property value.
```

Legend

- `{propertyName}`: The name of the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a context property value for the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.320 ALLOWANCE-407

Message

```
The context property name "{contextPropertyName}" specified in the property
"{propertyName}" is not valid.
```

Legend

- `{contextPropertyName}`: The name of the invalid context property
- `{propertyName}`: The name of the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a valid context property name for the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.321 ALLOWANCE-408

Message

```
The output property name "{outputPropertyValue}" is specified more than once.
```

Legend

- `{outputPropertyValue}`: The value of the output property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the output property name only once.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.322 ALLOWANCE-409

Message

```
The unit of time of the date shift is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a unit of time to the date shift if missing or set a valid unit of time otherwise.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.323 ALLOWANCE-410

Message

```
The shift of a one-shot rate triggered on the allowance creation is not
supported.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the date shift of the one-shot rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.324 ALLOWANCE-411

Message

```
The brought forward triggering of one-shot rates related to the allowance
activation is not supported (date shift is {dateShift}).
```

Legend

- `{dateShift}`: The not supported date shift

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the date shift of the one-shot rate or set a positive quantity to delay the one-shot triggering.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.325 ALLOWANCE-412

Message

```
The delayed triggering of one-shot rates related to the allowance expiration
is not supported (date shift is {dateShift}).
```

Legend

- `{dateShift}`: The not supported date shift

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the date shift of the one-shot rate or set a negative quantity to bring forward the one-shot triggering.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.326 ALLOWANCE-413

Message

```
The property "{propertyName}" specified in the Charged Item Mapping Entry
"{chargedItemMappingEntryName}" is invalid.
```

Legend

- `{propertyName}`: The name of the invalid property
- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a valid property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.327 ALLOWANCE-414

Message

```
The type "{propertyType}" of the property "{propertyName}" specified in the
Charged Item Mapping Entry "{chargedItemMappingEntryName}" is invalid. The
expected type is:
"{chargedItemMappingEntryType}".
```

Legend

- `{propertyType}`: The type of the property
- `{propertyName}`: The name of the property
- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry
- `{chargedItemMappingEntryType}`: The type of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the Charged Item Mapping Entry or set another property with the expected type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.328 ALLOWANCE-415

Message

```
The reporting scope "session" cannot be used in an allowance plan item.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the reporting scope "session" from the allowance plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.329 ALLOWANCE-416

Message

```
Unexpected error during the initialization of the Allowance Logic
"{allowanceLogicId}".
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic that has not been initialized

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.330 ALLOWANCE-417

Message

```
The Allowance Event Class "{allowanceEventClassId}" cannot be modified because
it does not exist.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class that does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the ID of the Allowance Event Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.331 ALLOWANCE-418

Message

```
The ID of the Allowance Event Class is missing in the
DeleteAllowanceEventClassOp
operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the ID of the Allowance Event Class in the `DeleteAllowanceEventClassOp` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.332 ALLOWANCE-419

Message

```
The Allowance Logic specified in the operation has no ID.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the ID of the Allowance Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.333 ALLOWANCE-420

Message

```
The data type additional information is missing in the parameter {parameterName}.
```

Legend

- `{parameterName}`: The name of the parameter which does not have data type additional information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the data type additional information for the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.334 ALLOWANCE-421

Message

```
Invalid structure of the clause properties.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the number and the order of the clause properties.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.335 ALLOWANCE-432

Message

```
The creation of allowances performed by an allowance logic is not allowed
in the one-shot rate [{allowance_oneshot_name}] because it is not configured
with the
expiration event.
```

Legend

- `{allowance_oneshot_name}`: The name of the oneshot rate that cannot accept the allowance creation

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the one-shot rate used in your allowance logic for renewing allowances is configured with the expiration event.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.336 ALLOWANCE-433

Message

```
The creation of allowances performed by the allowance logic is not allowed
in the one-shot rate [{allowance_oneshot_name}] because a shifted delay is used.
```

Legend

- `{allowance_oneshot_name}`: The name of the oneshot rate that cannot accept the allowance creation

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the one-shot rate used in your allowance logic for renewing allowances is configured with a zero-shifted delay.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.337 ALLOWANCE-434

Message

```
You cannot set a validity start date property in this allowance rate context.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.338 ALLOWANCE-435

Message

```
The Allowance Plan [{allowancePlanId}] cannot be deleted because it is
referred by the following Allowance Logic objects: [{allowanceLogicIds}].
```

Legend

- `{allowancePlanId}`: The ID of the allowance plan
- `{allowanceLogicIds}`: A `CSV` string that contains the list of Allowance Logic IDs that refer to the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the Allowance Logic objects.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.339 ALLOWANCE-436

Message

```
The allowance logic {allowanceLogicId} cannot be modified because the attribute
shareable has been changed from "{allowanceLogicShareableAttribute}" to
"{operationShareableAttribute}".
```

Legend

- `{allowanceLogicId}`: The ID of the allowance logic
- `{allowanceLogicShareableAttribute}`: The value of the attribute shareable in the allowance logic
- `{operationShareableAttribute}`: The value of the attribute shareable in the operation

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the attribute shareable to "{1}" in the modification operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.340 ALLOWANCE-437

Message

```
The allowance plan {allowancePlanId} cannot be modified because the attribute
shareable cannot be changed from "{allowancePlanShareableAttribute}" to
"{operationShareableAttribute}"
if the allowance plan is released.
```

Legend

- `{allowancePlanId}`: The ID of the allowance plan to be created
- `{allowancePlanShareableAttribute}`: The value of the attribute shareable in the allowance plan
- `{operationShareableAttribute}`: The value of the attribute shareable in the operation

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the attribute shareable to "{1}" in the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.341 ALLOWANCE-438

Message

```
A shareable allowance plan must only contain shareable allowance logic
components.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove any allowance logic that is not shareable or make sure that the allowance plan is not shareable.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.342 ALLOWANCE-439

Message

```
Because the allowance logic is shareable, you cannot use the allowance event
sender component in any trigger.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the allowance event sender component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.343 ALLOWANCE-440

Message

```
Because the allowance logic {allowanceLogicId} is shareable, you cannot use
a recurring trigger in this allowance logic.
```

Legend

- `{allowanceLogicId}`: The ID of the allowance logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the recurring trigger component from the allowance logic or make sure that the allowance logic is not shareable.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.344 ALLOWANCE-441

Message

```
Because the allowance logic {allowanceLogicId} is shareable, you cannot use
an activation one-shot trigger in this allowance.
```

Legend

- `{allowanceLogicId}`: The ID of the allowance logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the activation one-shot from the allowance logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.345 ALLOWANCE-442

Message

```
Because the allowance logic {allowanceLogicId} is shareable, you cannot shift
the expiration of a one-shot trigger component.
```

Legend

- `{allowanceLogicId}`: The ID of the allowance logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set to 0 the time shift of the activation one-shot of the allowance logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.346 ALLOWANCE-443

Message

```
Because the allowance logic is shareable, you cannot use the persistent counters
in the component {componentName} of the allowance logic.
```

Legend

- `{componentName}`: The component name that use the persistent counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the counter property from the allowance logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.347 ALLOWANCE-444

Message

```
The share identifier "{shareIdPropertyName}" of the allowance event sender
component is invalid because only parameter properties are allowed.
```

Legend

- `{shareIdPropertyName}`: The property name of the share identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a property of parameter type for the share identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.348 ALLOWANCE-445

Message

```
The share identifier "{shareIdPropertyName}" of the allowance event sender
component does not refer to an existing parameter property.
```

Legend

- `{shareIdPropertyName}`: The property name of the share identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a property of parameter type that exists in the rating context for the share identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.349 ALLOWANCE-446

Message

```
The share identifier "{shareIdPropertyName}" of the create allowance component
does not refer to an existing rating context property.
```

Legend

- `{shareIdPropertyName}`: The property name of the share identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a property name that exists in the rating context for the share identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.350 ALLOWANCE-447

Message

```
The counter property "{propertyName}" that is used in the charged item mapping
entry "{chargedItemMappingEntryName}" is not allowed in a shareable allowance
plan.
```

Legend

- `{propertyName}`: The name of the unallowed property
- `{chargedItemMappingEntryName}`: The name of the charged item mapping entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a property that is allowed in allowance plans.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.351 ALLOWANCE-448

Message

```
Because the allowance logic is not shareable, you can only use the allowance
event sender component in the event-based trigger to send events to shared
allowances.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the allowance event sender component from the event-based trigger or set a share identifier to send events to shared allowances.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.352 ALLOWANCE-449

Message

```
The allowance event sender component {allowanceEventSender} with a share
identifier can only be used in the allowance logic that is not shareable.
```

Legend

- `{allowanceEventSender}`: The name of the allowance event sender component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the allowance event sender component or deselect the share identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.353 ALLOWANCE-450

Message

```
The counterName "{counterPropertyName}" of a debit counter component must
refer to a valid persistent or transient counter.
```

Legend

- `{counterPropertyName}`: The property name of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the property name of the counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.354 ALLOWANCE-451

Message

```
The allowance validity period updater component is not allowed in the
event-base trigger of the shareable allowance logic.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the allowance validity period updater component from the event-based trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.355 ALLOWANCE-452

Message

```
The debitValueName "{debitValueName}" of a debit Counter component must
refer to a valid persistent or transient counter.
```

Legend

- `{debitValueName}`: The name of the debit value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the property name of the debit value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.356 ALLOWANCE-453

Message

```
The allowance property introducer component cannot be used in a shareable
allowance logic.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the allowance property introducer component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.357 ALLOWANCE-454

Message

```
The counter "{counterName}" that is defined as a clause property cannot be
used to select shared allowances.
```

Legend

- `{counterName}`: The name of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the clause properties of counter type if they are used for shared allowances.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.358 ALLOWANCE-455

Message

```
The counter "{counterName}" that is defined as a sorting criterion cannot
be used to sort shared allowances.
```

Legend

- `{counterName}`: The name of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the sorting criteria of counter type if they are used for shared allowances.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.359 ALLOWANCE-456

Message

```
The value of debit "{negativeDebitValue}" must be equal to 0 or greater than 0.
```

Legend

- `{negativeDebitValue}`: The negative value to debit

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the value of debit to a positive value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.360 ALLOWANCE-457

Message

```
The counter "{counterName}" that is used as the origin of the generated property
"{generatedPropertyName}" is not allowed with shared allowances.
```

Legend

- `{counterName}`: The name of the counter
- `{generatedPropertyName}`: The name of the generated property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the counter that is used as the origin of the generated property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.361 ALLOWANCE-458

Message

```
The share identifier property name "{shareIdPropertyName}" of the component
allowance property introducer does not refer to an existing rating context
property.
```

Legend

- `{shareIdPropertyName}`: The property name of the share identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a property that exists in the rating context for the share identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.362 ALLOWANCE-459

Message

```
The name of the debited value output is mandatory.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the debited value output.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.363 ALLOWANCE-460

Message

```
The name of the non debited value output is mandatory.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the non debited value output.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.364 ALLOWANCE-461

Message

```
In the expiration one-shot rate of the allowance logic, the renewal of
allowances
is only allowed for allowances that are not shared.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the create allowance component is configured to renew allowances that are not shared.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.365 ALLOWANCE-462

Message

```
The create allowance component cannot be used in a shareable allowance logic.
```

Legend

- `{counterName}`: The name of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the create allowance component from the shareable allowance logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.366 ALLOWANCE-463

Message

```
The create allowance component cannot be used with a share identifier if the
allowance plan is not shareable.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the share identifier or set a shareable allowance plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.367 ALLOWANCE-464

Message

```
The debit counter component must contain a debit value.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a debit value in the debit counter component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.368 ALLOWANCE-465

Message

```
The allowances of the charging contract "{chargingContractId}" cannot be
retrieved. Message: {message}
```

Legend

- `{chargingContractId}`: The charging contract identifier
- `{message}`: The error message

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Read the message for more details.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.369 ALLOWANCE-466

Message

```
The allowance event sender component {allowanceEventSender} with a share
identifier can only be used in the event-based trigger of the allowance logic
that is not shareable.
```

Legend

- `{allowanceEventSender}`: The name of the allowance event sender component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the allowance event sender component or move it in an event-based trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.370 ALLOWANCE-470

Message

```
The property "{propertyName}" specified in the Charged Item Mapping Entry
"{chargedItemMappingEntryName}" is not available in the context of the Allowance
Plan Item.
```

Legend

- `{propertyName}`: The name of the invalid property
- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a property available in the context of the Allowance Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 2 Patch Level 8 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.371 ALLOWANCE-471

Message

```
The parameter "{parameterName}" cannot reference the mapping table
"{mappingTableId}"
because this mapping table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a mapping table with an agreement ID
- `{mappingTableId}`: The identifier of the mapping table specified in the paramete

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a mapping table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.372 ALLOWANCE-472

Message

```
The parameter of the allowance plan item cannot reference the mapping table
"{parameterValue}" because this mapping table has an agreement ID.
```

Legend

- `{parameterValue}`: The identifier of the mapping table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a mapping table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.373 ALLOWANCE-473

Message

```
The parameter "{parameterName}" cannot reference the range table
"{rangeTableId}"
because this range table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a range table with an agreement ID

- `{rangeTableId}`: The identifier of the range table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.374 ALLOWANCE-474

Message

```
The parameter of the allowance plan item cannot reference the range table
"{parameterValue}" because this range table has an agreement ID.
```

Legend

- `{parameterValue}`: The identifier of the range table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.375 ALLOWANCE-475

Message

```
Recurring trigger "{recurringTriggerName}" is configured for a 4-4-5 calendar.
The only supported frequency type is month.
```

Legend

- `{recurringTriggerName}`: The name of the recurring trigger

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the frequency type to month.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.376 ALLOWANCE-476

Message

```
Recurring trigger "{recurringTriggerName}" is configured for a 4-4-5 calendar.
The only supported frequency periods are 1, 3, 6 and 12.
```

Legend

- `{recurringTriggerName}`: The name of the recurring trigger

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the frequency period to 1, 3, 6 or 12.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.377 ALLOWANCE-477

Message

```
The property "{propertyName}" specified in the charged item mapping entry
"{chargedItemMappingEntryName}" is invalid because the Prepaid Accounts
```

```
Management feature
is disabled.
```

Legend

- `{propertyName}`: The name of the invalid property
- `{chargedItemMappingEntryName}`: The name of the charged item mapping entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a valid property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.378 ALLOWANCE-478

Message

```
The frequency of the recurring trigger "{recurringAllowanceName}" is invalid.
```

Legend

- `{recurringAllowanceName}`: The name of the recurring trigger with invalid frequency

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid frequency in the recurring trigger.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.379 ALLOWANCE-479

Message

```
The counterName "{counterPropertyName}" of a credit counter component must
refer to a valid persistent or transient counter.
```

Legend

- `{counterPropertyName}`: The name of the recurring trigger with invalid frequency

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the property name of the counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.380 ALLOWANCE-480

Message

```
The creditValueName "{creditValueName}" of a credit Counter component must
refer to a valid persistent or transient counter.
```

Legend

- `{creditValueName}`: The name of the credit value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the property name of the credit value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.381 ALLOWANCE-481

Message

```
The value of credit "{negativeCreditValue}" must be equal to 0 or greater
than 0.
```

Legend

- `{negativeCreditValue}`: The negative value to credit

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the value of credit to a positive value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.382 ALLOWANCE-482

Message

```
The credit counter component must contain a name for the result value
output.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the result value output.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.383 ALLOWANCE-483

Message

```
The credit counter component must contain a credit value or a credit value
name.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a credit value or a credit value name in the credit counter component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.384 ALLOWANCE-484

Message

```
"{debitCounter}" is a counter of type debit. You cannot use a debit counter
in the credit counter component "{creditCounterComponentName}".
```

Legend

- `{debitCounter}`: The name of the counter of type debit
- `{creditCounterComponentName}`: The name of the credit counter component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a counter of type credit in the credit counter component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.385 ALLOWANCE-485

Message

```
"{creditCounter}" is a counter of type credit. You cannot use a credit
counter in the debit counter component "{debitCounterComponentName}".
```

Legend

- `{creditCounter}`: The name of the counter of type credit
- `{debitCounterComponentName}`: The name of the debit counter component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a counter of type credit in the credit counter component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.386 ALLOWANCE-486

Message

```
You cannot link the counter "{allowancePlanCounterName}" of type
"{allowancePlanCounterType}" defined in the allowance plan to the counter
"{allowancePlanItemCounterName}" of type "{allowancePlanItemCounterType}"
defined in the
allowance plan item.
```

Legend

- `{allowancePlanCounterName}`: The name of the counter of the allowance plan
- `{allowancePlanCounterType}`: The type of the counter of the allowance plan
- `{allowancePlanItemCounterName}`: The name of the counter of the allowance plan item
- `{allowancePlanItemCounterType}`: The type of the counter of the allowance plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the counter of the allowance plan or link the counter to a counter of the allowance plan item having the same type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.387 ALLOWANCE-487

Message

```
"{counterName}" is a counter of type credit. You cannot use a credit counter
in an allowance plan which is not shareable.
```

Legend

- `{counterName}`: The name of the counter of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.388 ALLOWANCE-488

Message

```
"{counterName}" is a counter of type credit. You cannot use a credit counter
in an allowance logic which is not shareable.
```

Legend

- `{counterName}`: The name of the counter of the allowance logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the counter or remove the type credit.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.389 ALLOWANCE-489

Message

```
The operation of the counter "{counterName}" cannot be modified because the
Allowance Plan "{allowancePlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Allowance Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.390 ALLOWANCE-490

Message

```
You cannot create the allowance plan "{allowancePlanId}" with the flag
ManagedByCockpit
set to true with the create operation.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the import operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.391 ALLOWANCE-491

Message

```
You cannot create the allowance logic "{allowanceLogicId}" with the flag
ManagedByCockpit
set to true with the create operation.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the import operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.392 ALLOWANCE-492

Message

```
You cannot create the allowance event class "{allowanceEventClassId}" with the
flag ManagedByCockpit
set to true with the create operation.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the import operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.393 ALLOWANCE-493

Message

```
The allowance logic "{allowanceLogicId}" referenced by the allowance plan
item has the flag ManagedByCockpit set to "{isAllowanceLogicCockpitCompatible}"
whereas the allowance plan has
the flag ManagedByCockpit set to "{isAllowancePlanCockpitCompatible}".
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic
- `{isAllowanceLogicCockpitCompatible}`: The value of the attribute `ManagedByCockpit` in the Allowance Logic
- `{isAllowancePlanCockpitCompatible}`: The value of the attribute `ManagedByCockpit` in the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the value of the attribute `ManagedByCockpit` of the allowance logic is the same as the one of the allowance plan.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.394 ALLOWANCE-494

Message

```
The allowance event class "{allowanceEventClassId}" referenced by
the allowance logic in trigger "{allowanceEventTriggerId}" has the flag
ManagedByCockpit set to
"{isAllowanceEventClassCockpitCompatible}" whereas the allowance logic has the
flag ManagedByCockpit set to
"{isAllowanceLogicCockpitCompatible}".
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class
- `{allowanceEventTriggerId}`: The index of the Allowance Event Trigger in the Allowance Logic
- `{isAllowanceEventClassCockpitCompatible}`: The value of the attribute `ManagedByCockpit` in the Allowance Event Class
- `{isAllowancePlanCockpitCompatible}`: The value of the attribute `ManagedByCockpit` in the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the value of the attribute `ManagedByCockpit` of the allowance event class is the same as the one of the allowance logic.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.395 ALLOWANCE-495

Message

```
You cannot create the allowance plan with the flag ManagedByCockpit set
to true with the status OPEN. Use the status RELEASED.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the status of the allowance plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.396 ALLOWANCE-496

Message

```
You cannot change the flag ManagedByCockpit to "{newManagedByCockpitFlag}"
in the allowance plan.
```

Legend

- `{newManagedByCockpitFlag}`: The new `ManagedByCockpit` flag

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.397 ALLOWANCE-497

Message

```
You cannot change the flag ManagedByCockpit to "{newManagedByCockpitFlag}"
in the allowance logic.
```

Legend

- `{newManagedByCockpitFlag}`: The new `ManagedByCockpit` flag

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.398 ALLOWANCE-498

Message

```
You cannot change the flag ManagedByCockpit to "{newManagedByCockpitFlag}"
in the allowance event class.
```

Legend

- `{newManagedByCockpitFlag}`: The new `ManagedByCockpit` flag

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.399 ALLOWANCE-499

Message

```
You cannot change the content of an allowance logic with the flag
ManagedByCockpit set to true.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.400 ALLOWANCE-500

Message

```
You cannot change the content of an allowance event class with the flag
ManagedByCockpit set to true.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.401 ALLOWANCE-501

Message

```
The allowance logic or the charge component with the flag ManagedByCockpit
set to true cannot reference the allowance plan "{allowancePlanId}" of which
flag ManagedByCockpit is set to false.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the allowance plan which is referenced to one of which attribute `ManagedByCockpit` is set to true.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.402 ALLOWANCE-502

Message

```
The allowance logic or the charge component with the flag ManagedByCockpit
set to true cannot reference the allowance event class "{allowanceEventClassId}"
of which flag ManagedByCockpit is set to
false.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the allowance event class which is referenced to one of which attribute `ManagedByCockpit` is set to true.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.403 ALLOWANCE-503

Message

```
The allowance logic "{allowanceLogicId}" is already referenced by
the allowance plan "{referencingAllowancePlanId}". You cannot reference twice an
allowance logic with the flag ManagedByCockpit
set to true.
```

Legend

- `{allowanceLogicId}`: The ID of the Allowance Logic
- `{referencingAllowancePlanId}`: The ID of the Allowance Plan which references the Allowance Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Choose another allowance logic or create a new one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.404 ALLOWANCE-504

Message

```
The allowance event class "{allowanceEventClassId}" is already referenced
by the allowance logic "{referencingAllowanceLogicId}". You cannot reference
twice an allowance event class
with the flag ManagedByCockpit set to true.
```

Legend

- `{allowanceEventClassId}`: The ID of the Allowance Event Class
- `{referencingAllowanceLogicId}`: The ID of the Allowance Logic which references the Allowance Event Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Choose another allowance event class or create a new one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.405 ALLOWANCE-505

Message

```
This allowance plan "{allowancePlanId}" is not managed by Cockpit. You cannot
use
the operation deleteAllowancePlanManagedByCockpit.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the `deleteAllowancePlan` operation instead.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.406 ALLOWANCE-506

Message

```
This allowance plan "{allowancePlanId}" is managed by Cockpit. You cannot use
the
operation deleteAllowancePlan.
```

Legend

- `{allowancePlanId}`: The ID of the Allowance Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the `deleteAllowancePlanManagedByCockpit` operation instead.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.407 ALLOWANCE-507

Message

```
The parameter "{parameterName}" specified as a sorting criterion does not
exist in the allowance plan "{allowancePlanId}".
```

Legend

- `{parameterName}`: The name of the parameter
- `{allowancePlanId}`: The ID of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the sorting criterion, specify the name of a parameter that exists in the allowance plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.408 ALLOWANCE-508

Message

```
The parameter "{parameterName}" is specified as a sorting criterion of type
"{typeInSortingCriterion}" while its type is "{typeInAllowancePlan}" in the
allowance plan
"{allowancePlanId}".
```

Legend

- `{parameterName}`: The name of the parameter
- `{typeInSortingCriterion}`: The type of the parameter in the sorting criterion
- `{typeInAllowancePlan}`: The type of the parameter declared in the allowance plan
- `{allowancePlanId}`: The ID of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the sorting criterion, specify the correct type for the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.409 ALLOWANCE-509

Message

```
The counter "{counterName}" specified as a sorting criterion does not
exist in the allowance plan "{allowancePlanId}".
```

Legend

- `{counterName}`: The name of the counter
- `{allowancePlanId}`: The ID of the allowance plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the sorting criterion, specify the name of a counter that exists in the allowance plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2021 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.410 CC-SEC-AUTH-2

Message

```
Authentication failure because no match found for user/password combination.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check your login or your password.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.411 CC-SEC-AUTH-3

Message

```
Authentication failure because no match found for user/password combination.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check your login or your password.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.412 CC-SEC-AUTH-4

Message

```
Authentication failure because the password has expired.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change your password.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.413 CC-SEC-AUTH-5

Message

```
The user profile ''{userLogin}'' is locked.
```

Legend

- `{userLogin}`: the identifier of the user

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact your system administrator to unlock your profile.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.414 CC-SEC-AUTH-6

Message

```
The user ''{userLogin}'' is not allowed to invoke the operation
''{operationName}''.
```

Legend

- `{userLogin}`: the identifier of the user
- `{operationName}`: the name of the operation invoked by the user

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.415 CC-SEC-AUTH-7

Message

```
Authentication failure because the password needs to be changed.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change your password.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.416 CC-SEC-AUTH-8

Message

```
The user session with identifier ''{sessionId}'' does not exist.
```

Legend

- `{sessionId}`: the identifier of the user session

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Open a new user session.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.417 CC-SEC-AUTH-9

Message

```
The user session ''{sessionId}'' is associated to another user.
```

Legend

- `{sessionId}`: the identifier of the user session

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Open a new user session.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.418 CC-SEC-AUTH-10

Message

```
Authentication failure because the user and/or the authentication context
is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change your password.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.419 CC-SEC-AUTH-11

Message

```
The user ''{userLogin}'' is not allowed to use this technical interface.
```

Legend

- `{userLogin}`: the identifier of the user

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Authenticate with another user which has the appropriate security profile for using this technical interface.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.420 CC-SEC-AUTH-1000

Message

```
Invalid user credential because the login is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.421 CC-SEC-AUTH-1001

Message

```
Invalid user credential because the password is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.422 CHANGEID-1

Message

```
The change id of the object [{objectId}] with type [{objectType}] is
[{currentChangeId}]. It is different from the change id [{changeIdToCheck}]
provided for
checking.
```

Legend

- `{objectId}`: The ID of the object
- `{objectType}`: The type of the object
- `{currentChangeId}`: The change ID of the object provided by the server
- `{changeIdToCheck}`: The change ID which is provided for checking

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Cancel the modifications or overwrite the object.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.423 CHANGEID-2

Message

```
The id of the change id model is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a change ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.424 CHANGEID-3

Message

```
The object type is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an object type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.425 CHANGEID-4

Message

```
The object id is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an object ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.426 CHANGEID-5

Message

```
The change id model is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a change ID model.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.427 CHANGEID-6

Message

```
The id of the change id model must be a positive number.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a positive number as change ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.428 CHANGEID-7

Message

```
The catalog object identified by [{objectId}] with type [{objectType}]
does not exist.
```

Legend

- `{objectId}`: The ID of the object
- `{objectType}`: The type of the object

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a pair (object ID, object type) corresponding to an existing object.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.429 CHANGEID-8

Message

```
The id of the change id model must not be a negative number.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a strictly positive number as change ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.430 CHANGEID-9

Message

```
Cannot set the flag on the resource identified by the code "{code}". This
flag was already set by user "{user}" during session "{session}" with another
Core Tool.
```

Legend

- `{code}`: The code used to identify the resource

- `{user}`: The user who has already set the flag
- `{session}`: The ID of the session used to set the flag

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Unset the flag by asking this user to stop editing the resource or by asking the administrator to delete his/her session.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.431 CHANGEID-10

Message

```
This flag action is not supported.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use 'set' or 'unset' as valid action.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.432 CHANGEID-11

Message

```
The flag code is null or empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid code.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.433 CHANGEID-12

Message

```
The owner cannot be empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.434 CHANGELIST-1

Message

```
The Change List is missing in the creation operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a Change List to the creation operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.435 CHANGELIST-2

Message

```
The name of the Change List is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a name for the Change List.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.436 CHANGELIST-3

Message

```
The Change List cannot be created because a Change List with the name
"{changeListName}" already exists.
```

Legend

- `{changeListName}`: The name of the Change List

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Change List.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.437 CHANGELIST-4

Message

```
Error while validating the Change List "{changeListName}".
```

Legend

- `{changeListName}`: The name of the Change List

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.438 CHANGELIST-5

Message

```
The Change List does not contain any object.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one object to the Change List.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.439 CHANGELIST-6

Message

```
Error while validating the object at index "{changeListObjectIndex}".
```

Legend

- `{changeListObjectIndex}`: The index of the object in the Change List

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.440 CHANGELIST-7

Message

```
The code of the object is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a code for the object.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.441 CHANGELIST-8

Message

```
The type of the object is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a type for the object.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.442 CHANGELIST-9

Message

```
The object "{changeListObjectCode}" of type "{changeListObjectType}" does
not exist.
```

Legend

- `{changeListObjectCode}`: The code of the object
- `{changeListObjectType}`: The type of the object

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the code or the type of the object to reference an existing object.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.443 CHANGELIST-10

Message

```
The Change List "{changeListName}" cannot be deleted because it does not exist.
```

Legend

- `{changeListName}`: The name of the Change List

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an existing name for the Change List.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.444 CHANGELIST-11

Message

```
The mandatory filter in the Search Change List operation is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a filter in the Search Change List operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.445 CHANGELIST-12

Message

```
An error occurred during the execution of the search operation: {errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.446 CHANGELIST-13

Message

```
The name of the Change List is missing in the operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the name of a Change List for the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.447 CHANGELIST-14

Message

```
The code of the object is missing in the operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the code of an object for the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.448 CHANGELIST-15

Message

```
The type of the object is missing in the operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the type of an object for the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.449 CHANGELIST-16

Message

```
The Change List "{changeListName}" does not exist.
```

Legend

- `{changeListName}`: The name of the Change List

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the name of the Change List to reference an existing one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.450 CHANGELIST-17

Message

```
The object "{changeListObjectCode}" of type "{changeListObjectType}" does
not exist in the Change List "{changeListName}".
```

Legend

- `{changeListObjectCode}`: The code of the object
- `{changeListObjectType}`: The type of the object
- `{changeListName}`: The name of the Change List

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the code and type of an existing object to include in the Change List.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.451 CHANGELIST-18

Message

```
The name of the Change List is missing in the delete operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the name of a Change List for the delete operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.452 CHANGELIST-19

Message

```
The object "{changeListObjectCode}" of type "{changeListObjectType}" is
specified more than once in the Change List.
```

Legend

- `{changeListObjectCode}`: The code of the object
- `{changeListObjectType}`: The type of the object

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicate object from the Change List.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.453 CHANGELIST-20 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The Change List cannot be created until Transport Destinations are configured.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add Transport Destination(s) to the system.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to 4.0 SP07. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.454 CHANGELIST-22

Message

```
The name of the change list is missing in the change list header of the create
operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Assign a name to the change list header of the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.455 CHANGELIST-23

Message

```
The change list built from object references cannot be created because a
change list with the name "{changeListName}" already exists.
```

Legend

- `{changeListName}`: The name of the Change List

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the change list in the change list header of the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.456 CHANGELIST-24

Message

```
Error while validating the object references of the change list
"{changeListName}".
```

Legend

- `{changeListName}`: The name of the Change List

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.457 CHANGELIST-25

Message

```
The change list does not contain any object reference.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one object reference to the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.458 CHANGELIST-26

Message

```
Error while validating the object reference at index "{objectReferenceIndex}".
```

Legend

- `{objectReferenceIndex}`: The index of the Object Reference in the change list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.459 CHANGELIST-27

Message

```
The identifier of the object reference is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Assign an identifier to the object reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.460 CHANGELIST-28

Message

```
The type of the object reference is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Assign a type to the object reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.461 CHANGELIST-29

Message

```
The object reference with the object identifier "{objectReferenceObjectId}"
and the object type "{objectReferenceObjectType}" does not match any existing
object in
the SAP CC system.
```

Legend

- `{objectReferenceObjectId}`: The object identifier in the object reference
- `{objectReferenceObjectType}`: The object type in the object reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the object identifier or the object type in the object reference to match an existing object.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.462 CHANGELIST-30

Message

```
The object reference with the object identifier "{objectReferenceObjectId}"
and the object type "{objectReferenceObjectType}" already exists in the change
list
create operation.
```

Legend

- `{objectReferenceObjectId}`: The object identifier in the object reference
- `{objectReferenceObjectType}`: The object type in the object reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicate object reference from the change list create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.463 CHARGECOMPONENT-1

Message

```
The code of the charge component is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an identification code to the charge component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.464 CHARGECOMPONENT-2

Message

```
The owner of the charge component "{chargeComponentCode}" is missing.
```

Legend

- `{chargeComponentCode}`: The code of the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an owner to the charge component. It is the a pricing catalog of the service provider.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.465 CHARGECOMPONENT-3

Message

```
The price plan of the charge component "{chargeComponentCode}" is missing.
```

Legend

- `{chargeComponentCode}`: The code of the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a Price Plan to the Charge Component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.466 CHARGECOMPONENT-4

Message

```
The charge component "{chargeComponentCode}" is set to manage multicurrencies
but the currency "{currencyCode}" is set.
```

Legend

- `{chargeComponentCode}`: The code of the Charge Component
- `{currencyCode}`: The code of the set currency

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check whether the charge component is marked as multicurrencies or remove the set currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.467 CHARGECOMPONENT-5

Message

```
The charge component "{chargeComponentCode}" is marked as monocurrency but
no currency is set.
```

Legend

- `{chargeComponentCode}`: The code of the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a currency in the charge component or in the price plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.468 CHARGECOMPONENT-6

Message

```
The Charge Component "{chargeComponentCode}" is set with the currency
"{chargeComponentCurrencyCode}" and Price Plan with currency
"{pricePlanCurrencyCode}".
```

Legend

- `{chargeComponentCode}`: The code of the Charge Component
- `{chargeComponentCurrencyCode}`: The code of the charge component currency
- `{pricePlanCurrencyCode}`: The code of the price plan currency

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the currency only in one of the two places.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.469 CHARGECOMPONENT-7

Message

```
The currency "{currencyCode}" of the charge component "{chargeComponentCode}"
is not a valid currency.
```

Legend

- `{currencyCode}`: The code of the currency
- `{chargeComponentCode}`: The code of the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.470 CHARGECOMPONENT-8

Message

```
The name of the price plan is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Price Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.471 CHARGECOMPONENT-9

Message

```
The currency "{currencyCode}" of the Price Plan "{pricePlanName}" is not
a valid currency.
```

Legend

- `{currencyCode}`: The code of the currency
- `{pricePlanName}`: The name of the Price Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.472 CHARGECOMPONENT-10

Message

```
The currency code of the Price Plan is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a currency code in the Price Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.473 CHARGECOMPONENT-11

Message

```
The currency code "{invalidCurrencyCode}" of the Price Plan is not a valid
currency code.
```

Legend

- `{invalidCurrencyCode}`: The code of the invalid currency code

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the currency code in the Price Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.474 CHARGECOMPONENT-12

Message

```
The rate component of type "{rateComponentType}" is invalid.
```

Legend

- `{rateComponentType}`: The type of the invalid rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.475 CHARGECOMPONENT-13

Message

```
The usage rate name is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the usage rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.476 CHARGECOMPONENT-14

Message

```
The usage rate "{usageRateName}" does not contain any rate component.
```

Legend

- `{usageRateName}`: The name of the usage rate with no rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a rate component in the usage rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.477 CHARGECOMPONENT-15

Message

```
The recurring rate name is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the recurring rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.478 CHARGECOMPONENT-16

Message

```
The recurring rate "{recurringRateName}" does not contain any rate component.
```

Legend

- `{recurringRateName}`: The name of the recurring rate with no rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a rate component in the recurring rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.479 CHARGECOMPONENT-17

Message

```
The recurring rate "{recurringRateName}" is marked as proratable but does
not contain any prorata.
```

Legend

- `{recurringRateName}`: The name of the recurring rate with no prorata

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a prorata in the recurring rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.480 CHARGECOMPONENT-18

Message

```
The one-shot rate name is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the one-shot rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.481 CHARGECOMPONENT-19

Message

```
The one-shot rate "{oneShotRateName}" does not contain any rate component.
```

Legend

- `{oneShotRateName}`: The name of the one-shot rate with no rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a rate component in the one-shot rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.482 CHARGECOMPONENT-20

Message

```
The counter description has no name.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the counter description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.483 CHARGECOMPONENT-21

Message

```
The counter description "{counterDescriptionName}" has no initial value.
```

Legend

- `{counterDescriptionName}`: The name of the counter description with no initial value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of an initial value in the counter description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.484 CHARGECOMPONENT-22

Message

```
The counter description "{counterDescriptionName}" is duplicated.
```

Legend

- `{counterDescriptionName}`: The name of the duplicated counter description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the counter description name is unique.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.485 CHARGECOMPONENT-23

Message

```
The transient counter description has no name.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the transient counter description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.486 CHARGECOMPONENT-24

Message

```
The transient counter description "{counterDescriptionName}" has no initial
value.
```

Legend

- `{counterDescriptionName}`: The name of the counter description with no initial value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of an initial value in the transient counter description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.487 CHARGECOMPONENT-25

Message

```
The transient counter description "{counterDescriptionName}" is duplicated.
```

Legend

- `{counterDescriptionName}`: The name of the duplicated counter description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the transient counter description name is unique.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.488 CHARGECOMPONENT-26

Message

```
One parameter does not have any name.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the parameter name is not empty.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.489 CHARGECOMPONENT-27

Message

```
The parameter "{parameterName}" has a null value.
```

Legend

- `{parameterName}`: The name of the duplicated parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the parameter value is not null.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.490 CHARGECOMPONENT-28

Message

```
The parameter "{parameterName}" is duplicated.
```

Legend

- `{parameterName}`: The name of the duplicated parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the parameter name is unique.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.491 CHARGECOMPONENT-29

Message

```
The charging plan name is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the charging plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.492 CHARGECOMPONENT-30

Message

```
The usage charge name is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the usage charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.493 CHARGECOMPONENT-31

Message

```
The chargeable item name is not set in the usage charge "{usageChargeName}".
```

Legend

- `{usageChargeName}`: The name of the usage charge with no chargeable item name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a chargeable item name in the usage charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.494 CHARGECOMPONENT-32

Message

```
There is no child in the usage charge "{usageChargeName}".
```

Legend

- `{usageChargeName}`: The name of the usage charge with no chargeable item name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a child in the usage charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.495 CHARGECOMPONENT-33

Message

```
There are multiple children in the usage charge "{usageChargeName}".
```

Legend

- `{usageChargeName}`: The name of the usage charge with no chargeable item name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of only one child in the usage charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.496 CHARGECOMPONENT-34

Message

```
The rate component of type "{rateComponentType}" is invalid in the charging plan.
```

Legend

- `{rateComponentType}`: The type of the invalid rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.497 CHARGECOMPONENT-35

Message

```
The recurring charge name is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the recurring charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.498 CHARGECOMPONENT-36

Message

```
There is no child in the recurring charge "{recurringChargeName}".
```

Legend

- `{recurringChargeName}`: The name of the recurring charge with no chargeable item name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a child in the recurring charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.499 CHARGECOMPONENT-37

Message

```
There are multiple children in the recurring charge "{recurringChargeName}".
```

Legend

- `{recurringChargeName}`: The name of the recurring charge with no chargeable item name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of only one child in the recurring charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.500 CHARGECOMPONENT-38

Message

```
The rate component of type "{rateComponentType}" is invalid in the usage
charge "{usageChargeName}".
```

Legend

- `{rateComponentType}`: The type of the invalid rate component
- `{usageChargeName}`: The name of the usage charge

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.501 CHARGECOMPONENT-39

Message

```
The rate component of type "{rateComponentType}" is invalid in the recurring
charge "{recurringChargeName}".
```

Legend

- `{rateComponentType}`: The type of the invalid rate component
- `{recurringChargeName}`: The name of the recurring charge

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.502 CHARGECOMPONENT-40

Message

```
The rate component of type "{rateComponentType}" is invalid in the one-shot
charge "{oneShotChargeName}".
```

Legend

- `{rateComponentType}`: The type of the invalid rate component
- `{oneShotChargeName}`: The name of the one-shot charge

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.503 CHARGECOMPONENT-41

Message

```
The one-shot charge name is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the one-shot charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.504 CHARGECOMPONENT-42

Message

```
There is no child in the one-shot charge "{oneShotChargeName}".
```

Legend

- `{oneShotChargeName}`: The name of the one-shot charge with no chargeable item name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a child in the one-shot charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.505 CHARGECOMPONENT-43

Message

```
There are multiple children in the one-shot charge "{oneShotChargeName}".
```

Legend

- `{oneShotChargeName}`: The name of the one-shot charge with no chargeable item name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of only one child in the one-shot charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.506 CHARGECOMPONENT-44

Message

```
The default charge name is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the default charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.507 CHARGECOMPONENT-45

Message

```
There is no child in the default charge "{defaultChargeName}".
```

Legend

- `{defaultChargeName}`: The name of the default charge with no chargeable item name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a child in the default charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.508 CHARGECOMPONENT-46

Message

```
There are multiple children in the default charge "{defaultChargeName}".
```

Legend

- `{defaultChargeName}`: The name of the default charge with no chargeable item name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of only one child in the default charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.509 CHARGECOMPONENT-47

Message

```
The rate component of type "{rateComponentType}" is invalid in the default
charge "{defaultChargeName}".
```

Legend

- `{rateComponentType}`: The type of the invalid rate component
- `{defaultChargeName}`: The name of the default charge

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.510 CHARGECOMPONENT-48

Message

```
The usage charge "{usageChargeName}" already exists in the charging plan
"{chargingPlanName}".
```

Legend

- `{usageChargeName}`: The name of the usage charge
- `{chargingPlanName}`: The name of the charging plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the uniqueness of the usage charge name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.511 CHARGECOMPONENT-49

Message

```
The charging plan "{chargingPlanName}" has several usage charges using the
chargeable item class "{chargeableItemClassName}".
```

Legend

- `{chargingPlanName}`: The name of the charging plan
- `{chargeableItemClassName}`: The name of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the uniqueness of the chargeable item class in the charging plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.512 CHARGECOMPONENT-50

Message

```
The usage rate "{usageRateName}" already exists in the price plan
"{pricePlanName}".
```

Legend

- `{usageRateName}`: The name of the usage rate
- `{pricePlanName}`: The name of the price plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the uniqueness of the usage rate name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.513 CHARGECOMPONENT-51

Message

```
The price plan "{pricePlanName}" has several usage rates using the chargeable
item class "{chargeableItemClassName}".
```

Legend

- `{pricePlanName}`: The name of the price plan
- `{chargeableItemClassName}`: The name of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the uniqueness of the chargeable item class in the price plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.514 CHARGECOMPONENT-52

Message

```
The usage rate "{usageRateName}" is invalid because its component tree is
invalid.
```

Legend

- `{usageRateName}`: The name of the usage rate with invalid rate components

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate components in the usage rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.515 CHARGECOMPONENT-53

Message

```
The recurring rate "{recurringRateName}" is invalid because its component tree
is invalid.
```

Legend

- `{recurringRateName}`: The name of the recurring rate with invalid rate components

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate components in the recurring rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.516 CHARGECOMPONENT-54

Message

```
The one-shot rate "{oneshotRateName}" is invalid because its component tree
is invalid.
```

Legend

- `{oneshotRateName}`: The name of the one-shot rate with invalid rate components

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate components in the one-shot rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.517 CHARGECOMPONENT-55

Message

```
The rate component has an empty name.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the presence of a name in the rate component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.518 CHARGECOMPONENT-56

Message

```
The rate component "{rateComponentName}" must have exactly
"{expectedChildrenCount}"
children but has "{childrenCount}" children.
```

Legend

- `{rateComponentName}`: The name of the invalid rate component

- `{expectedChildrenCount}`: The expected number of children
- `{childrenCount}`: The number of children

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add or remove children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.519 CHARGECOMPONENT-57

Message

```
The rate component "{rateComponentName}" has an undefined child at index
"{childIndex}".
```

Legend

- `{rateComponentName}`: The name of the invalid rate component
- `{childIndex}`: The undefined child index

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add or remove erroneous children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.520 CHARGECOMPONENT-58

Message

```
The rate component "{rateComponentName}" is invalid.
```

Legend

- `{rateComponentName}`: The name of the invalid rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.521 CHARGECOMPONENT-59

Message

```
The mapping table class "{mappingTableClassId}" defined in the parameter
"{parameterName}" does not exist in the SAP CC system.
```

Legend

- `{mappingTableClassId}`: The identifier of the mapping table class specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid ID of mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing mapping table class for additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.522 CHARGECOMPONENT-60

Message

```
The mapping table "{mappingTableId}" defined in the parameter "{parameterName}"
does not exist in the SAP CC system.
```

Legend

- `{mappingTableId}`: The identifier of the mapping table specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid ID of mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing mapping table for additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.523 CHARGECOMPONENT-61

Message

```
The range table class "{rangeTableClassId}" defined in the parameter
"{parameterName}" does not exist in the SAP CC system.
```

Legend

- `{rangeTableClassId}`: The identifier of the range table class specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid ID of range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing range table class for additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.524 CHARGECOMPONENT-62

Message

```
The range table "{rangeTableId}" defined in the parameter "{parameterName}"
does not exist in the SAP CC system.
```

Legend

- `{rangeTableId}`: The identifier of the range table specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid ID of range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the identifier of an existing range table for additional information value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.525 CHARGECOMPONENT-63

Message

```
The additional information named "{addInfoName}" defined in the parameter
"{parameterName}" is not supported.
```

Legend

- `{addInfoName}`: The name of the additional information specified in the parameter
- `{parameterName}`: The name of the parameter containing an unsupported additional information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the parameter. The supported values are: `dataType`, `mappingTableClass` and `rangeTableClass`.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.526 CHARGECOMPONENT-64

Message

```
The additional information value "{addInfoValue}" defined in the parameter
"{parameterName}" is not a valid data type.
```

Legend

- `{addInfoValue}`: The value of the additional information specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid data type

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the parameter additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.527 CHARGECOMPONENT-65

Message

```
The additional information value "{addInfoValue}" requires that parameter
"{parameterName}" is of type string.
```

Legend

- `{addInfoValue}`: The value of the additional information specified in the parameter
- `{parameterName}`: The name of the parameter containing an invalid data type

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Most probably you defined the wrong type. Check the type and correct it to string.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.528 CHARGECOMPONENT-66

Message

```
The rate component "{rateComponentName}" defines no child but has
"{childrenCount}" child(ren) defined.
```

Legend

- `{rateComponentName}`: The name of the invalid rate component
- `{childrenCount}`: The number of child(ren)

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove all children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.529 CHARGECOMPONENT-67

Message

```
The rate "{rateName}" is invalid because it contains an allowance event
sender component while the charging plan dictionary of the charge component is
not typed.
```

Legend

- `{rateName}`: The name of the rate with the invalid rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the allowance event sender component from the rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.530 CHARGECOMPONENT-68

Message

```
The rate "{rateName}" is invalid because it contains an allowance property
introducer component while the charging plan dictionary of the charge component
```

```
is not
typed.
```

Legend

- `{rateName}`: The name of the rate with the invalid rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the allowance property introducer component from the rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.531 CHARGECOMPONENT-69

Message

```
The rate "{rateName}" is invalid because it contains a create allowance
component while the charging plan dictionary of the charge component is not
typed.
```

Legend

- `{rateName}`: The name of the rate with the invalid rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the create allowance component from the rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.532 CHARGECOMPONENT-70

Message

```
The property at index {propertyIndex} does not have a name.
```

Legend

- `{propertyIndex}`: The index of the property in the property introducer component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a name for the property to introduce.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.533 CHARGECOMPONENT-71

Message

```
The property "{propertyName}" is configured as a context property but
does not specify the name of a context property.
```

Legend

- `{propertyName}`: The name of the property to introduce

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a context property in the property to introduce.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.534 CHARGECOMPONENT-72

Message

```
The property "{propertyName}" specifies an invalid context property:
"{invalidContextPropertyName}".
```

Legend

- `{propertyName}`: The name of the property to introduce
- `{invalidContextPropertyName}`: The name of the invalid context property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a valid context property in the property to introduce.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.535 CHARGECOMPONENT-73

Message

```
The property "{propertyName}" does not specify a value.
```

Legend

- `{propertyName}`: The name of the property to introduce

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a value in the property to introduce.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.536 CHARGECOMPONENT-74

Message

```
The property "{propertyName}" specifies an invalid type.
```

Legend

- `{propertyName}`: The name of the property to introduce

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid type in the property to introduce ("decimal", "string", or "date").

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.537 CHARGECOMPONENT-75

Message

```
The property "{duplicatePropertyName}" is specified more than once.
```

Legend

- `{duplicatePropertyName}`: The duplicate name of the property to introduce

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Rename one of the duplicate properties.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.538 CHARGECOMPONENT-76

Message

```
The public holiday "{code}" does not exist.
```

Legend

- `{code}`: The code of the public holiday

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a valid public holiday.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.539 CHARGECOMPONENT-77

Message

```
The data type additional information is missing in the parameter {parameterName}.
```

Legend

- `{parameterName}`: The name of the parameter which does not have data type additional information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the data type additional information for the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.540 CHARGECOMPONENT-78

Message

```
A no access function that contains a "bestEffortReservation" property
is only allowed in a charge component, in a pricing macro or in an allowance
logic.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the "bestEffortReservation" property from the no access function.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 1 Patch Level 7 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.541 CHARGECOMPONENT-79

Message

```
The property type of the source "{sourcePropertyType}" is unknown.
```

Legend

- `{sourcePropertyType}`: The type of the source property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the type as follows: 0 for a Number, 1 for a String, 2 for a Date, 4 for a Multi-valued String, or 5 for a Multi-valued NumberSet the type as follows: 0 for a Number, 1 for a String, 2 for a Date, 4 for a Multi-valued String, or 5 for a Multi-valued Number.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.542 CHARGECOMPONENT-80

Message

```
The property type of the target "{targetPropertyType}" is unknown.
```

Legend

- `{targetPropertyType}`: The type of the target property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the type as follows: 0 for a Number, 1 for a String, 2 for a Date, 4 for a Multi-valued String, or 5 for a Multi-valued Number.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.543 CHARGECOMPONENT-81

Message

```
The conversion between the source property type "{sourcePropertyType}"
and the target property type "{targetPropertyType}" is not allowed.
```

Legend

- `{sourcePropertyType}`: The type of the source property
- `{targetPropertyType}`: The type of the target property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a source type that can be converted into a target type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.544 CHARGECOMPONENT-82

Message

```
The field separator "{fieldSeparator}" must exactly contain one character.
```

Legend

- `{fieldSeparator}`: The field separator value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the field separator to one character.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.545 CHARGECOMPONENT-83

Message

```
The field separator is mandatory for converting source type
"{sourcePropertyType}"
into target type "{targetPropertyType}".
```

Legend

- `{sourcePropertyType}`: The type of the source property
- `{targetPropertyType}`: The type of the target property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the field separator, or change the source or the target type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.546 CHARGECOMPONENT-84

Message

```
The decimal separator is mandatory for converting source type
"{sourcePropertyType}"
into target type "{targetPropertyType}".
```

Legend

- `{sourcePropertyType}`: The type of the source property
- `{targetPropertyType}`: The type of the target property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the decimal separator attribute, or change the source or the target type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.547 CHARGECOMPONENT-85

Message

```
The decimal separator "{decimalSeparator}" must exactly contain one character.
```

Legend

- `{decimalSeparator}`: The decimal separator value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the decimal separator to one character.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.548 CHARGECOMPONENT-86

Message

```
The thousand separator is mandatory for converting source type
"{sourcePropertyType}"
into target type "{targetPropertyType}".
```

Legend

- `{sourcePropertyType}`: The type of the source property
- `{targetPropertyType}`: The type of the target property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the thousand separator, or change the source or the target type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.549 CHARGECOMPONENT-87

Message

```
The thousand separator "{thousandSeparator}" must contain at least one character.
```

Legend

- `{thousandSeparator}`: The thousand separator value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the thousand separator to at least one character.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.550 CHARGECOMPONENT-88

Message

```
The field separator and the decimal separator must be different.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the field separator and the decimal separator to different values.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.551 CHARGECOMPONENT-89

Message

```
The field separator and the thousand separator must be different.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the field separator and the thousand separator to different values.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.552 CHARGECOMPONENT-90

Message

```
The decimal separator and the thousand separator must be different.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the decimal separator and the thousand separator to different values.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.553 CHARGECOMPONENT-91

Message

```
The date format pattern is mandatory for converting source type
"{sourcePropertyType}"
into target type "{targetPropertyType}".
```

Legend

- `{sourcePropertyType}`: The type of the source property
- `{targetPropertyType}`: The type of the target property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the date format pattern, or change the source or the target type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.554 CHARGECOMPONENT-92

Message

```
The date format pattern "{dateFormatPattern}" is invalid.
```

Legend

- `{dateFormatPattern}`: The pattern describing the date and time format

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid date format pattern.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.555 CHARGECOMPONENT-93

Message

```
The field to use "{fieldToUse}" is not supported.
```

Legend

- `{fieldToUse}`: The field to use from the date

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid field to use between -1 and 16.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.556 CHARGECOMPONENT-94

Message

```
The start offset "{startOffset}" must be greater than 0.
```

Legend

- `{startOffset}`: The start offset of the string

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the start offset to a value greater than 0.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.557 CHARGECOMPONENT-95

Message

```
The start offset "{startOffset}" must be lower than or equal to the stop
offset "{stopOffset}" plus one.
```

Legend

- `{startOffset}`: The start offset of the string
- `{stopOffset}`: The stop offset of the string

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the start offset to a value lower than or equal to the stop offset plus one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.558 CHARGECOMPONENT-96

Message

```
The stop offset "{stopOffset}" must be greater than or equal to -1.
```

Legend

- `{stopOffset}`: The stop offset of the string

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the stop offset to a value greater than or equal to -1.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.559 CHARGECOMPONENT-97

Message

```
Property "{propertyName}" of type "{type}" is required by the component
but does not exist in the context.
```

Legend

- `{propertyName}`: The name of the missing property
- `{type}`: The type expected for the missing property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Detailed Information

As of SP 1 patch level 3 for release 5.0, the SAP CC Core Server system performs stricter validations on the SAP CC logic components, each time you modify, import, or transport data objects that include some logic.

This error code is part of these supplementary validations. See SAP Note 2618936 for the latest information.

Next Actions and Steps (Troubleshooting)

Declare the missing property or remove the invalid reference from the logic component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

To facilitate your troubleshooting and provide you with more user guidance, see:

- SAP Note 2618936
- SAP Note 2580200
- PRICING_LOGIC_STRICT_VALIDATION_ENABLED system parameter

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging

- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.560 CHARGECOMPONENT-98

Message

```
Property "{propertyName}" of type "{expectedType}" is required by the component
but is declared in the context with a different type.
```

Legend

- `{propertyName}`: The name of the property
- `{expectedType}`: The type expected for the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Detailed Information

As of SP 1 patch level 3 for release 5.0, the SAP CC Core Server system performs stricter validations on the SAP CC logic components, each time you modify, import, or transport data objects that include some logic.

This error code is part of these supplementary validations. See SAP Note 2618936 for the latest information.

Next Actions and Steps (Troubleshooting)

Fix the logic component to reference a property of the expected type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

To facilitate your troubleshooting and provide you with more user guidance, see:

- SAP Note 2618936
- SAP Note 2580200
- PRICING_LOGIC_STRICT_VALIDATION_ENABLED system parameter

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging

- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.561 CHARGECOMPONENT-99

Message

```
Property "{propertyName}" exists in the context but does not meet the
constraints of the component.
```

Legend

- `{propertyName}`: The name of the referenced property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Detailed Information

As of SP 1 patch level 3 for release 5.0, the SAP CC Core Server system performs stricter validations on the SAP CC logic components, each time you modify, import, or transport data objects that include some logic.

This error code is part of these supplementary validations. See SAP Note 2618936 for the latest information.

Next Actions and Steps (Troubleshooting)

Change the logic component to reference an appropriate property (table ID, counter, etc.).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

To facilitate your troubleshooting and provide you with more user guidance, see:

- SAP Note 2618936
- SAP Note 2580200
- PRICING_LOGIC_STRICT_VALIDATION_ENABLED system parameter

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.562 CHARGECOMPONENT-100

Message

```
Property "{propertyName}" of type "{type}" is referenced by the component
but has no valid category.
```

Legend

- `{propertyName}`: The name of the missing property
- `{type}`: The type expected for the missing property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Detailed Information

As of SP 1 patch level 3 for release 5.0, the SAP CC Core Server system performs stricter validations on the SAP CC logic components, each time you modify, import, or transport data objects that include some logic.

This error code is part of these supplementary validations. See SAP Note 2618936 for the latest information.

Next Actions and Steps (Troubleshooting)

Fix the XML envelope that contains the incorrect pricing logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

To facilitate your troubleshooting and provide you with more user guidance, see:

- SAP Note 2618936
- SAP Note 2580200
- PRICING_LOGIC_STRICT_VALIDATION_ENABLED system parameter

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.563 CHARGECOMPONENT-101

Message

```
The source property is mandatory.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a source property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.564 CHARGECOMPONENT-102

Message

```
The parameter "{parameterName}" cannot reference the mapping table
"{mappingTableId}" because this mapping table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a mapping table with an agreement ID
- `{mappingTableId}`: The identifier of the mapping table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a mapping table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.565 CHARGECOMPONENT-103

Message

```
The parameter "{parameterName}" cannot reference the range table
"{rangeTableId}"
because this range table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a range table with an agreement ID
- `{rangeTableId}`: The identifier of the range table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.566 CHARGECOMPONENT-104

Message

```
Recurring rate "{recurringRateName}" is configured for a 4-4-5 calendar.
The only supported frequency type is month.
```

Legend

- `{recurringRateName}`: The name of the recurring rate

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the frequency type to month.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.567 CHARGECOMPONENT-105

Message

```
Recurring rate "{recurringRateName}" is configured for a 4-4-5 calendar. T
                    he only supported frequency periods are 1, 3, 6 and 12.
```

Legend

- `{recurringRateName}`: The name of the recurring rate

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the frequency period to 1, 3, 6 or 12.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.568 CHARGECOMPONENT-106

Message

```
The prorata component is configured for a 4-4-5 calendar. The only supported
frequency type is month.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the frequency type to month.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.569 CHARGECOMPONENT-107

Message

```
The prorata component is configured for a 4-4-5 calendar. The only supported
frequency periods are 1, 3, 6 and 12.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the frequency period to 1, 3, 6 or 12.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.570 CHARGECOMPONENT-108

Message

```
The charge component "{chargeComponentCode}" must not contain any prepaid
charging reference because the Prepaid Accounts Management feature is disabled.
```

Legend

- `{chargeComponentCode}`: The code of the charge component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove all prepaid charging references from the charge component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.571 CHARGECOMPONENT-109

Message

```
Overspending on prepaid account is not available because the Prepaid Accounts
Management feature is disabled.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the overspending parameters.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.572 CHARGECOMPONENT-110

Message

```
The Switching Comparator component is not available because the Prepaid
Accounts Management feature is disabled.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the Switching Comparator component from the charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.573 CHARGECOMPONENT-111

Message

```
The Default Reference component is not available because the Prepaid
Accounts Management feature is disabled.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the Default Reference component from the charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.574 CHARGECOMPONENT-112

Message

```
The frequency of recurring rate "{recurringRateName}" is not valid.
```

Legend

- `{recurringRateName}`: The name of the recurring rate

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid frequency in the recurring rate.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.575 CHARGECOMPONENT-113

Message

```
The frequency of prorata component "{componentName}" is not valid.
```

Legend

- `{componentName}`: The name of the prorata component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid frequency in the prorata component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.576 CHARGECOMPONENT-114

Message

```
The property is mandatory.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a valid property from the rating context.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.577 CHARGECOMPONENT-115

Message

```
The recurring time slot is invalid.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `115`

Related Technical Module: `CHARGECOMPONENT`

`CHARGECOMPONENT [page 66]`

Next Actions and Steps (Troubleshooting)

Check that the time slot is correctly defined (beginning of the slot before the end for example).

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.578 CHARGECOMPONENT-116

Message

```
The property "{propertyName}" is mandatory.
```

Legend

- `{propertytName}`: The name of the number property to be split

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `116`

Related Technical Module: `CHARGECOMPONENT`

`CHARGECOMPONENT [page 66]`

Next Actions and Steps (Troubleshooting)

Select a valid number property from the rating context.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.579 CHARGECOMPONENT-117

Message

```
The property "{propertyName}" or the split value must be provided.
```

Legend

- `{propertytName}`: The name of the number property to be split

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `117`

Related Technical Module: `CHARGECOMPONENT`

`CHARGECOMPONENT [page 66]`

Next Actions and Steps (Troubleshooting)

Check that at least the number property or the split value is defined.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.580 CHARGEPLAN-1

Message

```
The charge plan is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a charge plan to the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.581 CHARGEPLAN-2

Message

```
The id of the charge plan is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.582 CHARGEPLAN-3

Message

```
The owner of the charge plan "{chargePlanId}" is missing.
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an owner to the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.583 CHARGEPLAN-4

Message

```
The description of the charge plan "{chargePlanId}" is missing.
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.584 CHARGEPLAN-5

Message

```
Error while validating the charge plan "{chargePlanId}".
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.585 CHARGEPLAN-6 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Replaced by:

- HCI-1 [page 2031]

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The name of the Additional Information at index {additionalInformationIndex}
is missing.
```

Legend

- `{additionalInformationIndex}`: The position index of the Additional Information within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Additional Information item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.586 CHARGEPLAN-7 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.
>
> **Replaced by:**
>
> - HCI-1 [page 2031]

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The name "{additionalInformationName}" of the Additional Information at index
{secondIndex} is already used by the Additional Information at index
{firstIndex}.
```

Legend

- `{additionalInformationName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Additional Informations
- `{firstIndex}`: The index of the first occurrence of the name within Additional Informations

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.587 CHARGEPLAN-8 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The description of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.588 CHARGEPLAN-9 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The type of the Additional Information "{additionalInformationName}" at
index {additionalInformationIndex} is missing or unknown (supported types are
```

```
string,
number, date).
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Additional Information or change it to a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.589 CHARGEPLAN-10 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The date value of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date value to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.590 CHARGEPLAN-11 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The number value of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.591 CHARGEPLAN-12 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The string value of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.592 CHARGEPLAN-13 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The type "{additionalInformationType}" of the Additional Information
"{additionalInformationName}" at index {additionalInformationIndex} is
unsupported (supported
types are string, number, date).
```

Legend

- `{additionalInformationType}`: The unsupported type of the Additional Information
- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date) for the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.593 CHARGEPLAN-14

Message

```
The name of the Parameter at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.594 CHARGEPLAN-15

Message

```
The name "{parameterName}" of the Parameter at index {secondIndex} is
already used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Parameters
- `{firstIndex}`: The index of the first occurrence of the name within Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.595 CHARGEPLAN-16

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex} is
missing or unknown (supported types are string, number, date, currency).
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter or change it to a supported one: string, number, date, currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.596 CHARGEPLAN-17

Message

```
The visibility of the Parameter "{parameterName}" at index {parameterIndex}
is missing or unknown (supported visibilities are chargePlan, chargePlanClass).
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a visibility to the Parameter or change it to a supported one: chargePlan, chargePlanClass.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.597 CHARGEPLAN-18

Message

```
The description of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.598 CHARGEPLAN-19

Message

```
The date value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.599 CHARGEPLAN-20

Message

```
The number value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.600 CHARGEPLAN-21

Message

```
The string value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.601 CHARGEPLAN-22

Message

```
The type "{parameterType}" of the Parameter "{parameterName}" at index
{parameterIndex} is unsupported (supported types are string, number, date,
currency).
```

Legend

- `{parameterType}`: The unsupported type of the Parameter
- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date, currency) for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.602 CHARGEPLAN-23

Message

```
The Parameter "{parameterName}" at index {parameterIndex} is not linked
to a charge plan item Parameter Reference.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Parameter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.603 CHARGEPLAN-24

Message

```
The name of the Counter at index {counterIndex} is missing.
```

Legend

- `{counterIndex}`: The index of the Counter within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.604 CHARGEPLAN-25

Message

```
The name "{counterName}" of the Counter at index {secondIndex} is already
used by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Counters
- `{firstIndex}`: The index of the first occurrence of the name within Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.605 CHARGEPLAN-26

Message

```
The initial value of the Counter "{counterName}" at index {counterIndex} is
missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an initial value to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.606 CHARGEPLAN-27

Message

```
The visibility of the Counter "{counterName}" at index {counterIndex} is
missing or unknown (supported visibilities are chargePlan, chargePlanClass).
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a visibility to the Counter or change it to a supported one: chargePlan, chargePlanClass.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.607 CHARGEPLAN-28

Message

```
The description of the Counter "{counterName}" at index {counterIndex} is
missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.608 CHARGEPLAN-29

Message

```
The Counter "{counterName}" at index {counterIndex} is not linked to a
charge plan item Counter Reference.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Counter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.609 CHARGEPLAN-30

Message

```
The name of the Account Assignment at index {accountAssignmentIndex} is
missing.
```

Legend

- `{accountAssignmentIndex}`: The index of the Account Assignment within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.610 CHARGEPLAN-31

Message

```
The name "{accountAssignmentName}" of the Account Assignment at index
{secondIndex}
    is already used by the Account Assignment at index {firstIndex}.
```

Legend

- `{accountAssignmentName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Account Assignments
- `{firstIndex}`: The index of the first occurrence of the name within Account Assignments

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.611 CHARGEPLAN-32

Message

```
The type of the Account Assignment "{accountAssignmentName}" at index
{accountAssignmentIndex} is missing or unknown (supported types are prepaid,
postpaid).
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{accountAssignmentIndex}`: The index of the Account Assignment

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Account Assignment or change it to a supported one: prepaid, postpaid.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.612 CHARGEPLAN-33

Message

```
The description of the Account Assignment "{accountAssignmentName}" at
index {accountAssignmentIndex} is missing.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{accountAssignmentIndex}`: The index of the Account Assignment

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.613 CHARGEPLAN-34

Message

```
The Account Assignment "{accountAssignmentName}" at index
{accountAssignmentIndex}
is not linked to a charge plan item Account Assignment Reference.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{accountAssignmentIndex}`: The index of the Account Assignment

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Account Assignment or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.614 CHARGEPLAN-35

Message

```
The name of the User Technical Identifier at index {userTechIdIndex} is
missing.
```

Legend

- `{userTechIdIndex}`: The index of the User Technical Identifier within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the User Technical Identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.615 CHARGEPLAN-36

Message

```
The name "{userTechIdName}" of the User Technical Identifier at index
{secondIndex} is already used by the User Technical Identifier at index
{firstIndex}.
```

Legend

- `{userTechIdName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within User Technical Identifiers
- `{firstIndex}`: The index of the first occurrence of the name within User Technical Identifiers

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the User Technical Identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.616 CHARGEPLAN-37

Message

```
The description of the User Technical Identifier "{userTechIdName}" at
index {userTechIdIndex} is missing.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{userTechIdIndex}`: The index of the User Technical Identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the User Technical Identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.617 CHARGEPLAN-38

Message

```
The User Technical Identifier "{userTechIdName}" at index {userTechIdIndex}
is not linked to a charge plan item User Technical Identifier Reference.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{userTechIdIndex}`: The index of the User Technical Identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the User Technical Identifier or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.618 CHARGEPLAN-39

Message

```
The ID of the charge plan item at index {chargePlanItemIndex} is missing.
```

Legend

- `{chargePlanItemIndex}`: The index of the charge plan item within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.619 CHARGEPLAN-40

Message

```
The ID "{chargePlanItemId}" of the charge plan item at index {secondIndex}
is already used by the charge plan item at index {firstIndex}.
```

Legend

- `{chargePlanItemId}`: The duplicated ID
- `{secondIndex}`: The index of the second occurrence of the name within charge plan items
- `{firstIndex}`: The index of the first occurrence of the name within charge plan items

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.620 CHARGEPLAN-41

Message

```
The operation type of the charge plan item "{chargePlanItemId}" at index
{chargePlanItemIndex} is missing or unknown (supported types are debit, credit).
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an operation type to the charge plan item or change it to a supported one: debit, credit.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.621 CHARGEPLAN-42

Message

```
The relationship type of the charge plan item "{chargePlanItemId}" at
index {chargePlanItemIndex} is missing or unknown (supported types are client,
partner).
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a relationship type to the charge plan item or change it to a supported one: client, partner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.622 CHARGEPLAN-43

Message

```
No charge component is referenced by the charge plan item "{chargePlanItemId}"
at index {chargePlanItemIndex}.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a charge component to the charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.623 CHARGEPLAN-44

Message

```
The ID of the master charge component referenced by the charge plan item
"{chargePlanItemId}" at index {chargePlanItemIndex} is missing.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the master charge component within the charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.624 CHARGEPLAN-45

Message

```
The ID of the dependent charge component referenced by the charge plan item
"{chargePlanItemId}" at index {chargePlanItemIndex} is missing.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the dependent charge component within the charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.625 CHARGEPLAN-46

Message

```
The role of the dependent charge component "{chargeComponentId}" referenced
by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is
missing or
unknown (supported roles are partnerCommission, commission, sponsorship,
discount, other).
```

Legend

- `{chargeComponentId}`: The ID of the charge component
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a role to the dependent charge component within the charge plan item or change it to a supported one: partnerCommission, commission, sponsorship, discount, other.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.626 CHARGEPLAN-47

Message

```
The adjustment mode of the dependent charge component "{chargeComponentId}"
referenced by the charge plan item "{chargePlanItemId}" at index
{chargePlanItemIndex}
is missing or unknown (supported modes are none, merging, splitting).
```

Legend

- `{chargeComponentId}`: The ID of the charge component
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an adjustment mode to the dependent charge component within the charge plan item or change it to a supported one: none, merging, splitting.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.627 CHARGEPLAN-48

Message

```
TheError while validating the charge plan item "{chargePlanItemId}" at
index {chargePlanItemIndex}.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.628 CHARGEPLAN-49

Message

```
The name of the Parameter at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter within the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.629 CHARGEPLAN-50

Message

```
The name "{parameterName}" of the Parameter at index {secondIndex} is
already used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Parameters
- `{firstIndex}`: The index of the first occurrence of the name within Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.630 CHARGEPLAN-51

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex} is
missing or unknown (supported types are string, number, date).
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter or change it to a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.631 CHARGEPLAN-52

Message

```
The date value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.632 CHARGEPLAN-53

Message

```
The number value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.633 CHARGEPLAN-54

Message

```
The string value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.634 CHARGEPLAN-55

Message

```
The type "{parameterType}" of the Parameter "{parameterName}" at index
{parameterIndex} is unsupported (supported types are string, number, date).
```

Legend

- `{parameterType}`: The unsupported type of the Parameter
- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date) for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.635 CHARGEPLAN-56

Message

```
The name of the Parameter Reference at index {parameterReferenceIndex}
is missing.
```

Legend

- `{parameterReferenceIndex}`: The index of the Parameter Reference within the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.636 CHARGEPLAN-57

Message

```
The name "{parameterReferenceName}" of the Parameter Reference at index
{secondIndex} is already used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterReferenceName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Parameters
- `{firstIndex}`: The index of the first occurrence of the name within Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.637 CHARGEPLAN-58

Message

```
The target name of the Parameter Reference "{parameterReferenceName}" at
index {parameterReferenceIndex} is missing.
```

Legend

- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.638 CHARGEPLAN-59

Message

```
The Parameter "{targetName}" targeted by the Parameter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} does not exist.
```

Legend

- `{targetName}`: The target name of the Parameter Reference
- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the Parameter Reference to an existing one or create a new Parameter in the charge plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.639 CHARGEPLAN-60

Message

```
The type of the Parameter Reference "{parameterReferenceName}" at index
{parameterReferenceIndex} is missing or unknown (supported types are string,
number, date).
```

Legend

- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter Reference or change it to a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.640 CHARGEPLAN-61

Message

```
The type "{parameterReferenceType}" of the Parameter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} is not compatible with the type
"{parameterType}" of
the targeted Parameter.
```

Legend

- `{parameterReferenceType}`: The type of the Parameter Reference
- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference
- `{parameterType}`: The type of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Parameter Reference to a compatible Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.641 CHARGEPLAN-62

Message

```
The name of the Counter at index {counterIndex} is missing.
```

Legend

- `{counterIndex}`: The index of the Counter within the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.642 CHARGEPLAN-63

Message

```
The name "{counterName}" of the Counter at index {secondIndex} is already
used by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Counters
- `{firstIndex}`: The index of the first occurrence of the name within Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.643 CHARGEPLAN-64

Message

```
The initial value of the Counter "{counterName}" at index {counterIndex}
is missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an initial value to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.644 CHARGEPLAN-65

Message

```
The name of the Counter Reference at index {counterReferenceIndex} is
missing.
```

Legend

- `{counterReferenceIndex}`: The index of the Counter Reference within the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.645 CHARGEPLAN-66

Message

```
The name "{counterName}" of the Counter Reference at index {secondIndex}
is already used by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Counters
- `{firstIndex}`: The index of the first occurrence of the name within Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.646 CHARGEPLAN-67

Message

```
The target name of the Counter Reference "{counterReferenceName}" at
index {counterReferenceIndex} is missing.
```

Legend

- `{counterReferenceName}`: The name of the Counter Reference
- `{counterReferenceIndex}`: The index of the Counter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.647 CHARGEPLAN-68

Message

```
The Counter "{targetName}" targeted by the Counter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} does not exist.
```

Legend

- `{targetName}`: The target name of the Counter Reference
- `{parameterReferenceName}`: The name of the Counter Reference
- `{parameterReferenceIndex}`: The index of the Counter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the Counter Reference to an existing one or create a new Counter in the charge plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.648 CHARGEPLAN-69

Message

```
The name of the Account Assignment Reference at index
{accountAssignmentReferenceIndex}
is missing.
```

Legend

- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference within the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Account Assignment Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.649 CHARGEPLAN-70

Message

```
The name "{accountAssignmentReferenceName}" of the Account Assignment
Reference at index {secondIndex} is already used by the Account Assignment
Reference at index
{firstIndex}.
```

Legend

- `{accountAssignmentReferenceName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Account Assignment References
- `{firstIndex}`: The index of the first occurrence of the name within Account Assignment References

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Account Assignment Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.650 CHARGEPLAN-71

Message

```
The target name of the Account Assignment Reference
"{accountAssignmentReferenceName}"
at index {accountAssignmentReferenceIndex} is missing.
```

Legend

- `{accountAssignmentReferenceName}`: The name of the Account Assignment Reference
- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the Account Assignment Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.651 CHARGEPLAN-72

Message

```
The Account Assignment "{targetName}" targeted by the Account Assignment
Reference "{accountAssignmentReferenceName}" at index
{accountAssignmentReferenceIndex} does not exist.
```

Legend

- `{targetName}`: The target name of the Account Assignment Reference
- `{accountAssignmentReferenceName}`: The name of the Account Assignment Reference
- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the Account Assignment Reference to an existing one or create a new Account Assignment in the Charge Plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.652 CHARGEPLAN-73

Message

```
The type of the Account Assignment Reference "{accountAssignmentReferenceName}"
at index {accountAssignmentReferenceIndex} is missing or unknown (supported
```

```
types are
prepaid, postpaid).
```

Legend

- `{accountAssignmentReferenceName}`: The name of the Account Assignment Reference
- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Account Assignment Reference or change it to a supported one: prepaid, postpaid.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.653 CHARGEPLAN-74

Message

```
The type "{accountAssignmentReferenceType}" of the Account Assignment
Reference "{accountAssignmentReferenceName}" at index
{accountAssignmentReferenceIndex} is
not compatible with the type "{accountAssignmentType}" of the targeted Account
Assignment.
```

Legend

- `{accountAssignmentReferenceType}`: The type of the Account Assignment Reference
- `{accountAssignmentReferenceName}`: The name of the Account Assignment Reference
- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference
- `{accountAssignmentType}`: The type of the Account Assignment

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Account Assignment Reference to a compatible Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.654 CHARGEPLAN-75

Message

```
The service name of the User Technical Identifier Reference at index
{userTechnicalIdentifierReferenceIndex} is missing.
```

Legend

- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference within the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a service name to the User Technical Identifier Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.655 CHARGEPLAN-76

Message

```
The service "{userTechnicalIdentifierReferenceService}" of the User
Technical Identifier Reference at index {secondIndex} is already used by the
User Technical
Identifier Reference at index {firstIndex}.
```

Legend

- `{userTechnicalIdentifierReferenceService}`: The duplicated service
- `{secondIndex}`: The index of the second occurrence of the name within User Technical Identifier References
- `{firstIndex}`: The index of the first occurrence of the name within User Technical Identifier References

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the service of the User Technical Identifier Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.656 CHARGEPLAN-77

Message

```
The target name of the User Technical Identifier Reference
"{userTechnicalIdentifierReferenceName}"
at index {userTechnicalIdentifierReferenceIndex} is missing.
```

Legend

- `{userTechnicalIdentifierReferenceName}`: The name of the User Technical Identifier Reference
- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the User Technical Identifier Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.657 CHARGEPLAN-78

Message

```
The User Technical Identifier "{targetName}" targeted by the User Technical
Identifier Reference "{userTechnicalIdentifierReferenceService}" at index
{userTechnicalIdentifierReferenceIndex} does not exist.
```

Legend

- `{targetName}`: The target name of the User Technical Identifier Reference
- `{userTechnicalIdentifierReferenceService}`: The service of the User Technical Identifier Reference
- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the User Technical Identifier Reference to an existing one or create a new User Technical Identifier in the charge plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.658 CHARGEPLAN-79

Message

```
The Charged Item Mapping is missing in the charge plan item.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a Charged Item Mapping to the charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.659 CHARGEPLAN-80

Message

```
The class of the Charged Item Mapping is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a class to the Charged Item Mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.660 CHARGEPLAN-81

Message

```
Error while validating the Charged Item Mapping of class "{citcClass}".
```

Legend

- `{citcClass}`: The class of the Charged Item Mapping

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.661 CHARGEPLAN-82

Message

```
The name of the Charged Item Mapping Entry at index
{chargedItemMappingEntryIndex}
is missing.
```

Legend

- `{chargedItemMappingEntryIndex}`: The index of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Charged Item Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.662 CHARGEPLAN-83

Message

```
The name "{chargedItemMappingEntryName}" of the Charged Item Mapping
Entry at index {secondIndex} is already used by the Charged Item Mapping Entry
at index
{firstIndex}.
```

Legend

- `{chargedItemMappingEntryName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Charged Item Mapping Entries
- `{firstIndex}`: The index of the first occurrence of the name within Charged Item Mapping Entries

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Charged Item Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.663 CHARGEPLAN-84

Message

```
The type of the Charged Item Mapping Entry "{chargedItemMappingEntryName}"
at index {chargedItemMappingEntryIndex} is missing or unknown (supported types
are string,
number, date, boolean).
```

Legend

- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry
- `{chargedItemMappingEntryIndex}`: The index of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Charged Item Mapping Entry or change it to a supported one: string, number, date, boolean.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.664 CHARGEPLAN-85

Message

```
The tax module of the Tax Parameter Set is missing or unknown (supported
modules are vatTax, usTax).
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a tax module to the Tax Parameter Set or change it to a supported one: vatTax, usTax.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.665 CHARGEPLAN-86

Message

```
The tax module "{taxParameterSetModule}" of the Tax Parameter Set at
index {secondIndex} is already used by the Tax Parameter Set at index
{firstIndex}.
```

Legend

- `{taxParameterSetModule}`: The duplicated module
- `{secondIndex}`: The index of the second occurrence of the tax module within Tax Parameter Sets
- `{firstIndex}`: The index of the first occurrence of the tax module within Tax Parameter Sets

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the tax module of the Tax Parameter Set.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.666 CHARGEPLAN-87

Message

```
Error while validating the Tax Parameter Set with tax module
"{taxParameterSetModule}".
```

Legend

- `{taxParameterSetModule}`: The tax module of the Tax Parameter Set

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.667 CHARGEPLAN-88

Message

```
The name of the Tax Parameter at index {taxParameterIndex} is missing.
```

Legend

- `{taxParameterIndex}`: The index of the Tax Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Tax Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.668 CHARGEPLAN-89

Message

```
The name "{taxParameterName}" of the Tax Parameter at index {secondIndex}
is already used by the Tax Parameter at index {firstIndex}.
```

Legend

- `{taxParameterName}`: The duplicated module
- `{secondIndex}`: The index of the second occurrence of the name within Tax Parameters
- `{firstIndex}`: The index of the first occurrence of the name within Tax Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Tax Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.669 CHARGEPLAN-90

Message

```
The type of the Tax Parameter "{taxParameterName}" at index {taxParameterIndex}
is missing or unknown (supported types are string, number, date).
```

Legend

- `{taxParameterName}`: The name of the Tax Parameter
- `{taxParameterIndex}`: The index of the Tax Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Tax Parameter or change it to a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.670 CHARGEPLAN-91

Message

```
Impossible to create the charge plan because its ID {chargePlanId} already
exists.
```

Legend

- `{chargePlanId}`: The ID of the charge plan that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.671 CHARGEPLAN-92

Message

```
The ID of the charge plan is missing in the delete charge plan operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID in the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.672 CHARGEPLAN-93

Message

```
Impossible to delete the charge plan because its ID {chargePlanId} does not
exist.
```

Legend

- `{chargePlanId}`: The ID of the charge plan that needs to be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.673 CHARGEPLAN-94

Message

```
Error while deleting the charge plan "{chargePlanId}". The charge plan is
still activated in one provider contract.
```

Legend

- `{chargePlanId}`: The ID of the charge plan that needs to be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete all provider contract items referencing the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.674 CHARGEPLAN-95

Message

```
Impossible to modify the charge plan because its ID {chargePlanId} does not
exist.
```

Legend

- `{chargePlanId}`: The ID of the charge plan that needs to be modified

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.675 CHARGEPLAN-96

Message

```
The Account Assignment at the index {accountAssignmentIndex} is empty.
```

Legend

- `{accountAssignmentIndex}`: The index of the empty Account Assignment that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Account Assignment or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.676 CHARGEPLAN-97 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Replaced by:

- HCI-1 [page 2031]

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The Additional Info at the index {additionalInfoIndex} is empty.
```

Legend

- `{additionalInfoIndex}`: The position index of the empty Additional Information item that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Additional Information item or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.677 CHARGEPLAN-98

Message

```
The Charge Dependency at the index {chargeDependencyIndex} is empty.
```

Legend

- `{chargeDependencyIndex}`: The index of the empty Charge Dependency that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Charge Dependency or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.678 CHARGEPLAN-99

Message

```
The masterCode of the Charge Dependency at index {chargeDependencyIndex} is
missing.
```

Legend

- `{chargeDependencyIndex}`: The index of the Charge Dependency within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a masterCode to the Charge Dependency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.679 CHARGEPLAN-100

Message

```
The dependentCode of the Charge Dependency at index {chargeDependencyIndex}
is missing.
```

Legend

- `{chargeDependencyIndex}`: The index of the Charge Dependency within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a dependentCode to the Charge Dependency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.680 CHARGEPLAN-101

Message

```
The Charge Dependency at index {firstIndex} having the masterCode "{masterCode}"
and the dependentCode "{dependentCode}" is already used at index {secondIndex}.
```

Legend

- `{firstIndex}`: The index of the first occurrence of the Charge Dependency
- `{masterCode}`: The masterCode that appears in the two Charge Dependency
- `{dependentCode}`: The dependentCode that appears in the two Charge Dependency
- `{secondIndex}`: The index of the second occurrence of the Charge Dependency

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove one of the dependencies.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.681 CHARGEPLAN-102

Message

```
The masterCode "{masterCode}" of the Charge Dependency at index
{chargeDependencyIndex}
does not match the ID of an existing Master Charge Component.
```

Legend

- `{masterCode}`: The masterCode of the Charge Dependentcy that does not match any ID of Master Charge Component
- `{chargeDependencyIndex}`: The index of the Charge Dependency

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the masterCode to the ID of an existing Master Charge Component or remove the Charge Dependency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.682 CHARGEPLAN-103

Message

```
The dependentCode "{dependentCode}" of the Charge Dependency at index
{chargeDependencyIndex} does not match the ID of an existing Dependent Charge
Component.
```

Legend

- `{dependentCode}`: The dependentCode of the Charge Dependentcy that does not match any ID of Master Charge Component
- `{chargeDependencyIndex}`: The index of the Charge Dependency

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the dependentCode to the ID of an existing Dependent Charge Component or remove the Charge Dependency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.683 CHARGEPLAN-104

Message

```
The Counter at the index {counterIndex} is empty.
```

Legend

- `{counterIndex}`: The index of the empty Counter that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Counter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.684 CHARGEPLAN-105

Message

```
The Visibility "{counterVisibility}" of the Counter "{counterName}" at
index {counterIndex} is unsupported (supported visibilities are chargePlan,
chargePlanClass).
```

Legend

- `{counterVisibility}`: The unsupported Visibility of the Counter
- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported visibility (chargePlan, chargePlanClass) for the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.685 CHARGEPLAN-106

Message

```
The Parameter at the index {parameterIndex} is empty.
```

Legend

- `{parameterIndex}`: The index of the empty Parameter that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Parameter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.686 CHARGEPLAN-107

Message

```
The Visibility "{parameterVisibility}" of the Parameter "{parameterName}"
at index {parameterIndex} is unsupported (supported visibilities are chargePlan,
chargePlanClass).
```

Legend

- `{counterVisibility}`: The unsupported Visibility of the Counter
- `{counterName}`: The name of the Parameter
- `{counterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported visibility (chargePlan, chargePlanClass) for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.687 CHARGEPLAN-108

Message

```
The User Technical Identifier at the index {userTechnicalIdentifierIndex}
is empty.
```

Legend

- `{userTechnicalIdentifierIndex}`: The index of the empty User Technical Identifier that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid User Technical Identifier or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.688 CHARGEPLAN-109

Message

```
The charge plan item at the index {chargePlanItemIndex} is empty.
```

Legend

- `{chargePlanItemIndex}`: The index of the empty charge plan item that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid charge plan item or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.689 CHARGEPLAN-110

Message

```
The ID of the charge component referenced by the charge plan item
"{chargePlanItemId}"
at index {chargePlanItemIndex} does not match any Charge Component.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing Charge Component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.690 CHARGEPLAN-111

Message

```
The ID of the dependent charge component referenced by the charge plan item
"{chargePlanItemId}" at index {chargePlanItemIndex} and the code
"{retrievedChargeComponentCode}"
of the Charge Component retrieved do not match.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item
- `{retrievedChargeComponentCode}`: The code of the retrieved Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.691 CHARGEPLAN-112

Message

```
The dependent charge component referenced by the charge plan item
"{chargePlanItemId}"
at index {chargePlanItemIndex} matches a master Charge Component instead of a
dependent one.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an ID matching a dependent Charge Component and not a master Charge Component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.692 CHARGEPLAN-113

Message

```
The owner of the charge plan and the owner of the Charge Component referenced
by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} do
not match.
The owner of the charge plan is "{chargePlanOwner}". The owner of the Charge
Component
is "{chargeComponentOwner}".
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item
- `{chargePlanOwner}`: The owner of the charge plan
- `{chargeComponentOwner}`: The owner of the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an ID of dependent Charge Component that has the same owner as the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.693 CHARGEPLAN-114

Message

```
The Charging Mapping "{chargingMappingName}" of the referred Charge Component
"{chargeComponentId}" is not declared in the charge plan.
```

Legend

- `{chargingMappingName}`: The name of the Charging Mapping
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Charging Mapping in the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.694 CHARGEPLAN-115

Message

```
The ID of the master charge component referenced by the charge plan item
"{chargePlanItemId}" at index {chargePlanItemIndex} and the code
"{retrievedChargeComponentCode}"
of the Charge Component retrieved do not match.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item
- `{retrievedChargeComponentCode}`: The code of the retrieved Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.695 CHARGEPLAN-116

Message

```
The master charge component referenced by the charge plan item
"{chargePlanItemId}"
```

```
at index {chargePlanItemIndex} matches a dependent Charge Component instead of a
master one.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an ID matching a master Charge Component and not a dependent Charge Component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.696 CHARGEPLAN-117

Message

```
The owner of the charge plan and the owner of the Charge Component referenced
by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} do
not match.
The owner of the charge plan is "{chargePlanOwner}". The owner of the Charge
Component is
"{chargeComponentOwner}".
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item
- `{chargePlanOwner}`: The owner of the charge plan
- `{chargeComponentOwner}`: The owner of the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an ID of master Charge Component that has the same owner as the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.697 CHARGEPLAN-118

Message

```
The mandatory filter in the Search charge plan operation is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter in the Search charge plan operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.698 CHARGEPLAN-119

Message

```
An error occurred during the execution of the search operation: {errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.699 CHARGEPLAN-120

Message

```
The mandatory filter in the Search charge plan Class operation is missing.
```

Next Actions and Steps (Troubleshooting)

Add a filter in the Search charge plan Class operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.700 CHARGEPLAN-121

Message

```
An error occurred during the execution of the search operation: {errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.701 CHARGEPLAN-122

Message

```
Only one charge component (master or dependent) must be declared in
the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex}.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the extra charge component(s) from the charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.702 CHARGEPLAN-123

Message

```
The Account Assignment Reference "{accountAssignmentRefName}" at index
{accountAssignmentRefIndex} does not exist in the Charging Mapping of the
referred Charge
Component "{chargeComponentId}".
```

Legend

- `{accountAssignmentRefName}`: The name of the Account Assignment Reference
- `{accountAssignmentRefIndex}`: The index of the Account Assignment Reference
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Account Assignment Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.703 CHARGEPLAN-124

Message

```
The Charging Mapping "{chargingMappingName}" of the referred Charge Component
"{chargeComponentId}" is not typed (this is mandatory).
```

Legend

- `{chargingMappingName}`: The name of the Charging Mapping
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a type to the Charging Mapping in the Charge Component or choose another Charge Component with a typed Charging Mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.704 CHARGEPLAN-125

Message

```
The type "{accountAssignmentRefType}" of the Account Assignment Reference
"{accountAssignmentRefName}" at index {accountAssignmentRefIndex} is
incompatible with the
type of the Charging Mapping "{chargingMappingName}" in the referred Charge
Component
"{chargeComponentId}".
```

Legend

- `{accountAssignmentRefType}`: The type of the Account Assignment Reference
- `{accountAssignmentRefName}`: The name of the Account Assignment Reference
- `{accountAssignmentRefIndex}`: The index of the Account Assignment Reference
- `{chargingMappingName}`: The name of the Charging Mapping in the Charge Component
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the Account Assignment Reference to the type of the Charging Mapping in the Charge Component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.705 CHARGEPLAN-126

Message

```
The Counter "{counterName}" at index {counterIndex} does not exist in
the referred Charge Component "{chargeComponentId}".
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.706 CHARGEPLAN-127

Message

```
The Counter Reference "{counterRefName}" at index {counterRefIndex} does
not exist in the referred Charge Component "{chargeComponentId}".
```

Legend

- `{counterRefName}`: The name of the Counter Reference
- `{counterRefIndex}`: The index of the Counter Reference
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.707 CHARGEPLAN-128

Message

```
The Parameter "{parameterName}" at index {parameterIndex} does not exist
in the referred Charge Component "{chargeComponentId}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.708 CHARGEPLAN-129

Message

```
The Parameter Reference "{parameterRefName}" at index {parameterRefIndex}
does not exist in the referred Charge Component "{chargeComponentId}".
```

Legend

- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.709 CHARGEPLAN-130

Message

```
User Technical Identifiers are declared although the referred Charge Component
"{chargeComponentId}" does not have usage rates.
```

Legend

- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove User Technical Identifiers.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.710 CHARGEPLAN-131

Message

```
User Technical Identifiers are not declared although the referred Master
Charge Component "{chargeComponentId}" has usage rates.
```

Legend

- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add User Technical Identifiers.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.711 CHARGEPLAN-132

Message

```
The charge plan is missing.
```

Legend

- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a charge plan to the modify operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.712 CHARGEPLAN-133

Message

```
The charge plan with the ID {chargePlanId} does not exist.
```

Legend

- `{chargePlanId}`: The ID of the charge plan which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the charge plan to an existing one or create the charge plan first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.713 CHARGEPLAN-134

Message

```
Impossible to modify the charge plan because the specified owner
{specifiedOwner}
does not correspond to the owner {realOwner} existing in the charge plan.
```

Legend

- `{specifiedOwner}`: The specified owner in the operation
- `{realOwner}`: The owner existing in the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the owner to the owner of the charge plan or create a new charge plan for the specified owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.714 CHARGEPLAN-135

Message

```
The Charge Component "{chargeComponentId}" referred by the charge plan
item "{chargePlanItemId}" at index {chargePlanItemIndex} is unknown.
```

Legend

- `{chargeComponentId}`: The ID of the Charge Component
- `{chargePlanItemId}`: The ID of the Charging Contract Item
- `{chargePlanItemIndex}`: The index of the Charging Contract Item within the Charging Contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the chargeComponentId to an existing Charge Component identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.715 CHARGEPLAN-136

Message

```
Internal server error. Impossible to modify the charge plan because the
charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} refers to
an unknown
Charge Component.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.716 CHARGEPLAN-137

Message

```
User Technical Identifiers are declared although the referred Charge Component
"{chargeComponentId}" is dependent.
```

Legend

- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove User Technical Identifiers.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.717 CHARGEPLAN-138

Message

```
The charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} is
already referencing the Charge Component "{originalChargeComponentId}" and
cannot reference
the Charge Component "{newChargeComponentId}" at the same time.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item within the charge plan
- `{originalChargeComponentId}`: The original ID of the Charge Component
- `{newChargeComponentId}`: The new ID of the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the Charge Component already referenced by the charge plan item or create a new charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.718 CHARGEPLAN-139

Message

```
Internal server error. Impossible to modify the charge plan because the charge
plan item "{chargePlanItemId}" at index {chargePlanItemIndex} refers to an
incompatible
Charge Component "{chargeComponentId}". To be compatible, a Charge Component
must have an
Internal Reference Dictionary with typed references.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item within the charge plan
- `{chargeComponentId}`: The ID of the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.719 CHARGEPLAN-140

Message

```
charge plan "{chargePlanId}" must at least declare one charge plan item.
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.720 CHARGEPLAN-141

Message

```
The mandatory modification date is missing in the modify charge plan operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a modification date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.721 CHARGEPLAN-142

Message

```
The status of the charge plan "{chargePlanId}" is missing.
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a status to the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.722 CHARGEPLAN-143

Message

```
The status of new charge plan "{chargePlanId}" must be open.
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new charge plan to open.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.723 CHARGEPLAN-144

Message

```
The status of already released charge plan "{chargePlanId}" cannot be set
back to open.
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new charge plan to released or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.724 CHARGEPLAN-145

Message

```
The status of already obsolete charge plan "{chargePlanId}" cannot be set
back to open.
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new charge plan to released or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.725 CHARGEPLAN-146

Message

```
The status of already obsolete charge plan "{chargePlanId}" cannot be set
back to released.
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new charge plan to released or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.726 CHARGEPLAN-147

Message

```
The parameter "{parameterName}" at index {parameterIndex} has a date type
which is incompatible with the charge component parameter whose type is
{chargeComponentParameterType}.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: TThe index of the Parameter
- `{chargeComponentParameterType}`: The type of the Charge Component Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.727 CHARGEPLAN-148

Message

```
The parameter "{parameterName}" at index {parameterIndex} has a number
type which is incompatible with the charge component parameter whose type is
{chargeComponentParameterType}.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{chargeComponentParameterType}`: The type of the Charge Component Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.728 CHARGEPLAN-149

Message

```
The parameter "{parameterName}" at index {parameterIndex} has a string type
which is incompatible with the charge component parameter whose type is
{chargeComponentParameterType}.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{chargeComponentParameterType}`: The type of the Charge Component Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.729 CHARGEPLAN-150

Message

```
The parameter reference "{parameterRefName}" at index {parameterRefIndex}
has a date type which is incompatible with the charge component parameter whose
type is
{chargeComponentParameterType}.
```

Legend

- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference
- `{chargeComponentParameterType}`: The type of the Charge Component Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter reference type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.730 CHARGEPLAN-151

Message

```
The parameter reference "{parameterRefName}" at index {parameterRefIndex}
has a number type which is incompatible with the charge component parameter
whose type is
{chargeComponentParameterType}.
```

Legend

- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference
- `{chargeComponentParameterType}`: The type of the Charge Component Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter reference type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.731 CHARGEPLAN-152

Message

```
The parameter reference "{parameterRefName}" at index {parameterRefIndex}
has a string type which is incompatible with the charge component parameter
```

```
whose type is
{chargeComponentParameterType}.
```

Legend

- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference
- `{chargeComponentParameterType}`: The type of the Charge Component Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter reference type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.732 CHARGEPLAN-153

Message

```
The type "{parameterRefType}" of the Parameter Reference "{parameterRefName}"
at index {parameterRefIndex} is unsupported (supported types are string, number,
date).
```

Legend

- `{parameterRefType}`: The unsupported type of the Parameter Reference
- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date) for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.733 CHARGEPLAN-154

Message

```
The currency value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a currency value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.734 CHARGEPLAN-155

Message

```
The currency Parameter "{parameterName}" at index {parameterIndex} is
unnecessary because the referred Charge Component "{chargeComponentId}" has a
fixed currency.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.735 CHARGEPLAN-156

Message

```
The currency Parameter "{parameterName}" at index {secondIndex} is unnecessary
because another one is already present in Parameter or Parameter Reference list.
```

Legend

- `{parameterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the currency within Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.736 CHARGEPLAN-157

Message

```
The currency Parameter value "{parameterValue}" at index {parameterIndex}
is unknown by the SAP Convergent Charging system.
```

Legend

- `{parameterValue}`: The value of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Find a valid currency value using `exportCurrencies` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.737 CHARGEPLAN-158

Message

```
The currency value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a currency value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.738 CHARGEPLAN-159

Message

```
A currency must be defined in the charge plan item "{chargePlanItemId}" because
the referred charge Component "{chargeComponentId}" is multiCurrencies.
```

Legend

- `{chargePlanItemId}`: The name of the charge plan item
- `{chargeComponentId}`: The identifier of the referred Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a currency Parameter or Parameter Reference to the charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.739 CHARGEPLAN-160

Message

```
The currency of the Dependent Charge "{dependentChargeId}" ({dependentCurrency})
must be the same as the Master Charge "{masterChargeComponentId}"
({masterCurrency}) because
the adjustment mode of the dependent is merging or splitting.
```

Legend

- `{dependentChargeId}`: The identifier of the Dependent Charge Component
- `{dependentCurrency}`: The currency of the Dependent Charge Component
- `{masterChargeComponentId}`: The identifier of the Master Charge Component
- `{masterCurrency}`: The currency of the Master Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the adjustment mode or remove the dependency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.740 CHARGEPLAN-161

Message

```
The Master charge plan item "{masterChargePlanItemId}" and the Dependent
charge plan item "{dependentChargePlanItemId}" must define their currency at the
same level
and with the same value because the adjustment mode of the dependent is merging
or splitting.
```

Legend

- `{masterChargePlanItemId}`: The identifier of the Master charge plan item
- `{dependentChargePlanItemId}`: The identifier of the Dependent charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define the both charges currency at the charge plan item level and with the same value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.741 CHARGEPLAN-162

Message

```
The Master charge plan item "{masterChargePlanItemId}" refers to the charge
plan Currency parameter "{masterChargePlanCurrencyParam}" and the Dependent
charge plan item
"{dependentChargePlanItemId}" refers to the Charge Plan Currency parameter
"{dependentChargePlanCurrencyParam}",
but they must both refer to the same parameter because the adjustment mode of
the dependent
is merging or splitting.
```

Legend

- `{masterChargePlanItemId}`: The identifier of the Master charge plan item
- `{masterChargePlanCurrencyParam}`: The currency of the Master charge plan item
- `{dependentChargePlanItemId}`: The identifier of the Dependent charge plan item
- `{dependentChargePlanCurrencyParam}`: The charge plan parameter that the Dependent charge plan item refers to

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Make both charge plan items currency parameter refer to the same charge plan currency parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.742 CHARGEPLAN-163

Message

```
The master Charge Component "{masterChargeComponentId}" is multiCurencies
and the Dependent Charge Component "{dependentChargeComponentId}" is
monoCurrency, but this
case is not supported because the adjustment mode of the dependent is merging or
splitting.
```

Legend

- `{masterChargeComponentId}`: The identifier of the Master Charge Component
- `{dependentChargeComponentId}`: The identifier of the Dependent Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the adjustment mode or remove the dependency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.743 CHARGEPLAN-164

Message

```
The master Charge Component "{masterChargeComponentId}" is monoCurencies
and the Dependent Charge Component "{dependentChargeComponentId}" is
multiCurrency, but only
Charge Plan Item currency definition is supported because the adjustment mode of
the dependent
is merging or splitting.
```

Legend

- `{masterChargeComponentId}`: The identifier of the Master Charge Component
- `{dependentChargeComponentId}`: The identifier of the Dependent Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the adjustment mode or remove the dependency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.744 CHARGEPLAN-165

Message

```
The master charge plan item "{masterChargePlanItemId}" is defined with
the currency "{masterChargeCurrency}" and the Dependent charge plan item
"{dependentChargePlanItemId}"
is defined with the currency "{dependentChargeCurrency}" but they must have the
same currency
because the adjustment mode of the dependent is merging or splitting.
```

Legend

- `{masterChargePlanItemId}`: The identifier of the Master charge plan item
- `{masterChargeCurrency}`: The currency of the Master charge plan item
- `{dependentChargePlanItemId}`: The identifier of the Master charge plan item
- `{dependentChargeCurrency}`: The currency of the Dependent charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the adjustment mode or remove the dependency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.745 CHARGEPLAN-166

Message

```
The service "{aUserTechnicalIdentifierReference}" of the User Technical
Identifier Reference is already used by another charge plan item for the User
```

```
Technical Identifier
"{userTechnicalIdentifierTargetName}".
```

Legend

- `{aUserTechnicalIdentifierReference}`: The duplicated service
- `{userTechnicalIdentifierTargetName}`: The duplicated User Technical Identifier name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the service of the User Technical Identifier Reference or the target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.746 CHARGEPLAN-167

Message

```
The counter name "{counterName}" at index {counterIndex} is unknown to the
counter names dictionary whereas it is visible to the external system.
```

Legend

- `{counterName}`: The name of the counter unknown to the counter names dictionary
- `{counterIndex}`: The index of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the counter name to the counter names dictionary or change the counter name to a known one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.747 CHARGEPLAN-168

Message

```
The service name "{serviceName}" of the User Technical Identifier Reference
at index {userTechnicalIdentifierReferenceIndex} is missing is not ASCII.
Invalid characters
are "{invalidCharacters}".
```

Legend

- `{serviceName}`: The name of the service, as provided
- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference within the charge plan item
- `{invalidCharacters}`: A CSV string of non-ASCII characters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace the invalid characters of service name with ASCII characters.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.748 CHARGEPLAN-169

Message

```
The service name "{serviceName}" of the User Technical Identifier Reference
at index {userTechnicalIdentifierReferenceIndex} has more than 128 characters.
```

Legend

- `{serviceName}`: The name of the service, as provided
- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference within the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Shorten the service name to 128 ASCII characters.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.749 CHARGEPLAN-170

Message

```
The parameter additional information "{additionalInformationName}" at index
{additionalInformationIndex} is unknown.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this additional information or replace it with a known one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.750 CHARGEPLAN-171

Message

```
The data type of the parameter is not defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add this additional information or remove all additional informations.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.751 CHARGEPLAN-172

Message

```
The parameter is a mapping table ID but no mapping table class is defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the mapping table class additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.752 CHARGEPLAN-173

Message

```
The parameter is a mapping table key and could not be linked to a mapping
table class.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the mapping table class additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.753 CHARGEPLAN-174

Message

```
The parameter cannot declare additional informations without a data type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a data type additional information or remove all additional informations.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.754 CHARGEPLAN-175

Message

```
Error while validating the Parameter "{parameterName}" at index {parameterIndex}.
```

Legend

- `{parameterName}`: The name of the charge plan Parameter
- `{parameterIndex}`: The index of the charge plan Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.755 CHARGEPLAN-176

Message

```
The mapping table ID "{mappingTableIdName}" is not declared whereas it is
used in the charge component.
```

Legend

- `{mappingTableIdName}`: The name of the Parameter which is a mapping table ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the corresponding mapping table ID parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.756 CHARGEPLAN-177

Message

```
The mapping table key "{mappingTableKeyName}" of type "{mappingTableKeyType}"
is not declared whereas it is used in the charge component.
```

Legend

- `{mappingTableKeyName}`: The name of the Parameter which is a mapping table key
- `{mappingTableKeyType}`: The type of the mapping table key

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the corresponding mapping table ID parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.757 CHARGEPLAN-178

Message

```
Error while validating the Parameter "{parameterName}" at index {parameterIndex}.
```

Legend

- `{parameterName}`: The name of the charge plan item Parameter
- `{parameterIndex}`: The index of the charge plan item Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.758 CHARGEPLAN-179

Message

```
Error while validating the Parameter Reference "{parameterName}" at
index {parameterIndex}.
```

Legend

- `{parameterName}`: The name of the charge plan item Parameter Reference
- `{parameterIndex}`: The index of the charge plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.759 CHARGEPLAN-180

Message

```
The charge plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared as
a mapping table ID.
```

Legend

- `{cpParameterName}`: The name of the charge plan Parameter
- `{parameterReferenceName}`: The name of the charge plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the charge plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the mapping table ID data type and the mapping table class additional informations in the charge plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.760 CHARGEPLAN-181

Message

```
The charge plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declare
an incompatible
mapping table class "{cpParameterMappingTableClass}" while the Parameter
Reference is of class
"{parameterReferenceMappingTableClass}".
```

Legend

- `{cpParameterName}`: The name of the charge plan Parameter
- `{parameterReferenceName}`: The name of the charge plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the charge plan item Parameter Reference
- `{cpParameterMappingTableClass}`: The mapping table class of the charge plan Parameter
- `{parameterReferenceMappingTableClass}`: The mapping table class of the charge plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the mapping table ID data type and the mapping table class additional informations in the charge plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.761 CHARGEPLAN-182

Message

```
The charge plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared as
a mapping table key.
```

Legend

- `{cpParameterName}`: The name of the charge plan Parameter
- `{parameterReferenceName}`: The name of the charge plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the charge plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the mapping table key data type additional information in the charge plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.762 CHARGEPLAN-183

Message

```
The Parameter is declared as a mapping table ID while it does not exist
in the Charge Component.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the mapping table ID data type additional information from the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.763 CHARGEPLAN-184

Message

```
The Parameter is declared as a mapping table ID but it does not have a STRING
type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the parameter as a STRING.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.764 CHARGEPLAN-185

Message

```
The mapping table class "{parameterMappingTableClass}" declared in the
Parameter is incompatible with the one declared in the Charge Component
"{chargeComponentMappingTableClass}".
```

Legend

- `{parameterMappingTableClass}`: The mapping table class of the Parameter
- `{chargeComponentMappingTableClass}`: The mapping table class declared in the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the right mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.765 CHARGEPLAN-186

Message

```
The Parameter is declared as a mapping table key while it does not exist
in the Charge Component.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the mapping table key data type additional information from the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.766 CHARGEPLAN-187

Message

```
The Parameter is declared with a mapping table key but has a wrong type
"{parameterType}" while it should be "{chargeComponentType}".
```

Legend

- `{parameterType}`: The type of the Parameter
- `{chargeComponentType}`: The type declared in the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the right type for the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.767 CHARGEPLAN-188

Message

```
The code of the charged item class ({chargedItemClassCode}) referenced
by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} does
not match
any Charged Item Class.
```

Legend

- `{chargedItemClassCode}`: The code of the Charged Item Class
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.768 CHARGEPLAN-189

Message

```
The code of the charged item class ({chargedItemClassCode}) referenced
by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} does
not match
any Charged Item Class.
```

Legend

- `{chargedItemClassCode}`: The code of the Charged Item Class
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.769 CHARGEPLAN-190

Message

```
Internal server error. Impossible to modify the charge plan because the
charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} refers to
an unknown
Charged Item Class.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item within the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.770 CHARGEPLAN-191

Message

```
The code of the charged item class ({chargedItemClassCode}) referenced
by the charge plan item "{chargePlanItemId}" at index {chargePlanItemIndex} does
```

```
not match
any Charged Item Class.
```

Legend

- `{chargedItemClassCode}`: The code of the Charged Item Class
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.771 CHARGEPLAN-192

Message

```
The description of the charge plan "{chargePlanId}" cannot be modified
because the charge plan has been released.
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.772 CHARGEPLAN-193

Message

```
The additional info "{additionalInformationName}" cannot be removed because
the charge plan "{chargePlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.773 CHARGEPLAN-194

Message

```
The additional info "{additionalInformationName}" cannot be added because
the charge plan "{chargePlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.774 CHARGEPLAN-195

Message

```
The description of the additional info "{additionalInformationName}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.775 CHARGEPLAN-196

Message

```
The type of the additional info "{additionalInformationName}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.776 CHARGEPLAN-198

Message

```
The date value of the additional info "{additionalInformationName}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.777 CHARGEPLAN-199

Message

```
The number value of the additional info "{additionalInformationName}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.778 CHARGEPLAN-200

Message

```
The string value of the additional info "{additionalInformationName}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.779 CHARGEPLAN-201

Message

```
The counter "{counterName}" cannot be removed because the charge plan
"{chargePlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.780 CHARGEPLAN-202

Message

```
The counter "{counterName}" cannot be added because the charge plan
"{chargePlanId}"
has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.781 CHARGEPLAN-203

Message

```
The description of the counter "{counterName}" cannot be modified because
the charge plan "{chargePlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.782 CHARGEPLAN-204

Message

```
The initial value of the counter "{counterName}" cannot be modified because
the charge plan "{chargePlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.783 CHARGEPLAN-205

Message

```
The account assignment "{accountAssignmentName}" cannot be removed because
the charge plan "{chargePlanId}" has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.784 CHARGEPLAN-206

Message

```
The account assignment "{accountAssignmentName}" cannot be added because
the charge plan "{chargePlanId}" has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.785 CHARGEPLAN-207

Message

```
The description of the account assignment "{accountAssignmentName}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.786 CHARGEPLAN-208

Message

```
The type of the account assignment "{accountAssignmentName}" cannot be
modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.787 CHARGEPLAN-209

Message

```
The user technical identifier "{userTechIdName}" cannot be removed because
the charge plan "{chargePlanId}" has been released.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.788 CHARGEPLAN-210

Message

```
The user technical identifier "{userTechIdName}" cannot be added because
the charge plan "{chargePlanId}" has been released.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.789 CHARGEPLAN-211

Message

```
The description of the user technical identifier "{userTechIdName}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.790 CHARGEPLAN-212

Message

```
The charge plan item "{chargePlanItemId}" cannot be removed because the
charge plan "{chargePlanId}" has been released.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.791 CHARGEPLAN-213

Message

```
The charge plan item "{chargePlanItemId}" cannot be added because the
charge plan "{chargePlanId}" has been released.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.792 CHARGEPLAN-214

Message

```
The master charge component of the charge plan item "{chargePlanItemId}"
cannot be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.793 CHARGEPLAN-215

Message

```
The parameter "{parameterName}" cannot be removed because the charge plan
"{chargePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.794 CHARGEPLAN-216

Message

```
The parameter "{parameterName}" cannot be added because the charge plan
"{chargePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.795 CHARGEPLAN-217

Message

```
The description of the parameter "{parameterName}" cannot be modified
because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.796 CHARGEPLAN-218

Message

```
The type of the parameter "{parameterName}" cannot be modified because
the charge plan "{chargePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.797 CHARGEPLAN-219

Message

```
The currency value of the parameter "{parameterName}" cannot be modified
because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.798 CHARGEPLAN-220

Message

```
The date value of the parameter "{parameterName}" cannot be modified
because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.799 CHARGEPLAN-221

Message

```
The number value of the parameter "{parameterName}" cannot be modified
because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.800 CHARGEPLAN-222

Message

```
The string value of the parameter "{parameterName}" cannot be modified
because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.801 CHARGEPLAN-223

Message

```
The relationship type of the charge plan item "{chargePlanItemId}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.802 CHARGEPLAN-224

Message

```
The operation type of the charge plan item "{chargePlanItemId}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.803 CHARGEPLAN-225

Message

```
The dependent charge component of the charge plan item "{chargePlanItemId}"
cannot be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.804 CHARGEPLAN-226

Message

```
The account assignment "{accountAssignmentName}" of the charge plan item
"{chargePlanItemId}" cannot be added because the charge plan "{chargePlanId}"
has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.805 CHARGEPLAN-227

Message

```
The account assignment "{accountAssignmentName}" of the charge plan item
"{chargePlanItemId}" cannot be removed because the charge plan "{chargePlanId}"
has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.806 CHARGEPLAN-228

Message

```
The user technical identifier "{userTechIdService}" of the charge plan
item "{chargePlanItemId}" cannot be added because the charge plan
"{chargePlanId}" has
been released.
```

Legend

- `{userTechIdService}`: The service of the User Technical Identifier
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.807 CHARGEPLAN-229

Message

```
The user technical identifier "{userTechIdService}" of the charge plan
item "{chargePlanItemId}" cannot be removed because the charge plan
```

```
"{chargePlanId}" has
been released.
```

Legend

- `{userTechIdService}`: The service of the User Technical Identifier
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.808 CHARGEPLAN-230 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The charged item mapping of the charge plan item "{chargePlanItemId}" cannot
be modified because the charge plan "{chargePlanId}" has been released.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.809 CHARGEPLAN-231

Message

```
The account assignment "{accountAssignmentName}" of the charge plan item
"{chargePlanItemId}" cannot be modified because the charge plan "{chargePlanId}"
has been
released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.810 CHARGEPLAN-232

Message

```
The charge plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared as
an invoice text.
```

Legend

- `{cpParameterName}`: The name of the charge plan Parameter
- `{parameterReferenceName}`: The name of the charge plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the charge plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the invoice text data type additional information in the charge plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.811 CHARGEPLAN-233

Message

```
The charge plan Parameter "{parameterName}" at index {parameterIndex}
points to an unknown mapping table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.812 CHARGEPLAN-234

Message

```
The charge component Parameter "{parameterName}" points to an unknown
mapping table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.813 CHARGEPLAN-235

Message

```
The charge plan item Parameter "{parameterName}" at index {parameterIndex}
points to an unknown mapping table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.814 CHARGEPLAN-236

Message

```
The default value and property name of the Tax Parameter "{taxParameterName}"
at index {taxParameterIndex} cannot be null.
```

Legend

- `{taxParameterName}`: The name of the Tax Parameter
- `{taxParameterIndex}`: The index of the Tax Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a default value or a property name to the Tax Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.815 CHARGEPLAN-237

Message

```
The default value of the Tax Parameter "{taxParameterName}" at index
{taxParameterIndex} is empty.
```

Legend

- `{taxParameterName}`: The name of the Tax Parameter
- `{taxParameterIndex}`: The index of the Tax Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a default value to the Tax Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.816 CHARGEPLAN-238

Message

```
The property name of the Tax Parameter "{taxParameterName}" at index
{taxParameterIndex} is empty.
```

Legend

- `{taxParameterName}`: The name of the Tax Parameter
- `{taxParameterIndex}`: The index of the Tax Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a property name to the Tax Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.817 CHARGEPLAN-239

Message

```
The VAT rule "{vatRuleId}" referenced by the charge plan item
"{chargePlanItemId}"
    at index {chargePlanItemIndex} does not match any known VAT rule.
```

Legend

- `{vatRuleId}`: The ID of the VAT rule
- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing VAT rule.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.818 CHARGEPLAN-240

Message

```
The VAT rule referenced by the charge plan item "{chargePlanItemId}" at index
{chargePlanItemIndex} must not be set as a property, but as a fixed value
```

```
matching an
existing VAT rule ID.
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing VAT rule.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.819 CHARGEPLAN-241

Message

```
The tax module of the Tax Parameter Set has changed (the tax module cannot
be changed).
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the original tax module of the Tax Parameter Set.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.820 CHARGEPLAN-242

Message

```
The parameter is a range table ID but no range table class is defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the range table class additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.821 CHARGEPLAN-243

Message

```
The range table ID "{rangeTableIdName}" is not declared whereas it is used
in the charge component.
```

Legend

- `{rangeTableIdName}`: The name of the Parameter which is a range table ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the corresponding range table ID parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.822 CHARGEPLAN-244

Message

```
The charge plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared as a
range table ID.
```

Legend

- `{cpParameterName}`: The name of the charge plan Parameter
- `{parameterReferenceName}`: The name of the charge plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the charge plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the range table ID data type and the range table class additional informations in the charge plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.823 CHARGEPLAN-245

Message

```
The charge plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declare
an incompatible
range table class "{cpParameterRangeTableClass}" while the Parameter Reference
is of class
"{parameterReferenceRangeTableClass}".
```

Legend

- `{cpParameterName}`: The name of the charge plan Parameter
- `{parameterReferenceName}`: The name of the charge plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the charge plan item Parameter Reference
- `{cpParameterRangeTableClass}`: The range table class of the charge plan Parameter
- `{parameterReferenceRangeTableClass}`: The range table class of the charge plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the range table ID data type and the range table class additional informations in the charge plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

> See also Deprecated and Revoked Error Codes [page 58].

4.824 CHARGEPLAN-246

Message

```
The Parameter is declared as a range table ID while it does not exist
in the Charge Component.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the range table ID data type additional information from the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.825 CHARGEPLAN-247

Message

```
The Parameter is declared as a range table ID but it does not have a STRING
type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the parameter as a STRING.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.826 CHARGEPLAN-248

Message

```
The range table class "{parameterRangeTableClass}" declared in the Parameter
is incompatible with the one declared in the Charge Component
"{chargeComponentRangeTableClass}".
```

Legend

- `{parameterRangeTableClass}`: The range table class of the Parameter
- `{chargeComponentRangeTableClass}`: The range table class declared in the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the right range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.827 CHARGEPLAN-249

Message

```
The charge plan Parameter "{parameterName}" at index {parameterIndex}
points to an unknown range table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.828 CHARGEPLAN-250

Message

```
The charge component Parameter "{parameterName}" points to an unknown range
table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.829 CHARGEPLAN-251

Message

```
The charge plan item Parameter "{parameterName}" at index {parameterIndex}
points to an unknown range table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.830 CHARGEPLAN-252

Message

```
The tax parameters of the dependent charge plan item
"{dependentChargePlanItemId}"
are different from the tax parameters of the master charge plan item
"{masterChargePlanItemId}".
```

Legend

- `{dependentChargePlanItemId}`: The identifier of the Dependent charge plan item
- `{masterChargePlanItemId}`: The identifier of the Master charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set axactlly the same tax parameters in both the master and dependent charge plan items.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.831 CHARGEPLAN-253

Message

```
The code of the Charged Item Aggregation Policy
({chargedItemAggregationPolicyCode})
referenced by the charge plan item "{chargePlanItemId}" at index
```

```
{chargePlanItemIndex} does
not exist.
```

Legend

- `{chargedItemAggregationPolicyCode}`: The code of the Charged Item Aggregation Policy
- `{chargePlanItemId}`: The identifier of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the Charge Plan Item with a code of an existing Charged Item Aggregation Policy.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.832 CHARGEPLAN-254

Message

```
The "{chargedItemAggregationPolicyOwner}" owner of the Charged Item Aggregation
Policy is different from the "{chargePlanItemOwner}" of the Charge Plan.
```

Legend

- `{chargedItemAggregationPolicyOwner}`: The owner of the Charged Item Aggregation Policy
- `{chargePlanItemOwner}`: The owner of the Charge Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a Charged Item Aggregation Policy which is owned by the same owner than the Charge Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.833 CHARGEPLAN-255

Message

```
The "{chargedItemAggregationPolicyCode}" Charged Item Aggregation Policy
and the "{chargePlanItemId}" Charge Plan Item must have same the
"{chargedItemClassCode}"
Charged Item Class.
```

Legend

- `{chargedItemAggregationPolicyCode}`: The code of the Charged Item Aggregation Policy
- `{chargePlanItemId}`: TThe identifier of the Charge Plan Item
- `{chargedItemClassCode}`: The code of the Charged Item Class of the Charge Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a Charged Item Aggregation Policy whose Charged Item Class corresponds to the Charged Item Class of the Charge Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.834 CHARGEPLAN-256

Message

```
The name "{chargedItemMappingEntryName}" of the Charged Item Mapping Entry
at index {index} does not exist in the Charged Item Class
"{chargedItemClassCode}" of the
Charge Plan Item "{chargePlanItemId}".
```

Legend

- `{chargedItemMappingEntryName}`: The unknown name
- `{index}`: The index of the unknown name within Charged Item Mapping Entries
- `{chargedItemClassCode}`: The code of the Charged Item Class of the Charge Plan Item

- `{chargePlanItemId}`: The ID of the Charge Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Charged Item Mapping Entry or remove the entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.835 CHARGEPLAN-257

Message

```
The initial value of the Counter "{counterName}" at index {counterIndex}
is forbidden.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the initial value of the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.836 CHARGEPLAN-258 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The code of the charged item class ({chargedItemClassCode}) referred to
by the charge plan item "{chargePlanItemId}" cannot be changed to
({newChargedItemClassCode}).
```

Legend

- `{chargedItemClassCode}`: The original code of the Charged Item Class
- `{chargePlanItemId}`: The ID of the charge plan item
- `{newChargedItemClassCode}`: The new code of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of the original charged item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to 4.0 SP09. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.837 CHARGEPLAN-259

Message

```
Parameter "{parameterName}" at index {parameterIndex} points to the range
table "{parameterValue}" which is not an instance of the previously defined
range table
class "{rangeTableClass}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter
- `{rangeTableClass}`: The range table class of the charge plan Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.838 CHARGEPLAN-260

Message

```
Error while validating the Response Charged Item Mapping Entry at index
{chargedItemMappingEntryIndex}.
```

Legend

- `{chargedItemMappingEntryIndex}`: The index of the Response Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.839 CHARGEPLAN-261

Message

```
The Charged Item Class of the Response Charged Item Mapping is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of a Charged Item Class in the Response Charged Item Mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.840 CHARGEPLAN-262

Message

```
The code of the Charged Item Class "{chargedItemClassCode}" referenced by
the Response Charged Item Mapping does not match any existing Charged Item Class.
```

Legend

- `{chargedItemClassCode}`: The code of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of an existing Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.841 CHARGEPLAN-263

Message

```
The owner of the Charged Item Class of the Response Charged Item Mapping
does not match with the owner of the Charge Plan. The owner of the Charged Item
Class is
"{chargedItemClassOwner}". The owner of the Charge Plan is
"{allowancePlanOwner}".
```

Legend

- `{chargedItemClassOwner}`: The owner of the Charged Item Class
- `{allowancePlanOwner}`: The owner of the Charge Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of a Charged Item Class that has the same owner as the Charge Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.842 CHARGEPLAN-264

Message

```
The name of the Charged Item Mapping Entry is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the Charged Item Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.843 CHARGEPLAN-265

Message

```
The name "{chargedItemMappingEntryName}" of the Charged Item Mapping Entry
is already used by the Charged Item Mapping Entry at index
{firstOccurrenceIndex}.
```

Legend

- `{chargedItemMappingEntryName}`: The duplicated name
- `{firstOccurrenceIndex}`: The index of the first occurrence of the name in Charged Item Mapping Entries

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Charged Item Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.844 CHARGEPLAN-266

Message

```
The type of the Charged Item Mapping Entry "{chargedItemMappingEntryName}"
is missing or unknown (the supported types are string, number, date, boolean).
```

Legend

- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Charged Item Mapping Entry or change it into a supported one: string, number, date, boolean.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.845 CHARGEPLAN-267

Message

```
The Response Charged Item Mapping contains the entry
"{chargedItemMappingEntryName}".
This entry does not exist in the Charged Item Class "{chargedItemClassCode}".
```

Legend

- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry
- `{chargedItemClassCode}`: The code of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the entry from the Response Charged Item Mapping or replace it by an existing property of the Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.846 CHARGEPLAN-269

Message

```
The Response Charged Item Mapping contains the entry
"{chargedItemMappingEntryName}"
with the type "{chargedItemMappingEntryType}". This type is not compatible with
the one
defined in the Charged Item Class: "{chargedItemClassFieldType}".
```

Legend

- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry
- `{chargedItemMappingEntryType}`: The type of the Charged Item Mapping Entry
- `{chargedItemClassFieldType}`: The type of the field in the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the Charged Item Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.847 CHARGEPLAN-270

Message

```
The value of the Charged Item Mapping Entry "{chargedItemMappingEntryName}"
is not set.
```

Legend

- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set either a value or a property name in the Charged Item Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.848 CHARGEPLAN-271

Message

```
The property "{propertyName}" specified in the Charged Item Mapping Entry
"{chargedItemMappingEntryName}" is invalid.
```

Legend

- `{propertyName}`: The name of the invalid property
- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a valid property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.849 CHARGEPLAN-272

Message

```
The type "{propertyType}" of the property "{propertyName}" specified in
the Charged Item Mapping Entry "{chargedItemMappingEntryName}" is invalid. The
expected type is:
"{chargedItemMappingEntryType}".
```

Legend

- `{propertyType}`: The type of the property
- `{propertyName}`: The name of the property
- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry
- `{chargedItemMappingEntryType}`: The type of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the Charged Item Mapping Entry or set another property with the expected type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.850 CHARGEPLAN-273

Message

```
The property "{propertyName}" specified in the Charged Item Mapping Entry
"{chargedItemMappingEntryName}" is not allowed in a Charge Plan.
```

Legend

- `{propertyName}`: The name of the forbidden property
- `{chargedItemMappingEntryName}`: The name of the Charged Item Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of a property allowed in Charge Plans.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.851 CHARGEPLAN-274

Message

```
The Response Charged Item Mapping does not contain the entry
"{missingChargedItemMappingEntryName}".
This entry has no value or the value is not applicable in this context in the
Charged Item
Class "{chargedItemClassName}".
```

Legend

- `{missingChargedItemMappingEntryName}`: The name of the missing entry in the Response Charged Item Mapping
- `{chargedItemClassName}`: The name of the Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the missing entry in the Charged Item Mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.852 CHARGEPLAN-275

Message

```
The service name "{serviceName}" of the User Technical Identifier Reference
at index {userTechnicalIdentifierReferenceIndex} is reserved for internal use.
```

Legend

- `{serviceName}`: The name of the service, as provided
- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference within the charge plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the service name to a value that is not reserved for internal use.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.853 CHARGEPLAN-276

Message

```
The reporting scope "session" cannot be used in a dependent charge plan item.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the reporting scope "session" from the charge plan item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 Patch Level 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.854 CHARGEPLAN-277

Message

```
The currency Parameter Reference "{parameterReferenceName}" at index
{parameterReferenceIndex} is not necessary because the related Charge Component
"{chargeComponentId}" has a fixed currency.
```

Legend

- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference
- `{chargeComponentId}`: The identifier of the related Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.855 CHARGEPLAN-278

Message

```
The currency Parameter Reference "{parameterReferenceName}" at index
{parameterReferenceIndex} is not necessary because the currency is already
specified in the
list of Parameters or Parameter References.
```

Legend

- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.856 CHARGEPLAN-279

Message

```
The currency Parameter value "{parameterValue}" at index {parameterIndex}
is unknown by the SAP Convergent Charging system.
```

Legend

- `{parameterValue}`: The value of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a valid currency value in the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.857 CHARGEPLAN-280

Message

```
The parameter of the charge plan item cannot reference the mapping table
"{parameterValue}" because this mapping table has an agreement ID.
```

Legend

- `{parameterValue}`: The identifier of the mapping table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a mapping table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.858 CHARGEPLAN-281

Message

```
The parameter "{parameterName}" of the charge plan cannot reference the
mapping table "{parameterValue}" because this mapping table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a mapping table with an agreement ID
- `{parameterValue}`: The identifier of the mapping table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a mapping table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.859 CHARGEPLAN-282

Message

```
The parameter of the charge plan item cannot reference the range table
"{parameterValue}" because this range table has an agreement ID.
```

Legend

- `{parameterValue}`: The identifier of the range table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.860 CHARGEPLAN-283

Message

```
The parameter "{parameterName}" of the charge plan cannot reference the
range table "{parameterValue}" because this range table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a range table with an agreement ID
- `{parameterValue}`: The identifier of the range table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.861 CHARGEPLAN-284

Message

```
The type of the account assignment "{accountAssignmentName}" at index
{accountAssignmentIndex} must not be prepaid because the Prepaid Accounts
Management feature
is disabled.
```

Legend

- `{accountAssignmentName}`: The name of the account assignment
- `{accountAssignmentIndex}`: The index of the account assignment

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the account assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.862 CHARGEPLAN-285

Message

```
The property "{propertyName}" specified in the charged item mapping entry
"{chargedItemMappingEntryName}" is invalid because the Prepaid Accounts
```

```
Management feature
is disabled.
```

Legend

- `{propertyName}`: The name of the invalid property
- `{chargedItemMappingEntryName}`: The name of the charged item mapping entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a valid property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.863 CHARGEPLAN-286

Message

```
You cannot set ManagedByCockpit to true in charge plan "{chargePlanId}".
```

Legend

- `{chargePlanId}`: The ID of the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.864 CHARGEPLAN-287

Message

```
The charge component referenced by the charge plan item "{chargePlanItemId}"
at index {chargePlanItemIndex} has the flag ManagedByCockpit set to
"{isChargeComponentCockpitCompatible}"
```

```
whereas the charge plan has the same flag set to
"{isChargePlanCockpitCompatible}".
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item
- `{isChargeComponentCockpitCompatible}`: The value of the attribute ManagedByCockpit in the charge component
- `{isChargePlanCockpitCompatible}`: The value of the attribute ManagedByCockpit in the charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add charge components where ManagedByCockpit has the same value as the charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2020 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.865 CHARGEPLAN-288

Message

```
The charge component referenced by the charge plan item "{chargePlanItemId}"
at index {chargePlanItemIndex} is already referenced by the charge plan
"referencingChargePlanId".
```

Legend

- `{chargePlanItemId}`: The ID of the charge plan item
- `{chargePlanItemIndex}`: The index of the charge plan item
- `{referencingChargePlanId}`: The ID of the charge plan which references the charge component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a charge component which is not already referenced by a charge plan item of another charge plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2020 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.866 CHARGEPLAN-289

Message

```
The parameter "{parameterName}" at index "{parameterIndex}" must be modifiable
due to its charge plan visibility.
```

Legend

- `{parameterName}`: The name of the parameter
- `{parameterIndex}`: The index of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the visibility level of the parameter.

Save your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.867 CHARGEPLAN-290

Message

```
The parameter "{parameterName}" at index "{parameterIndex}" must be modifiable
because it has a value and a charge plan class visibility.
```

Legend

- `{parameterName}`: The name of the parameter
- `{parameterIndex}`: The index of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the visibility level of the parameter.

Save your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.868 CHARGEPLAN-291

Message

```
A charge plan managed by Cockpit cannot be converted to a charge plan managed
by Core Tool because it references Pricing Functions.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use Cockpit user interface to edit the charge plan.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.869 CHARGINGPLAN-1

Message

```
Rate operation failed for usage rate "{usageRateName}".
```

Legend

- `{usageRateName}`: The name of the usage rate

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the usage rate component, or one of its children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.870 CHARGINGPLAN-2

Message

```
Rate operation failed for recurring rate "{recurringRateName}".
```

Legend

- `{recurringRateName}`: The name of the recurring rate

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the recurring rate component, or one of its children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.871 CHARGINGPLAN-3

Message

```
Rate operation failed for oneshot rate "{oneshotRateName}".
```

Legend

- `{oneshotRateName}`: The name of the oneshot rate

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the oneshot rate component, or one of its children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.872 CHARGINGPLAN-4

Message

```
Charge operation failed for usage charge "{usageChargeName}".
```

Legend

- `{usageChargeName}`: The name of the usage charge

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the usage charge component, or one of its children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.873 CHARGINGPLAN-5

Message

```
Charge operation failed for recurring charge "{recurringChargeName}".
```

Legend

- `{recurringChargeName}`: The name of the recurring charge

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the recurring charge component, or one of its children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.874 CHARGINGPLAN-6

Message

```
Charge operation failed for oneshot charge "{oneshotChargeName}".
```

Legend

- `{oneshotChargeName}`: The name of the oneshot charge

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the oneshot charge component, or one of its children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.875 CHARGINGPLAN-7

Message

```
Rating failure in price plan "{pricePlanName}".
```

Legend

- `{pricePlanName}`: The name of the price plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the price plan or one of its children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.876 CHARGINGPLAN-8

Message

```
Rating failure in charge activation "{chargeActivationName}" in charging
contract or subscription "{contractName}".
```

Legend

- `{chargeActivationName}`: The name of the charge activation
- `{contractName}`: The name of the charging contract or subscription

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the price plan or one of its children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.877 CHARGINGPLAN-9

Message

```
Invalid delimitation ''{stringDelimitation}'' used for the conversion from
type String to type Multi-Valued String in component ''{componentName}''.
```

Legend

- `{stringDelimitation}`: string delimitation
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a delimitation character of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.878 CHARGINGPLAN-10

Message

```
Invalid delimitation ''{stringDelimitation}'' used for the conversion from
type String to type Multi-Valued Number in component ''{componentName}''
```

Legend

- `{stringDelimitation}`: string delimitation
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

The string that you define as delimitation to convert String into Multi-Valued Number must respect the following constraints:

- the delimitation string must be exactly one character long
- the delimitation string must be different from the decimal separator
- the delimitation string must be different from the thousand separator

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.879 CHARGINGPLAN-11

Message

```
Invalid decimal separator ''{decimalSeparator}'' used for the conversion from
type String to type Multi-Valued Number in component ''{componentName}''.
```

Legend

- `{decimalSeparator}`: decimal separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a decimal separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.880 CHARGINGPLAN-12

Message

```
Invalid thousand separator ''{thousandSeparator}'' used for the conversion from
type String to type Multi-Valued Number in component ''{componentName}''.
```

Legend

- `{thousandSeparator}`: thousand separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a thousand separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.881 CHARGINGPLAN-13

Message

```
Invalid conversion from type String to type Multi-Valued Number in component
''{componentName}'', the substring ''{subString}'' from the string
''{wholeString}'' cannot
be converted to a number
```

Legend

- `{componentName}`: The component name
- `{subString}`: part of the string to convert
- `{wholeString}`: string to convert

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

The part of the input string to convert must be a number.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.882 CHARGINGPLAN-14

Message

```
Invalid conversion from type String to type Multi-Valued Number in component
''{componentName}'', the substring ''{subString}'' from the string
''{wholeString}'' cannot
be converted to a number
```

Legend

- `{componentName}`: The component name
- `{subString}`: part of the string to convert
- `{wholeString}`: string to convert

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

The part of the input string to convert must be a number.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.883 CHARGINGPLAN-15

Message

```
Invalid delimitation ''{stringDelimitation}'' used for the conversion from
type Multi-Valued String to type String in component ''{componentName}''.
```

Legend

- `{stringDelimitation}`: string delimitation
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a delimitation character of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.884 CHARGINGPLAN-16

Message

```
Invalid decimal separator ''{decimalSeparator}'' used for the conversion
from type Multi-Valued String to type Multi-Valued Number in component
''{componentName}''.
```

Legend

- `{decimalSeparator}`: decimal separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a decimal separator of exactly on character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.885 CHARGINGPLAN-17

Message

```
Invalid thousand separator ''{thousandSeparator}'' used for the conversion
from type Multi-Valued String to type Multi-Valued Number in component
''{componentName}''.
```

Legend

- `{thousandSeparator}`: thousand separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a thousand separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.886 CHARGINGPLAN-18

Message

```
Invalid conversion from type Multi-Valued String to type Multi-Valued Number
in component ''{componentName}'', the field ''{subString}'' cannot be converted
to a number.
```

Legend

- `{componentName}`: The component name
- `{subString}`: part of the string to convert

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Every field of the Multi-Valued String must be convertible to a number.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.887 CHARGINGPLAN-19

Message

```
Invalid delimitation ''{stringDelimitation}'' used for the conversion from
type Multi-Valued Number to type String in component ''{componentName}''.
```

Legend

- `{stringDelimitation}`: The invalid delimitation character
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a delimitation character of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.888 CHARGINGPLAN-20

Message

```
Invalid decimal separator ''{decimalSeparator}'' used for the conversion
from type Multi-Valued Number to type String in component ''{componentName}''.
```

Legend

- `{decimalSeparator}`: The invalid decimal separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a decimal separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.889 CHARGINGPLAN-21

Message

```
Invalid thousand separator ''{thousandSeparator}'' used for the conversion
from type Multi-Valued Number to type String in component ''{componentName}''.
```

Legend

- `{thousandSeparator}`: thousand separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a thousand separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.890 CHARGINGPLAN-22

Message

```
Invalid decimal separator ''{decimalSeparator}'' used for the conversion
from type Multi-Valued Number to type Multi-Valued String in component
''{componentName}''.
```

Legend

- `{decimalSeparator}`: The invalid decimal separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a decimal separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.891 CHARGINGPLAN-23

Message

```
Invalid thousand separator ''{thousandSeparator}'' used for the conversion
from type Multi-Valued Number to type Multi-Valued String in component
''{componentName}''.
```

Legend

- `{thousandSeparator}`: thousand separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a thousand separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.892 CHARGINGPLAN-24

Message

```
Invalid conversion in component ''{componentName}''. The start offset
''{startOffset}'' must be greater than 0. The start offset ''{startOffset}''
must be
lower than or equal to the stop offset value ''{stopOffset}'' plus one, and the
length
''{stringLength}'' of the input string plus one.
```

Legend

- `{componentName}`: The component name
- `{startOffset}`: The start offset
- `{stopOffset}`: The stop offset
- `{stringLength}`: The length of the input string

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the start offset or the stop offset according to those constraints.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.893 CHARGINGPLAN-25

Message

```
Invalid decimal separator ''{decimalSeparator}'' used for the conversion
from type String to type Number in component ''{componentName}''.
```

Legend

- `{decimalSeparator}`: decimal separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a decimal separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.894 CHARGINGPLAN-26

Message

```
Invalid thousand separator ''{thousandSeparator}'' used for the conversion
from type String to type Number in component ''{componentName}''.
```

Legend

- `{thousandSeparator}`: The invalid thousand separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a thousand separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.895 CHARGINGPLAN-27

Message

```
Invalid conversion from type String to type Number in component
''{componentName}'',
    the string ''{stringToConvert}'' cannot be converted to a number
```

Legend

- `{componentName}`: The component name
- `{stringToConvert}`: The string

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.896 CHARGINGPLAN-28

Message

```
Invalid conversion from type String to type Date in component
''{componentName}'',
the string ''{stringToConvert}'' cannot be converted to a date
```

Legend

- `{componentName}`: The component name
- `{stringToConvert}`: The string

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.897 CHARGINGPLAN-29

Message

```
Invalid decimal separator ''{decimalSeparator}'' used for the conversion
from type Number in component ''{componentName}''.
```

Legend

- `{decimalSeparator}`: The invalid decimal separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a decimal separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.898 CHARGINGPLAN-30

Message

```
Invalid thousand separator ''{thousandSeparator}'' used for the conversion
from type Number in component ''{componentName}''.
```

Legend

- `{thousandSeparator}`: The invalid thousand separator
- `{componentName}`: The component name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define a thousand separator of exactly one character long.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.899 CHARGINGPLAN-31

Message

```
Invalid conversion from type Date to type String in component
''{componentName}'',
the date ''{dateToConvert}'' cannot be converted to a string
```

Legend

- `{componentName}`: The component name
- `{dateToConvert}`: The date

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.900 CHARGINGPLAN-32

Message

```
Invalid conversion from type Multi-Valued String in component
''{componentName}''.
The start offset ''{startOffset}'' and the stop offset ''{stopOffset}'' must be
greater than 0.
The start offset ''{startOffset}'' must be lower than or equals to the stop
offset value
''{stopOffset}'' plus one, and the length ''{stringLength}'' of the input sub-
string plus one.
```

Legend

- `{componentName}`: The component name
- `{startOffset}`: The start offset
- `{stopOffset}`: The stop offset
- `{stringLength}`: The length of the input sub-string

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the start offset or the stop offset according to those constraints.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.901 CHARGINGPLAN-33

Message

```
Rating operation failed for Account Event Refill rate component
"{accountEventRefillRateName}".
```

Legend

- `{accountEventRefillRateName}`: The name of the accountEventRefill rate

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the Account Event Refill rate component, or one of its children.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.902 CHARGINGPLAN-34

Message

```
The date "{toDate}" specified for an activation or a charging operation
is too far in the future considering the value of the parameter
PERIOD_LIMIT_ACTIVATION
("{periodLimitActivation}") and the current system date.
```

Legend

- `{toDate}`: The consumption date or the date at which the activation process is run
- `{periodLimitActivation}`: The runtime value of the parameter PERIOD_LIMIT_ACTIVATION

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the business operation requests, change the activation date or the consumption date to a date before the period limit. Verify if the value of the parameter PERIOD_LIMIT_ACTIVATION is correct depending on the business requirements.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP09 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.903 CHARGINGPLAN-35

Message

```
The technical configuration of the shared allowances feature is not complete.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a positive value for the following parameters: DISTRIBUTED_COUNTER_RESERVATION_POOL_SIZE, DISTRIBUTED_COUNTER_CLEANUP_POOL_SIZE and DISTRIBUTED_COUNTER_CHECK_POOL_SIZE

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.904 CICLASS-1

Message

```
The chargeable item class is missing in the create operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a chargeable item class to the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.905 CICLASS-2

Message

```
The product identifier of the chargeable item class must be null in the
create operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the product identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.906 CICLASS-3

Message

```
The id of the chargeable item class is missing in the create operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an id to the chargeable item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.907 CICLASS-4

Message

```
The service provider of the chargeable item class "{chargeableItemClassId}"
is missing.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the service provider to the chargeable item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.908 CICLASS-5

Message

```
In the chargeable item class "{chargeableItemClassId}", the name of the
property at index {propertyIndex} is missing.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{propertyIndex}`: The index of the property in the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.909 CICLASS-6

Message

```
In the chargeable item class "{chargeableItemClassId}", the name "{counterName}"
of the property at index {secondIndex} is already used at index {firstIndex}.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{counterNamecounterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Counters
- `{firstIndex}`: The index of the first occurrence of the name in Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.910 CICLASS-7

Message

```
Impossible to create the chargeable item class because its id
{chargeableItemClassId}
already exists.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the chargeable item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.911 CICLASS-8

Message

```
The id of the chargeable item class "{chargeableItemClassId}" and the
service provider "{serviceProviderId}" are both provided, but they are mutually
exclusive.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{serviceProviderId}`: The service provider of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the ID or the service provider from the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.912 CICLASS-9

Message

```
The service provider "{serviceProviderId}" and the product ID "{productId}"
of the chargeable item class are both provided, but they are mutually exclusive.
```

Legend

- `{serviceProviderId}`: The service provider of the chargeable item class
- `{productId}`: The product ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the product ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.913 CICLASS-10

Message

```
The chargeable item class is missing in the modify operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a chargeable item class to the modify operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.914 CICLASS-11

Message

```
The chargeable item class with the id {chargeableItemClassId} in the modify
operation does not exist.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the chargeable item class to an existing one or create the chargeable item class first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.915 CICLASS-12

Message

```
The chargeable item class with the id {chargeableItemClassId} and product
id {productId} does not exist.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{productId}`: The product ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the chargeable item class or the product ID to an existing one or remove the product ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.916 CICLASS-13

Message

```
Impossible to modify the chargeable item class because the specified service
provider {specifiedServiceProviderId} does not correspond to the service
provider
{realServiceProviderId} existing in the chargeable item class.
```

Legend

- `{specifiedServiceProviderId}`: The specified service provider in the chargeable item class of the operation
- `{realServiceProviderId}`: The service provider existing in the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the service provider to the one of the chargeable item class or create a new chargeable item class for the specified service provider.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.917 CICLASS-14

Message

```
Impossible to modify the chargeable item class {chargeableItemClassId}
because the type of the property {propertyName} is {specifiedPropertyType} in
the database
while the server has received the type {realPropertyType} in the operation.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{propertyName}`: The property name in the chargeable item class
- `{specifiedPropertyType}`: The specified type in the property of the operation
- `{realPropertyType}`: The type existing in the property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.918 CICLASS-15

Message

```
Impossible to modify the chargeable item class {chargeableItemClassId}
because the following properties are missing: {missingPropertyName}.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{missingPropertyName}`: The name of the missing properties in the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the missing properties to the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.919 CICLASS-16

Message

```
The id of chargeable item class is missing in the delete operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the chargeable item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.920 CICLASS-17

Message

```
The chargeable item class with the id {chargeableItemClassId} in the delete
operation does not exist.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the chargeable item class to an existing one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.921 CICLASS-18

Message

```
The chargeable item class with the id {chargeableItemClassId} is still
referenced in following charges: {referrencedChargeIds}.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{referrencedChargeIds}`: The `CSV` list of charge ID still refer the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete the referenced charges first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.922 CICLASS-19

Message

```
The chargeable item class with the id {chargeableItemClassId} and product
id {productId} in the delete operation does not exist.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{productId}`: The product ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID or the product ID of the chargeable item class to an existing one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.923 CICLASS-20

Message

```
The chargeable item class with the id {chargeableItemClassId} and product
id {productId} is still referenced in the following charges: {referredChargeIds}.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{productId}`: The product ID of the chargeable item class
- `{productId}`: The `CSV` list of charge ID still refer to the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete the referenced charges first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.924 CICLASS-21

Message

```
The chargeable item class with the id {chargeableItemClassId} is still
referenced in the following exportable item mappings:
{exportableItemMappingCodes}.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class
- `{exportableItemMappingCodes}`: The CSV list of exportable item mapping codes still refer to the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete the referenced exportable item mappings first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.925 CICLASS-22

Message

```
The chargeable item class with the id {chargeableItemClassId} is still
referenced by at least one data file.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Trigger the processing of the data files by the bulk loader instances first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.926 CICLASS-23

Message

```
The bulk loader instances cannot be contacted to check if data files still
reference the chargeable item class with the id {chargeableItemClassId}.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the bulkloader instances are running.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.927 CICLASS-24

Message

```
The old product identifier of the chargeable item class must be null in
the create and modify operations.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the old product identifier of the chargeable item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.928 CICLASS-25

Message

```
The old identifier of the chargeable item class must be null in the create
and modify operations.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the old identifier of the chargeable item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.929 CICLASS-26

Message

```
The chargeable item class identifier {chargeableItemClassId} is reserved for
internal use.
```

Legend

- `{chargeableItemClassId}`: The ID of the chargeable item class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the identifier of the chargeable item class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.930 CONTRACT-1

Message

```
The date is missing in the create contract operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.931 CONTRACT-2

Message

```
The charging contract is missing in the create contract operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a contract data object in the operation request. The charging contract is the charging view of a provider contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.932 CONTRACT-3

Message

```
The ID of the contract is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a contract identifier to the contract object in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.933 CONTRACT-4

Message

```
The subscriber account ID of the contract is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a subscriber account identifier in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.934 CONTRACT-5

Message

```
The name of the service provider who has delivered the provider contract is
missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the name of the service provider in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.935 CONTRACT-6

Message

```
The subscriber ID "{subscriberId}" defined in the provider contract does
not exist for the service provider "{serviceProvider}".
```

Legend

- `{subscriberId}`: The subscriber ID
- `{serviceProvider}`: The name of the service provider

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber ID to an existing one or create the subscriber ID for the given service provider.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.936 CONTRACT-7

Message

```
Impossible to create the provider contract because its ID already exists:
{chargingContractId}.
```

Legend

- `{chargingContractId}`: The ID of the provider contract that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the provider contract in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.937 CONTRACT-8

Message

```
The date is missing in the modify provider contract operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a date in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.938 CONTRACT-9

Message

```
The provider contract is missing in the modify provider contract operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a provider contract in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.939 CONTRACT-10

Message

```
The charging contract with the ID {chargingContractId} does not exist.
```

Legend

- `{chargingContractId}`: The ID of the provider contract which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the contract to an existing one or create the provider contract first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.940 CONTRACT-11

Message

```
Internal SAP CC system error: Impossible to modify the contract because
the related subscriber account is not found.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.941 CONTRACT-12

Message

```
Impossible to modify the contract because the subscriber ID
{specifiedSubscriberAccountId}
specified in the operation does not correspond to the subscriber ID
{realSubscriberAccountId}
which already exists in the provider contract.
```

Legend

- `{specifiedSubscriberAccountId}`: The subscriber ID specified in the operation
- `{realSubscriberAccountId}`: The subscriber ID which already exists in the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber ID to the existing one {1} or create a new provider contract for the specified subscriber ID {0}.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.942 CONTRACT-13

Message

```
Impossible to modify the provider contract because the subscriber account
service provider name {specifiedSubscriberAccountServiceProviderName} specified
in the
operation does not correspond to the subscriber account service provider name
{realSubscriberAccountServiceProviderName} which already exists in the provider
contract.
```

Legend

- `{specifiedSubscriberAccountServiceProviderName}`: The subscriber account service provider name specified in the operation
- `{realSubscriberAccountServiceProviderName}`: The subscriber account service provider name which already exists in the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber account service provider name to the existing one {1} or create a new provider contract for the specified subscriber account service provider name {0}.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.943 CONTRACT-14

Message

```
The ID is missing in the delete contract operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a contract ID in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.944 CONTRACT-15

Message

```
The provider contract with the ID {chargingContractId} does not exist.
```

Legend

- `{chargingContractId}`: The ID of the provider contract which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the provider contract to an existing one or create the provider contract first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.945 CONTRACT-16

Message

```
Internal SAP CC system error. Impossible to delete the contract because
its subscriber account is not found.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.946 CONTRACT-17

Message

```
Error while validating the provider contract "{chargingContractId}".
```

Legend

- `{chargingContractId}`: The ID of the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.947 CONTRACT-18

Message

```
The ID of the contract item at index {chargingContractItemIndex} is missing.
```

Legend

- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.948 CONTRACT-19

Message

```
The ID "{chargingContractItemId}" of the contract item at index {secondIndex}
is already used by the contract item at index {firstIndex}. Two contract items
cannot have
the same identifier.
```

Legend

- `{chargingContractItemId}`: The duplicated ID
- `{secondIndex}`: The index of the second occurrence of the ID within contract items
- `{firstIndex}`: The index of the first occurrence of the ID within contract items

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.949 CONTRACT-20

Message

```
The chargePlanClassId, the refillPlanClassId or the monitoringPlanClassId
of the contract item "{chargingContractItemId}" at index
{chargingContractItemIndex} is missing.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a chargePlanClassId, a refillPlanClassId or a monitoringPlanClassId to the contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.950 CONTRACT-21

Message

```
The charge plan class "{chargePlanClassId}" referred by the contract item
"{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.
```

Legend

- `{chargePlanClassId}`: The ID of the charge plan class
- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another identifier of a charge plan class that exists.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.951 CONTRACT-22

Message

```
The chargePlanClassId retrieved from the previous contract item
"{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Clearly set the chargePlanClassId in the contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.952 CONTRACT-23

Message

```
The Charge Plan Class referred by the contract item "{chargingContractItemId}"
at index {chargingContractItemIndex} is unknown.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the chargePlanClassId to an existing Charge Plan Class identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.953 CONTRACT-24

Message

```
Error while validating the contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.954 CONTRACT-25

Message

```
The name of the User Technical Identifier at index {userTechIdIndex} is
missing.
```

Legend

- `{userTechIdIndex}`: The index of the User Technical Identifier within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the User Technical Identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.955 CONTRACT-26

Message

```
Impossible to create the linked contract because its parent contract
"{chargingContractId}" does not exist.
```

Legend

- `{chargingContractId}`: The ID of a parent contract that does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the parent contract or first create a new contract with this identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.956 CONTRACT-27

Message

```
The User Technical Identifier "{userTechIdName}" at index {userTechIdIndex}
does not exist in the referred charge plan class "{chargePlanClassId}".
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{userTechIdIndex}`: The index of the User Technical Identifier
- `{chargePlanClassId}`: The ID of the referred charge plan class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the User Technical Identifier or change its name to a User Technical Identifier which exists in the charge plan class

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.957 CONTRACT-28

Message

```
Impossible to modify the linked contract because the parent contract ID
{specifiedchargingContractId} specified in the operation request does not
correspond to the
```

```
parent contract ID {realchargingContractId} which already exists in the linked
contract.
```

Legend

- `{specifiedchargingContractId}`: The provider contract ID specified in the operation
- `{realchargingContractId}`: The provider contract ID which already exists in the linked provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the provider contract ID to the existing one {1}.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.958 CONTRACT-29

Message

```
The User Service Identifier (USID) of the user technical identifier
"{userTechIdName}" at index {userTechIdIndex} is empty.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{userTechIdIndex}`: The index of the User Technical Identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the user service identifier or remove this empty user technical identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.959 CONTRACT-30 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The User Technical Identifier "{userTechIdName}" of the referred charge plan
class "{chargePlanClassId}" is not declared in the contract item.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{chargePlanClassId}`: The ID of the referred Charge Plan Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the User Technical Identifier or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.960 CONTRACT-31

Message

```
The charge plan class "{chargePlanClassId}" referred by the contract item
"{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.
```

Legend

- `{chargePlanClassId}`: The ID of the Charge Plan Class
- `{chargingContractItemId}`: The ID of the contract item

- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the chargePlanClassId to an existing charge plan class identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.961 CONTRACT-32

Message

```
Internal SAP CC system error. Impossible to modify the provider contract
because the contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}
is not found.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.962 CONTRACT-33

Message

```
The name of the Account Assignment at index {accountAssignmentIndex} is missing.
```

Legend

- `{accountAssignmentIndex}`: The index of the Account Assignment within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.963 CONTRACT-34

Message

```
The name "{accountAssignmentName}" of the Account Assignment at index
{secondIndex}
is already used by the Account Assignment at index {firstIndex}.
```

Legend

- `{accountAssignmentName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Account Assignments
- `{firstIndex}`: The index of the first occurrence of the name within Account Assignments

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.964 CONTRACT-35

Message

```
The Account Assignment "{accountAssignmentName}" at index
{accountAssignmentIndex}
does not exist in the referred charge plan class "{chargePlanClassId}".
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{accountAssignmentIndex}`: The index of the Account Assignment
- `{chargePlanClassId}`: The identifier of the referred charge plan class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the Account Assignment or give the name of an Account Assignment which already exists in the charge plan class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.965 CONTRACT-36

Message

```
Internal server error. Impossible to delete the provider contract
"{chargingContractId}"
because it has, at least, one provider contract linked to it.
```

Legend

- `{chargingContractId}`: The ID of the provider contract that cannot be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete the linked provider contract(s) first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.966 CONTRACT-37

Message

```
Impossible to create the linked contract because the parent contract ID
{chargingContractId} specified in the operation request actually matches a
linked contract.
```

Legend

- `{chargingContractId}`: The specified contract ID that corresponds to a linked contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another parent contract in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.967 CONTRACT-38

Message

```
The account ID of the Account Assignment at index {accountAssignmentIndex}
is missing.
```

Legend

- `{accountAssignmentIndex}`: The index of the Account Assignment within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an account ID to the Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.968 CONTRACT-39

Message

```
The Account Assignment "{accountAssignmentName}" of the referred Charge Plan
Class "{chargePlanClassId}" is not declared in the contract item.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{chargePlanClassId}`: The identifier of the referred Charge Plan Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Account Assignment or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.969 CONTRACT-40 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The name of the Additional Information at index {additionalInformationIndex} is
missing.
```

Legend

- `{additionalInformationIndex}`: The index of the Additional Information within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.970 CONTRACT-41 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The name "{additionalInformationName}" of the Additional Information at index
{secondIndex} is already used by the Additional Information at index
{firstIndex}.
```

Legend

- `{additionalInformationIndex}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Additional Informations
- `{firstIndex}`: The index of the first occurrence of the name within Additional Informations

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.971 CONTRACT-42 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The type of the Additional Information "{additionalInformationName}" at
index {additionalInformationIndex} is missing or unknown. The supported types
```

```
are: String,
number, and date.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Additional Information or change it to a valid type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.972 CONTRACT-43 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The date value of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date value to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.973 CONTRACT-44 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The number value of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.974 CONTRACT-45 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The string value of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.975 CONTRACT-46 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The type "{additionalInformationType}" of the Additional Information
"{additionalInformationName}" at index {additionalInformationIndex} is
unsupported.
The supported types are: String, number, and date.
```

Legend

- `{additionalInformationType}`: The unsupported type of the Additional Information
- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a valid type (string, number, date) for the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.976 CONTRACT-47

Message

```
The name of the Parameter at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter within the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.977 CONTRACT-48

Message

```
The name "{parameterName}" of the Parameter at index {secondIndex} is
already used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterName}`: The duplicated name
- `{secondIndexsecondIndex}`: The index of the second occurrence of the name within Parameters
- `{firstIndex}`: The index of the first occurrence of the name within Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.978 CONTRACT-49

Message

```
The Parameter "{parameterName}" at index {parameterIndex} does not exist
in the referred Charge Plan Class "{chargePlanClassId}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{chargePlanClassId}`: The identifier of the referred Charge Plan Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the Parameter or change its name to a Parameter which exists in the Charge Plan Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.979 CONTRACT-50

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex} is
missing or unknown. The supported types are: String, number, date, currency.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter or change it to a supported one: string, number, date, or currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.980 CONTRACT-51

Message

```
The type "{parameterType}" of the Parameter "{parameterName}" at index
{parameterIndex} is incompatible with the type of the referred Parameter
({chargePlanClassParameterType}) in the Charge Plan Class "{chargePlanClassId}".
```

Legend

- `{parameterTypeparameterType}`: The type of the Parameter
- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{chargePlanClassParameterType}`: The type of the Parameter in the Charge Plan Class
- `{chargePlanClassId}`: The identifier of the referred Charge Plan Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the Parameter type to the type of the Parameter in the Charge Plan Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.981 CONTRACT-52

Message

```
The date value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.982 CONTRACT-53

Message

```
The number value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.983 CONTRACT-54

Message

```
The string value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.984 CONTRACT-55

Message

```
The type "{parameterType}" of the Parameter "{parameterName}" at index
{parameterIndex} is unsupported. The supported types are: String, number, date,
and currency.
```

Legend

- `{parameterType}`: The unsupported type of the Parameter
- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date, currency) for the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.985 CONTRACT-56

Message

```
The mandatory parameter "{parameterName}" of the referred Charge Plan Class
"{chargePlanClassId}" is not declared in the contract item.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{chargePlanClassId}`: The identifier of the referred Charge Plan Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the missing mandatory Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.986 CONTRACT-57

Message

```
The contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}
is already referencing the Charge Plan Class "{originalChargePlanClassId}" and
cannot reference
the Charge Plan Class "{newChargePlanClassId}" at the same time.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract
- `{originalChargePlanClassId}`: The ID of the Charge Plan Class which is already referenced by the contract item
- `{newChargePlanClassId}`: The ID of the Charge Plan Class to be referenced

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the Charge Plan Class which is already referenced by the contract item or create a new contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.987 CONTRACT-58

Message

```
The access (user "{user}" / service "{service}") cannot be created because
it already exists.
```

Legend

- `{user}`: The user access
- `{service}`: The service access

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the access.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.988 CONTRACT-59

Message

```
The end date {endDate} declared in the contract item "{chargingContractItemId}"
at index {chargingContractItemIndex} is before or equal to the operation date
{operationDate}.
```

Legend

- `{endDate}`: The end date of the contract item
- `{chargingContractItemId}`: The contract item identifier
- `{chargingContractItemIndex}`: The contract item index
- `{operationDate}`: The provider contract operation date

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the end date to a date strictly after the operation date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.989 CONTRACT-60

Message

```
The Refill Plan Class "{refillPlanClassId}" referred by the contract item
"{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.
```

Legend

- `{refillPlanClassId}`: The ID of the Refill Plan Class
- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the refillPlanClassId to an existing Refill Plan Class identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.990 CONTRACT-61

Message

```
The Refill Plan Class "{refillPlanClassId}" referred by the contract item
"{refillPlanClassId}" at index {chargingContractItemIndex} is unknown.
```

Legend

- `{refillPlanClassId}`: The ID of the Refill Plan Class
- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the refillPlanClassId to an existing Refill Plan Class identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.991 CONTRACT-62

Message

```
Internal server error. Impossible to modify the provider contract because
the contract item "{chargingContractItemId}" at index
{chargingContractItemIndex} is not found on the server.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.992 CONTRACT-63

Message

```
The contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}
is already referencing the Refill Plan Class "{originalRefillPlanClassId}" and
cannot reference
the Refill Plan Class "{newRefillPlanClassId}" at the same time.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract
- `{originalRefillPlanClassId}`: The ID of the Refill Plan Class which is already referenced by the contract item
- `{newRefillPlanClassId}`: The ID of the Refill Plan Class to be referenced

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the Refill Plan Class which is already referenced by the contract item or create a new contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.993 CONTRACT-64

Message

```
Only one of chargePlanClassId, refillPlanClassId and monitoringPlanClassId
can be set in the contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Keep only one of the chargePlanClassId, the refillPlanClassId or the monitoringPlanClassId in the contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.994 CONTRACT-65

Message

```
The name of the shared counter at index {sharedCounterIndex} is missing.
```

Legend

- `{sharedCounterIndex}`: The index of the shared counter within the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the shared counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.995 CONTRACT-66

Message

```
The name "{sharedCounterName}" of the shared counter at index {secondIndex}
is already used by the shared counter at index {firstIndex}.
```

Legend

- `{sharedCounterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within shared counters
- `{firstIndex}`: The index of the first occurrence of the name within shared counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the shared counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.996 CONTRACT-67

Message

```
The shared counter "{sharedCounterName}" at index {sharedCounterIndex}
does not exist in the referred Charge Plan Class "{chargePlanClassId}".
```

Legend

- `{sharedCounterName}`: The name of the shared counter
- `{sharedCounterIndex}`: The index of the shared counter
- `{chargePlanClassId}`: The identifier of the referred Charge Plan Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the shared counter or change its name to a Counter which exists in the Charge Plan Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.997 CONTRACT-68

Message

```
The {accountType} account "{accountId}" is not found.
```

Legend

- `{accountType}`: The identifier of the account type
- `{accountId}`: The identifier of the account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an account identifier that referenced an existing account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.998 CONTRACT-69

Message

```
The currency parameter value "{parameterValue}" at index {parameterIndex}
is unknown by the SAP CC system.
```

Legend

- `{parameterValue}`: The value of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Find a valid currency value using the `exportCurrencies` operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.999 CONTRACT-70

Message

```
The CURRENCY value of the parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a currency value to the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1000 CONTRACT-71

Message

```
Duplicate access for service "{serviceAccess}" and user identifier
"{identifierAccess}"
is defined in provider contract "{chargingContractId}" in contract item
"{firstChargingContractItemId}"
linked to Charge Plan Item "{firstChargePlanItemId}" in Charge Plan
"{firstChargePlanId}"
and in contract item "{secondChargingContractItemId}" linked to Charge Plan Item
"{secondChargePlanItemId}" in charge plan "{secondChargePlanId}".
```

Legend

- `{serviceAccess}`: The service of the duplicate access
- `{identifierAccess}`: The identifier of the duplicate access
- `{chargingContractId}`: The identifier of the contract
- `{firstChargingContractItemId}`: The identifier of the first contract item
- `{firstChargePlanItemId}`: The identifier of the first charge plan item
- `{firstChargePlanId}`: The identifier of the first charge plan
- `{secondChargingContractItemId}`: The identifier of the second contract item
- `{secondChargePlanItemId}`: The identifier of the second charge plan item
- `{secondChargePlanId}`: The identifier of the second charge plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the contract configuration.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1001 CONTRACT-72

Message

```
The contract batch rating group assignment policy is not defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the configuration of the updater BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1002 CONTRACT-73

Message

```
The batch rating group identifier returned by the implementation of the batch
rating group assignment policy is null.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the implementation of the batch rating group assignment policy. The batch rating group assignment policy is defined by the parameter BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1003 CONTRACT-74

Message

```
The code of the batch rating group identifier
"{codeOfBatchRatingGroupIdentifier}"
is unknown.
```

Legend

- `{codeOfBatchRatingGroupIdentifier}`: The code of the batch rating group identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the implementation of the batch rating group assignment policy and the configuration of the batch rating groups. The batch rating group assignment policy is defined by the parameter BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1004 CONTRACT-75

Message

```
The ID of the batch rating group identifier "{idOfBatchRatingGroupIdentifier}"
is unknown.
```

Legend

- `{idOfBatchRatingGroupIdentifier}`: The ID of the batch rating group identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the implementation of the batch rating group assignment policy and the configuration of the batch rating groups. The batch rating group assignment policy is defined by the parameter BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1005 CONTRACT-76

Message

```
The batch rating group assignment policy cannot compute the batch rating group
identifier for the provider contract "{chargingContractId}". The message of the
```

```
exception is
"{batchRatingGroupErrorMessage}".
```

Legend

- `{chargingContractId}`: The ID of the provider contract that needs to be changed
- `{batchRatingGroupErrorMessage}`: The error message returned by the implementation of the batch rating group assignment policy

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the implementation of the batch rating group assignment policy and the configuration of the batch rating groups. The batch rating group assignment policy is defined by the parameter BATCH_RATING_GROUP_ASSIGNMENT_POLICY_CLASS.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1006 CONTRACT-77

Message

```
The User Service Identifier "{userServiceId}" of the User Technical Identifier
Reference at index {userTechnicalIdentifierReferenceIndex} is missing is not
ASCII. Invalid
characters are "{invalidCharacters}".
```

Legend

- `{userServiceId}`: The name of the User Service Identifier, as provided
- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference within the Charge Plan Item
- `{invalidCharacters}`: A `CSV` string of non-ASCII characters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace the invalid characters of User Service Identifier with ASCII characters.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1007 CONTRACT-78

Message

```
The User Service Identifier "{userServiceId}" of the User Technical Identifier
Reference at index {userTechnicalIdentifierReferenceIndex} has more than 128
characters.
```

Legend

- `{userServiceId}`: The name of the User Service Identifier, as provided
- `{codeOfBatchRatingGroupIdentifier}`: The index of the User Technical Identifier Reference within the Charge Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Shorten the service name to 128 ASCII characters.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1008 CONTRACT-79

Message

```
The Parameter "{parameterName}" at index {parameterIndex} points to an unknown
mapping table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1009 CONTRACT-80

Message

```
The Parameter "{parameterName}" at index {parameterIndex} points to a mapping
table "{mappingTableId}" which has an invalid mapping table class
"{mappingTableClass}".
It should be "{parameterMappingTableClass}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{mappingTableId}`: The identifier of the Mapping Table
- `{mappingTableClass}`: The Mapping Table Class of the Mapping Table
- `{parameterMappingTableClass}`: The Mapping Table Class of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter value to a mapping table with the correct mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1010 CONTRACT-81

Message

```
The refill access (Service provider "{serviceProvider}" / Subscriber account
code "{subAccountCode}" / Prepaid account code "{prepaidAccountCode}") cannot be
created
```

```
because it is already assigned between "{assignmentStartDate}" and
"{assignmentEndDate}".
```

Legend

- `{serviceProvider}`: The subscriber account service provider
- `{subAccountCode}`: The subscriber account code
- `{prepaidAccountCode}`: The prepaid account code
- `{assignmentStartDate}`: The assignement start date
- `{assignmentEndDate}`: The assignement end date

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the already assigned prepaid account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1011 CONTRACT-82

Message

```
The access (User Service Identifier "{userServiceId}" / Service Identifier
"{serviceId}") cannot be created because it is already assigned between
"{assignmentStartDate}"
and "{assignmentEndDate}".
```

Legend

- `{userServiceId}`: The access user service ID
- `{serviceId}`: The access service ID
- `{assignmentStartDate}`: The assignement start date
- `{assignmentEndDate}`: The assignement end date

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the already assigned access.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1012 CONTRACT-83

Message

```
The provider contract with the ID {chargingContractId} does not exist.
```

Legend

- `{chargingContractId}`: The ID of the provider contract which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the provider contract to an existing one or create the provider contract first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1013 CONTRACT-84

Message

```
The Account Assignment "{accountAssignmentName}" at index {firstIndex} of type
postpaid is invalid for contract item pointing to a refill plan.
```

Legend

- `{accountAssignmentName}`: The Account Assignment name
- `{firstIndex}`: The index of the first occurrence of the name within Account Assignments

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Assign a Prepaid Account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1014 CONTRACT-85

Message

```
The identification code of the prepaid account currency "{accountCurrencyCode}"
differs from the one of the mono currency refill logic
"{refillLogicCurrencyCode}" for the
provider contract item of ID "{chargingContractItemId}" pointing to a Refill
Plan.
```

Legend

- `{accountCurrencyCode}`: The code of the Prepaid Account Currency
- `{refillLogicCurrencyCode}`: The code of the Refill Logic Currency
- `{chargingContractItemId}`: The ID of the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the currencies of the Prepaid Account and Refill Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1015 CONTRACT-86

Message

```
The status of activated Charge Plan or Refill Plan "{chargePlanId}" is open.
Only released or obsolete Charge Plans and Refill Plans can be activated.
```

Legend

- `{chargePlanId}`: The identifier of the Charge Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the status of activated Charge Plan or Refill Plan to release or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1016 CONTRACT-87

Message

```
The currency "{currencyCode}" of the charge plan parameter "{parameterName}" is
not compatible with any account currency declared in the account assignment list.
```

Legend

- `{currencyCode}`: The code of the currency
- `{parameterName}`: The name of the charge plan parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the currency value of the charge plan parameter or add an account compatible with this currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1017 CONTRACT-88

Message

```
The currency "{currencyCode}" of the charge plan item parameter
"{parameterName}"
is not compatible with any account currency declared in the account assignment
list.
```

Legend

- `{currencyCode}`: The code of the currency
- `{parameterName}`: The name of the charge plan item parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the currency value of the charge plan item parameter or add an account compatible with this currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1018 CONTRACT-89

Message

```
The currency "{currencyCode}" of the provider contract parameter
"{parameterName}"
is not compatible with any account currency declared in the account assignment
list.
```

Legend

- `{currencyCode}`: The code of the currency
- `{parameterName}`: The name of the provider contract parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the currency of the provider contract parameter or add an account compatible with this currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1019 CONTRACT-90

Message

```
The currency "{currencyCode}" of the charge component "{chargeComponentId}"
is not compatible with any account currency declared in the account assignment
list.
```

Legend

- `{currencyCode}`: The code of the currency
- `{chargeComponentId}`: The ID of the charge component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an account compatible with this currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1020 CONTRACT-91

Message

```
The taxation module "{chargePlanItemTaxationModule}" of the charge plan item
"{chargePlanItemId}" is not compatible with the taxation module
"{accountTaxationModule}" of
the account declared in the account assignment list.
```

Legend

- `{chargePlanItemTaxationModule}`: The charge plan item taxation module
- `{chargePlanItemId}`: The ID of the charge plan item
- `{accountTaxationModule}`: The account taxation module

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the taxation module value of the charge plan item or add an account compatible with this taxation module.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1021 CONTRACT-92

Message

```
The Parameter "{parameterName}" at index {parameterIndex} points to an
unknown range table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1022 CONTRACT-93

Message

```
The Parameter "{parameterName}" at index {parameterIndex} points to a range
table "{rangeTableId}" which has an invalid range table class
"{rangeTableClass}". It should
be "{parameterRangeTableClass}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{rangeTableId}`: The identifier of the Range Table
- `{rangeTableClass}`: The Range Table Class of the Range Table
- `{parameterRangeTableClass}`: The Range Table Class of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter value to a range table with the correct range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1023 CONTRACT-94

Message

```
The name of the counter shared with other contracts at index
{pooledCounterIndex}
is missing.
```

Legend

- `{pooledCounterIndex}`: The index of the counter shared with other contracts within the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the counter shared with other contracts.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1024 CONTRACT-95

Message

```
The name "{pooledCounterName}" of the counter shared with other contracts at
index {secondIndex} is already used by the counter at index {firstIndex}.
```

Legend

- `{pooledCounterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within the counter shared with other contracts
- `{firstIndex}`: The index of the first occurrence of the name within the counter shared with other contracts

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the counter shared with other contracts.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1025 CONTRACT-96

Message

```
The shared counter "{pooledCounterName}" at index {pooledCounterIndex} does
not exist in the referred Charge Plan Class "{chargePlanClassId}".
```

Legend

- `{pooledCounterName}`: The name of the counter shared with other contracts
- `{pooledCounterIndex}`: The index of the counter shared with other contracts
- `{chargePlanClassId}`: The identifier of the referred Charge Plan Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the counter shared with other contracts or change its name to a Counter which exists in the Charge Plan Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1026 CONTRACT-97

Message

```
The name "{pooledCounterName}" of the counter at index {secondIndex} is already
used by the shared counter at index {firstIndex}.
```

Legend

- `{pooledCounterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within the counter shared with other contracts
- `{firstIndex}`: The index of the first occurrence of the name within the shared counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1027 CONTRACT-98

Message

```
Impossible to change the provider contract "{chargingContractId}" into a
linked provider contract.
```

Legend

- `{chargingContractId}`: The ID of the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the provider contract ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1028 CONTRACT-99

Message

```
The counter "{pooledCounterName}" at index {firstIndex} cannot be shared
with other contracts because is not declared in the parent contract
"{chargingContractId}".
```

Legend

- `{pooledCounterName}`: The duplicated name

- `{firstIndex}`: The index of the counter name within the counter shared with other contracts
- `{chargingContractId}`: The ID of the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the counter to an existing one or add the counter to the parent contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1029 CONTRACT-101

Message

```
The shared counter "{sharedCounterName}" is already declared as a counter
shared with other contracts in another contract item.
```

Legend

- `{sharedCounterName}`: The duplicated name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the shared counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1030 CONTRACT-102

Message

```
The counter shared with other contracts "{pooledCounterName}" is already
declared as a shared counter in another contract item.
```

Legend

- `{pooledCounterName}`: The duplicated name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the counter shared with other contracts.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1031 CONTRACT-103

Message

```
Impossible to change the linked provider contract "{linkedChargingContractId}"
into a provider contract.
```

Legend

- `{linkedChargingContractId}`: The ID of the linked provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Do not change the existing provider contract ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1032 CONTRACT-104

Message

```
Impossible to modify the provider contract because the counter shared with
other contracts "{pooledCounterName}" is still referenced in the contract item
"{linkedChargingContractItemId}" of the linked provider contract
```

```
"{linkedChargingContractId}"
during the period "{period}".
```

Legend

- `{pooledCounterName}`: The removed counter name
- `{linkedChargingContractItemId}`: The ID of the linked contract item
- `{linkedChargingContractId}`: The ID of the linked provider contract
- `{period}`: The period where the counter is referenced

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the counter shared with other contracts in the linked provider contract first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1033 CONTRACT-105

Message

```
The monitoring plan class "{monitoringPlanClassId}" referred by the contract
item
"{chargingContractItemId}" at index {chargingContractItemIndex} is unknown.
```

Legend

- `{monitoringPlanClassId}`: The ID of the monitoring plan class
- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the monitoringPlanClassId to an existing monitoring plan class identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1034 CONTRACT-106

Message

```
The contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}
already refers to a plan class "{originalPlanClassId}" (type:
{originalPlanClassType}) and
cannot be changed to refer to the monitoring plan class
"{newMonitoringPlanClassId}" at the
same time.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract
- `{originalPlanClassId}`: The ID of the plan class which is already referenced by the contract item
- `{originalPlanClassType}`: The type of the plan class which is already referenced by the contract item
- `{newMonitoringPlanClassId}`: The other ID of a monitoring plan class to be referenced. This ID is specified in the operation request

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1035 CONTRACT-107

Message

```
The contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}
already refers to the monitoring plan class "{originalMonitoringPlanClassId}"
and cannot be
changed to refer to "{newMonitoringPlanClassId}" at the same time.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract
- `{originalMonitoringPlanClassId}`: The ID of the monitoring plan class which is already referenced by the contract item
- `{newMonitoringPlanClassId}`: The other ID of a monitoring plan class to be referenced. This ID is specified in the operation request

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the monitoring plan class which is already referenced by the contract item or create a new contract item. Change the modify operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1036 CONTRACT-108

Message

```
The monitoring plan class "{monitoringPlanClassId}" referred to by the
contract item "{chargingContractItemId}" at index {chargingContractItemIndex} is
unknown.
```

Legend

- `{monitoringPlanClassId}`: The ID of the monitoring plan class
- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the monitoringPlanClassId to an existing monitoring plan class identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1037 CONTRACT-109

Message

```
The User Technical Identifier (UTI) "{userTechIdName}" at index
{userTechIdIndex}
does not exist in the referred monitoring plan class "{monitoringPlanClassId}".
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{userTechIdIndex}`: The index of the User Technical Identifier
- `{monitoringPlanClassId}`: The ID of the referred monitoring plan class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the User Technical Identifier or change its name to a User Technical Identifier which exists in the monitoring plan class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1038 CONTRACT-110

Message

```
The contract item "{chargingContractItemId}" referring to the monitoring
plan class "{monitoringPlanClassId}" contains account assignments.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{monitoringPlanClassId}`: The ID of the referred monitoring plan class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the Account Assignments from the contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1039 CONTRACT-111

Message

```
The status of activated monitoring plan "{monitoringPlanId}" is open.
Only released or obsolete monitoring plans can be activated.
```

Legend

- `{monitoringPlanId}`: The identifier of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the status of activated monitoring plan to release or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1040 CONTRACT-112

Message

```
The contract item "{chargingContractItemId}" referring to the monitoring
plan class "{monitoringPlanClassId}" contains redefinition parameters.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{monitoringPlanClassId}`: The ID of the referred monitoring plan class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the parameters from the contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1041 CONTRACT-113

Message

```
The contract item "{chargingContractItemId}" referring to the monitoring
plan class "{monitoringPlanClassId}" contains pooled counters.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{monitoringPlanClassId}`: The ID of the referred monitoring plan class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the pooled counters from the contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1042 CONTRACT-114

Message

```
Duplicate access for service "{serviceAccess}" and user identifier
"{identifierAccess}" is defined in provider contract "{chargingContractId}" in
contract item
"{firstChargingContractItemId}" linked to monitoring plan
"{firstMonitoringPlanId}" and
in contract item "{secondChargingContractItemId}" linked to monitoring plan
"{secondMonitoringPlanId}".
```

Legend

- `{serviceAccess}`: The service of the duplicate access
- `{identifierAccess}`: The identifier of the duplicate access
- `{chargingContractId}`: The identifier of the contract
- `{firstChargingContractItemId}`: The identifier of the first contract item
- `{firstMonitoringPlanId}`: The identifier of the first monitoring plan
- `{secondChargingContractItemId}`: The identifier of the second contract item

- `{secondMonitoringPlanId}`: The identifier of the second monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the contract configuration.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1043 CONTRACT-115

Message

```
The shared counter "{sharedCounterName}" at index {sharedCounterIndex}
does not exist in the referred monitoring plan class "{monitoringPlanClassId}".
```

Legend

- `{sharedCounterName}`: The name of the shared counter
- `{sharedCounterIndex}`: The index of the shared counter
- `{monitoringPlanClassId}`: The identifier of the referred monitoring plan class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the shared counter or change its name to a Counter which exists in the monitoring plan class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1044 CONTRACT-116

Message

```
At least one counter mapped in the monitoring plan class
"{monitoringPlanClassId}"
is not shared in the contract item "{chargingContractItemId}".
```

Legend

- `{monitoringPlanClassId}`: The ID of the referred monitoring plan class
- `{chargingContractItemId}`: The ID of the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the missing shared counters from the monitoring plan class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1045 CONTRACT-117

Message

```
The spending status "{spendingStatusDescription}" referenced in the contract
item "{chargingContractItemId}" has been already referenced in the contract item
"{alreadyAssignedChargingContractItemId}".
```

Legend

- `{spendingStatusDescription}`: The identifier of the Spending Status Description
- `{chargingContractItemId}`: The ID of the contract item
- `{alreadyAssignedChargingContractItemId}`: The ID of the already assigned contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Refer to a spending status only once in a contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1046 CONTRACT-118

Message

```
The contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}
already refers to a plan class "{originalPlanClassId}" (type:
{originalPlanClassType}) and
cannot be changed to refer to the charge plan class "{newChargePlanClassId}" at
the same time.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract
- `{originalPlanClassId}`: The ID of the plan class which is already referenced by the contract item
- `{originalPlanClassType}`: The type of the plan class which is already referenced by the contract item
- `{newChargePlanClassId}`: The other ID of a charge plan class to be referenced. This ID is specified in the operation request

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1047 CONTRACT-119

Message

```
The contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}
already refers to a plan class "{originalPlanClassId}" (type:
{originalPlanClassType}) and cannot
be changed to refer to the refill plan class "{newRefillPlanClassId}" at the
same time.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract
- `{originalPlanClassId}`: The ID of the plan class which is already referenced by the contract item
- `{originalPlanClassType}`: The type of the plan class which is already referenced by the contract item
- `{newRefillPlanClassId}`: The other ID of a refill plan class to be referenced. This ID is specified in the operation request

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1048 CONTRACT-120

Message

```
The status of the contract item "{chargingContractItemId}" is suspended
with a suspension date/time {suspensionDate}. It is not possible to resume the
contract item
at the date/time {resumptionDate}. The given resumption date/time should be set
after this
suspension date/time.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{suspensionDate}`: The suspension date/time of the contract item in the provider contract
- `{resumptionDate}`: The resumption date/time in the operation request

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the resumption date/time after this suspension date/time.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 Patch Level 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1049 CONTRACT-121

Message

```
The contract item "{chargingContractItemId}" at index
{chargingContractItemIndex}
must not refer to a refill plan because the Prepaid Accounts Management feature
is disabled.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the contract item from the provider contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1050 CONTRACT-122

Message

```
The parameter "{parameterName}" in the contract item "{chargingContractItemId}"
at
index {chargingContractItemIndex} cannot be modified.
```

Legend

- `{parameterName}`: The name of the parameter
- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemIndex}`: The index of the contract item within the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the visibility level of the parameter.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1051 CONTRACTSTATE-1

Message

```
The shared counter "{sharedCounterName}" does not exist in the charging
contract "{chargingContractId}".
```

Legend

- `{sharedCounterName}`: The name of the shared counter to modify
- `{chargingContractId}`: The ID of the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the shared counter to an existing one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1052 CONTRACTSTATE-2

Message

```
The contract item "{chargingContractItemId}" specified in the contract
item state does not exist in the charging contract "{chargingContractId}".
```

Legend

- `{chargingContractItemId}`: The ID of the contract item specified in the operation request
- `{chargingContractId}`: The ID of the provider contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the contract item to an existing contract item (customer master data).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1053 CONTRACTSTATE-3

Message

```
The counter "{counterName}" does not exist in the charge plan "{chargePlanId}"
activated in the contract item "{chargingContractItemId}" specified in the
operation request.
```

Legend

- `{counterName}`: The name of the counter to modify and specified in the operation request
- `{chargePlanId}`: The ID of the charge plan retrieved from the specified contract item
- `{chargingContractItemId}`: The ID of the contract item specified in the operation request

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the counter name to an existing one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1054 CONTRACTSTATE-4

Message

```
The specified charge activation "{chargeActivationId}" does not exist in the
contract item "{chargingContractItemId}" of the charging contract
"{chargingContractId}".
```

Legend

- `{chargeActivationId}`: The ID of the charge activation (or refill activation) specified in the operation request
- `{chargingContractItemId}`: The ID of the contract item specified in the operation request
- `{chargingContractId}`: The ID of the provider contract specified in the operation request

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the charge activation to an existing one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1055 CONTRACTSTATE-5

Message

```
The specified counter "{counterName}" of the charge activation
"{chargeActivationId}"
in the contract item "{chargingContractItemId}" does not exist in the customized
charge
"{chargeComponentId}" or is always redefined.
```

Legend

- `{counterName}`: The name of the counter to modify
- `{chargeActivationId}`: The ID of the charge activation (or refill activation)
- `{chargingContractItemId}`: The ID of the contract item
- `{chargeComponentId}`: The ID of the charge component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the counter name to an existing one and check that the counter is not redefined.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1056 CONTRACTSTATE-6

Message

```
The shared counter "{counterName}" specified in the operation request is
referenced several times.
```

Legend

- `{counterName}`: The name of the counter to modify

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the shared counter name only once in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1057 CONTRACTSTATE-7

Message

```
The specified counter "{counterName}" of the contract item
"{chargingContractItemId}"
is referenced several times.
```

Legend

- `{counterName}`: The name of the counter to modify
- `{chargingContractItemId}`: The ID of the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the counter name only once in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1058 CONTRACTSTATE-8

Message

```
The specified counter "{counterName}" in the charge activation
"{chargeActivationId}"
of the contract item "{chargingContractItemId}" is referenced several times.
```

Legend

- `{counterName}`: The name of the counter to modify
- `{chargeActivationId}`: The ID of the charge activation (or refill activation)
- `{chargingContractItemId}`: The ID of the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the counter name only once in this charge activation in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1059 CONTRACTSTATE-9

Message

```
The specified counter name "{counterName}" is reserved for internal use only.
```

Legend

- `{counterName}`: The name of the counter to modify

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Do not use this counter name in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1060 CONTRACTSTATE-10

Message

```
Cannot change the charging contract "{chargingContractId}". This master data
does not exist.
```

Legend

- `{chargingContractId}`: The ID of the provider contract which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the charging contract to an existing contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1061 CONTRACTSTATE-11

Message

```
Cannot read the charging contract "{chargingContractId}". This master data
does not exist.
```

Legend

- `{chargingContractId}`: The ID of the provider contract which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the charging contract to an existing contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1062 CONTRACTSTATE-12

Message

```
Cannot change the state of the charging contract. The contract item
"{chargingContractItemId}" is referenced several times.
```

Legend

- `{chargingContractItemId}`: The ID of the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify this contract item only once in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1063 CONTRACTSTATE-13

Message

```
Cannot change the state of the charging contract. The charge activation
"{chargeActivationId}" in the contract item "{chargingContractItemId}" is
referenced several times.
```

Legend

- `{chargeActivationId}`: The ID of the charge activation (or refill activation)
- `{chargingContractItemId}`: The ID of the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify this charge activation only once in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1064 CONTRACTSTATE-14

Message

```
The specified LastActivationDate "{lastActivationDate}" in the charge activation
"{chargeActivationId}" of the contract item "{chargingContractItemId}" is
anterior to the
validity start date of the contract item
"{chargingContractItemValidityStartDate}".
```

Legend

- `{lastActivationDate}`: The LastActivationDate of the charge activation (or refill activation)
- `{chargeActivationId}`: The ID of the charge activation (or refill activation)
- `{chargingContractItemId}`: The ID of the contract item
- `{chargingContractItemValidityStartDate}`: The validity start date of the contract item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a LastActivationDate posterior to the validity start date of the contract item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1065 CUSTOMERDATA-1

Message

```
Neither the subscriber account ID or the root charging contract ID is
provided in the request.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a subscriber account ID or at least one root charging contract ID to the export request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1066 CUSTOMERDATA-2

Message

```
The subscriber account with the ID "{subscriberAccountId}" does not exist
in the SAP CC system.
```

Legend

- `{subscriberAccountId}`: The ID of the subscriber account which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber account ID in the export request to an existing one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1067 CUSTOMERDATA-3

Message

```
The root charging contract with the ID "{rootChargingContractId}" does not
exist in the SAP CC system.
```

Legend

- `{rootChargingContractId}`: The ID of the root charging contract which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the root charging contract ID in the export request to an existing one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1068 CUSTOMERDATA-4

Message

```
The contracts to be exported do not belong to the same subscriber account.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

To export several contracts at the same time, choose contracts having the same subscriber account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1069 CUSTOMERDATA-5

Message

```
The root charging contract ID "{rootChargingContractId}" is duplicated
in the export request.
```

Legend

- `{rootChargingContractId}`: The duplicate ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicate ID from the export request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1070 CUSTOMERDATA-6

Message

```
The rootChargingContractId "{chargingContractId}" refers to a linked charging
contract in the SAP CC system.
```

Legend

- `{chargingContractId}`: The ID of the charging contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the rootChargingContractId to a root charging contract ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1071 CUSTOMERDATA-7

Message

```
The external account with the ID "{externalAccountId}" is duplicated in
the import request.
```

Legend

- `{externalAccountId}`: The ID of the duplicate external account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicate external account from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1072 CUSTOMERDATA-8

Message

```
The external account with the ID "{externalAccountId}" does not reference
the subscriber account with the ID "{subscriberAccountId}" specified in the
request.
```

Legend

- `{externalAccountId}`: The ID of the external account
- `{subscriberAccountId}`: The ID of the subscriber account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber account ID or remove the external account from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1073 CUSTOMERDATA-9

Message

```
The prepaid account with the ID "{prepaidAccountId}" is duplicated in the
import request.
```

Legend

- `{prepaidAccountId}`: The ID of the duplicate prepaid account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicate prepaid account from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1074 CUSTOMERDATA-10

Message

```
The prepaid account with the ID "{prepaidAccountId}" does not reference the
subscriber
account with the ID "{subscriberAccountId}" specified in the request.
```

Legend

- `{prepaidAccountId}`: The ID of the prepaid account
- `{subscriberAccountId}`: The ID of the subscriber account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber account ID or remove the prepaid account from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1075 CUSTOMERDATA-11

Message

```
The subscriber mapping table with the ID "{subscriberMappingTableId}" is
duplicated in the import request.
```

Legend

- `{subscriberMappingTableId}`: The ID of the duplicate subscriber mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicate subscriber mapping table from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1076 CUSTOMERDATA-12

Message

```
The subscriber mapping table with the ID "{subscriberMappingTableId}" does not
reference the subscriber account with the ID "{subscriberAccountId}" specified
in the request.
```

Legend

- `{subscriberMappingTableId}`: The ID of the subscriber mapping table
- `{subscriberAccountId}`: The ID of the subscriber account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber account ID or remove the subscriber mapping table from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1077 CUSTOMERDATA-13

Message

```
The subscriber mapping table "{subscriberMappingTableId}" to be imported
already exists in the SAP CC destination system.
```

Legend

- `{subscriberMappingTableId}`: The ID of the subscriber mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

To keep the existing table, remove the table from the import request. To overwrite the existing table, set the onAlreadyExistingTable attribute to "overwrite".

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1078 CUSTOMERDATA-14

Message

```
The subscriber range table with the ID "{subscriberRangeTableId}" is duplicated
in the import request.
```

Legend

- `{subscriberRangeTableId}`: The ID of the duplicate subscriber range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicate subscriber range table from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1079 CUSTOMERDATA-15

Message

```
The subscriber range table with the ID "{subscriberRangeTableId}" does not
reference the subscriber account with the ID "{subscriberAccountId}" specified
in the request.
```

Legend

- `{subscriberRangeTableId}`: The ID of the subscriber range table
- `{subscriberAccountId}`: The ID of the subscriber account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber account ID or remove the subscriber range table from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1080 CUSTOMERDATA-16

Message

```
The subscriber range table "{subscriberRangeTableId}" to be imported already
exists in the SAP CC destination system.
```

Legend

- `{subscriberRangeTableId}`: The ID of the subscriber range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

To keep the existing table, remove the table from the import request. To overwrite the existing table, set the onAlreadyExistingTable attribute to "overwrite".

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1081 CUSTOMERDATA-17

Message

```
The charging contract with the ID "{chargingContractId}" is duplicated in
the import request.
```

Legend

- `{chargingContractId}`: The ID of the duplicate charging contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicate charging contract from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1082 CUSTOMERDATA-18

Message

```
The charging contract with the ID "{chargingContractId}" does not reference
the subscriber account with the ID "{subscriberAccountId}" specified in the
request.
```

Legend

- `{chargingContractId}`: The ID of the charging contract
- `{subscriberAccountId}`: The ID of the subscriber account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber account ID or remove the subscriber range table from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1083 CUSTOMERDATA-19

Message

```
The object with the type "{objectType}" and the ID "{objectId}" does not
reference the subscriber account with the ID "{subscriberAccountId}".
```

Legend

- `{objectType}`: The type of the object
- `{objectId}`: The ID of the object
- `{subscriberAccountId}`: The ID of the subscriber account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the object from the import request and check that all the objects to be imported belong to the same subscriber account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1084 CUSTOMERDATA-20

Message

```
The linked charging contract "{linkedChargingContractId}" to be imported
references the root charging contract "{rootChargingContractId}" which does not
exist in
the SAP CC destination system.
```

Legend

- `{linkedChargingContractId}`: The ID of the linked charging contract
- `{rootChargingContractId}`: The ID of the root charging contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the linked charging contract from the import request or import the root charging contract first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1085 CUSTOMERDATA-21

Message

```
The linked charging contract "{linkedChargingContractId}" to be imported
reference the root charging contract "{rootChargingContractId}" having a
different subscriber
account in the SAP CC destination system.
```

Legend

- `{linkedChargingContractId}`: The ID of the linked charging contract
- `{rootChargingContractId}`: The ID of the root charging contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the linked charging contract from the import request and check that all the objects to be imported belong to the same subscriber account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1086 CUSTOMERDATA-22

Message

```
The subscriber account "{subscriberAccountId}" to be imported already
exists in the SAP CC destination system.
```

Legend

- `{subscriberAccountId}`: The ID of the subscriber account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the subscriber account from the import request or delete the existing one in the SAP CC destination system.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1087 CUSTOMERDATA-23

Message

```
The external account "{externalAccountId}" to be imported already exists
in the SAP CC destination system.
```

Legend

- `{externalAccountId}`: The ID of the external account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the external account from the import request or delete the existing one in the SAP CC destination system.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1088 CUSTOMERDATA-24

Message

```
The prepaid account "{prepaidAccountId}" to be imported already exists
in the SAP CC destination system.
```

Legend

- `{prepaidAccountId}`: The ID of the prepaid account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the prepaid account from the import request or delete the existing one in the SAP CC destination system.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1089 CUSTOMERDATA-25

Message

```
The charging contract "{chargingContractId}" to be imported already exists
in the SAP CC destination system.
```

Legend

- `{chargingContractId}`: The ID of the charging contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the charging contract from the import request or delete the existing one in the SAP CC destination system.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1090 CUSTOMERDATA-26

Message

```
The chargingContractOperationalStatusChangedTo cannot be set to "closed".
Only "active" or "locked" are allowed in the import request.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the chargingContractOperationalStatusChangedTo or set it to an appropriate value: "active" or "locked" (default).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

> See also Deprecated and Revoked Error Codes [page 58].

4.1091 CUSTOMERDATA-27

Message

```
You cannot provide both a subscriber account ID and root charging contract
IDs in the export request.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a subscriber account ID or one or more root charging contract IDs in the export request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1092 CUSTOMERDATA-28

Message

```
The subscriber range table with the ID "{subscriberRangeTableId}" belongs
to another subscriber account in the SAP CC destination system.
```

Legend

- `{subscriberRangeTableId}`: The ID of the duplicate subscriber range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber range table ID. Update the charging contract with the new subscriber range table ID and relaunch the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1093 CUSTOMERDATA-29

Message

```
The subscriber mapping table with the ID "{subscriberMappingTableId}" belongs
to another subscriber account in the SAP CC destination system.
```

Legend

- `{subscriberMappingTableId}`: The ID of the duplicate subscriber mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber mapping table ID. Update the charging contract with the new subscriber mapping table ID and relaunch the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1094 CUSTOMERDATA-30

Message

```
The allowance ID "{allowanceId}" is duplicated in the import request.
```

Legend

- `{allowanceId}`: The duplicate ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicate ID from the import request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1095 CUSTOMERMANAGEMENTAREA-1

Message

```
The name of the customer management area at index {customerManagementAreaIndex}
is missing.
```

Legend

- `{customerManagementAreaIndex}`: The index of the customer management area in the customer management area list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the customer management area.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1096 CUSTOMERMANAGEMENTAREA-2

Message

```
The name of the customer management area at index {customerManagementAreaIndex}
is empty.
```

Legend

- `{customerManagementAreaIndex}`: The index of the customer management area in the customer management area list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the customer management area.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1097 CUSTOMERMANAGEMENTAREA-3

Message

```
The name "{customerManagementAreaName}" of the customer management area at
index {secondIndex} is already used by another customer management area at index
{firstIndex}.
```

Legend

- `{customerManagementAreaName}`: The duplicated customer management area name
- `{secondIndex}`: The index of the second occurrence of the customer management area name in the customer management area list
- `{firstIndex}`: The index of the first occurrence of the customer management area name in the customer management area list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the customer management area.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1098 CUSTOMERMANAGEMENTAREA-4

Message

```
The name of the ERP JCo destination in the customer management area at index
{sapSystemDefinitionIndex} is missing.
```

Legend

- `{sapSystemDefinitionIndex}`: The index of the customer management area definition in the customer management area list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name of ERP JCo destination to the customer management area.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1099 CUSTOMERMANAGEMENTAREA-5

Message

```
The name of the ERP JCo destination in the customer management area at
index {customerManagementAreaIndex} is empty.
```

Legend

- `{customerManagementAreaIndex}`: The index of the customer management area definition in the customer management area list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the ERP JCo destination in the customer management area.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1100 CUSTOMERMANAGEMENTAREA-6

Message

```
The name "{erpJcoDestinationName}" of the ERP JCo destination in the customer
management area at index {customerManagementAreaIndex} matches no existing ERP
JCo destination.
```

Legend

- `{erpJcoDestinationName}`: The name of the ERP JCo destination in the customer management area definition
- `{customerManagementAreaIndex}`: The index of the customer management area in the customer management area list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an existing ERP JCo destination name to the customer management area.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1101 CUSTOMERMANAGEMENTAREA-7

Message

```
The name of the CRM JCo destination in the customer management area at index
{customerManagementAreaIndex} is empty.The name of the CRM JCo destination in
the customer
management area at index {customerManagementAreaIndex} is empty.
```

Legend

- `{customerManagementAreaIndex}`: The index of the customer management area in the customer management area list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the CRM JCo destination in the customer management area.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1102 CUSTOMERMANAGEMENTAREA-8

Message

```
The name "{crmJcoDestinationName}" of the CRM JCo destination in the definition
at index {customerManagementAreaDefinitionIndex} matches no existing CRM JCo
destination.
```

Legend

- `{crmJcoDestinationName}`: The name of the CRM JCo destination in the customer management area
- `{customerManagementAreaDefinitionIndex}`: The index of the customer management area in the customer management area list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an existing CRM JCo destination name to the customer management area.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1103 CUSTOMERMANAGEMENTAREA-9

Message

```
The name of the default customer management area is empty in the customer
management area list.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the default customer management area in the customer management area list.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1104 CUSTOMERMANAGEMENTAREA-10

Message

```
The name "{defaultCustomerManagementAreaName}" of the default customer
management area matches no customer management area name in the customer
management area list.
```

Legend

- `{defaultCustomerManagementAreaName}`: The default customer management area name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid default customer management area or change the name of a customer management area to the default customer management area name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1105 CUSTOMERMANAGEMENTAREA-11

Message

```
The customer management area list is missing in the maintain operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the customer management area list to the maintain operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1106 CUSTOMERMANAGEMENTAREA-12

Message

```
The customer management area "{customerManagementAreaName}" cannot be
removed because it is still used by at least one subscriber account.
```

Legend

- `{customerManagementAreaName}`: The still used customer management area name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete all the subscriber accounts that use this customer management area.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1107 DICTIONARY-1

Message

```
Counter name at index {counterNameIndex} is null.
```

Legend

- `{counterNameIndex}`: The index of the counter name in the dictionary

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a value to that counter name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1108 DICTIONARY-2

Message

```
The name of the counter name at index {counterNameIndex} is missing.
```

Legend

- `{counterNameIndex}`: The index of the counter name in the dictionary

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the counter name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1109 DICTIONARY-3

Message

```
The description of the counter name "{counterName}" at index {counterNameIndex}
is missing.
```

Legend

- `{counterNamecounterName}`: The name of the counter name
- `{counterNameIndex}`: The index of the counter name in the dictionary

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the counter name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1110 DICTIONARY-4

Message

```
The name "{counterName}" of the Counter name at index {secondIndex} is already
used by the Counter name at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name
- `{firstIndex}`: The index of the first occurrence of the name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1111 DICTIONARY-5

Message

```
Error while validating the dictionary of counter names.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1112 DICTIONARY-6

Message

```
The counter name entry "{counterName}" cannot be deleted from the dictionary
because it is still used by charge plans.
```

Legend

- `{counterName}`: The name of the counter that is intended to be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Do not remove this counter name entry or delete charge plans that are referencing it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1113 DICTIONARY-7

Message

```
The counter names dictionary is missing in the modification operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid counter names dictionary in the modification operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1114 DICTIONARY-8

Message

```
The counter name entry "{counterName}" cannot be deleted from the dictionary
because it is still used by monitoring plans.
```

Legend

- `{counterName}`: The name of the counter that is intended to be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Do not remove this counter name entry or delete monitoring plans that are referencing it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1115 HCI-1

Message

```
The name of the Additional Information at index {additionalInformationIndex} is
missing.
```

Legend

- `{additionalInformationIndex}`: The position index of the invalid Additional Information item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the 'Additional Information' item. The message indicates the position of the invalid item: index 1 means first item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1116 HCI-2

Message

```
The name "{additionalInformationName}" of the Additional Information at
index {secondIndex} is already used by the Additional Information at index
{firstIndex}.
```

Legend

- `{additionalInformationName}`: The duplicated name
- `{secondIndex}`: The position index of the second occurrence of the name within Additional Information items
- `{firstIndex}`: The position index of the first occurrence of the name within Additional Information items

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of one Additional Information item or remove the duplicate item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1117 HCI-3

Message

```
The description of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The position index of the Additional Information item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the 'Additional Information' item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1118 HCI-4

Message

```
The type of the Additional Information "{additionalInformationName}" at index
{additionalInformationIndex} is missing or unknown (supported types are string,
number, date).
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The position index of the Additional Information item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Additional Information item or change it to a supported one: string, number, or date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1119 HCI-5

Message

```
The date value of the Additional Information "{additionalInformationName}" at
index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The position index of the Additional Information item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date value to the Additional Information item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1120 HCI-6

Message

```
The number value of the Additional Information "{additionalInformationName}" at
index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The position index of the Additional Information item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the Additional Information item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1121 HCI-7

Message

```
The string value of the Additional Information "{additionalInformationName}" at
index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The position index of the Additional Information item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the Additional Information item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1122 HCI-8

Message

```
The type "{additionalInformationType}" of the Additional Information
"{additionalInformationName}" at index {additionalInformationIndex} is not
supported (supported
types are string, number, date).
```

Legend

- `{additionalInformationType}`: The type of the Additional Information item
- `{additionalInformationName}`: The name of the Additional Information item
- `{additionalInformationIndex}`: The position index of the Additional Information item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a type that is supported (string, number, or date/time) for the Additional Information item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1123 HCI-9

Message

```
The Additional Information item at index {additionalInformationIndex} is empty.
```

Legend

- `{additionalInformationIndex}`: The position index of the empty Additional Information item that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Additional Information item or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1124 HCI-10

Message

```
You must provide at least one object reference for the search object
dependencies
operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an object reference to the search object dependencies operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1125 HCI-11

Message

```
The object reference at index {objectReferenceIndex} has no object identifier.
```

Legend

- `{objectReferenceIndex}`: The index of the object reference that needs an object identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an object identifier to the object reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1126 HCI-12

Message

```
The object reference "{objectReferenceObjectID}" at index {objectReferenceIndex}
has no object type.
```

Legend

- `{objectReferenceObjectID}`: The ID of the object in the object reference
- `{objectReferenceIndex}`: The index of the object reference that needs an object identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an object type to the object reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1127 HCI-13

Message

```
The object reference "{objectReferenceObjectID}" at index {objectReferenceIndex}
has no object type.
```

Legend

- `{objectReferenceObjectID}`: The ID of the object in the object reference
- `{objectReferenceIndex}`: The index of the object reference that needs an object identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an object type to the object reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1128 HCI-14

Message

```
You cannot concurrently set a modification date and a validity date range.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify either the validity date range or the modification date but do not specify both at the same time.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1129 HCI-15

Message

```
The end date {endDate} of the validity date range is before or equal to
the start date {startDate}.
```

Legend

- `{endDate}`: The end date of the validity date range
- `{startDate}`: The start date of the validity date range

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an end date/time after the start date/time.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1130 HCI-16

Message

```
The mandatory filter in the search operation is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter to the search operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1131 HCI-17

Message

```
The search filter {searchFilter} does not know the name of the attribute
description {attributeDescriptionName}.
```

Legend

- `{searchFilter}`: The search filter
- `{attributeDescriptionName}`: The name of the attribute description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a known attribute description name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1132 HCI-18

Message

```
The attribute name {attributeName} cannot be present more than one time in
the attribute result description.
```

Legend

- `{attributeName}`: The name of the attribute in attribute result description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicated attribute name in the attribute result description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1133 HCI-19

Message

```
The search filter {searchFilter} does not know the name of the attribute
result description {attributeName}.
```

Legend

- `{searchFilter}`: The search filter
- `{attributeName}`: The name of the attribute in attribute result description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a known attribute name in the attribute result description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1134 HCI-20

Message

```
The attribute result description can only be used with the result type
'attributes'.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the result type 'attributes' or remove the attribute result descriptions.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1135 HCI-21

Message

```
The constraint of the attribute description {attributeDescriptionName} is null
or invalid.
```

Legend

- `{attributeDescriptionName}`: he name of the attribute description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a not null and well formatted constraint according to the type of the attribute description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1136 HCI-22

Message

```
The object "{objectID}" of type "{objectType}" is invalid.
```

Legend

- `{objectID}`: The ID of the object
- `{objectType}`: The type of the object

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First correct the object according to the other error messages, then perform the import operation again.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1137 HCI-23

Message

```
The object of type "{objectType}" is invalid.
```

Legend

- `{objectType}`: The type of the object

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First correct the object according to the other error messages, then perform the import operation again.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1138 HCI-24

Message

```
The start date of the validity date range cannot be null while the end date
{endDate} is defined in this context.
```

Legend

- `{endDate}`: The end date of the validity date range

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a start date or remove the end date. Specify a start date or remove the end date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1139 HCI-25

Message

```
The login of the user is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a valid user name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 20223 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1140 HCI-26

Message

```
The object access rule is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a valid object access rule.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1141 HCI-27

Message

```
The user {userName} does not exist in the SAP CC system.
```

Legend

- `{userName}`: The user name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the specified user exists, if not, create it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1142 HCI-28

Message

```
The object access rule cannot be created for {userName} because this user does
not
have the role Pricing Specialist - Price Data.
```

Legend

- `{userName}`: The user name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Assign the role Pricig Specialist - Price Data to the user.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1143 HCI-31

Message

```
The object access rule with the additional info name {addInfoName} and the
additional
```

```
info value "{addInfoValue} cannot be created because both must be either null or
not null.
```

Legend

- `{addInfoName}`: The name of the additional information
- `{addInfoValue}`: The value of the additional information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Ensure that de name of the additional information and its value are both defined or both null.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1144 MACROCOMPONENT-1

Message

```
The logic component defines the mapping between a mapping table ID property
"{componentMappedPropertyName}" and a pricing macro "{pricingMacroId}" input
property
"{pricingMacroInputPropertyName}" that is not a mapping table ID property.
```

Legend

- `{componentMappedPropertyName}`: The name of the mapped property
- `{pricingMacroId}`: The ID of the pricing macro
- `{pricingMacroInputPropertyName}`: The name of the pricing macro input property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the mapping to a standard string or change the input property of the pricing macro to a mapping table ID property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1145 MACROCOMPONENT-2

Message

```
The component defines a mapping between a mapping table ID property
"{componentMappedPropertyName}"
and pricing macro "{pricingMacroId}" input property
"{pricingMacroInputPropertyName}" that
do not define the same mapping table class IDs:
"{componentMappedPropertyMappingTableClassId}"
/"{pricingMacroInputPropertyMappingTableClassId}".
```

Legend

- `{componentMappedPropertyName}`: The name of the mapped property
- `{pricingMacroId}`: The ID of the pricing macro
- `{pricingMacroInputPropertyName}`: The name of the pricing macro input property
- `{componentMappedPropertyMappingTableClassId}`: TThe mapping table class ID the pricing macro input property
- `{pricingMacroInputPropertyMappingTableClassId}`: The mapping table class ID of the pricing macro input property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the property mapping table class ID or change the pricing macro input property to the correct mapping table class ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1146 MACROCOMPONENT-3

Message

```
The component defines a mapping between a mapping table key property
"{componentMappedPropertyName}" and a pricing macro "{pricingMacroId}" input
```

```
property
"{pricingMacroInputPropertyName}" that is not a mapping table key property.
```

Legend

- `{componentMappedPropertyName}`: The name of the mapped property
- `{pricingMacroId}`: The ID of the pricing macro
- `{pricingMacroInputPropertyName}`: The name of the pricing macro input property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the mapping to a standard string or change the pricing macro input property to a mapping table key property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1147 MACROCOMPONENT-4

Message

```
The component defines a mapping between a range table ID property
"{componentMappedPropertyName}" and a pricing macro "{pricingMacroId}" input
property
"{pricingMacroInputPropertyName}" that is not a range table ID property.
```

Legend

- `{componentMappedPropertyName}`: The name of the mapped property
- `{pricingMacroId}`: The ID of the pricing macro
- `{pricingMacroInputPropertyName}`: The name of the pricing macro input property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the mapping to a standard string or change the pricing macro input property to a range table ID property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1148 MACROCOMPONENT-5

Message

```
The component defines a mapping between a range table ID property
"{componentMappedPropertyName}" and pricing macro "{pricingMacroId}" input
property
"{pricingMacroInputPropertyName}" that both do not define the same range table
class IDs:
"{componentMappedPropertyRangeTableClassId}"/"{pricingMacroInputPropertyRangeTabl
eClassId}".
```

Legend

- `{componentMappedPropertyName}`: The name of the mapped property
- `{pricingMacroId}`: The ID of the pricing macro
- `{pricingMacroInputPropertyName}`: The name of the pricing macro input property
- `{componentMappedPropertyRangeTableClassId}`: The range table class ID the pricing macro input property
- `{pricingMacroInputPropertyRangeTableClassId}`: The range table class ID of the pricing macro input property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the property range table class ID or change the pricing macro input property to the correct range table class ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1149 MACROCOMPONENT-6

Message

```
The pricing macro "{pricingMacroId}" defines a string property
"{pricingMacroInputPropertyName}" but component mapped property
```

```
"{componentMappedPropertyName}"
is a mapping table ID property.
```

Legend

- `{pricingMacroId}`: The ID of the pricing macro
- `{pricingMacroInputPropertyName}`: The name of the pricing macro input property
- `{componentMappedPropertyName}`: The name of the mapped property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the mapping to a mapping table ID or change the pricing macro input property to a string property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1150 MACROCOMPONENT-7

Message

```
The pricing macro "{pricingMacroId}" defines a string property
"{pricingMacroInputPropertyName}" but component mapped property
"{componentMappedPropertyName}"
is a mapping table key property.
```

Legend

- `{pricingMacroId}`: The ID of the pricing macro
- `{pricingMacroInputPropertyName}`: The name of the pricing macro input property
- `{componentMappedPropertyName}`: The name of the mapped property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the mapping to a mapping table key or change the pricing macro input property to a string property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1151 MACROCOMPONENT-8

Message

```
The pricing macro "{pricingMacroId}" defines a string property
"{pricingMacroInputPropertyName}" but component mapped property
"{componentMappedPropertyName}"
is a range table ID property.
```

Legend

- `{pricingMacroId}`: The ID of the pricing macro
- `{pricingMacroInputPropertyName}`: The name of the pricing macro input property
- `{componentMappedPropertyName}`: The name of the mapped property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the mapping to a range table ID or change the pricing macro input property to a string property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1152 MACROCOMPONENT-9

Message

```
Component "{macroComponent}" calls pricing macro "{pricingMacroId}"
with {actualParameterCount} parameter(s) instead of {expectedParameterCount}.
```

Legend

- `{macroComponent}`: The name of the macro component
- `{pricingMacroId}`: The ID of the pricing macro
- `{actualParameterCount}`: The number of parameters actually specified
- `{expectedParameterCount}`: The number of parameters expected by the macro

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

As of SP 1 patch level 3 for release 5.0, the SAP CC Core Server system performs stricter validations on the SAP CC logic components, each time you modify, import, or transport data objects that include some logic.

This error code is part of these supplementary validations. See SAP Note 2618936 for the latest information.

Next Actions and Steps (Troubleshooting)

Modify the component to pass in the right number of parameters to the macro.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

To facilitate your troubleshooting and provide you with more user guidance, see:

- SAP Note 2618936
- SAP Note 2618936
- PRICING_LOGIC_STRICT_VALIDATION_ENABLED system parameter

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1153 MACROCOMPONENT-10

Message

```
Pricing macro "{pricingMacroId}" is called by component "{macroComponentName}"
but is not defined.
```

Legend

- `{pricingMacroId}`: The ID of the pricing macro
- `{macroComponentName}`: The name of the macro component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the component to call a known macro or create the macro first.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1154 MACROCOMPONENT-11

Message

```
Component "{macroComponent}" calls pricing macro "{pricingMacroId}"
                  with {actualParameterCount} output parameter(s) instead of
{expectedParameterCount}.
```

Legend

- `{macroComponent}`: The name of the macro component
- `{pricingMacroId}`: The ID of the pricing macro
- `{actualParameterCount}`: The number of output parameters actually specified
- `{expectedParameterCount}`: The number of parameters generated by the macro

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

As of SP 1 patch level 3 for release 5.0, the SAP CC Core Server system performs stricter validations on the SAP CC logic components, each time you modify, import, or transport data objects that include some logic.

This error code is part of these supplementary validations. See SAP Note 2618936 for the latest information.

Next Actions and Steps (Troubleshooting)

Modify the component to generate the right number of parameters by the macro.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

To facilitate your troubleshooting and provide you with more user guidance, see:

- SAP Note 2618936
- SAP Note 2618936
- PRICING_LOGIC_STRICT_VALIDATION_ENABLED system parameter

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2022 FPS 0 Patch Level 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1155 MACROCOMPONENT-12

Message

```
Pricing macro "{pricingMacroId}" called by component "{macroComponent}" has the
flag
ManagedByCockpit set to "{isPricingMacroCockpitCompatible}" which is not
compatible.
```

Legend

- `{pricingMacroId}`: The ID of the pricing macro
- `{macroComponent}`: The name of the macro component
- `{isPricingMacroCockpitCompatible}`: The value of the attribute ManagedByCockpit in the Pricing Macro

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the correct user interface.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1156 MAPPINGTABLE-1

Message

```
The mapping table class to create is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a mapping table class to the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1157 MAPPINGTABLE-2

Message

```
The ID of the mapping table class is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an identifier to the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1158 MAPPINGTABLE-3

Message

```
The owner of the mapping table class "{mappingTableClassId}" is missing.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

When configuring a pricing element in a pricing catalog, you set up the **owner information** with the owner information that is already set for the catalog that includes your element (data object).

The service provider company that provides some marketable end-customer services with SAP CC owns such a pricing catalog to monetize the service usage and consumption.

In SAP Convergent Charging, the **catalog owner** is a textual reference to:

- The "contracting" service provider (such as the company name) that want to monetize one or multiple end-customer services

- An end-customer service (such as the service name or a comprehensive abbreviation)
- A bundle of end-customer services (such as the name of this bundle) that can be priced by using some common pricing elements from a unique catalog

The exact meaning depends on your implementation requirements.

> → Tip
>
> When modeling and designing the catalog owner information, use a **combination** of:
>
> - The **company name** of the service provider that you represent
> - The **name of the marketable end-customer service** or the name of a service bundle that must be priced by using the corresponding pricing catalog
>
> For example, configure your system with: *GAFA*, *GAFA Digital Services*, or *GAFA Duo Services*.
>
> Use the same information to rename a pricing catalog and facilitate the maintenance and troubleshooting.
>
> In a training system, SAP CC users can set up the catalog owners by using their user ID or lastname for example.

The SAP CC system uses this technical information to control the master data consistency. A pricing catalog and all its pricing elements must have the same owner information.

> ⓘ Note
>
> The catalog owner is not the SAP CC user who configures a pricing catalog and its elements.

Next Actions and Steps (Troubleshooting)

Add an owner to the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1159 MAPPINGTABLE-4

Message

```
The description of the mapping table class "{mappingTableClassId}" is missing.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1160 MAPPINGTABLE-5

Message

```
The mapping table class "{mappingTableClassId}" must at least declare one
input column.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one input column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1161 MAPPINGTABLE-6 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Replaced by MAPPINGTABLE-232 [page 2199].

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The mapping table class "{mappingTableClassId}" must have less than four
input columns.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete an input column to have 4 input columns maximum.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.1 SP 0.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1162 MAPPINGTABLE-7

Message

```
The mapping table class "{mappingTableClassId}" must at least declare one
output column.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one output column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1163 MAPPINGTABLE-8 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.
>
> Replaced by MAPPINGTABLE-233 [page 2201].

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The mapping table class "{mappingTableClassId}" must have less than 15
output columns.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete output column(s) to have 15 output columns maximum.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.1 SP 0.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1164 MAPPINGTABLE-9

Message

```
The name of the input column at index {inColumnIndex} is missing.
```

Legend

- `{inColumnIndex}`: The index of the input column within the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

This specific error code defines an error cause. It results from a validation failure. Refer to the MAPPINGTABLE-15 [page 2116] error code.

Next Actions and Steps (Troubleshooting)

Add a name to the input column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

SAP Convergent Charging uses this error code to identify an error cause. It refers to the validation error MAPPINGTABLE-15 [page 2116]

View **similar causes**:

- MAPPINGTABLE-11 [page 2110]
- MAPPINGTABLE-12 [page 2112]
- MAPPINGTABLE-17 [page 2119]
- MAPPINGTABLE-18 [page 2121]

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1165 MAPPINGTABLE-10

Message

```
The type of the input column at index {inColumnIndex} is missing.
```

Legend

- `{inColumnIndex}`: The index of the input column within the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the input column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1166 MAPPINGTABLE-11

Message

```
The column name "{columnName}" already exists in the mapping table class.
```

Legend

- `{inColumnIndex}`: The duplicated name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

This specific error code defines an error cause. It results from a validation failure. Refer to the MAPPINGTABLE-15 [page 2116] error code.

Next Actions and Steps (Troubleshooting)

Change the name of the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

SAP Convergent Charging uses this error code to identify an error cause. It refers to the validation error MAPPINGTABLE-15 [page 2116]

View **similar causes**:

- MAPPINGTABLE-9 [page 2107]
- MAPPINGTABLE-12 [page 2112]
- MAPPINGTABLE-17 [page 2119]
- MAPPINGTABLE-18 [page 2121]

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1167 MAPPINGTABLE-12

Message

```
The name of the output column at index {outColumnIndex} is missing.
```

Legend

- `{inColumnIndex}`: The index of the output column within the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

This specific error code defines an error cause. It results from a validation failure. Refer to the MAPPINGTABLE-15 [page 2116] error code.

Next Actions and Steps (Troubleshooting)

Add a name to the output column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

SAP Convergent Charging uses this error code to identify an error cause. It refers to the validation error MAPPINGTABLE-15 [page 2116]

View **similar causes**:

- MAPPINGTABLE-9 [page 2107]
- MAPPINGTABLE-11 [page 2110]
- MAPPINGTABLE-17 [page 2119]
- MAPPINGTABLE-18 [page 2121]

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1168 MAPPINGTABLE-13

Message

```
The type of the output column at index {outColumnIndex} is missing.
```

Legend

- `{outColumnIndex}`: The index of the output column within the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the output column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1169 MAPPINGTABLE-15

Message

```
Error while validating the mapping table class "{mappingTableClassId}".
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Additional Information

SAP Convergent Charging uses this error code to identify an error cause. It refers to the validation error MAPPINGTABLE-15 [page 2116]

View **similar causes**:

- MAPPINGTABLE-9 [page 2107]
- MAPPINGTABLE-11 [page 2110]
- MAPPINGTABLE-12 [page 2112]
- MAPPINGTABLE-17 [page 2119]
- MAPPINGTABLE-18 [page 2121]

Next Actions and Steps (Troubleshooting)

See the caused-by information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1170 MAPPINGTABLE-16

Message

```
Impossible to create the mapping table class because its ID
{mappingTableClassId}
already exists.
```

Legend

- `{mappingTableClassId}`: The specified ID that needs to be changed because it already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

In the SAP CC Core Server system, a data object of same type is already available and has exactly the same identifier (ID) or identification name.

The data may belong to another pricing catalog.

Next Actions and Steps (Troubleshooting)

Change the identifier of the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

- MACA database table
- com/highdeal/hci/InvalidCreationErrorException class
- com/highdeal/mappingtable/hci/MappingTableClassModel class

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1171 MAPPINGTABLE-17

Message

```
The description of the input column at index {inColumnIndex} is missing.
```

Legend

- `{inColumnIndex}`: The index of the input column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

This specific error code defines an error cause. It results from a validation failure. Refer to the MAPPINGTABLE-15 [page 2116] error code.

Next Actions and Steps (Troubleshooting)

Add a description to the input column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

SAP Convergent Charging uses this error code to identify an error cause. It refers to the validation error MAPPINGTABLE-15 [page 2116]

View **similar causes**:

- MAPPINGTABLE-9 [page 2107]
- MAPPINGTABLE-11 [page 2110]
- MAPPINGTABLE-12 [page 2112]
- MAPPINGTABLE-18 [page 2121]

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1172 MAPPINGTABLE-18

Message

```
The description of the output column at index {outColumnIndex} is missing.
```

Legend

- `{inColumnIndex}`: The index of the output column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

This specific error code defines an error cause. It results from a validation failure. Refer to the MAPPINGTABLE-15 [page 2116] error code.

Next Actions and Steps (Troubleshooting)

Add a description to the output column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

SAP Convergent Charging uses this error code to identify an error cause. It refers to the validation error MAPPINGTABLE-15 [page 2116]

View **similar causes**:

- MAPPINGTABLE-9 [page 2107]
- MAPPINGTABLE-11 [page 2110]
- MAPPINGTABLE-12 [page 2112]
- MAPPINGTABLE-17 [page 2119]

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1173 MAPPINGTABLE-19

Message

```
The ID of the mapping table class is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the identifier of the mapping table class to the delete operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1174 MAPPINGTABLE-20

Message

```
Impossible to remove the mapping table class because its ID
"{mappingTableClassId}"
does not exist.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1175 MAPPINGTABLE-21

Message

```
Impossible to remove the mapping table class "{mappingTableClassId}" because
it is still used by a mapping table.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Determine and delete all the mapping tables that reference the specified mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1176 MAPPINGTABLE-22

Message

```
The filter is missing in the search mapping table class operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter to the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1177 MAPPINGTABLE-23

Message

```
An error occurred when processing the search mapping table class operation:
{errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1178 MAPPINGTABLE-24

Message

```
Impossible to remove the mapping table class "{mappingTableClassId}" because
it is still used by a subscriber mapping table.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Determine and delete all the subscriber mapping tables that reference the specified mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1179 MAPPINGTABLE-101

Message

```
The ID of the mapping table is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1180 MAPPINGTABLE-102

Message

```
The ID of the mapping table class used by the mapping table "{mappingTableId}"
is missing.
```

Legend

- `{mappingTableId}`: The ID of the mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the mapping table class used by the mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1181 MAPPINGTABLE-103

Message

```
The mapping table is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a mapping table to the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1182 MAPPINGTABLE-104

Message

```
The ID "{mappingTableId}" is already used by another mapping table.
```

Legend

- `{mappingTableId}`: The ID of the mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1183 MAPPINGTABLE-105

Message

```
The ID "{mappingTableClassId}" of the mapping table class used by the mapping
table does not exist.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the mapping table class identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1184 MAPPINGTABLE-107

Message

```
The ID of the mapping table to delete is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the mapping table identifier to the delete operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1185 MAPPINGTABLE-108

Message

```
The mapping table "{mappingTableId}" does not exist.
```

Legend

- `{mappingTableId}`: The ID of the mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1186 MAPPINGTABLE-109

Message

```
The filter is missing in the search mapping table operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter to the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1187 MAPPINGTABLE-110

Message

```
An error occurred when processing the search mapping table operation:
{errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1188 MAPPINGTABLE-111

Message

```
The subscriber account ID of the subscriber mapping table
"{subscriberMappingTableID}"
is missing.
```

Legend

- `{subscriberMappingTableID}`: The ID of the subscriber mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a subscriber account identifier to the subscriber mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1189 MAPPINGTABLE-112

Message

```
The service provider name of the subscriber mapping table
"{subscriberMappingTableId}"
is missing.
```

Legend

- `{subscriberMappingTableId}`: The ID of the subscriber mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a service provider name to the subscriber mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1190 MAPPINGTABLE-113

Message

```
The subscriber account "{subscriberAccountId}", with service provider
"{subscriberAccountServiceProviderName}", does not exist. These identifiers are
provided by
the subscriber mapping table "{subscriberMappingTableId}".
```

Legend

- `{subscriberAccountId}`: The ID of the subscriber account
- `{subscriberAccountServiceProviderName}`: The name of the service provider
- `{subscriberMappingTableId}`: The ID of the subscriber mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the subscriber account and/or the service provider.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1191 MAPPINGTABLE-114

Message

```
Unable to create a subscriber mapping table with an ID already used by
an existing mapping table "{mappingTableId}".
```

Legend

- `{mappingTableId}`: The ID of the mapping table that already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber mapping table identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1192 MAPPINGTABLE-115

Message

```
Unable to create a mapping table with the same ID "{subscriberMappingTableId}"
of a subscriber mapping table that already exists.
```

Legend

- `{subscriberMappingTableId}`: The ID of the subscriber mapping table that already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the mapping table identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1193 MAPPINGTABLE-116

Message

```
The owner "{owner}" of the mapping table class used by the subscriber
mapping table does not match the subscriber account service provider name
"{subscriberAccountServiceProviderName}" of the subscriber mapping table.
```

Legend

- `{owner}`: The owner of the mapping table class
- `{subscriberAccountServiceProviderName}`: The name of the service provider

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber mapping table subscriber account service provider name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1194 MAPPINGTABLE-117

Message

```
The filter is missing in the search subscriber mapping table operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter to the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1195 MAPPINGTABLE-118

Message

```
An error occurred when processing the search subscriber mapping table
operation: {errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1196 MAPPINGTABLE-201

Message

```
The ID of the row is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an identifier to the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1197 MAPPINGTABLE-202

Message

```
The start date of the row "{rowId}" is missing.
```

Legend

- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a start date to the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1198 MAPPINGTABLE-203

Message

```
The end date of the row "{rowId}" is missing.
```

Legend

- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an end date to the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1199 MAPPINGTABLE-204

Message

```
The row "{rowId}" is empty.
```

Legend

- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fill in the column of the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1200 MAPPINGTABLE-205

Message

```
The column of the row "{rowId}" at index {columnIndex} has no name.
```

Legend

- `{rowId}`: The ID of the row
- `{columnIndex}`: The position of the column in the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1201 MAPPINGTABLE-206

Message

```
The column "{columnName}" of the row "{rowId}" has no type.
```

Legend

- `{columnName}`: The name of the column
- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1202 MAPPINGTABLE-207

Message

```
The column "{columnName}" of the row "{rowId}" has no string value.
```

Legend

- `{columnName}`: The name of the column
- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1203 MAPPINGTABLE-208

Message

```
The column "{columnName}" of the row "{rowId}" has no currency value.
```

Legend

- `{columnName}`: The name of the column
- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a currency value to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1204 MAPPINGTABLE-209

Message

```
The column "{columnName}" of the row "{rowId}" has no number value.
```

Legend

- `{columnName}`: The name of the column
- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1205 MAPPINGTABLE-210

Message

```
The number of columns for the row "{rowId}" does not match with the number
of columns specified in the related mapping table class.
```

Legend

- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the row to have the same number of columns than the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1206 MAPPINGTABLE-211

Message

```
The column with name "{columnName}" in the row "{rowId}" is missing.
```

Legend

- `{columnName}`: The name of the column
- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the column in the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1207 MAPPINGTABLE-212

Message

```
The column of the row "{rowId}" at index {columnIndex} has no type.
```

Legend

- `{rowId}`: The ID of the row
- `{columnIndex}`: The position of the column in the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1208 MAPPINGTABLE-213

Message

```
The type of the column in the row "{rowId}" does not match with the type
of the input column of the mapping table class "{inColumnName}".
```

Legend

- `{rowId}`: The ID of the row
- `{inColumnName}`: The name of the input column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1209 MAPPINGTABLE-215

Message

```
The type of the column in the row "{rowId}" does not match with the type
of the output column "{outColumnName}" of the mapping table class.
```

Legend

- `{rowId}`: The ID of the row
- `{outColumnName}`: The name of the output column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1210 MAPPINGTABLE-217 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The list of rows is empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one row in the list of the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 3.0 SP04.. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1211 MAPPINGTABLE-218

Message

```
The mapping table ID is null or empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the identifier of the mapping table that owns the rows.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1212 MAPPINGTABLE-219

Message

```
The mapping table "{mappingTableId}" does not exist.
```

Legend

- `{mappingTableId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the mapping table that owns the rows.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1213 MAPPINGTABLE-220

Message

```
The ID "{rowId}" of the row already exists.
```

Legend

- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1214 MAPPINGTABLE-221

Message

```
The list of row identifiers is null.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a list of row identifiers to the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1215 MAPPINGTABLE-222

Message

```
The list of row identifiers is empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one row ID in the list of the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1216 MAPPINGTABLE-224

Message

```
The start date and the end date of the row "{rowId}" are the same.
```

Legend

- `{rowId}`: The ID of the row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the start date or the end date of the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1217 MAPPINGTABLE-225

Message

```
The row ID "{rowId}" is already used.
```

Legend

- `{rowId}`: The duplicate ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1218 MAPPINGTABLE-226

Message

```
The row "{rowId1}" is duplicated with the row "{rowId2}".
```

Legend

- `{rowId1}`: The ID of the row 1
- `{rowId2}`: The ID of the row 2

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the input values or the validity dates of the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1219 MAPPINGTABLE-227

Message

```
The mapping table row "{mappingTableRowId}" does not exist.
```

Legend

- `{mappingTableRowId}`: The ID of the mapping table row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1220 MAPPINGTABLE-228

Message

```
The start date of mapping table row "{mappingTableRowId}" is after its end date.
```

Legend

- `{mappingTableRowId}`: The ID of the mapping table row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the dates of the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1221 MAPPINGTABLE-229

Message

```
The mapping table class "{mappingTableClassId}" cannot be deleted because
it is referenced by at least one charge or refill logic object or pricing macro
or allowance
logic.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete the charge(s) and/or refill logic object(s) and/or pricing macro(s) referencing the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1222 MAPPINGTABLE-230

Message

```
The mapping table "{mappingTableId}" cannot be deleted because it is referenced
by at least one of the following components:
charge component, refill logic, allowance logic, charge plan, refill plan,
pricing macro, or provider contract.
```

Legend

- `{mappingTableId}`: The ID of the mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete the charge(s), refill logic object(s), allowance logic object(s), charge plan(s), refill plan(s), pricing macro(s) and/or provider contract(s) referencing the mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1223 MAPPINGTABLE-231

Message

```
The new row "{rowId1}" is duplicated with the existing row "{rowId2}".
```

Legend

- `{rowId1}`: The ID of new row
- `{rowId2}`: The ID of existing row

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the input values or the validity dates of the row.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1224 MAPPINGTABLE-232

Message

```
The mapping table class "{mappingTableClassId}" cannot have more than 20
input columns.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Split the existing mapping table class into several mapping table classes to respect the above limitation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1225 MAPPINGTABLE-233

Message

```
The mapping table class "{mappingTableClassId}" cannot have more than
30 output columns.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Split the existing mapping table class into several mapping table classes to respect the above limitation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1226 MAPPINGTABLE-234

Message

```
The mapping table code is missing in the search mapping table row operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the code of the mapping table to the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1227 MAPPINGTABLE-235

Message

```
The mapping table "{mappingTableId}" does not exist.
```

Legend

- `{mappingTableId}`: The ID of the mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1228 MAPPINGTABLE-236

Message

```
The identifier of the mapping table is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the code of the mapping table to the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1229 MAPPINGTABLE-237

Message

```
The mapping table "{mappingTableId}" does not exist.
```

Legend

- `{mappingTableId}`: The ID of the mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1230 MAPPINGTABLE-238

Message

```
The identifier of the subscriber mapping table is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the code of the subscriber mapping table to the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1231 MAPPINGTABLE-239

Message

```
The subscriber mapping table "{subscriberMappingTableId}" does not exist.
```

Legend

- `{subscriberMappingTableId}`: The ID of the subscriber mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the subscriber mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1232 MAPPINGTABLE-240

Message

```
The CSV field delimiter must be a single character, except a double quote.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the CSV field delimiter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1233 MAPPINGTABLE-241

Message

```
The decimal separator must be a dot or a comma.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the decimal separator.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1234 MAPPINGTABLE-242

Message

```
The thousand separator must be a dot, a comma, a single quote, a space, or empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the separator for thousands.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1235 MAPPINGTABLE-243

Message

```
The decimal and thousand separators must be different.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the thousand or the decimal separator.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1236 MAPPINGTABLE-244

Message

```
The value "{value}" cannot be formatted as a number.
```

Legend

- `{value}`: The value that cannot be formatted as a number

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact your SAP Support Team.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1237 MAPPINGTABLE-245

Message

```
The mapping table class to modify is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a mapping table class to the modify operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1238 MAPPINGTABLE-246

Message

```
Impossible to modify the mapping table class because its ID
{mappingTableClassId}
does not exist.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the operation request, change the ID of the mapping table class or determine why the mapping table class does not exist in the pricing catalog (in master data).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1239 MAPPINGTABLE-247

Message

```
Impossible to modify the mapping table class "{mappingTableClassId}" because
it is still used by a mapping table. Only restricted modifications are possible.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class to change

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete all the mapping tables that are based on and refer to this mapping table class. See the other error messages about the detailed reason.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1240 MAPPINGTABLE-248

Message

```
Impossible to modify the mapping table class "{mappingTableClassId}" because
it is referenced by at least one charge, refill logic object, pricing macro, or
allowance logic
object. Only restricted modifications are possible.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class to change

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete all the charges, refill logic objects, pricing macros, or allowance logic objects that refer to this mapping table class. See the other error messages about the detailed reason.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1241 MAPPINGTABLE-249

Message

```
Impossible to modify the mapping table class "{mappingTableClassId}" because
it is still used by a subscriber mapping table. Only restricted modifications
are possible.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class to change

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete all the subscriber mapping tables that are based on and refer to this mapping table class. See the other error messages about the detailed reason.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1242 MAPPINGTABLE-250

Message

```
Impossible to modify the mapping table class "{mappingTableClassId}" because
the specified owner {specifiedOwner} does not correspond to the owner
{realOwner} already
configured in the existing mapping table class.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class to change
- `{specifiedOwner}`: The owner specified in the operation request
- `{realOwner}`: The owner already declared in the existing mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the operation request, change the owner to the owner of the mapping table class or create a new mapping table class for the specified owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1243 MAPPINGTABLE-251

Message

```
In the current context of use, you cannot modify the number of input columns
{specifiedInColumns}. It must equal the number of input columns {realInColumns}
```

```
already
configured in the existing mapping table class.
```

Legend

- `{specifiedInColumns}`: The specified number of input columns in the operation request
- `{realInColumns}`: The number of input columns existing in the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the operation request, correct the number of input columns or create a new mapping table class for the specified number of input columns. See the other error messages to determine your use context.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1244 MAPPINGTABLE-252

Message

```
In the current context of use, you cannot replace the name of the input column
"{existingInColumnName}" at index {inColumnIndex} by "{operationInColumnName}".
```

Legend

- `{existingInColumnName}`: The name of the input column already defined in the mapping table class
- `{inColumnIndex}`: The index of the input column in the mapping table class
- `{operationInColumnName}`: The name of the input column within the operation request

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the operation request, correct the name of the input column or create a new mapping table class with an input column having the specified name. See the other error messages to determine your use context.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1245 MAPPINGTABLE-253

Message

```
In the current context of use, you cannot modify the type of the input column
at index {specifiedInColumnIndex}. It must equal the type of the input column at
index
{realInColumnIndex} that is already configured in the mapping table class.
```

Legend

- `{specifiedInColumnIndex}`: The index of the input column within the operation request
- `{realInColumnIndex}`: The index of the input column within the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the operation request, correct the type of the input column or create a new mapping table class for the specified input column type. See the other error messages to determine your use context.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1246 MAPPINGTABLE-254

Message

```
In the current context of use, you cannot modify the number of output columns
{specifiedOutColumns}. It must equal the number of output columns
{realOutColumns} already
configured in the existing mapping table class.
```

Legend

- `{specifiedOutColumns}`: The specified number of output columns in the operation request
- `{realOutColumns}`: The number of output columns existing in the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the operation request, correct the number of output columns or create a new mapping table class for the specified number of output columns. See the other error messages to determine your use context.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1247 MAPPINGTABLE-255

Message

```
In the current context of use, you cannot replace the name of the output
                    column "{existingOutColumnName}" at index {outColumnIndex}
by "{operationOutColumnName}".
```

Legend

- `{existingOutColumnName}`: The name of the output column in the mapping table class
- `{outColumnIndex}`: The index of the output column in the mapping table class
- `{operationOutColumnName}`: The name of the output column within the operation request

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the operation request, correct the name of the output column or create a new mapping table class with an output column having the specified name. See the other error messages to determine your use context.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1248 MAPPINGTABLE-256

Message

```
In the current context of use, you cannot modify the type of the output column
at index {specifiedOutColumnIndex}. It must equal the type of the output column
```

```
at index
{realOutColumnIndex} that is already configured in the mapping table class.
```

Legend

- `{specifiedOutColumnIndex}`: The index of the output column within the operation request
- `{realOutColumnIndexrealOutColumnIndex}`: The index of the output column within the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the operation request, correct the type of the output column or create a new mapping table class for the specified output column type. See the other error messages to determine your use context.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1249 MAPPINGTABLE-257

Message

```
You cannot modify the agreement ID "{operationAgreementId}". The agreement
ID of the mapping table is "{mappingTableAgreementId}".
```

Legend

- `{operationAgreementId}`: The agreement ID in the operation
- `{mappingTableAgreementId}`: The agreement ID of the mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the agreement ID to "{1}" in the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1250 MAPPINGTABLE-258

Message

```
The agreement ID cannot be filled only with spaces.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value of the agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1251 MAPPINGTABLE-259

Message

```
The version of the mapping table is null or empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the version of the mapping table you want to search from.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1252 MAPPINGTABLE-260

Message

```
The mapping table class cannot contain more than one input column of type
currency.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the second column of type currency or change the column type of the input column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1253 MAPPINGTABLE-262

Message

```
Impossible to import the mapping table rows because the CSV contains two rows
with identifier equal to "{duplicatedIdentifier}".
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Legend

- `{duplicatedIdentifier}`: The identifier of the duplicated mapping table row

Related Error Code: `262`

Related Technical Module: `MAPPINGTABLE`

`MAPPINGTABLE [page 73]`

Next Actions and Steps (Troubleshooting)

1. Check the CSV content.
2. Check why two rows have the same row identifier.
   Several reasons are possible: the row is duplicated, one row identifier must be different.
3. Change the data to import.
4. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging

- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1254 MAPPINGTABLE-263

Message

```
Cannot parse the token "{csvFieldIndex}" of the mapping table row
"{csvRowLine}". {errorMessageDetails}
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Legend

- `{csvFieldIndex}`: The index of the CSV field in error
- `{csvRowLine}`: The number of the CSV line in error
- `{errorMessageDetails}`: The message detailing the error

Related Error Code: `263`

Related Technical Module: `MAPPINGTABLE`

`MAPPINGTABLE [page 73]`

Next Actions and Steps (Troubleshooting)

1. Carefully read the part of the message that details the error. This information is added by the system to the error message for troubleshooting purpose.
2. Check the CSV content.
3. Check the line indicated in the error message.
   In this line, check the data at the position indicated.
4. Change the CSV content.
5. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

See Also

RANGETABLE-267 [page 2571]

4.1255 MAPPINGTABLE-264

Message

```
The comment line mark must be a hash, a dollar, or empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `264`

Related Technical Module: `MAPPINGTABLE`

`MAPPINGTABLE [page 73]`

Next Actions and Steps (Troubleshooting)

1. Check the settings of the operation request. Some information is required and was not specified.
   When you work with a comment line at the beginning, specify a hash ('#') or a dollar (`'$'`) character as the comment line mark.
2. Change the API call or SOAP Web Services operation consumption.
3. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

See Also

RANGETABLE-259 [page 2557]

4.1256 MAPPINGTABLE-265

Message

```
The value of the element "csvImportMode" must be "Merge" or "ClearAndReplace".
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `265`

Related Technical Module: `MAPPINGTABLE`

`MAPPINGTABLE [page 73]`

Next Actions and Steps (Troubleshooting)

1. In the operation request, check the option that was specified as a setting of the operation request.
2. Change the value of the XML element `csvImportMode`:
   - Use `<csvImportMode>Merge</csvImportMode>` to merge alreay-existing data with the imported data.
   - Use `<csvImportMode>ClearAndReplace</csvImportMode>` to erase alreay-existing data and replace it with the imported data.
3. Verify your changes.

Check the technical specifications. For example, refer to the SAP CC 2023 Web Services Documentation (SOAP).

> ### Example
>
> For example, as of version 2023 FPS 2 and the version 4 of the SOAP Web Services of SAP CC, the WS operation `mappingTableDataCSVImport` is available and provides you with two processing modes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> ### → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1257 MAPPINGTABLE-266

Message

```
Failed to read the CSV content representing the mapping table rows.
{errorMessageDetails}
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Legend

- `{errorMessageDetails}`: The message detailing the error

Related Technical Module: `MAPPINGTABLE`

`MAPPINGTABLE [page 73]`

Next Actions and Steps (Troubleshooting)

1. Carefully read the part of the message that details the error. This information is added by the system to the error message for troubleshooting purpose.
2. Check and change the CSV content.
3. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1258 MAPPINGTABLECOMPONENT-1

Message

```
The mapping table class ID is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the mapping table class ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1259 MAPPINGTABLECOMPONENT-2

Message

```
Both mapping table ID and mapping table ID property name are missing. At least
one of them must be defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a mapping table ID or a mapping table ID property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1260 MAPPINGTABLECOMPONENT-3

Message

```
Both mapping table ID and mapping table ID property name are defined. Only
one of them must be defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a mapping table ID or a mapping table ID property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1261 MAPPINGTABLECOMPONENT-4

Message

```
The mapping table class "{mappingTableClassId}" does not exist.
```

Legend

- `{mappingTableClassId}`: The ID of the mapping table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1262 MAPPINGTABLECOMPONENT-5

Message

```
The mapping table ID defined by a charge component parameter named
"{mappingTableIdPropertyName}" does not exist.
```

Legend

- `{mappingTableIdPropertyName}`: The name of the mapping table ID parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a parameter in the charge component or define a mapping table ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1263 MAPPINGTABLECOMPONENT-6

Message

```
The mapping table "{mappingTableId}" does not exist.
```

Legend

- `{mappingTableId}`: The ID of the mapping table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1264 MAPPINGTABLECOMPONENT-7

Message

```
The mapping table class "{mappingTableClassIdFromParameter}" referenced in
the parameter "{parameterName}" does not correspond to the mapping table class
"{mappingTableClassIdFromRateComponent}" defined in the rate component.
```

Legend

- `{mappingTableClassIdFromParameter}`: The ID of the mapping table class from the parameter
- `{parameterName}`: The name of the parameter
- `{mappingTableClassIdFromRateComponent}`: The ID of the mapping table class from the rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the same mapping table class in the parameter and in the component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1265 MAPPINGTABLECOMPONENT-8

Message

```
The mapping table class "{mappingTableClassIdFromParameter}" from range table
"{parameterName}" does not correspond to the mapping table class
"{mappingTableClassIdFromRateComponent}" defined in the rate component.
```

Legend

- `{mappingTableClassIdFromParameter}`: The ID of the mapping table class from the parameter
- `{parameterName}`: The name of the parameter
- `{mappingTableClassIdFromRateComponent}`: The ID of the mapping table class from the rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the same mapping table class in the parameter and in the component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1266 MAPPINGTABLECOMPONENT-9

Message

```
The rating context property "{mappingTableIdPropertyName}" defining a mapping
table ID does not include the mandatory additional information "{addInfoName}".
```

Legend

- `{mappingTableIdPropertyName}`: The name of the mapping table ID rating context property
- `{addInfoName}`: The name of the data type additional information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the additional information to this property specified in the logic component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1267 MAPPINGTABLECOMPONENT-10

Message

```
The index of the input column that represents the prefix is lower than 0
or greater than the number of input columns minus 1.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select an index that ranges from 0 to the number of input columns minus 1.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.1 SP 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1268 MAPPINGTABLECOMPONENT-11

Message

```
Component "{component}" invokes a mapping table of class "{mappingTableClass}"
with {actualKeyCount} keys instead of {expectedKeyCount}.
```

Legend

- `{component}`: The name of the mapping table comparator
- `{mappingTableClass}`: The name of the referenced mapping table class
- `{actualKeyCount}`: The number of keys expected by the mapping table
- `{expectedKeyCount}`: The number of keys specified by the component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Detailed Information

As of SP 1 patch level 3 for release 5.0, the SAP CC Core Server system performs stricter validations on the SAP CC logic components, each time you modify, import, or transport data objects that include some logic.

This error code is part of these supplementary validations. See SAP Note 2618936 for the latest information.

Next Actions and Steps (Troubleshooting)

Match the number of input columns of the mapping table class and the number of key(s) provided by the component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

To facilitate your troubleshooting and provide you with more user guidance, see:

- SAP Note 2618936
- SAP Note 2580200
- PRICING_LOGIC_STRICT_VALIDATION_ENABLED system parameter

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1269 MAPPINGTABLECOMPONENT-12

Message

```
Component "{component}" references a mapping table of class
"{mappingTableClass}"
and expects {mappedValueCount} output value(s) instead of {generatedValueCount}.
```

Legend

- `{component}`: The name of the mapping table comparator
- `{mappingTableClass}`: The name of the referenced mapping table class
- `{mappedValueCount}`: The number of output values generated by the mapping table
- `{generatedValueCount}`: The number of output values expected by the component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Detailed Information

As of SP 1 patch level 3 for release 5.0, the SAP CC Core Server system performs stricter validations on the SAP CC logic components, each time you modify, import, or transport data objects that include some logic.

This error code is part of these supplementary validations. See SAP Note 2618936 for the latest information.

Next Actions and Steps (Troubleshooting)

Match the number of outputs columns of the mapping table and the number of values expected by the component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

Additional Information

To facilitate your troubleshooting and provide you with more user guidance, see:

- SAP Note 2618936
- SAP Note 2580200
- PRICING_LOGIC_STRICT_VALIDATION_ENABLED system parameter

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1270 MAPPINGTABLECOMPONENT-13

Message

```
The component cannot reference the mapping table "{mappingTable}" because
this mapping table has an agreement ID.
```

Legend

- `{mappingTable}`: The name of the mapping table referenced by the component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a mapping table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1271 MONITORINGPLAN-1

Message

```
The ID of the monitoring plan is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1272 MONITORINGPLAN-2

Message

```
The owner of the monitoring plan "{monitoringPlanId}" is missing.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an owner to the monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1273 MONITORINGPLAN-3

Message

```
The description of the monitoring plan "{monitoringPlanId}" is missing.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1274 MONITORINGPLAN-4

Message

```
The status of the monitoring plan "{monitoringPlanId}" is missing.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a status to the monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1275 MONITORINGPLAN-5

Message

```
The monitoring plan "{monitoringPlanId}" must at least declare one spending
status mapping.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one spending status mapping that configures the generation of a spending status.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1276 MONITORINGPLAN-6

Message

```
The ID of the spending status description in the spending status mapping
at index {spendingStatusMappingIndex} is missing.
```

Legend

- `{spendingStatusMappingIndex}`: The index of the spending status mapping within the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a spending status description ID to the spending status mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1277 MONITORINGPLAN-7

Message

```
The ID "{spendingStatusDescriptionId}" of the spending status description
in the spending status mapping at index {spendingStatusMappingIndex} is unknown.
```

Legend

- `{spendingStatusDescriptionId}`: The name of the unknown spending status description
- `{spendingStatusMappingIndex}`: The index of the spending status mapping within the monitoring planThe index of the spending status mapping within the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the ID of an existing spending status description to the spending status mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1278 MONITORINGPLAN-8

Message

```
The ID "{spendingStatusDescriptionId}" of the spending status description in
the spending status mapping at index {secondIndex} is already used by the
spending status
mapping at index {firstIndex}.
```

Legend

- `{spendingStatusDescriptionIdspendingStatusDescriptionId}`: The duplicated spending status description ID
- `{secondIndex}`: The index of the second occurrence of the name within spending status mappings
- `{firstIndex}`: The index of the first occurrence of the name within spending status mappings

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another ID of the spending status description in the spending status mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1279 MONITORINGPLAN-9

Message

```
The name of the counter in the spending status mapping at index
{spendingStatusMappingIndex} is missing.
```

Legend

- `{spendingStatusMappingIndex}`: The index of the spending status mapping within the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a counter name from the counter name dictionary to the spending status mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1280 MONITORINGPLAN-10

Message

```
The name "{counterName}" of the counter in the spending status mapping
at index {spendingStatusMappingIndex} is unknown in the counter name dictionary.
```

Legend

- `{counterName}`: The name of the unknown counter
- `{spendingStatusMappingIndex}`: The index of the spending status mapping within the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify an existing counter name to the spending status mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1281 MONITORINGPLAN-11

Message

```
The name of the parameter in the spending status mapping at index
{spendingStatusMappingIndex} is missing.
```

Legend

- `{spendingStatusMappingIndex}`: The index of the spending status mapping within the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the relevant parameter name to the spending status mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1282 MONITORINGPLAN-12

Message

```
The parameter name "{parameterTargetName}" in the spending status mapping
at index {spendingStatusMappingIndex} is unknown.
```

Legend

- `{parameterTargetName}`: The target name of the parameter
- `{spendingStatusMappingIndex}`: The index of the spending status mapping within the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the name of an existing parameter to the spending status mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1283 MONITORINGPLAN-13

Message

```
The parameter "{parameterName}" at index {parameterIndex} in the monitoring
plan is not used in a spending status mapping.
```

Legend

- `{parameterName}`: The name of the parameter
- `{parameterIndex}`: The index of the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the parameter or remove it from the monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1284 MONITORINGPLAN-14

Message

```
The monitoring plan is missing in the create operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a monitoring plan in the create operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1285 MONITORINGPLAN-15

Message

```
Cannot create the monitoring plan: The monitoring plan "{monitoringPlanId}"
already exists.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another monitoring plan in the create operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1286 MONITORINGPLAN-16

Message

```
The monitoring plan is missing in the modify operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a monitoring plan to the modify operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1287 MONITORINGPLAN-17

Message

```
The monitoring plan "{monitoringPlanId}" does not exist.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another monitoring plan to the modify operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1288 MONITORINGPLAN-18

Message

```
The mandatory filter is missing in the search operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a filter in the search operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1289 MONITORINGPLAN-19

Message

```
An unknown error occurred during the execution of the monitoring plan search
operation: {reasonInformation}
```

Legend

- `{reasonInformation}`: The additional information describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the reason information recorded in your error message. The reason is based on the Java Technology. It details the exception raised in the connected SAP CC system.
Typical reasons are: Invalid search filter, Back-end database failure.

Refer to the Java/XML API Reference (Core Library) documentation for more information about the com.highdeal.filter.hci.InvalidSearchException.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1290 MONITORINGPLAN-20

Message

```
The ID of the monitoring plan is missing in the delete operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the relevant monitoring plan ID in the delete operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1291 MONITORINGPLAN-21

Message

```
Cannot delete the monitoring plan: The monitoring plan "{monitoringPlanId}"
does not exist.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another ID of monitoring plan to the delete operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1292 MONITORINGPLAN-22

Message

```
Error while deleting the monitoring plan "{monitoringPlanId}". The monitoring
plan is still activated in one provider contract.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan that needs to be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete all contract items referencing the monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1293 MONITORINGPLAN-23

Message

```
The monitoring plan "{monitoringPlanId}" cannot be modified because the
specified
owner {specifiedOwner} does not correspond to the owner {realOwner} existing in
the monitoring
plan.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan
- `{specifiedOwner}`: The specified owner in the operation
- `{realOwner}`: The owner existing in the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the owner to the owner of the monitoring plan or create a new monitoring plan for the specified owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1294 MONITORINGPLAN-24

Message

```
The status of already released monitoring plan "{monitoringPlanId}" cannot
be set back to open.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new monitoring plan to released or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1295 MONITORINGPLAN-25

Message

```
The status of already obsolete monitoring plan "{monitoringPlanId}" cannot
be set back to open.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new monitoring plan to released or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1296 MONITORINGPLAN-26

Message

```
The status of already obsolete monitoring plan "{monitoringPlanId}" cannot
be set back to released.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new monitoring plan to released or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1297 MONITORINGPLAN-27

Message

```
The text description of the monitoring plan "{monitoringPlanId}" cannot
be modified because the monitoring plan has been released or is obsolete.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1298 MONITORINGPLAN-28

Message

```
The additional information "{additionalInformationName}" cannot be removed
because the monitoring plan "{monitoringPlanId}" has been released or is
obsolete.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1299 MONITORINGPLAN-29

Message

```
The additional information "{additionalInformationName}" cannot be added
because the monitoring plan "{monitoringPlanId}" has been released or is
obsolete.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1300 MONITORINGPLAN-30

Message

```
The description of the additional information "{additionalInformationName}"
cannot be modified because the monitoring plan "{monitoringPlanId}" has been
released or
is obsolete.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1301 MONITORINGPLAN-31

Message

```
The type of the additional information "{additionalInformationName}" cannot
be modified because the monitoring plan "{monitoringPlanId}" has been released
or is obsolete.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1302 MONITORINGPLAN-32

Message

```
The date value of the additional information "{additionalInformationName}"
cannot
be modified because the monitoring plan "{monitoringPlanId}" has been released
or is obsolete.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1303 MONITORINGPLAN-33

Message

```
The number value of the additional information "{additionalInformationName}"
cannot be modified because the monitoring plan "{monitoringPlanId}" has been
released or is
obsolete.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1304 MONITORINGPLAN-34

Message

```
The string value of the additional information "{additionalInformationName}"
cannot be modified because the monitoring plan "{monitoringPlanId}" has been
released or is
obsolete.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1305 MONITORINGPLAN-35

Message

```
The user technical identifier "{userTechIdName}" cannot be removed because
the monitoring plan "{monitoringPlanId}" has been released or is obsolete.
```

Legend

- `{userTechIdName}`: The name of the user technical identifier
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1306 MONITORINGPLAN-36

Message

```
The user technical identifier "{userTechIdName}" cannot be added because
the monitoring plan "{monitoringPlanId}" has been released or is obsolete.
```

Legend

- `{userTechIdName}`: The name of the user technical identifier
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1307 MONITORINGPLAN-37

Message

```
The description of the user technical identifier "{userTechIdName}" cannot
be modified because the monitoring plan "{monitoringPlanId}" has been released
or is obsolete.
```

Legend

- `{userTechIdName}`: The name of the user technical identifier
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1308 MONITORINGPLAN-38

Message

```
The parameter "{parameterName}" cannot be removed because the monitoring plan
"{monitoringPlanId}" has been released or is obsolete.
```

Legend

- `{parameterName}`: The name of the parameter
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1309 MONITORINGPLAN-39

Message

```
The parameter "{parameterName}" cannot be added because the monitoring plan
"{monitoringPlanId}" has been released or is obsolete.
```

Legend

- `{parameterName}`: The name of the parameter
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1310 MONITORINGPLAN-40

Message

```
The description of the parameter "{parameterName}" cannot be modified
because the monitoring plan "{monitoringPlanId}" has been released or is
obsolete.
```

Legend

- `{parameterName}`: The name of the parameter
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1311 MONITORINGPLAN-41

Message

```
The string value of the parameter "{parameterName}" cannot be modified
because the monitoring plan "{monitoringPlanId}" has been released or is
obsolete.
```

Legend

- `{parameterName}`: The name of the parameter
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1312 MONITORINGPLAN-42

Message

```
The spending status mapping "{spendingStatusDescriptionId}" cannot be
removed because the monitoring plan "{monitoringPlanId}" has been released or is
obsolete.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1313 MONITORINGPLAN-43

Message

```
The spending status mapping "{spendingStatusDescriptionId}" cannot be
added because the monitoring plan "{monitoringPlanId}" has been released or is
obsolete.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1314 MONITORINGPLAN-44

Message

```
The name of the counter in the spending status mapping
"{spendingStatusDescriptionId}"
cannot be changed because the monitoring plan "{monitoringPlanId}" has been
released or
is obsolete.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1315 MONITORINGPLAN-45

Message

```
The parameter name in the spending status mapping
"{spendingStatusDescriptionId}"
```

```
cannot be changed because the monitoring plan "{monitoringPlanId}" has been
released or is obsolete.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description
- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new monitoring plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1316 MONITORINGPLAN-46

Message

```
The status of new monitoring plan "{monitoringPlanId}" must be open.
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new monitoring plan to open.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1317 MONITORINGPLAN-47

Message

```
Error(s) while validating the monitoring plan "{monitoringPlanId}".
```

Legend

- `{monitoringPlanId}`: The ID of the monitoring plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the nested errors in the error stack.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1318 MONITORINGPLAN-48

Message

```
The name "{counterName}" of the counter in the spending status mapping at
index {secondIndex} is already used by the spending status mapping at index
{firstIndex}.
```

Legend

- `{counterNamecounterName}`: The name of the unknown counter
- `{secondIndex}`: The index of the second occurrence of the name within spending status mappings
- `{firstIndex}`: The index of the first occurrence of the name within spending status mappings

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the counter in the relevant spending status mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1319 MONITORINGPLAN-49

Message

```
The parameter name "{parameterTargetName}" in the spending status mapping
at index {secondIndex} is already used by the spending status mapping at index
{firstIndex}.
```

Legend

- `{parameterTargetName}`: The target name of the parameter
- `{secondIndex}`: The index of the second occurrence of the name within spending status mappings
- `{firstIndex}`: The index of the first occurrence of the name within spending status mappings

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter name in the spending status mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1320 MONITORINGPLAN-50

Message

```
The Parameter at index {parameterIndex} is empty.
```

Legend

- `{parameterIndex}`: The index of the Parameter within the Monitoring Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Parameter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1321 MONITORINGPLAN-51

Message

```
The name of the Parameter at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter within the Monitoring Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1322 MONITORINGPLAN-52

Message

```
The name "{parameterName}" of the Parameter at index {secondIndex} is already
used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterIndex}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name within Parameters
- `{firstIndex}`: The index of the first occurrence of the name within Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1323 MONITORINGPLAN-53

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex} is
missing or unknown (the only supported type is string).
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter within the Monitoring Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter or change it to the only supported one: string.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1324 MONITORINGPLAN-54

Message

```
The description of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter within the Monitoring Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1325 MONITORINGPLAN-55

Message

```
The value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter within the Monitoring Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1326 MONITORINGPLAN-56

Message

```
Error while validating the Parameter "{parameterName}" at index {parameterIndex}.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter within the Monitoring Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1327 MONITORINGPLAN-57

Message

```
The Parameter additional information "{additionalInformationName}" at index
{additionalInformationIndex} is unknown.
```

Legend

- `{additionalInformationName}`: The name of the additional information
- `{additionalInformationIndex}`: The index of the additional information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this additional information or replace it with a known one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1328 MONITORINGPLAN-58

Message

```
The data type of the Parameter is missing or unknown (the only supported type
is rangeTableId).
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a data type to the Parameter or change it to the only supported one: rangeTableId.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1329 MONITORINGPLAN-59

Message

```
The Parameter is a Range Table ID but no Range Table Class is defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Range Table Class additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1330 MONITORINGPLAN-60

Message

```
The Parameter points to an unknown Range Table Class "{rangeTableClassId}".
```

Legend

- `{rangeTableClassId}`: The ID of the Range Table Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known Range Table Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1331 MONITORINGPLAN-61

Message

```
The Parameter points to the Range Table Class "{rangeTableClassId}" which
does not have a single output column of type string.
```

Legend

- `{rangeTableClassId}`: The ID of the Range Table Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a Range Table Class with a single output column of type string.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1332 MONITORINGPLAN-62

Message

```
The Parameter points to an unknown Range Table "{rangeTableId}".
```

Legend

- `{rangeTableId}`: The ID of the Range Table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known Range Table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1333 MONITORINGPLAN-63

Message

```
The Parameter points to the Range Table "{rangeTableId}" which is not an
instance of the previously defined Range Table Class "{rangeTableClassId}".
```

Legend

- `{rangeTableId}`: The ID of the Range Table
- `{rangeTableClassId}`: The ID of the Range Table Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a Range Table which is an instance of the previously defined Range Table Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1334 MONITORINGPLAN-64

Message

```
The parameter cannot reference the range table "{parameterValue}" because
this range table has an agreement ID.
```

Legend

- `{parameterValue}`: The identifier of the range table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1335 OPERATIONALSTATUS-1

Message

```
The process cannot access the contract with the ID "{chargingContractId}"
because
the operational status of the contract is not set to active.
```

Legend

- `{chargingContractId}`: The ID of the contract whose the operational status is locked or closed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

If the contract is locked, set its operational status to active and launch the process again.
If the contract is closed, the process cannot access it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1336 OPERATIONALSTATUS-2

Message

```
The string entered as rootChargingContractId is empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Enter a string that is not empty.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1337 OPERATIONALSTATUS-3

Message

```
The contract does not exist.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Enter a rootChargingContractId corresponding to an existing contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1338 OPERATIONALSTATUS-4

Message

```
The operational status of the contract cannot be modified because the
contract is a linked charging contract.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Modify the operational status of the root charging contract corresponding to this linked charging contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1339 OPERATIONALSTATUS-5

Message

```
The operational status of the contract is empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact your SAP Support Team.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1340 OPERATIONALSTATUS-6

Message

```
The operational status of the contract cannot be changed because it is used
for a rerating or a recharging session.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Wait until the rerating session is completed.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1341 OPERATIONALSTATUS-7

Message

```
The contract cannot be closed because its operational status is set to active.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the operational status of the contract to locked first, and then set it to closed.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1342 OPERATIONALSTATUS-8

Message

```
The linked contract with the ID "{chargingContractId}" cannot be modified
because its root contract is locked or closed.
```

Legend

- `{chargingContractId}`: The ID of the linked contract whose root contract is locked or closed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the operational status of the root contract to active first, and then perform the modification.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1343 OPERATIONALSTATUS-9

Message

```
The root charging contract with the ID "{chargingContractId}" cannot be
modified because its operational status is set to locked or closed.
```

Legend

- `{chargingContractId}`: The ID of the root contract which is locked or closed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the operational status of the root charging contract to active first, and then modify the root charging contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1344 OPERATIONALSTATUS-10

Message

```
The charging contract with the ID "{chargingContractId}" cannot be deleted
because its operational status is set to locked.
```

Legend

- `{chargingContractId}`: The ID of the contract whose root contract is locked

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the operational status of the corresponding root charging contract to active or closed first, and then delete the charging contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1345 OPERATIONALSTATUS-11

Message

```
The linked charging contract cannot be created because the operational status
of the root charging contract with the ID "{chargingContractId}" is not set to
active.
```

Legend

- `{chargingContractId}`: The ID of the root contract which is locked

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the operational status of the root charging contract to active first, and then create the linked charging contract.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1346 OPERATIONALSTATUS-12

Message

```
The operational status of the root charging contract with the ID
"{chargingContractId}"
cannot be changed because it is set to closed.
```

Legend

- `{chargingContractId}`: The ID of the root contract which is closed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new root charging contract or export it and re-create it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP08 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1347 PREPAIDACCOUNTSTATE-1

Message

```
The prepaid account ID is missing in the prepaid account reference specified
in the operation request.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a prepaid account identifier in the prepaid account reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1348 PREPAIDACCOUNTSTATE-2

Message

```
The subscriber account ID is missing in the prepaid account reference specified
in the operation request.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a prepaid account identifier in the prepaid account reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1349 PREPAIDACCOUNTSTATE-3

Message

```
The amount is missing in the operation request.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the amount in the operation operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1350 PREPAIDACCOUNTSTATE-4

Message

```
The amount value is missing in the operation request.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the amount value in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1351 PREPAIDACCOUNTSTATE-5

Message

```
The subscriber account "{subscriberAccountId}" specified in the operation
request does not exist.
```

Legend

- `{subscriberAccountId}`: The subscriber account ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the subscriber account ID to an existing subscriber account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1352 PREPAIDACCOUNTSTATE-6

Message

```
The prepaid account "{prepaidAccountId}" does not exist in the subscriber
account "{subscriberAccountId}".
```

Legend

- `{prepaidAccountId}`: The prepaid account ID
- `{subscriberAccountId}`: The subscriber account ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the prepaid account ID belongs to this subscriber account or determine another prepaid account or another subscriber account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1353 PREPAIDACCOUNTSTATE-7

Message

```
The currency code "{prepaidAccountStateCurrencyCode}" specified in the operation
request does not correspond to the currency code "{prepaidAccountCurrencyCode}"
of the
balance of the prepaid account.
```

Legend

- `{prepaidAccountStateCurrencyCode}`: The currency code specified to set the initial amount of the balance
- `{prepaidAccountCurrencyCode}`: The current currency code of the balance of the prepaid account

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the currency in the operation request to the currency of the balance of the prepaid acccount.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP06 Patch Level 3 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1354 RANGETABLE-1

Message

```
The ID of the range table class is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1355 RANGETABLE-2

Message

```
The owner of the range table class is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an owner to the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1356 RANGETABLE-3

Message

```
The description of the range table class is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1357 RANGETABLE-4

Message

```
The range table class must declare the range upper bound.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the range upper bound.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1358 RANGETABLE-5

Message

```
The range table class must at least declare one output column.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one output column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1359 RANGETABLE-6

Message

```
The range table class must have less than {outColumnMax} output columns.
```

Legend

- `{outColumnMax}`: The maximum of output column allowed in the range table class definition

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete output columns to have a count of output column underneath the maximum.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1360 RANGETABLE-7

Message

```
Error while validating the range table class "{rangeTableClassId}".
```

Legend

- `{rangeTableClassId}`: The ID of the range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1361 RANGETABLE-8

Message

```
The name of the output column at index {outColumnIndex} is missing.
```

Legend

- `{outColumnIndex}`: The index of the output column within the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the output column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1362 RANGETABLE-9

Message

```
The description of output column at index {outColumnIndex} is missing.
```

Legend

- `{outColumnIndex}`: The index of the output column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the output column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1363 RANGETABLE-10

Message

```
The type of the output column at index {outColumnIndex} is missing.
```

Legend

- `{outColumnIndex}`: The index of the output column within the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the output column.Add a type to the output column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1364 RANGETABLE-11

Message

```
The column name "{columnName}" is duplicated in the range table class.
```

Legend

- `{columnName}`: The duplicated name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1365 RANGETABLE-12

Message

```
The ID of the range table class is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the range table class to delete operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1366 RANGETABLE-13

Message

```
Impossible to remove the range table class because its ID "{rangeTableClassId}"
does not exist.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1367 RANGETABLE-14

Message

```
The filter is missing in the search range table class operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter to the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1368 RANGETABLE-15

Message

```
An error occurred during the search range table class execution: {errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1369 RANGETABLE-16

Message

```
Impossible to create the range table class because its ID {rangeTableClassId}
already exists.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1370 RANGETABLE-17

Message

```
The range table class to create is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a range table class to the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1371 RANGETABLE-18

Message

```
The range table class to modify is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a range table class to the modify operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1372 RANGETABLE-19

Message

```
Impossible to modify the range table class because its ID {rangeTableClassId}
does not exist.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1373 RANGETABLE-20

Message

```
Impossible to modify the range table class "{rangeTableClassId}" because
the specified owner {specifiedOwner} does not correspond to the owner
{realOwner} existing
in the range table class.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class
- `{specifiedOwner}`: The specified owner in the operation
- `{realOwner}`: The owner existing in the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the owner to the owner of the range table class or create a new range table class for the specified owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1374 RANGETABLE-21

Message

```
Impossible to remove the range table class "{rangeTableClassId}" because
it is still used by a range table.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete all the subscriber range tables and all the range tables that relate to this range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1375 RANGETABLE-22

Message

```
Impossible to modify the range table class because the specified range upper
bound value "{specifiedRangeUpperBound}" does not correspond to the range upper
bound value
"{realRangeUpperBound}" existing in the range table class.
```

Legend

- `{specifiedRangeUpperBound}`: The specified range upper bound value in the operation
- `{realRangeUpperBound}`: The range upper bound value existing in the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the range upper bound value to the range upper bound value of the range table class or create a new range table class for the specified range upper bound value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1376 RANGETABLE-23

Message

```
Impossible to modify the range table class because the number of output
column(s) {specifiedOutColumns} does not correspond to the number of output
column(s) {realOutColumns}
existing in the range table class.
```

Legend

- `{specifiedOutColumns}`: The specified number of output column(s) in the operation
- `{realOutColumns}`: The number of output column(s) existing in the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the number of output column(s) to the number of output column(s) of the range table class or create a new range table class for the specified output column(s).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1377 RANGETABLE-24

Message

```
Impossible to remove the range table class "{rangeTableClassId}" because
it is still used by a subscriber range table.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete all the subscriber range tables and all the range tables that relate to this range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1378 RANGETABLE-25

Message

```
Impossible to modify the range table class because the name of the output column
at index {specifiedOutColumnIndex} does not correspond to the name of the output
column at
index {realOutColumnIndex} existing in the range table class.
```

Legend

- `{specifiedOutColumnIndex}`: The index of the output column within the operation
- `{realOutColumnIndex}`: The index of the output column within the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the output column to the name of the output column of the range table class or create a new range table class for the specified output column name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1379 RANGETABLE-26

Message

```
Impossible to modify the range table class because the type of the output
column at index {specifiedOutColumnIndex} does not correspond to the type of the
```

```
output column
at index {realOutColumnIndex} existing in the range table class.
```

Legend

- `{specifiedOutColumnIndex}`: The index of the output column within the operation
- `{realOutColumnIndex}`: The index of the output column within the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the output column to the type of the output column of the range table class or create a new range table class for the specified output column type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1380 RANGETABLE-27

Message

```
The range table class has an owner "{rangeTableClassOwner}" with no catalog.
```

Legend

- `{rangeTableClassOwner}`: The owner of the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the owner of the range table class to a catalog owner or create the catalog owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1381 RANGETABLE-28

Message

```
The range table class must declare the last range type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the last range type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1382 RANGETABLE-29

Message

```
Impossible to modify the range table class because the specified last range
type "{specifiedLastRangeType}" does not correspond to the last range type
"{realLastRangeType}"
existing in the range table class.
```

Legend

- `{specifiedLastRangeType}`: The specified range last range type in the operation
- `{realLastRangeType}`: The last range type existing in the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the last range type to the last range type of the range table class or create a new range table class for the specified last range type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1383 RANGETABLE-30

Message

```
Impossible to modify the range table class "{rangeTableClassId}" because
it is referenced by a range table, a charge, a refill logic, an allowance logic
object or
a pricing macro.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new range table class of remove all the objects that refer to this class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1384 RANGETABLE-107

Message

```
The ID of the range table to delete is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the identifier of the range table to the delete operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1385 RANGETABLE-108

Message

```
The range table "{rangeTableId}" does not exist.
```

Legend

- `{rangeTableId}`: The ID of the range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1386 RANGETABLE-109

Message

```
The filter is missing in the search range table operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter to the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1387 RANGETABLE-110

Message

```
An error occurred when processing the search range table operation:
{errorMessage}
```

Legend

- `{errorMessage}`: The message describing the error

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the error stack and the linked errors.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1388 RANGETABLE-111

Message

```
The filter is missing in the search subscriber range table operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter to the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1389 RANGETABLE-112

Message

```
An error occurred during the search subscriber range table execution:
{errorMessage}.
```

Legend

- `{errorMessage}`: The index of the output column within the operation

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1390 RANGETABLE-120

Message

```
The range table revision is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a range table revision in the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1391 RANGETABLE-121

Message

```
The revision for range table "{rangeTableId}" is not valid.
```

Legend

- `{rangeTableId}`: The ID of the range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a valid range table revision in the create operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1392 RANGETABLE-122

Message

```
The range table ID is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the range table identifier in the range table revision.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1393 RANGETABLE-123

Message

```
The range table rows or range sets are missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one row or range set to the range table revision.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1394 RANGETABLE-126

Message

```
The range table row #{rangeTableRowIndex} is not valid.
```

Legend

- `{rangeTableRowIndex}`: The index of the range table row in the revision

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the linked error.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1395 RANGETABLE-128

Message

```
The range table "{rangeTableId}" already exists in the SAP CC system.
The creation with this ID is not possible.
```

Legend

- `{rangeTableId}`: The ID of the already existing range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the range table revision of the create operation, set a new range table ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1396 RANGETABLE-129

Message

```
The subscriber range table "{subscriberRangeTableId}" already exists in the
SAP CC system. The creation with this ID is not possible.
```

Legend

- `{subscriberRangeTableId}`: The ID of the already existing subscriber range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the range table revision of the create operation, set a new range table ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1397 RANGETABLE-130

Message

```
The range table class ID is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the range table class ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1398 RANGETABLE-131

Message

```
The range table class ID "{rangeTableClassId}" is not valid. It does not
correspond to a range table class.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1399 RANGETABLE-132

Message

```
The rows or the ranges at indexes #{firstIndexWoUpperBound} and
#{secondIndexWoUpperBound}
have no upper bound.
```

Legend

- `{firstIndexWoUpperBound}`: The index of the first row or range without upper bound
- `{secondIndexWoUpperBound}`: The index of the second row or range without upper bound

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set an upper bound in one of the rows or the ranges.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1400 RANGETABLE-133

Message

```
The rows or the ranges at indexes #{firstIndexSameUpperBound} and
#{secondIndexSameUpperBound} must not have the same upper bound "{upperBound}".
```

Legend

- `{firstIndexSameUpperBound}`: The index of the first row or range with the same upper bound
- `{secondIndexSameUpperBound}`: The index of the second row or range with the same upper bound
- `{upperBound}`: The upper bound common to both

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the upper bound for one of the rows or the ranges.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1401 RANGETABLE-134

Message

```
The upper bound value is not valid. It must be strictly positive.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the upper bound to a positive value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1402 RANGETABLE-135

Message

```
Require {columnCountRequired} range table columns. See the range table
class "{rangeTableClassId}".
```

Legend

- `{columnCountRequired}`: The count of required columns
- `{rangeTableClassId}`: The range table class ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add or remove a column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1403 RANGETABLE-136

Message

```
The range table column #{rangeTableColumnIndex} is not valid.
```

Legend

- `{rangeTableColumnIndex}`: The index of the range table column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the linked error.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1404 RANGETABLE-137

Message

```
The column name "{rangeTableColumnName}" is not a column name of the
range table class "{rangeTableClassId}".
```

Legend

- `{rangeTableColumnName}`: The colmun name that is not a column name of the range table class
- `{rangeTableClassId}`: The range table class ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Choose a column name from the corresponding range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1405 RANGETABLE-138

Message

```
The type of the column is not valid. Replace it with
"{expectedRangeTableColumnType}".
```

Legend

- `{expectedRangeTableColumnType}`: The expected column type

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the column. Set the type that is defined in the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1406 RANGETABLE-139

Message

```
The type of the column is not valid. Replace it with
"{expectedRangeTableColumnType}".
```

Legend

- `{expectedRangeTableColumnType}`: The expected column type

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the column. Set the type that is defined in the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1407 RANGETABLE-140

Message

```
The column name is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1408 RANGETABLE-141

Message

```
The column type is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1409 RANGETABLE-142

Message

```
The number value of the column is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1410 RANGETABLE-143

Message

```
The string value of the column is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1411 RANGETABLE-145 (Revoked)

ALLOWANCE-350 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The modification date is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a modification date in the modify operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to 4.0 SP10. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1412 RANGETABLE-146

Message

```
The modification date is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a modification date in the modify operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1413 RANGETABLE-147

Message

```
Unable to modify the subscriber range table "{subscriberRangeTableId}" with
an operation that modifies a range table from a pricing catalog.
```

Legend

- `{subscriberRangeTableId}`: The identifier of the subcriber range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Implement the appropriate operation that modifies subscriber range tables.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1414 RANGETABLE-148

Message

```
Unable to modify the range table "{rangeTableId}" because it does not exist.
```

Legend

- `{rangeTableId}`: The identifier of the range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an ID of an existing range table to modify it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1415 RANGETABLE-149

Message

```
In the modify operation, the range table class ID
"{rangeTableClassIdFromRevision}"
from the revision "{rangeTableId}" does not correspond to the range table class
ID from the
SAP CC system "{rangeTableClassIdFromSystem}".
```

Legend

- `{rangeTableClassIdFromRevision}`: The range table class ID provided by the revision of the modify operation
- `{rangeTableId}`: The identifier of the range table to modify
- `{rangeTableClassIdFromSystem}`: The range table class ID provided by the range table of the system

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the correct ID of the range table class or let it empty.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1416 RANGETABLE-150

Message

```
The columns #{firstColumnIndex} and #{secondColumnIndex} have the same name
"{columnName}".
```

Legend

- `{firstColumnIndex}`: The first index of column
- `{secondColumnIndex}`: The second index of column
- `{columnName}`: The common column name

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of one of both or remove one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1417 RANGETABLE-151

Message

```
The create operation of a range table is not valid.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the linked error.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1418 RANGETABLE-152

Message

```
The modify operation of range table is not valid.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the linked error.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1419 RANGETABLE-153

Message

```
Unable to modify the range table "{catalogRangeTableId}" from pricing
catalog with an operation that modifies subscriber range tables.
```

Legend

- `{catalogRangeTableId}`: The identifier of the subcriber range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Implement the appropriate operation that modifies a range table of a pricing catalog.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1420 RANGETABLE-154

Message

```
The subscriber range table "{subscriberRangeTableId}" does not exist.
```

Legend

- `{subscriberRangeTableId}`: The identifier of the subscriber range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an ID of an existing subscriber range table to modify it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1421 RANGETABLE-155

Message

```
The create operation of subscriber range table is not valid.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the linked error.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1422 RANGETABLE-156

Message

```
The subscriber account ID is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the identifier of the subscriber account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1423 RANGETABLE-157

Message

```
The service provider name is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the service provider.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1424 RANGETABLE-158

Message

```
The couple subscriber account ID "{subscriberAccountId}" and service provider
"{serviceProviderName}" does not correspond to a subscriber account.
```

Legend

- `{subscriberAccountId}`: The identifier of the subscriber account
- `{serviceProviderName}`: The name of the service provider

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the identifier of the subscriber account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1425 RANGETABLE-159

Message

```
The modify operation of subscriber range table is not valid.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the linked error.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1426 RANGETABLE-160

Message

```
The subscriber account ID "{subscriberAccountId}" is not valid. It should be
"{initialSubscriberAccountId}".
```

Legend

- `{subscriberAccountId}`: The subscriber account ID set in the current subscriber range table revision
- `{initialSubscriberAccountId}`: The subscriber account ID previuosly set in the initial subscriber range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the subscriber account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1427 RANGETABLE-161

Message

```
The service provider name "{subscriberAccountServiceProviderName}" is not valid.
It should be "{initialSubscriberAccountServiceProviderName}".
```

Legend

- `{subscriberAccountServiceProviderName}`: The service provider name set in the current subscriber range table revision
- `{initialSubscriberAccountServiceProviderName}`: The service provider name previously set in the initial subscriber range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the service provider name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1428 RANGETABLE-162

Message

```
The range table row or the range #{unboundedIndex} has no upper bound.
The range table class requires a bounded last range.
```

Legend

- `{unboundedIndex}`: The index of the row or range without upper bound

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an upper bound to the row or to the range.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1429 RANGETABLE-163

Message

```
The range table is not unbounded. The range table class requires unbounded
only tables.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a row or a range without upper bound value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1430 RANGETABLE-229

Message

```
The range table class "{rangeTableClassId}" cannot be deleted because it is
referenced by at least one charge or refill logic, an allowance logic object or
pricing macro.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete the charge(s) and/or refill logic object(s) and/or pricing macro(s) referencing the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1431 RANGETABLE-230

Message

```
The range table "{rangeTableId}" cannot be deleted because it is referenced by
at least one of the following components:
charge component, refill logic, allowance logic, charge plan, refill plan,
pricing macro, or provider contract.
```

Legend

- `{rangeTableId}`: The ID of the range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete the charge(s), refill logic object(s), allowance logic object(s), charge plan(s), refill plan(s), pricing macro(s) and/or provider contract(s) referencing the range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1432 RANGETABLE-231

Message

```
The range table class must have less than {inColumnMax} input columns.
```

Legend

- `{inColumnMax}`: The maximum of input columns that is allowed in the range table class definition

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Delete the additional input columns.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1433 RANGETABLE-232

Message

```
The name of the input column at index {inColumnIndex} is missing.
```

Legend

- `{inColumnIndex}`: The index of the input column within the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the input column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1434 RANGETABLE-233

Message

```
The description of the input column at index {inColumnIndex} is missing.
```

Legend

- `{inColumnIndex}`: The index of the input column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the input column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1435 RANGETABLE-234

Message

```
Impossible to modify the range table class because the number of input columns
{specifiedInColumns} does not correspond to the number of input columns
{realInColumns}
existing in the range table class.
```

Legend

- `{specifiedInColumns}`: The specified number of input columns in the operation
- `{realInColumns}`: The number of input columns existing in the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the number of input columns to the number of input columns of the range table class or create a new range table class for the specified input columns.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1436 RANGETABLE-235

Message

```
You cannot replace the name of the input column "{existingInColumnName}" at
index {inColumnIndex} by "{operationInColumnName}".
```

Legend

- `{existingInColumnName}`: The name of the input column in the range table class
- `{inColumnIndex}`: The index of the input column in the range table class
- `{operationInColumnName}`: The name of the input column within the operation

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the input column in the operation or create a new range table class with an input column having the specified name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1437 RANGETABLE-236

Message

```
The type of the input column is not valid. Only the type
"{expectedRangeTableColumnType}"
is allowed.
```

Legend

- `{inColumnMax}`: The expected type for the range table column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the type of the column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1438 RANGETABLE-237

Message

```
All the rows or range sets with the input values {rangeTableInputValues} have
an upper bound. Because the range table class is unbounded, one row or range set
```

```
for those input
values must be unbounded.
```

Legend

- `{rangeTableInputValues}`: The input values of the range table that must be unbounded

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a row or range set without upper bound.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1439 RANGETABLE-238

Message

```
The ID of the range table is missing in the maintain range set operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the range table to the maintain operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1440 RANGETABLE-239

Message

```
The range table with the ID "{rangeTableId}" given in the maintain operation
does not exist.
```

Legend

- `{rangeTableId}`: The identifier of the range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the ID of an existing range table in the maintain operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1441 RANGETABLE-240

Message

```
The ID of the range table is missing in the delete range set operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the range table to the delete operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1442 RANGETABLE-241

Message

```
The range table with the ID "{rangeTableId}" given in the delete operation
does not exist.
```

Legend

- `{rangeTableId}`: The identifier of the range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the ID of an existing range table in the delete operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1443 RANGETABLE-242

Message

```
The range sets are missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one range set to the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1444 RANGETABLE-243

Message

```
The number of input columns {inputColumnNbOp} does not correspond to the number
of input columns {inputColumnNbClass} declared in the range table class.
```

Legend

- `{inputColumnNbOp}`: The number of input columns in the operation
- `{inputColumnNbClass}`: The number of input columns declared in the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the number of input columns.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1445 RANGETABLE-244

Message

```
The range set #{rangeSetIndex} is not valid.
```

Legend

- `{rangeSetIndex}`: The index of the range set in the operation

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the linked error.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1446 RANGETABLE-245

Message

```
The input column "{inputColumnName}" is missing.
```

Legend

- `{inputColumnName}`: The name of the input column that is missing

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the name of the input columns declared in the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1447 RANGETABLE-246

Message

```
The range #{rangeIndex} is not valid.
```

Legend

- `{rangeIndex}`: The index of the range in the range set

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the linked error.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1448 RANGETABLE-247

Message

```
The ranges are missing in the range set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one range to the range set.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1449 RANGETABLE-248

Message

```
The range set key #{rangeSetKeyIndex} is not valid.
```

Legend

- `{rangeSetKeyIndex}`: The index of the range set key in the operation

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the linked error.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1450 RANGETABLE-249

Message

```
The range set key is missing in the range set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a key to the range set.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1451 RANGETABLE-250

Message

```
The value of the input column #{inputColumnName} is missing.
```

Legend

- `{inputColumnName}`: The name of the input column that doesn't have a value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a value to the input column.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1452 RANGETABLE-251

Message

```
The range sets #{firstRangeSetIndex} and #{secondRangeSetIndex} must not have
the same range set key "{rangeSetKey}".
```

Legend

- `{firstRangeSetIndex}`: The index of the first range set with a duplicated range set key
- `{secondRangeSetIndex}`: The index of the second range set with a duplicated range set key
- `{rangeSetKey}`: The range set key common to both range sets

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the range set key for one of both.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1453 RANGETABLE-252

Message

```
The range set keys are missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least one range set key to the operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1454 RANGETABLE-253

Message

```
You cannot delete all the range sets of a period.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consider modifying the range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1455 RANGETABLE-254

Message

```
You cannot modify the agreement ID "{operationAgreementId}". The agreement
ID of the range table is "{rangeTableAgreementId}".
```

Legend

- `{operationAgreementId}`: The agreement ID in the operation
- `{rangeTableAgreementId}`: The agreement ID of the range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

1. In the operation request, change the agreement ID to the value "{rangeTableAgreementId}" that is indicated in the error message.
2. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

See Also

MAPPINGTABLE-257 [page 2237]

4.1456 RANGETABLE-255

Message

```
The agreement ID cannot be filled only with spaces.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value of the agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1457 RANGETABLE-256

Message

```
You cannot set rows and range sets simultaneously in the range table revision.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set rows or range sets in the range table revision.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1458 RANGETABLE-257

Message

```
Impossible to modify the range table "{rangeTableId}" because the specified
owner {specifiedOwner} does not correspond to the owner {actualOwner} already
configured
in the existing range table.
```

Legend

- `{rangeTableId}`: The ID of the range table to maintain
- `{specifiedOwner}`: The owner specified in the operation request
- `{actualOwner}`: The owner of the existing range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

In the operation request, change the owner to the owner of the range table or create a new range table for the specified owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 6 Patch Level 7 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1459 RANGETABLE-258

Message

```
The range table identifier is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: 258

Related Technical Module: RANGETABLE

RANGETABLE [page 76]

Next Actions and Steps (Troubleshooting)

1. Check the settings of the operation request. Some information is required and was not specified.
2. Change the API call or SOAP Web Services operation consumption.
3. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1460 RANGETABLE-259

Message

```
The comment line mark must be a hash, a dollar, or empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: 259

Related Technical Module: RANGETABLE

RANGETABLE [page 76]

Next Actions and Steps (Troubleshooting)

1. Check the settings of the operation request. Some information is required and was not specified.
   When you work with a comment line at the beginning, specify a hash ('#') or a dollar (`'$'`) character as the comment line mark.
2. Change the API call or SOAP Web Services operation consumption.
3. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging

- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

See Also

MAPPINGTABLE-264 [page 2247]

4.1461 RANGETABLE-260

Message

```
The field delimiter must be a single character, except a double quote.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `260`

Related Technical Module: `RANGETABLE`

`RANGETABLE [page 76]`

Next Actions and Steps (Troubleshooting)

1. Check the settings of the operation request. Some required information is wrong.
   The field delimiter must be a single character.

   > ⓘ Note
   >
   > In the operation request, you cannot specify a double quote as a field delimiter.

2. Change the API call or SOAP Web Services operation consumption.
3. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1462 RANGETABLE-261

Message

```
The decimal separator must be a dot or a comma.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `261`

Related Technical Module: `RANGETABLE`

`RANGETABLE [page 76]`

Next Actions and Steps (Troubleshooting)

1. Check the settings of the operation request. Some required information is wrong.
   The decimal separator must be a dot ('`.`') or a comma ('`,`') character.

   > **Note**
   >
   > In the operation request, specify a valid decimal separator.

2. Change the API call or SOAP Web Services operation consumption.
3. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1463 RANGETABLE-262

Message

```
The field separator must not be the same as the decimal separator.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: 262

Related Technical Module: RANGETABLE

RANGETABLE [page 76]

1. In the operation request, the CSV field separator and the decimal separator cannot be the same. The specified separators must be different to be able to process the CSV content.
2. Check the CSV field separator and the decimal separator that are specified in the operation request. Compare with the data in the CSV content.
3. Change one of these separators in the operation request.
4. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

> See also Deprecated and Revoked Error Codes [page 58].

Similar Message and Error Code

RANGETABLE-265 [page 2567]

See Also

4.1464 RANGETABLE-263

Message

```
The thousand separator must be a dot, a comma, a single quote, a space, or empty.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `263`

Related Technical Module: `RANGETABLE`

`RANGETABLE [page 76]`

Next Actions and Steps (Troubleshooting)

1. Check the settings of the operation request. Some required information is wrong.
   The thousand separator must be one of the following:
   - A dot (`'.'`)
   - A comma (`','`)
   - A single quote (`'`)
   - A space character (`' '`)
   - Empty

   In the operation request, specify a valid thousand separator.

2. Change the API call or SOAP Web Services operation consumption.
3. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1465 RANGETABLE-264

Message

```
The decimal separator must not be the same as the thousand separator.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: 264

Related Technical Module: RANGETABLE

RANGETABLE [page 76]

Next Actions and Steps (Troubleshooting)

1. In the operation request, the decimal separator and the thousand separator cannot be the same. The specified separators must be different to be able to process the CSV content.
2. Check the decimal separator and the thousand separator that are specified in the operation request. Compare with the data in the CSV content.
3. Change one of these separators in the operation request.
4. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1466 RANGETABLE-265

Message

```
The field separator must not be the same as the thousand separator.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: 265

Related Technical Module: RANGETABLE

RANGETABLE [page 76]

1. In the operation request, the CSV field separator and the thousand separator cannot be the same. The specified separators must be different to be able to process the CSV content.
2. Check the CSV field separator and the thousand separator that are specified in the operation request. Compare with the data in the CSV content.
3. Change one of these separators in the operation request.
4. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

> See also Deprecated and Revoked Error Codes [page 58].

Similar Message and Error Code

RANGETABLE-262 [page 2562]

See Also

4.1467 RANGETABLE-266

Message

```
The CSV content representing the range table rows is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `266`

Related Technical Module: `RANGETABLE`

`RANGETABLE [page 76]`

Next Actions and Steps (Troubleshooting)

1. Check the CSV content in the operation request.
2. Check why it is empty.
3. Change the CSV content or the implementation.
4. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1468 RANGETABLE-267

Message

```
Cannot parse the token "{csvFieldIndex}" of the range table row "{csvRowLine}".
{errorMessageDetails}
```

Legend

- `{csvFieldIndex}`: The index of the CSV field in error
- `{csvRowLine}`: The number of the CSV line in error
- `{errorMessageDetails}`: The message detailing the error

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Related Error Code: `267`

Related Technical Module: `RANGETABLE`

`RANGETABLE [page 76]`

Next Actions and Steps (Troubleshooting)

1. Carefully read the part of the message that details the error. This information is added by the system to the error message for troubleshooting purpose.
2. Check the CSV content.
3. Check the line indicated in the error message.
   In this line, check the data at the position indicated.
4. Change the CSV content.
5. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

See Also

MAPPINGTABLE-263 [page 2245]

4.1469 RANGETABLE-268

Message

```
The value "{value}" cannot be formatted as a number.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Legend

- `{value}`: The value that cannot be formatted as a number

Related Error Code: 268

Related Technical Module: RANGETABLE

`RANGETABLE [page 76]`

Next Actions and Steps (Troubleshooting)

1. Check the CSV content in the operation request.
2. Check the settings of the request: decimal separator, thousand separator.
3. Change the CSV content or the implementation.
4. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1470 RANGETABLE-269

Message

```
Failed to read the CSV content representing the range table rows.
{errorMessageDetails}
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Legend

- `{errorMessageDetails}`: The message detailing the error

Related Error Code: 269

Related Technical Module: RANGETABLE

RANGETABLE [page 76]

Next Actions and Steps (Troubleshooting)

1. Carefully read the part of the message that details the error. This information is added to the error message for troubleshooting purpose.
2. Check and change the CSV content.
3. Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2023 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1471 RANGETABLECOMPONENT-1

Message

```
The ID of the range table class is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the identifier of the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1472 RANGETABLECOMPONENT-2

Message

```
Both range table ID and range table ID property name are missing. At least one
of them must be defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up a range table ID or a range table ID property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1473 RANGETABLECOMPONENT-3

Message

```
Both range table ID and range table ID property name are defined. Only one
of them must be defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up a range table ID or a range table ID property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1474 RANGETABLECOMPONENT-4

Message

```
The range table class "{rangeTableClassId}" does not exist.
```

Legend

- `{rangeTableClassId}`: The ID of the range table class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1475 RANGETABLECOMPONENT-5

Message

```
The range table ID defined by a charge component parameter named
"{rangeTableIdPropertyName}"
does not exist.
```

Legend

- `{rangeTableIdPropertyName}`: The name of the range table ID parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a parameter in the charge component or define a range table ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1476 RANGETABLECOMPONENT-6

Message

```
The range table "{rangeTableId}" does not exist.
```

Legend

- `{rangeTableId}`: The ID of the range table

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the identifier of the range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1477 RANGETABLECOMPONENT-7

Message

```
The reference date property name is not defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the reference date property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1478 RANGETABLECOMPONENT-8

Message

```
The reference date property name "{referenceDatePropertyName}" does not
reference an existing rating context property.
```

Legend

- `{referenceDatePropertyName}`: The name of the reference date parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the reference date property name to an existing rating context property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1479 RANGETABLECOMPONENT-9

Message

```
The input property name is not defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the input property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1480 RANGETABLECOMPONENT-10

Message

```
The input property name "{inputPropertyName}" does not reference an existing
rating context property.
```

Legend

- `{inputPropertyName}`: The name of the input parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the input property name to an existing rating context property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1481 RANGETABLECOMPONENT-11

Message

```
The default output mapping property name "{defaultOutputMappingName}" at
index "{defaultOutputMappingIndex}" is not defined.
```

Legend

- `{defaultOutputMappingName}`: The name of the default output mapping property
- `{defaultOutputMappingIndex}`: The index of the default output mapping property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the default output property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1482 RANGETABLECOMPONENT-12

Message

```
The default output mapping property name "{defaultOutputMappingName}" at
index "{defaultOutputMappingIndex}" is already defined as a number rating
context property.
```

Legend

- `{defaultOutputMappingName}`: The name of the default output mapping property
- `{defaultOutputMappingIndex}`: The index of the default output mapping property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the default output property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1483 RANGETABLECOMPONENT-13

Message

```
The output mapping is mandatory and must contain rating context property
names that match range table class: "{outputMappingCount}".
```

Legend

- `{outputMappingCount}`: The number of output mapping properties to define

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up a rating context property name for each string or single number range table class column. Add the mapping for each column that is cumulative or range size cumulative.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1484 RANGETABLECOMPONENT-14

Message

```
The output mapping property name "{outputMappingName}" at index
"{outputMappingIndex}"
is not defined.
```

Legend

- `{outputMappingName}`: The name of the output mapping property
- `{outputMappingIndex}`: The index of the output mapping property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the output property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1485 RANGETABLECOMPONENT-15

Message

```
The output mapping property name "{outputMappingName}" at index
"{outputMappingIndex}"
of range table class column name "{rangeTableClassColumnName}" is already
defined as a
string rating context property.
```

Legend

- `{outputMappingName}`: The name of the output mapping property
- `{outputMappingIndex}`: The index of the output mapping property
- `{rangeTableClassColumnName}`: The name of the range table class column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the output property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1486 RANGETABLECOMPONENT-16

Message

```
The output mapping property name "{outputMappingName}" at index
"{outputMappingIndex}"
of range table class column name "{rangeTableClassColumnName}" is already
defined as a number
rating context property.
```

Legend

- `{outputMappingName}`: The name of the output mapping property
- `{outputMappingIndex}`: The index of the output mapping property

- `{rangeTableClassColumnName}`: The name of the range table class column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the output property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1487 RANGETABLECOMPONENT-17

Message

```
The output mapping for cumulative or range-size cumulative number property name
"{outputMappingName}" at index "{outputMappingIndex}" is not defined.
```

Legend

- `{outputMappingName}`: The name of the output mapping property
- `{outputMappingIndex}`: The index of the output mapping property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the output property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1488 RANGETABLECOMPONENT-18

Message

```
The output mapping for cumulative or range-size cumulative number property name
"{outputMappingName}" at index "{outputMappingIndex}" of range table class
column name
```

```
"{rangeTableClassColumnName}" is already defined as a number rating context
property.
```

Legend

- `{outputMappingName}`: The name of the output mapping property
- `{outputMappingIndex}`: The index of the output mapping property
- `{rangeTableClassColumnName}`: The name of the range table class column

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the output property name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1489 RANGETABLECOMPONENT-19

Message

```
The mapping "{outputMappingName}" defined for default output mapping property
"{defaultOutputMappingName}" is already used by the default output mapping
property
"{duplicatedDefaultOutputMappingName}".
```

Legend

- `{outputMappingName}`: The name of the output mapping property
- `{defaultOutputMappingName}`: The name of the default output mapping property
- `{duplicatedDefaultOutputMappingName}`: The name of the duplicated default output mapping property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1490 RANGETABLECOMPONENT-20

Message

```
The mapping "{outputMappingName}" defined for output mapping property at index
"{outputMappingIndex}" of range table class column name
"{rangeTableClassColumnName}" is already
used by the default output mapping property
"{duplicatedDefaultOutputMappingName}".
```

Legend

- `{outputMappingName}`: The name of the output mapping property
- `{outputMappingIndex}`: The index of the output mapping property
- `{rangeTableClassColumnName}`: The name of the range table class column
- `{duplicatedDefaultOutputMappingName}`: The name of the duplicated default output mapping property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1491 RANGETABLECOMPONENT-21

Message

```
The mapping "{outputMappingName}" defined for output mapping property at
index "{outputMappingIndex}" of range table class column name
"{rangeTableClassColumnName}"
is already used by the output mapping property at index
"{duplicatedOutputMappingName}".
```

Legend

- `{outputMappingName}`: The name of the output mapping property
- `{outputMappingIndex}`: The index of the output mapping property
- `{rangeTableClassColumnName}`: The name of the range table class column
- `{duplicatedDefaultOutputMappingName}`: The name of the duplicated default output mapping property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1492 RANGETABLECOMPONENT-22

Message

```
The range table class "{rangeTableClassIdFromParameter}" referenced in the
parameter "{parameterName}" does not correspond to the range table class
"{rangeTableClassIdFromRateComponent}"
defined in the rate component.
```

Legend

- `{rangeTableClassIdFromParameter}`: The ID of the range table class from the parameter
- `{parameterName}`: The name of the parameter
- `{rangeTableClassIdFromRateComponent}`: The ID of the range table class from the rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the same range table class in the parameter and in the component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1493 RANGETABLECOMPONENT-23

Message

```
The range table class "{rangeTableClassIdFromParameter}" from range table
"{parameterName}" does not correspond to the range table class
"{rangeTableClassIdFromRateComponent}"
defined in the rate component.
```

Legend

- `{rangeTableClassIdFromParameter}`: The ID of the range table class from the parameter
- `{parameterName}`: The name of the parameter
- `{rangeTableClassIdFromRateComponent}`: The ID of the range table class from the rate component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up the same range table class in the parameter and in the component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1494 RANGETABLECOMPONENT-24

Message

```
The rating context property "{rangeTableIdPropertyName}" defining a range
table ID does not include the mandatory additional information "{addInfoName}".
```

Legend

- `{rangeTableIdPropertyName}`: The name of the range table ID rating context property
- `{addInfoName}`: The name of the data type additional information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the additional information to this property specified in the logic component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1495 RANGETABLECOMPONENT-25

Message

```
The input mapping is mandatory and must contain rating context property names
that match range table class: "{inputMappingCount}".
```

Legend

- `{inputMappingCount}`: The number of input mapping properties to define

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up a rating context property name for each input column of the range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1496 RANGETABLECOMPONENT-26

Message

```
The property name "{inputMappingPropertyName}" defined for the input mapping
does not reference an existing rating context property of type String.
```

Legend

- `{inputMappingPropertyName}`: The name of the input mapping property

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up an existing property name of type String that exist in the rating context for the input mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1497 RANGETABLECOMPONENT-27

Message

```
You cannot set input mapping when the range table class does not have input
columns.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the input mapping properties.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 1 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1498 RANGETABLECOMPONENT-28

Message

```
The component cannot reference the range table "{rangeTable}" because
this range table has an agreement ID.
```

Legend

- `{rangeTable}`: The name of the range table referenced by the component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1499 REFILLPLAN-1

Message

```
The Refill Plan is missing in the CreateRefillPlanOp. The Refill Plan is missing
in the CreateRefillPlanOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Plan to the CreateRefillPlanOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1500 REFILLPLAN-2

Message

```
The id of the Refill Plan is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1501 REFILLPLAN-3

Message

```
The owner of the Refill Plan "{refillPlanId}" is missing.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the owner of the Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1502 REFILLPLAN-4

Message

```
The description of the Refill Plan "{refillPlanId}" is missing.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1503 REFILLPLAN-5

Message

```
Error while validating the Refill Plan "{refillPlanId}".
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1504 REFILLPLAN-6 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.
>
> **Replaced by:**
>
> - HCI-1 [page 2031]

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The name of the Additional Information at index {additionalInformationIndex}
is missing.
```

Legend

- `{additionalInformationIndex}`: The index of the Additional Information in the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Additional Information item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1505 REFILLPLAN-7 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.
>
> **Replaced by:**
>
> - HCI-2 [page 2032]

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The name "{additionalInformationName}" of the Additional Information at
index {secondIndex} is already used by the Additional Information at index
{firstIndex}.
```

Legend

- `{additionalInformationIndex}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in the Additional Information
- `{firstIndex}`: The index of the first occurrence of the name in the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

Related Information

HCI-2 [page 2032]

4.1506 REFILLPLAN-8 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The description of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1507 REFILLPLAN-9 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The type of the Additional Information "{additionalInformationName}" at
index {additionalInformationIndex} is missing or unknown (the supported types
```

```
are string,
number, date).
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Additional Information or change it into a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1508 REFILLPLAN-10 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The date value of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date value to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1509 REFILLPLAN-11 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The number value of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1510 REFILLPLAN-12 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The string value of the Additional Information "{additionalInformationName}"
at index {additionalInformationIndex} is missing.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1511 REFILLPLAN-13 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The type "{additionalInformationType}" of the Additional Information
"{additionalInformationName}" at index {additionalInformationIndex} is
unsupported (the
supported types are string, number, date).
```

Legend

- `{additionalInformationType}`: The unsupported type of the Additional Information
- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date) for the Additional Information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1512 REFILLPLAN-14

Message

```
The name of the Parameter at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter in the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1513 REFILLPLAN-15

Message

```
The name "{parameterName}" of the Parameter at index {secondIndex} is already
used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Parameters
- `{firstIndex}`: The index of the first occurrence of the name in Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1514 REFILLPLAN-16

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex} is
missing or unknown (the supported types are string, number, date, currency).
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter or change it into a supported one: string, number, date, currency.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1515 REFILLPLAN-18

Message

```
The description of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1516 REFILLPLAN-22

Message

```
The type "{parameterType}" of the Parameter "{parameterName}" at index
{parameterIndex} is unsupported (the supported types are string, number, date,
currency).
```

Legend

- `{parameterType}`: The unsupported type of the Parameter
- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date, currency) for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1517 REFILLPLAN-23

Message

```
Parameter "{parameterName}" at index {parameterIndex} is not linked to a
Parameter Reference of the Refill Plan Item.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Parameter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1518 REFILLPLAN-24

Message

```
The name of the Counter at index {counterIndex} is missing.
```

Legend

- `{counterIndex}`: The index of the Counter in the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1519 REFILLPLAN-25

Message

```
The name "{counterName}" of the Counter at index {secondIndex} is already
used by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Counters
- `{firstIndex}`: The index of the first occurrence of the name in Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1520 REFILLPLAN-26

Message

```
The initial value of the Counter "{counterName}" at index {counterIndex}
is missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an initial value to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1521 REFILLPLAN-28

Message

```
The description of the Counter "{counterName}" at index {counterIndex}
is missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1522 REFILLPLAN-29

Message

```
The Counter "{counterName}" at index {counterIndex} does not refer to a
Counter Reference of the Refill Plan Item.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Counter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1523 REFILLPLAN-30

Message

```
The name of the Account Assignment at index {accountAssignmentIndex}
is missing.
```

Legend

- `{accountAssignmentIndex}`: The index of the Account Assignment in the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1524 REFILLPLAN-31

Message

```
The name "{accountAssignmentName}" of the Account Assignment at index
{secondIndex} is already used by the Account Assignment at index {firstIndex}.
```

Legend

- `{accountAssignmentName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Account Assignments
- `{firstIndex}`: The index of the first occurrence of the name in Account Assignments

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1525 REFILLPLAN-32

Message

```
The type of the Account Assignment "{accountAssignmentName}" at index
{accountAssignmentIndex} is invalid, missing or unknown (the supported type is
prepaid).
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{accountAssignmentIndex}`: The index of the Account Assignment

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Account Assignment or set it to prepaid.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1526 REFILLPLAN-33

Message

```
The description of the Account Assignment "{accountAssignmentName}" at
index {accountAssignmentIndex} is missing.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{accountAssignmentIndex}`: The index of the Account Assignment

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1527 REFILLPLAN-34

Message

```
The Account Assignment "{accountAssignmentName}" at index
{accountAssignmentIndex}
does not refer to an Account Assignment Reference of the Refill Plan Item.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment

- `{accountAssignmentIndex}`: The index of the Account Assignment

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Account Assignment or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1528 REFILLPLAN-35

Message

```
The name of the User Technical Identifier at index {userTechIdIndex} is
missing.
```

Legend

- `{userTechIdIndex}`: The index of the User Technical Identifier in the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the User Technical Identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1529 REFILLPLAN-36

Message

```
The name "{userTechIdName}" of the User Technical Identifier at index
{secondIndex} is already used by the User Technical Identifier at index
{firstIndex}.
```

Legend

- `{userTechIdName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in User Technical Identifiers
- `{firstIndex}`: The index of the first occurrence of the name in User Technical Identifiers

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the User Technical Identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1530 REFILLPLAN-37

Message

```
The description of the User Technical Identifier "{userTechIdName}" at
index {userTechIdIndex} is missing.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{userTechIdIndex}`: The index of the User Technical Identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a description to the User Technical Identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1531 REFILLPLAN-38

Message

```
The User Technical Identifier "{userTechIdName}" at index {userTechIdIndex}
does not refer to a User Technical Identifier Reference of the Refill Plan Item.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{userTechIdIndex}`: The index of the User Technical Identifier

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the User Technical Identifier or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1532 REFILLPLAN-39

Message

```
The id of the Refill Plan Item at index {refillPlanItemIndex} is missing.
```

Legend

- `{refillPlanItemIndex}`: The index of the Refill Plan Item in the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an id to the Refill Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1533 REFILLPLAN-40

Message

```
The id "{refillPlanItemId}" of the Refill Plan Item at index {secondIndex}
is already used by the Refill Plan Item at index {firstIndex}.
```

Legend

- `{refillPlanItemId}`: The duplicated ID
- `{secondIndex}`: The index of the second occurrence of the name in Refill Plan Items
- `{firstIndex}`: The index of the first occurrence of the name in Refill Plan Items

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the Refill Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1534 REFILLPLAN-43

Message

```
No Refill Logic is referred to by the Refill Plan Item "{refillPlanItemId}"
at index {refillPlanItemIndex}.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Logic to the Refill Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1535 REFILLPLAN-44

Message

```
The id of the master Refill Logic referred to by the Refill Plan Item
"{refillPlanItemId}" at index {refillPlanItemIndex} is missing.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an ID to the master Refill Logic in the Refill Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1536 REFILLPLAN-45

Message

```
The Refill Plan Item "{refillPlanItemId}" must define one and only one
Account Assignment Reference.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Define one Account Assignment Reference for the Refill Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1537 REFILLPLAN-48

Message

```
Error while validating the Refill Plan Item "{refillPlanItemId}" at index
{refillPlanItemIndex}.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1538 REFILLPLAN-49

Message

```
The name of the Parameter at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter in the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1539 REFILLPLAN-50

Message

```
The name "{parameterName}" of the Parameter at index {secondIndex} is already
used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Parameters
- `{firstIndex}`: The index of the first occurrence of the name in Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1540 REFILLPLAN-51

Message

```
The type of the Parameter "{parameterName}" at index {parameterIndex}
is missing or unknown (the supported types are string, number, date).
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter or change it into a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1541 REFILLPLAN-52

Message

```
The date value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a date value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1542 REFILLPLAN-53

Message

```
The number value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a number value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1543 REFILLPLAN-54

Message

```
The string value of the Parameter "{parameterName}" at index {parameterIndex}
is missing.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a string value to the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1544 REFILLPLAN-55

Message

```
The type "{parameterType}" of the Parameter "{parameterName}" at index
{parameterIndex} is unsupported (the supported types are string, number, date).
```

Legend

- `{parameterType}`: The unsupported type of the Parameter
- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date) for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1545 REFILLPLAN-56

Message

```
The name of the Parameter Reference at index {parameterIndex} is missing.
```

Legend

- `{parameterIndex}`: The index of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1546 REFILLPLAN-57

Message

```
The name "{parameterReferenceName}" of the Parameter Reference at index
{secondIndex} is already used by the Parameter at index {firstIndex}.
```

Legend

- `{parameterReferenceName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Parameters
- `{firstIndex}`: The index of the first occurrence of the name in Parameters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1547 REFILLPLAN-58

Message

```
The target name of the Parameter Reference "{parameterReferenceName}" at
index {parameterReferenceIndex} is missing.
```

Legend

- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1548 REFILLPLAN-59

Message

```
The Parameter "{targetName}" targeted by the Parameter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} does not exist.
```

Legend

- `{targetName}`: The target name of the Parameter Reference
- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the Parameter Reference into an existing one or create a new Parameter in the Refill Plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1549 REFILLPLAN-60

Message

```
The type of the Parameter Reference "{parameterReferenceName}" at index
{parameterReferenceIndex} is missing or unknown (the supported types are string,
number, date).
```

Legend

- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Parameter Reference or change it into a supported one: string, number, date.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1550 REFILLPLAN-61

Message

```
The type "{parameterReferenceType}" of the Parameter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} is not compatible with the type
"{parameterType}" of
the targeted Parameter.
```

Legend

- `{parameterReferenceType}`: The type of the Parameter Reference
- `{parameterReferenceName}`: The name of the Parameter Reference
- `{parameterReferenceIndex}`: The index of the Parameter Reference
- `{parameterType}`: The type of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Parameter Reference to a compatible Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1551 REFILLPLAN-62

Message

```
The name of the Counter at index {counterIndex} is missing.
```

Legend

- `{counterIndex}`: The index of the Counter in the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1552 REFILLPLAN-63

Message

```
The name "{counterName}" of the Counter at index {secondIndex} is already
used by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Counters
- `{firstIndex}`: The index of the first occurrence of the name in Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1553 REFILLPLAN-64

Message

```
The initial value of the Counter "{counterName}" at index {counterIndex}
is missing.
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add an initial value to the Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1554 REFILLPLAN-65

Message

```
The name of the Counter Reference at index {counterReferenceIndex} is
missing.
```

Legend

- `{counterReferenceIndex}`: The index of the Counter Reference in the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1555 REFILLPLAN-66

Message

```
The name "{counterName}" of the Counter Reference at index {secondIndex} is
already used by the Counter at index {firstIndex}.
```

Legend

- `{counterName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Counters
- `{firstIndex}`: The index of the first occurrence of the name in Counters

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1556 REFILLPLAN-67

Message

```
The target name of the Counter Reference "{counterReferenceName}" at index
{counterReferenceIndex} is missing.
```

Legend

- `{counterReferenceName}`: The name of the Counter Reference
- `{counterReferenceIndex}`: The index of the Counter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1557 REFILLPLAN-68

Message

```
The Counter "{targetName}" targeted by the Counter Reference
"{parameterReferenceName}"
at index {parameterReferenceIndex} does not exist.
```

Legend

- `{targetName}`: The target name of the Counter Reference
- `{parameterReferenceName}`: The name of the Counter Reference
- `{parameterReferenceIndex}`: The index of the Counter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the Counter Reference into an existing one or create a new Counter in the Refill Plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1558 REFILLPLAN-69

Message

```
The name of the Account Assignment Reference at index
{accountAssignmentReferenceIndex}
is missing.
```

Legend

- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference in the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Account Assignment Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1559 REFILLPLAN-70

Message

```
The name "{accountAssignmentReferenceName}" of the Account Assignment Reference
at index {secondIndex} is already used by the Account Assignment Reference at
index {firstIndex}.
```

Legend

- `{accountAssignmentReferenceName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Account Assignment References
- `{firstIndex}`: The index of the first occurrence of the name in Account Assignment References

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Account Assignment Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1560 REFILLPLAN-71

Message

```
The target name of the Account Assignment Reference
"{accountAssignmentReferenceName}"
at index {accountAssignmentReferenceIndex} is missing.
```

Legend

- `{accountAssignmentReferenceName}`: The name of the Account Assignment Reference
- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the Account Assignment Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1561 REFILLPLAN-72

Message

```
The Account Assignment "{targetName}" targeted by the Account Assignment
Reference
"{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex}
does not exist.
```

Legend

- `{targetName}`: The target name of the Account Assignment Reference
- `{accountAssignmentReferenceName}`: The name of the Account Assignment Reference
- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the Account Assignment Reference into an existing one or create a new Account Assignment in the Refill Plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1562 REFILLPLAN-73

Message

```
The type of the Account Assignment Reference "{accountAssignmentReferenceName}"
at index {accountAssignmentReferenceIndex} is missing, invalid or unknown (the
supported type
is prepaid).
```

Legend

- `{accountAssignmentReferenceName}`: The name of the Account Assignment Reference
- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Account Assignment Reference or change it into prepaid.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1563 REFILLPLAN-74

Message

```
The type "{accountAssignmentReferenceType}" of the Account Assignment Reference
"{accountAssignmentReferenceName}" at index {accountAssignmentReferenceIndex} is
not
compatible with the type "{accountAssignmentType}" of the targeted Account
Assignment.
```

Legend

- `{accountAssignmentReferenceType}`: The type of the Account Assignment Reference
- `{accountAssignmentReferenceName}`: The name of the Account Assignment Reference
- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference
- `{accountAssignmentType}`: The type of the Account Assignment

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Link the Account Assignment Reference to a compatible Account Assignment.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1564 REFILLPLAN-75

Message

```
The service name of the User Technical Identifier Reference at index
{userTechnicalIdentifierReferenceIndex} is missing.
```

Legend

- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference in the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a service name to the User Technical Identifier Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1565 REFILLPLAN-76

Message

```
The service "{userTechnicalIdentifierReferenceService}" of the User Technical
Identifier Reference at index {secondIndex} is already used by the User
Technical Identifier
Reference at index {firstIndex}.
```

Legend

- `{userTechnicalIdentifierReferenceService}`: The duplicated service
- `{secondIndex}`: The index of the second occurrence of the name in User Technical Identifier References
- `{firstIndex}`: The index of the first occurrence of the name in User Technical Identifier References

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the service of the User Technical Identifier Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1566 REFILLPLAN-77

Message

```
The target name of the User Technical Identifier Reference
"{userTechnicalIdentifierReferenceName}" at index
```

```
{userTechnicalIdentifierReferenceIndex}
is missing.
```

Legend

- `{userTechnicalIdentifierReferenceName}`: The name of the User Technical Identifier Reference
- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a target name to the User Technical Identifier Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1567 REFILLPLAN-78

Message

```
The User Technical Identifier "{targetName}" targeted by the User Technical
Identifier Reference "{userTechnicalIdentifierReferenceService}" at index
{userTechnicalIdentifierReferenceIndex} does not exist.
```

Legend

- `{targetName}`: The target name of the User Technical Identifier Reference
- `{userTechnicalIdentifierReferenceService}`: The service of the User Technical Identifier Reference
- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the target name of the User Technical Identifier Reference into an existing one or create a new User Technical Identifier in the Refill Plan with this target name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1568 REFILLPLAN-79

Message

```
The Refill Record Mapping is missing in the Refill Plan Item.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the Refill Record Mapping of the Refill Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1569 REFILLPLAN-80

Message

```
The class of the Refill Record Mapping is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a class to the Refill Record Mapping.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1570 REFILLPLAN-81

Message

```
Error while validating the Refill Record Mapping of class "{citcClass}".
```

Legend

- `{citcClass}`: The class of the Refill Record Mapping

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1571 REFILLPLAN-82

Message

```
The name of the Refill Record Mapping Entry at index
{chargedItemMappingEntryIndex}
is missing.
```

Legend

- `{chargedItemMappingEntryIndex}`: The index of the Refill Record Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Refill Record Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1572 REFILLPLAN-83

Message

```
The name "{chargedItemMappingEntryName}" of the Refill Record Mapping Entry
at index {secondIndex} is already used by the Refill Record Mapping Entry at
index {firstIndex}.
```

Legend

- `{chargedItemMappingEntryName}`: The duplicated name
- `{secondIndex}`: The index of the second occurrence of the name in Refill Record Mapping Entries
- `{firstIndex}`: The index of the first occurrence of the name in Refill Record Mapping Entries

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Refill Record Mapping Entry.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1573 REFILLPLAN-84

Message

```
The type of the Refill Record Mapping Entry "{chargedItemMappingEntryName}"
at index {chargedItemMappingEntryIndex} is missing or unknown (the supported
types are string,
number, date, boolean).
```

Legend

- `{chargedItemMappingEntryName}`: The name of the Refill Record Mapping Entry
- `{chargedItemMappingEntryIndex}`: The index of the Refill Record Mapping Entry

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Refill Record Mapping Entry or change it into a supported one: string, number, date, boolean.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1574 REFILLPLAN-91

Message

```
The Refill Plan "{refillPlanId}" already exists.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan that already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use another ID or use the ModifyRefillPlanOp to modify the Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1575 REFILLPLAN-92

Message

```
The id of the Refill Plan is missing in the DeleteRefillPlanOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of the Refill Plan to the DeleteRefillPlanOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1576 REFILLPLAN-93

Message

```
The Refill Plan "{refillPlanId}" cannot be deleted because it does not exist.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan that needs to be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing ID for the Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1577 REFILLPLAN-94

Message

```
Error while deleting the Refill Plan "{refillPlanId}". The Refill Plan
is still linked to one or more Charging Contract Items.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan that needs to be deleted

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete all Charging Contract Items referring to the Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1578 REFILLPLAN-96

Message

```
The Account Assignment at the index {accountAssignmentIndex} is empty.
```

Legend

- `{accountAssignmentIndex}`: The index of the empty Account Assignment that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Account Assignment or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1579 REFILLPLAN-97 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.
>
> **Replaced by:**
>
> - HCI-9 [page 2043]

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The Additional Info at the index {additionalInfoIndex} is empty.
```

Legend

- `{additionalInfoIndex}`: The position index of the empty Additional Information item that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Additional Information item or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP00. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1580 REFILLPLAN-104

Message

```
The Counter at the index {counterIndex} is empty.
```

Legend

- `{counterIndex}`: The index of the empty Counter that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Counter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1581 REFILLPLAN-106

Message

```
The Parameter at the index {parameterIndex} is empty.
```

Legend

- `{parameterIndex}`: The index of the empty Counter that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Parameter or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1582 REFILLPLAN-108

Message

```
The User Technical Identifier at the index {userTechnicalIdentifierIndex} is
empty.
```

Legend

- `{userTechnicalIdentifierIndex}`: The index of the empty User Technical Identifier that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid User Technical Identifier or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1583 REFILLPLAN-109

Message

```
The Refill Plan Item at the index {refillPlanItemIndex} is empty.
```

Legend

- `{refillPlanItemIndex}`: The index of the empty Refill Plan Item that needs to be changed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Replace it by a valid Refill Plan Item or remove it.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1584 REFILLPLAN-110

Message

```
The id of the Refill Logic referred to by the Refill Plan Item
"{refillPlanItemId}"
at index {refillPlanItemIndex} does not match any Refill Logic.
```

Legend

- `{refillPlanItemId}`: The id of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of the existing Refill Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1585 REFILLPLAN-115

Message

```
The id of the master Refill Logic referred to by the Refill Plan Item
"{refillPlanItemId}"
at index {refillPlanItemIndex} and the code "{retrievedRefillLogicCode}" of the
retrieved
Refill Logic do not match.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item

- `{retrievedRefillLogicCode}`: The code of the retrieved Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1586 REFILLPLAN-117

Message

```
The owner of the Refill Plan and the owner of the Refill Logic referred to
by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} do
not match.
The owner of the Refill Plan is "{refillPlanOwner}". The owner of the Refill
Logic is
"{refillLogicOwner}".
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item
- `{refillPlanOwner}`: The owner of the Refill Plan
- `{refillLogicOwner}`: The owner of the Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the id the master Refill Logic that has the same owner as the Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1587 REFILLPLAN-118

Message

```
The mandatory filter in the SearchRefillPlanOp is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the filter to the SearchRefillPlanOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1588 REFILLPLAN-119

Message

```
An error occurred during the execution of the SearchRefillPlanOp: {errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1589 REFILLPLAN-120

Message

```
The mandatory filter in the SearchRefillPlanClassOp is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the filter to the SearchRefillPlanClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1590 REFILLPLAN-121

Message

```
An error occurred during the execution of the SearchRefillPlanClassOp:
{errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1591 REFILLPLAN-126

Message

```
The Counter "{counterName}" at index {counterIndex} does not exist in
the Refill Logic "{refillLogicId}".
```

Legend

- `{counterName}`: The name of the Counter
- `{counterIndex}`: The index of the Counter

- `{refillLogicId}`: The ID of the Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1592 REFILLPLAN-127

Message

```
The Counter Reference "{counterRefName}" at index {counterRefIndex} does not
exist in the Refill Logic "{refillLogicId}".
```

Legend

- `{counterRefName}`: The name of the Counter Reference
- `{counterRefIndex}`: The index of the Counter Reference
- `{refillLogicId}`: The ID of the Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Counter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1593 REFILLPLAN-128

Message

```
The Parameter "{parameterName}" at index {parameterIndex} does not exist
in the Refill Logic "{refillLogicId}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{refillLogicId}`: The ID of the Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1594 REFILLPLAN-129

Message

```
The Parameter Reference "{parameterRefName}" at index {parameterRefIndex}
does not exist in the Refill Logic "{refillLogicId}".
```

Legend

- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference
- `{refillLogicId}`: The ID of the Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this Parameter Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1595 REFILLPLAN-130

Message

```
User Technical Identifiers are defined while no usage refill is assigned to
the Refill Logic "{refillLogicId}".
```

Legend

- `{refillLogicId}`: The ID of the Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the User Technical Identifiers.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1596 REFILLPLAN-132

Message

```
The Refill Plan is missing in the ModifyRefillPlanOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Plan to the ModifyRefillPlanOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1597 REFILLPLAN-133

Message

```
The Refill Plan with the id {refillPlanId} does not exist.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan which does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the ID of the Refill Plan into an existing one or first create the Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1598 REFILLPLAN-134

Message

```
Impossible to modify the Refill Plan because the specified owner
{specifiedOwner}
    does not correspond to the owner {realOwner} existing in the Refill Plan.
```

Legend

- `{specifiedOwner}`: The specified owner in the operation
- `{realOwner}`: The owner existing in the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the owner into the owner of the Refill Plan or create a new Refill Plan for the specified owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1599 REFILLPLAN-135

Message

```
The Refill Logic "{refillLogicId}" referred to by the Refill Plan Item
"{refillPlanItemId}" at index {refillPlanItemIndex} is unknown.
```

Legend

- `{refillLogicId}`: The ID of the Refill Logic
- `{refillPlanItemId}`: The ID of the Charging Contract Item
- `{refillPlanItemIndex}`: The index of the Charging Contract Item in the Charging Contract

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the refillLogicId into an existing Refill Logic identifier.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1600 REFILLPLAN-136

Message

```
Internal server error. Impossible to modify the Refill Plan because the Refill
Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} refers to no known
Refill
Logic.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item in the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1601 REFILLPLAN-138

Message

```
The Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} already
refers to the Refill Logic "{originalRefillLogicId}" and cannot refer to the
Refill Logic
"{newRefillLogicId}" at the same time.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item in the Refill Plan
- `{originalRefillLogicId}`: The original ID of the Refill Logic
- `{newRefillLogicId}`: The new ID of the Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the Refill Logic already referred to by the Refill Plan Item or create a new Refill Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1602 REFILLPLAN-140

Message

```
Refill Plan "{refillPlanId}" must define one and only one Refill Plan Item.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a Refill Plan Item.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1603 REFILLPLAN-142

Message

```
The status of the Refill Plan "{refillPlanId}" is missing.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a status to the Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1604 REFILLPLAN-143

Message

```
The status of new Refill Plan "{refillPlanId}" must be set to open.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new Refill Plan to open.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1605 REFILLPLAN-144

Message

```
The Refill Plan "{refillPlanId}" whose status is already set to released
cannot be set back to open.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new Refill Plan to released or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1606 REFILLPLAN-145

Message

```
The Refill Plan "{refillPlanId}" whose status is already set to obsolete
cannot be set back to open.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new Refill Plan to released or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1607 REFILLPLAN-146

Message

```
The Refill Plan "{refillPlanId}" whose status is already set to obsolete cannot
be set back to released.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the status of this new Refill Plan to released or obsolete.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1608 REFILLPLAN-147

Message

```
The name of the Account Assignment Reference at index
{accountAssignmentReferenceIndex}
differs from the only one ({defaultReference}) available in the Refill Logic.
```

Legend

- `{accountAssignmentReferenceIndex}`: The index of the Account Assignment Reference within the Refill Plan Item
- `{defaultReference}`: The Refill Logic default reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a valid name to the Account Assignment Reference.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1609 REFILLPLAN-170

Message

```
The parameter additional information "{additionalInformationName}" at index
{additionalInformationIndex} is unknown.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{additionalInformationIndex}`: The index of the Additional Information

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove this additional information or replace it with a known one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1610 REFILLPLAN-171

Message

```
The data type of the parameter is not defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add this additional information or remove all additional informations.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1611 REFILLPLAN-172

Message

```
The parameter is a mapping table ID but no mapping table class is defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the mapping table class additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1612 REFILLPLAN-173

Message

```
The parameter is a mapping table key and could not be linked to a mapping
table class.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the mapping table class additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1613 REFILLPLAN-174

Message

```
The parameter cannot declare additional informations without a data type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a data type additional information or remove all additional informations.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1614 REFILLPLAN-175

Message

```
Error while validating the Parameter "{parameterName}" at index {parameterIndex}.
```

Legend

- `{parameterName}`: The name of the refill plan Parameter
- `{parameterIndex}`: The index of the refill plan Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1615 REFILLPLAN-176

Message

```
The mapping table ID "{mappingTableIdName}" is not declared whereas it is
used in the charge component.
```

Legend

- `{mappingTableIdName}`: The name of the Parameter which is a mapping table ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the corresponding mapping table ID parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1616 REFILLPLAN-177

Message

```
The mapping table key "{mappingTableKeyName}" of type "{mappingTableKeyType}"
is not declared whereas it is used in the charge component.
```

Legend

- `{mappingTableKeyName}`: The name of the Parameter which is a mapping table key
- `{mappingTableKeyType}`: The type of the mapping table key

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the corresponding mapping table ID parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1617 REFILLPLAN-178

Message

```
Error while validating the Parameter "{parameterName}" at index {parameterIndex}.
```

Legend

- `{parameterName}`: The name of the refill plan Parameter
- `{parameterIndex}`: The index of the refill plan Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1618 REFILLPLAN-179

Message

```
Error while validating the Parameter Reference "{parameterName}" at index
{parameterIndex}.
```

Legend

- `{parameterName}`: The name of the refill plan item Parameter Reference
- `{parameterIndex}`: The index of the refill plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1619 REFILLPLAN-180

Message

```
The refill plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared as
a mapping table ID.
```

Legend

- `{cpParameterName}`: The name of the refill plan Parameter
- `{parameterReferenceName}`: The name of the refill plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the refill plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the mapping table ID data type and the mapping table class additional informations in the refill plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1620 REFILLPLAN-181

Message

```
The refill plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declare
an incompatible
mapping table class "{cpParameterMappingTableClass}" while the Parameter
Reference is of
class "{parameterReferenceMappingTableClass}".
```

Legend

- `{cpParameterName}`: The name of the refill plan Parameter
- `{parameterReferenceName}`: The name of the refill plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the refill plan item Parameter Reference
- `{cpParameterMappingTableClass}`: The mapping table class of the refill plan Parameter
- `{parameterReferenceMappingTableClass}`: The mapping table class of the refill plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the mapping table ID data type and the mapping table class additional informations in the refill plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1621 REFILLPLAN-182

Message

```
The charge plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared as a mapping table key.
```

Legend

- `{cpParameterName}`: The name of the charge plan Parameter
- `{parameterReferenceName}`: The name of the charge plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the charge plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the mapping table key data type additional information in the charge plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1622 REFILLPLAN-183

Message

```
The Parameter is declared as a mapping table ID while it does not exist
in the Charge Component.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the mapping table ID data type additional information from the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1623 REFILLPLAN-184

Message

```
The Parameter is declared as a mapping table ID but it does not have a
STRING type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the parameter as a STRING.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1624 REFILLPLAN-185

Message

```
The mapping table class "{parameterMappingTableClass}" declared in the
Parameter is incompatible with the one declared in the Charge Component
"{chargeComponentMappingTableClass}".
```

Legend

- `{parameterMappingTableClass}`: The mapping table class of the Parameter
- `{chargeComponentMappingTableClass}`: The mapping table class declared in the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the right mapping table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1625 REFILLPLAN-186

Message

```
The Parameter is declared as a mapping table key while it does not exist
in the Charge Component.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the mapping table key data type additional information from the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1626 REFILLPLAN-187

Message

```
The Parameter is declared with a mapping table key but has a wrong type
"{parameterType}" while it should be "{chargeComponentType}".
```

Legend

- `{parameterType}`: The type of the Parameter
- `{chargeComponentType}`: The type declared in the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the right type for the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1627 REFILLPLAN-188

Message

```
The code of the refill record class ({refillRecordClassCode}) referred to
by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} does
not match
any Refill Record Class.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class
- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1628 REFILLPLAN-189

Message

```
The code of the refill record class ({refillRecordClassCode}) referred to
by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} does
not match
any Refill Record Class.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class
- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of an existing Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1629 REFILLPLAN-190

Message

```
Internal server error. Impossible to modify the Refill Plan because the Refill
Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} refers to an
unknown Refill
Record Class.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item in the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact the support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1630 REFILLPLAN-191

Message

```
The code of the refill record class ({refillRecordClassCode}) referred to
by the Refill Plan Item "{refillPlanItemId}" at index {refillPlanItemIndex} does
not
match any Refill Record Class.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class
- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanItemIndex}`: The index of the Refill Plan Item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of an existing Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1631 REFILLPLAN-201

Message

```
The Refill Item Class is missing in the CreateRefillItemClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Item Class to the CreateRefillItemClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1632 REFILLPLAN-202

Message

```
The ID of the Refill Item Class is missing in the CreateRefillItemClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the id of the Refill Item Class to the CreateRefillItemClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1633 REFILLPLAN-203

Message

```
The service provider of the Refill Item Class "{refillItemClassId}" is
missing in the CreateRefillItemClassOp.
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the service provider of the Refill Item Class to the CreateRefillItemClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1634 REFILLPLAN-204

Message

```
The name is missing in the Refill Item Class property at index {propertyIndex}.
```

Legend

- `{propertyIndex}`: The index of the property in the Refill Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a name to the Refill Item Class property.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1635 REFILLPLAN-205 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The Refill Item Class "{refillItemClassId}" has not been saved in the
database due to "{sqlErrorMessage}".
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class
- `{sqlErrorMessage}`: The error message of the SQL exception

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the database is online.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP07. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1636 REFILLPLAN-206

Message

```
The Refill Item Class "{refillItemClassId}" already exists.
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class that already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use another ID or use the ModifyRefillItemClassOp to modify the Refill Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1637 REFILLPLAN-207

Message

```
The Refill Item Class "{refillItemClassId}" cannot be modified because it
does not exist.
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing id for the Refill Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1638 REFILLPLAN-208

Message

```
Unable to change the service provider from "{oldServiceProvider}" to
"{newServiceProvider}" in the Refill Item Class "{refillItemClassId}". The
service provider
is not modifiable.
```

Legend

- `{oldServiceProvider}`: The old service provider of the Refill Item Class
- `{newServiceProvider}`: The new service provider of the Refill Item Class
- `{refillItemClassId}`: The ID of the Refill Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the service provider of the Refill Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1639 REFILLPLAN-209

Message

```
Unable to modify the type from "{oldPropertyType}" to "{newPropertyType}"
for the property "{propertyName}" in the Refill Item Class
"{refillItemClassId}". The property
type is not modifiable.
```

Legend

- `{oldPropertyType}`: The old property type of the Refill Item Class
- `{newPropertyType}`: The new property type of the Refill Item Class
- `{propertyName}`: The name of the property to modify
- `{refillItemClassId}`: The ID of the Refill Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the property type of the Refill Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1640 REFILLPLAN-210

Message

```
The Refill Item Class is missing in the ModifyRefillItemClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Item Class to the ModifyRefillItemClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1641 REFILLPLAN-211

Message

```
The id of the Refill Item Class is missing in the ModifyRefillItemClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the Refill Item Class to the ModifyRefillItemClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1642 REFILLPLAN-212

Message

```
The service provider of the Refill Item Class "{refillItemClassId}" is
missing in the ModifyRefillItemClassOp.
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the service provider of the Refill Item Class to the ModifyRefillItemClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1643 REFILLPLAN-213

Message

```
The id of the Refill Item Class is missing in the DeleteRefillItemClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the Refill Item Class to the DeleteRefillItemClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1644 REFILLPLAN-214

Message

```
The Refill Item Class "{refillItemClassId}" cannot be deleted because
it does not exist.
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing ID for the Refill Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1645 REFILLPLAN-215

Message

```
The Refill Item Class "{refillItemClassId}" cannot be deleted because it
is referred to by one or more Refill Logic objects.
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the Refill Logic object(s).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1646 REFILLPLAN-216 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The Refill Item Class "{refillItemClassId}" has not been deleted in the
database due to "{sqlErrorMessage}".
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class
- `{sqlErrorMessage}`: The error message of the SQL exception

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the database is online.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP07. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1647 REFILLPLAN-217 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
Unable to get the catalog entries related to the Refill Item Class
"{refillItemClassId}"
due to "{sqlErrorMessage}".
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class
- `{sqlErrorMessage}`: The error message of the SQL exception

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the database is online.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP07. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1648 REFILLPLAN-218 (Revoked)

> ⚠ Caution
>
> This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
Unable to delete the catalog entry related to the Refill Item Class
"{refillItemClassId}" due to "{sqlErrorMessage}".
```

Legend

- `{refillItemClassId}`: The ID of the Refill Item Class
- `{sqlErrorMessage}`: The error message of the SQL exception

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the database is online.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP07. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1649 REFILLPLAN-219

Message

```
Unable to remove the property "{propertyName}" in the Refill Item Class
"{refillItemClassId}". Properties are not removable.
```

Legend

- `{propertyName}`: The name of the missing property
- `{refillItemClassId}`: The ID of the Refill Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the Refill Item Class contains properties.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1650 REFILLPLAN-232

Message

```
The refill plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared as
an invoice text.
```

Legend

- `{cpParameterName}`: The name of the refill plan Parameter
- `{parameterReferenceName}`: The name of the refill plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the refill plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the invoice text data type additional information in the refill plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1651 REFILLPLAN-233

Message

```
The refill plan Parameter "{parameterName}" at index {parameterIndex} points
to an unknown mapping table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1652 REFILLPLAN-234

Message

```
The refill logic Parameter "{parameterName}" points to an unknown mapping
table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1653 REFILLPLAN-235

Message

```
The refill plan item Parameter "{parameterName}" at index {parameterIndex}
points to an unknown mapping table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known mapping table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1654 REFILLPLAN-236

Message

```
The {mappingTableClassName} Mapping Table Class associated with the
{parameterName}
parameter in the Refill Logic does not exist.
```

Legend

- `{mappingTableClassName}`: The name of the Mapping Table Class
- `{parameterName}`: The name of the parameter of type Mapping Table ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Mapping Table Class to an existing one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1655 REFILLPLAN-237

Message

```
The {parameterName} parameter of the Refill Plan declares the {mappingTableName}
Mapping Table with the {actualMappingTableClass} Mapping Table Class while this
table is
of class "{expectedMappingTableClass}".
```

Legend

- `{parameterName}`: The name of the parameter of type Mapping Table ID
- `{mappingTableName}`: The name of the Mapping Table
- `{actualMappingTableClass}`: The name of the Mapping Table Class associated with the Mapping Table
- `{expectedMappingTableClass}`: The name of the Mapping Table Class which is expected

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the name of the Mapping Table to a Mapping Table having the expected Mapping Table Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP10 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1656 REFILLPLAN-239

Message

```
The parameter is a range table ID but no range table class is defined.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the range table class additional information.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1657 REFILLPLAN-240

Message

```
The range table ID "{rangeTableIdName}" is not declared whereas it is used
in the charge component.
```

Legend

- `{rangeTableIdName}`: The name of the Parameter which is a range table ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the corresponding range table ID parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1658 REFILLPLAN-241

Message

```
The refill plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} is not
declared as
a range table ID.
```

Legend

- `{cpParameterName}`: The name of the refill plan Parameter
- `{parameterReferenceName}`: The name of the refill plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the refill plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the range table ID data type and the range table class additional informations in the refill plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1659 REFILLPLAN-242

Message

```
The refill plan Parameter "{cpParameterName}" referenced by the Parameter
Reference "{parameterReferenceName}" at index {parameterReferenceIndex} declare
an incompatible
range table class "{cpParameterRangeTableClass}" while the Parameter Reference
is of class
"{parameterReferenceRangeTableClass}".
```

Legend

- `{cpParameterName}`: The name of the refill plan Parameter
- `{parameterReferenceName}`: The name of the refill plan item Parameter Reference
- `{parameterReferenceIndex}`: The index of the refill plan item Parameter Reference
- `{cpParameterRangeTableClass}`: The range table class of the refill plan Parameter
- `{parameterReferenceRangeTableClass}`: The range table class of the refill plan item Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the range table ID data type and the range table class additional informations in the refill plan Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1660 REFILLPLAN-243

Message

```
The Parameter is declared as a range table ID while it does not exist in
the Charge Component.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the range table ID data type additional information from the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1661 REFILLPLAN-244

Message

```
The Parameter is declared as a range table ID but it does not have a STRING
type.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the parameter as a STRING.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1662 REFILLPLAN-245

Message

```
The range table class "{parameterRangeTableClass}" declared in the Parameter
is incompatible with the one declared in the Charge Component
"{chargeComponentRangeTableClass}".
```

Legend

- `{parameterRangeTableClass}`: The range table class of the Parameter
- `{chargeComponentRangeTableClass}`: The range table class declared in the Charge Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Declare the right range table class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1663 REFILLPLAN-246

Message

```
The refill plan Parameter "{parameterName}" at index {parameterIndex}
points to an unknown range table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1664 REFILLPLAN-247

Message

```
The refill logic Parameter "{parameterName}" points to an unknown range
table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1665 REFILLPLAN-248

Message

```
The refill plan item Parameter "{parameterName}" at index {parameterIndex}
points to an unknown range table "{parameterValue}".
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter

- `{parameterValue}`: The value of the Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the value to a known range table.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1666 REFILLPLAN-302

Message

```
The currency code "{invalidCurrencyCode}" of the Refill Logic is not a
valid currency code.
```

Legend

- `{invalidCurrencyCode}`: The code of the invalid currency code

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the currency code of the Refill Logic is valid.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1667 REFILLPLAN-304

Message

```
The name of the usage refill is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the usage refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1668 REFILLPLAN-305

Message

```
The usage refill "{usageRefillName}" does not contain any refill component.
```

Legend

- `{usageRefillName}`: The name of the usage refill with no refill component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a refill component to the usage refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1669 REFILLPLAN-306

Message

```
The name of the recurring refill is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the recurring refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1670 REFILLPLAN-307

Message

```
The recurring refill "{recurringRefillName}" does not contain any refill
component.
```

Legend

- `{recurringRefillName}`: The name of the recurring refill with no refill component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a refill component to the recurring refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1671 REFILLPLAN-309

Message

```
The name of the one-shot refill is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the one-shot refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1672 REFILLPLAN-310

Message

```
The one-shot refill "{oneShotRefillName}" does not contain any refill component.
```

Legend

- `{oneShotRefillName}`: The name of the one-shot refill with no refill component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a refill component to the one-shot refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1673 REFILLPLAN-311

Message

```
The counter has no name.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the counter name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1674 REFILLPLAN-312

Message

```
The counter "{counterDescriptionName}" has no initial value.
```

Legend

- `{counterDescriptionName}`: The name of the counter with no initial value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the initial value of the counter has.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1675 REFILLPLAN-313

Message

```
The counter "{counterDescriptionName}" is duplicated.
```

Legend

- `{counterDescriptionName}`: The name of the duplicated counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a unique name to the counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1676 REFILLPLAN-314

Message

```
The parameter "{parameterName}" is duplicated.
```

Legend

- `{parameterName}`: The name of the duplicated parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a unique name to the parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1677 REFILLPLAN-315

Message

```
The Refill Logic has no code.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the code of the Refill Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1678 REFILLPLAN-316

Message

```
The Refill Logic "{refillLogicId}" has no owner.
```

Legend

- `{refillLogicId}`: The ID of the Refill Logic with no owner

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the owner of the Refill Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1679 REFILLPLAN-317

Message

```
The Refill Logic "{refillLogicId}" has no refill logic tree.
```

Legend

- `{refillLogicId}`: The id of the Refill Logic with no refill logic tree

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the refill logic tree to the Refill Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1680 REFILLPLAN-318

Message

```
The Refill Item Class "{refillItemClassName}" referred to in the usage refill
"{usageRefillName}" does not exist.
```

Legend

- `{refillItemClassName}`: The name of the Refill Item Class that does not exist
- `{usageRefillName}`: The name of the usage refill with no refill component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing Refill Item Class in the usage refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1681 REFILLPLAN-319

Message

```
The Refill Logic "{refillLogicId}" already exists.
```

Legend

- `{refillLogicId}`: The ID of the Refill Logic that already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use another ID or use the ModifyRefillLogicOp to modify the Refill Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1682 REFILLPLAN-320

Message

```
The Refill Logic "{refillLogicId}" has not been initialized for an unknown
reason.
```

Legend

- `{refillLogicId}`: The ID of the Refill Logic that has not been initialized

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the Refill logic is unique.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1683 REFILLPLAN-321

Message

```
The Refill Logic is missing in the CreateRefillLogicOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Logic to the CreateRefillLogicOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1684 REFILLPLAN-322

Message

```
The Refill Logic is missing in the ModifyRefillLogicOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Logic to the ModifyRefillLogicOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1685 REFILLPLAN-323

Message

```
The Refill Logic "{refillLogicCode}" cannot be modified because it does not
exist.
```

Legend

- `{refillLogicCode}`: The ID of the Refill Logic that does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the ID of the Refill Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1686 REFILLPLAN-324

Message

```
The Refill Logic owner "{refillLogicOwner}" is not modifiable in the Refill
Logic "{refillLogicId}".
```

Legend

- `{refillLogicOwner}`: The owner of the Refill Logic
- `{refillLogicId}`: The ID of the Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the owner of the Refill Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1687 REFILLPLAN-325

Message

```
The id of the Refill Logic is missing in the DeleteRefillLogicOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the ID of the Refill Logic to the DeleteRefillLogicOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1688 REFILLPLAN-326

Message

```
The Refill Logic "{refillLogicId}" cannot be deleted because it is referred
to by one or more Refill Plans.
```

Legend

- `{refillLogicId}`: The ID of the Refill Logic that is referred to by a Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the Refill Plan(s).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1689 REFILLPLAN-327

Message

```
The Refill Logic "{refillLogicId}" cannot be deleted because it does not
exist.
```

Legend

- `{refillLogicId}`: The ID of the Refill Logic that does not exist

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the code of the Refill Logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1690 REFILLPLAN-333

Message

```
The Refill Logic "{refillLogicId}" is set to manage multicurrency but the
currency "{currencyCode}" is already set.
```

Legend

- `{refillLogicId}`: The ID of the Refill Logic
- `{currencyCode}`: The code of the currency that has been set

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Mark the Refill Logic as multicurrency or remove the currency that has been set.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1691 REFILLPLAN-334

Message

```
The Refill Logic "{refillLogicId}" is marked as monocurrency but no currency
is set.
```

Legend

- `{refillLogicId}`: The ID of the Refill Logic

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a currency in the refill logic.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1692 REFILLPLAN-335

Message

```
The counter name "{counterName}" at index {counterIndex} is unknown to the
counter name dictionary whereas it is visible to the external system.
```

Legend

- `{counterName}`: The name of the counter unknown to the counter name dictionary
- `{counterIndex}`: The index of the counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the counter name to the counter name dictionary or change the counter name into a known one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1693 REFILLPLAN-336

Message

```
The usage refill usageId is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that a usageId exists in the usage refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1694 REFILLPLAN-337

Message

```
The usage refill usageId "{usageId}" is used at least twice in the refill
logic.
```

Legend

- `{usageId}`: The usage ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that each usageId in the usage refill is unique.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1695 REFILLPLAN-400

Message

```
The Refill Record Class is missing in the CreateRefillRecordClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Record Class to the CreateRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1696 REFILLPLAN-401

Message

```
The code of the Refill Record Class is missing in the CreateRefillRecordClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the code of the Refill Record Class to the CreateRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1697 REFILLPLAN-402

Message

```
The owner of the Refill Record Class "{refillRecordClassCode}" is missing
in the CreateRefillRecordClassOp.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the owner of the Refill Record Class to the CreateRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1698 REFILLPLAN-403

Message

```
The Refill Record Class of code "{refillRecordClassCode}" already exists.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class that already exists

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use another code or use the ModifyRefillRecordClassOp to modify the Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1699 REFILLPLAN-404

Message

```
The Exportable Item Mapping of the Refill Record Class "{refillRecordClassCode}"
is invalid due to: {errorMessage}.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class
- `{errorMessage}`: The message of the error

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check that the Refill Record Class is valid.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1700 REFILLPLAN-405

Message

```
The name of the Refill Record Class Field is missing in the
CreateRefillRecordClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the name of the Refill Record Class Field to the CreateRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1701 REFILLPLAN-406

Message

```
The type of the Refill Record Class Field "{refillRecordClassFieldName}"
is missing in the CreateRefillRecordClassOp.
```

Legend

- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the type of the Refill Record Class Field to the CreateRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1702 REFILLPLAN-407

Message

```
The Refill Record Class Field "{refillRecordClassFieldName}" is duplicated.
```

Legend

- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicated Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1703 REFILLPLAN-408

Message

```
The property name "{propertyName}" does not exists for the Refill Record Class
Field "{refillRecordClassFieldName}".
```

Legend

- `{propertyName}`: The name of the property associated to the Refill Record Class Field
- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid property name for the Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1704 REFILLPLAN-409

Message

```
Impossible to map the property name "{propertyName}" of type "{propertyType}"
onto the Refill Record Class Field "{refillRecordClassFieldName}" of type
"{refillRecordClassFieldType}".
```

Legend

- `{propertyName}`: The name of the property associated to the Refill Record Class Field
- `{propertyTypepropertyType}`: The type of the property associated to the Refill Record Class Field
- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field
- `{refillRecordClassFieldType}`: The type of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid property type for the Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1705 REFILLPLAN-410

Message

```
The property name "{propertyName}" does not exists for the Refill Record
Class Field "{refillRecordClassFieldName}".
```

Legend

- `{propertyName}`: The name of the property associated to the Refill Record Class Field
- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid property name for the Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1706 REFILLPLAN-411

Message

```
A Charged Item Class with the code "{refillRecordClassCode}" exists.
```

Legend

- `{refillRecordClassCode}`: The code already used by a Charged Item Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use another code or delete the Charged Item Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1707 REFILLPLAN-450

Message

```
The Refill Record Class is missing in the ModifyRefillRecordClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Record Class to the ModifyRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1708 REFILLPLAN-451

Message

```
The Refill Record Class "{refillRecordClassCode}" cannot be modified because
it does not exist.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing code for the Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1709 REFILLPLAN-452

Message

```
The owner "{owner}" of the Refill Record Class "{refillRecordClassCode}"
cannot be changed to "{newOwner}".
```

Legend

- `{owner}`: The original owner of the Refill Record Class
- `{refillRecordClassCode}`: The code of the Refill Record Class
- `{newOwner}`: The new owner of the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the original owner of the Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1710 REFILLPLAN-453

Message

```
The Exportable Item Mapping of the Refill Record Class "{refillRecordClassCode}"
is invalid due to: {errorMessage}.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class
- `{errorMessage}`: The message of the error

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1711 REFILLPLAN-454

Message

```
The name of the Refill Record Class Field is missing in the
ModifyRefillRecordClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the name of the Refill Record Class Field to the ModifyRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1712 REFILLPLAN-455

Message

```
The type of the Refill Record Class Field "{refillRecordClassFieldName}" is
missing in the ModifyRefillRecordClassOp.
```

Legend

- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a type to the Refill Record Class Field to the ModifyRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1713 REFILLPLAN-456

Message

```
The Refill Record Class Field "{refillRecordClassFieldName}" is duplicated.
```

Legend

- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the duplicated Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1714 REFILLPLAN-457

Message

```
The property name "{propertyName}" does not exists for the Refill Record
Class Field "{refillRecordClassFieldName}".
```

Legend

- `{propertyName}`: The name of the property associated to the Refill Record Class Field
- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid property name for the Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1715 REFILLPLAN-458

Message

```
Impossible to map the property name "{propertyName}" of type "{propertyType}"
onto the Refill Record Class Field "{refillRecordClassFieldName}" of type
"{refillRecordClassFieldType}".
```

Legend

- `{propertyName}`: The name of the property associated to the Refill Record Class Field
- `{propertyType}`: The type of the property associated to the Refill Record Class Field
- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field
- `{refillRecordClassFieldType}`: The type of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid property type for the Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1716 REFILLPLAN-459

Message

```
The property name "{propertyName}" does not exists for the Refill Record
Class Field "{refillRecordClassFieldName}".
```

Legend

- `{propertyName}`: The name of the property associated to the Refill Record Class Field
- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid property name for the Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1717 REFILLPLAN-460

Message

```
The Refill Record Class Field "{refillRecordClassFieldName}" is missing
in the ModifyRefillRecordClassOp.
```

Legend

- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the Refill Record Class Field to the ModifyRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1718 REFILLPLAN-461

Message

```
The type "{refillRecordClassFieldType}" of the Refill Record Class Field
"{refillRecordClassFieldName}" cannot be modified to
"{newRefillRecordClassFieldType}".
```

Legend

- `{refillRecordClassFieldType}`: The original type of the Refill Record Class Field
- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field
- `{newRefillRecordClassFieldType}`: The new type of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use the original type of the Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1719 REFILLPLAN-462 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The Refill Record Class Field "{refillRecordClassFieldName}" cannot be
modified if no property value or property name is set.
```

Legend

- `{refillRecordClassFieldName}`: The name of the Refill Record Class Field

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the property name and the property value of the Refill Record Class Field.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to 4.0 SP09. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1720 REFILLPLAN-475

Message

```
The Refill Record Class "{refillRecordClassCode}" cannot be deleted because
it does not exist.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing code for the Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1721 REFILLPLAN-476

Message

```
The Refill Record Class referred to as "{refillRecordClassRef}" cannot be
deleted because it does not exist.
```

Legend

- `{refillRecordClassRef}`: The reference of the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use an existing reference for the Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1722 REFILLPLAN-477

Message

```
The Refill Record Class "{refillRecordClassCode}" cannot be deleted because
it is referred to by {refillPlanCount} Refill Plan(s). Codes: {refillPlanCodes}.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class
- `{refillPlanCount}`: The number of Refill Plans
- `{refillPlanCodes}`: The codes of Refill Plans

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the Refill Plan(s).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1723 REFILLPLAN-478

Message

```
The Refill Record Class "{refillRecordClassCode}" cannot be deleted because
it is referred to by one or more Exportable Item Mappings. Codes:
{exportableItemMappingCodes}.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class
- `{exportableItemMappingCodes}`: A `CSV` string contening the list of Exportable Item Mapping codes

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the Exportable Item Mapping(s).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1724 REFILLPLAN-479

Message

```
The Refill Record Class "{refillRecordClassCode}" cannot be deleted because
it is referred to by one or more data files.
```

Legend

- `{refillRecordClassCode}`: The code of the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete the data file(s).

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1725 REFILLPLAN-480

Message

```
The code of the Refill Record Class is missing in the DeleteRefillRecordClassOp.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the code of Refill Record Class to the DeleteRefillRecordClassOp.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1726 REFILLPLAN-481

Message

```
The Refill Record Class referred to by "{refillRecordClassRef}" cannot be
deleted because the reference is not a number.
```

Legend

- `{refillRecordClassRef}`: The reference of the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the reference of the Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1727 REFILLPLAN-482

Message

```
The description of the Refill Plan "{refillPlanId}" cannot be modified
because the Refill Plan has been released.
```

Legend

- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1728 REFILLPLAN-483

Message

```
The additional info "{additionalInformationName}" cannot be removed because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1729 REFILLPLAN-484

Message

```
The additional info "{additionalInformationName}" cannot be added because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1730 REFILLPLAN-485

Message

```
The description of the additional info "{additionalInformationName}" cannot
be modified because the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1731 REFILLPLAN-486

Message

```
The type of the additional info "{additionalInformationName}" cannot be
modified because the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1732 REFILLPLAN-488

Message

```
The date value of the additional info "{additionalInformationName}" cannot be
modified because the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1733 REFILLPLAN-489

Message

```
The number value of the additional info "{additionalInformationName}" cannot be
modified because the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1734 REFILLPLAN-490

Message

```
The string value of the additional info "{additionalInformationName}" cannot be
modified because the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{additionalInformationName}`: The name of the Additional Information
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1735 REFILLPLAN-491

Message

```
The counter "{counterName}" cannot be removed because the Refill Plan
"{refillPlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1736 REFILLPLAN-492

Message

```
The counter "{counterName}" cannot be added because the Refill Plan
"{refillPlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1737 REFILLPLAN-493

Message

```
The description of the counter "{counterName}" cannot be modified because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1738 REFILLPLAN-494

Message

```
The initial value of the counter "{counterName}" cannot be modified because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{counterName}`: The name of the Counter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1739 REFILLPLAN-495

Message

```
The account assignment "{accountAssignmentName}" cannot be removed because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1740 REFILLPLAN-496

Message

```
The account assignment "{accountAssignmentName}" cannot be added because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1741 REFILLPLAN-497

Message

```
The description of the account assignment "{accountAssignmentName}" cannot
be modified because the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1742 REFILLPLAN-498

Message

```
The type of the account assignment "{accountAssignmentName}" cannot be
modified because the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1743 REFILLPLAN-499

Message

```
The user technical identifier "{userTechIdName}" cannot be removed because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1744 REFILLPLAN-500

Message

```
The user technical identifier "{userTechIdName}" cannot be added because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1745 REFILLPLAN-501

Message

```
The description of the user technical identifier "{userTechIdName}" cannot be
modified because the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{userTechIdName}`: The name of the User Technical Identifier
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1746 REFILLPLAN-502

Message

```
The refill plan item "{refillPlanItemId}" cannot be removed because the Refill
Plan "{refillPlanId}" has been released.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1747 REFILLPLAN-503

Message

```
The refill plan item "{refillPlanItemId}" cannot be added because the Refill
Plan "{refillPlanId}" has been released.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1748 REFILLPLAN-504

Message

```
The refill plan item "{refillPlanItemId}" cannot be modified because the Refill
Plan "{refillPlanId}" has been released.
```

Legend

- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1749 REFILLPLAN-505

Message

```
The parameter "{parameterName}" cannot be removed because the Refill Plan
"{refillPlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1750 REFILLPLAN-506

Message

```
The parameter "{parameterName}" cannot be added because the Refill Plan
"{refillPlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1751 REFILLPLAN-507

Message

```
The description of the parameter "{parameterName}" cannot be modified because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1752 REFILLPLAN-508

Message

```
The type of the parameter "{parameterName}" cannot be modified because the
Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1753 REFILLPLAN-510

Message

```
The date value of the parameter "{parameterName}" cannot be modified because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1754 REFILLPLAN-511

Message

```
The number value of the parameter "{parameterName}" cannot be modified because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1755 REFILLPLAN-512

Message

```
The string value of the parameter "{parameterName}" cannot be modified because
the Refill Plan "{refillPlanId}" has been released.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{refillPlanId}`: The ID of the Refill Plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new Refill Plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1756 REFILLPLAN-513

Message

```
The Refill Logic fails to initialize because the Refill Component
"{refillComponentName}"
of type "{refillComponentType}" is not valid.
```

Legend

- `{refillComponentName}`: The name of the Refill Component
- `{refillComponentType}`: The type of the Refill Component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the Refill Component.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1757 REFILLPLAN-514

Message

```
The account assignment "{accountAssignmentName}" of the refill plan item
"{refillPlanItemId}" cannot be added because the refill plan "{refillPlanId}"
has been
released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{refillPlanItemId}`: The ID of the refill plan item
- `{refillPlanId}`: The ID of the refill plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new refill plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1758 REFILLPLAN-515

Message

```
The account assignment "{accountAssignmentName}" of the refill plan item
"{refillPlanItemId}" cannot be removed because the refill plan "{refillPlanId}"
has been
released.
```

Legend

- `{accountAssignmentName}`: The name of the Account Assignment
- `{refillPlanItemId}`: The ID of the refill plan item
- `{refillPlanId}`: The ID of the refill plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new refill plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1759 REFILLPLAN-516

Message

```
The user technical identifier "{userTechIdService}" of the refill plan item
"{refillPlanItemId}" cannot be added because the refill plan "{refillPlanId}"
has been
released.
```

Legend

- `{userTechIdService}`: The service of the User Technical Identifier
- `{refillPlanItemId}`: The ID of the refill plan item
- `{refillPlanId}`: The ID of the refill plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new refill plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1760 REFILLPLAN-517

Message

```
The user technical identifier "{userTechIdService}" of the refill plan
item "{refillPlanItemId}" cannot be removed because the refill plan
```

```
"{refillPlanId}" has been
released.
```

Legend

- `{userTechIdService}`: The service of the User Technical Identifier
- `{refillPlanItemId}`: The ID of the refill plan item
- `{refillPlanId}`: The ID of the refill plan

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new refill plan.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1761 REFILLPLAN-518

Message

```
The usage refill "{usageRateName}" is invalid because its component tree is
invalid.
```

Legend

- `{usageRateName}`: The name of the usage refill with invalid components

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the components in the usage refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1762 REFILLPLAN-519

Message

```
The recurring refill "{recurringRateName}" is invalid because its component
tree is invalid.
```

Legend

- `{recurringRateName}`: The name of the recurring refill with invalid components

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the rate components in the recurring refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1763 REFILLPLAN-520

Message

```
The one-shot refill "{oneshotRateName}" is invalid because its component tree
is invalid.
```

Legend

- `{oneshotRateName}`: The name of the one-shot refill with invalid components

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the components in the one-shot refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1764 REFILLPLAN-521

Message

```
The Refill Record Mapping of "{refillPlanItemId}" Refill Plan Item contains
the "{entryName}" entry. This entry does not exist in the
"{refillRecordClassId}" Refill
Record Class.
```

Legend

- `{refillPlanItemId}`: The ID of the refill plan item
- `{entryName}`: The entry name in the Refill Record Mapping
- `{refillRecordClassId}`: The ID of the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove the entry from the Refill Record Mapping or replace it by an existing property of the Refill Record Class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1765 REFILLPLAN-522

Message

```
The Refill Record Mapping of "{refillPlanItemId}" Refill Plan Item contains
the "{entryName}" entry with the type: {entryType}. This type is not compatible
with the one
defined in the "{refillRecordClassId}" Refill Record Class: {propertyType}.
```

Legend

- `{refillPlanItemId}`: The ID of the refill plan item
- `{entryName}`: The entry name in the Refill Record Mapping
- `{entryType}`: The entry type in the Refill Record Mapping

- `{refillRecordClassId}`: The ID of the Refill Record Class
- `{propertyType}`: The property type in the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the components in the one-shot refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1766 REFILLPLAN-523 (Revoked)

⚠ Caution

This error code has been **revoked**. Verify its validity in your running SAP CC system.

Message

This error code is now revoked in SAP Convergent Charging (SAP CC):

```
The code of the refill record class ({refillRecordClassCode}) referred to
by the Refill Plan Item "{refillPlanItemId}" cannot be changed to
({newRefillRecordClassCode}).
```

Legend

- `{refillRecordClassCode}`: The original code of the Refill Record Class
- `{refillPlanItemId}`: The ID of the Refill Plan Item
- `{newRefillRecordClassCode}`: The new code of the Refill Record Class

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the ID of the original refill record class.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to 4.0 SP09.. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1767 REFILLPLAN-525

Message

```
The name of the account event refill is not set.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the name of the account event refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1768 REFILLPLAN-526

Message

```
The account event refill "{accountEventRefillName}" does not contain any
refill component.
```

Legend

- `{accountEventRefillName}`: The name of the account event refill with no refill component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a refill component to the account event refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1769 REFILLPLAN-527

Message

```
The account event refill "{accountEventRefillName}" is invalid because the
component tree is invalid.
```

Legend

- `{accountEventRefillName}`: The name of the account event refill with the invalid component

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the validity of the components in the account event refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1770 REFILLPLAN-528

Message

```
The service name "{serviceName}" of the User Technical Identifier Reference
at index {userTechnicalIdentifierReferenceIndex} is reserved for internal use.
```

Legend

- `{serviceName}`: The name of the service, as provided
- `{userTechnicalIdentifierReferenceIndex}`: The index of the User Technical Identifier Reference within the refill plan item

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the service name to a value that is not reserved for internal use.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1771 REFILLPLAN-529

Message

```
The parameter reference "{parameterRefName}" at index {parameterRefIndex} has
a date type which is incompatible with the refill logic parameter whose type is
{refillLogicParameterType}.
```

Legend

- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference
- `{refillLogicParameterType}`: The type of the Refill Logic Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter reference type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1772 REFILLPLAN-530

Message

```
The parameter reference "{parameterRefName}" at index {parameterRefIndex} has
a number type which is incompatible with the refill logic parameter whose type
is
{refillLogicParameterType}.
```

Legend

- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference
- `{refillLogicParameterType}`: The type of the Refill Logic Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter reference type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1773 REFILLPLAN-531

Message

```
The parameter reference "{parameterRefName}" at index {parameterRefIndex} has
a string type which is incompatible with the refill logic parameter whose type
is
{refillLogicParameterType}.
```

Legend

- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference
- `{refillLogicParameterType}`: The type of the Refill Logic Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter reference type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1774 REFILLPLAN-532

Message

```
The type "{parameterRefType}" of the Parameter Reference "{parameterRefName}"
at index {parameterRefIndex} is unsupported (supported types are string, number,
date).
```

Legend

- `{parameterRefType}`: The unsupported type of the Parameter Reference
- `{parameterRefName}`: The name of the Parameter Reference
- `{parameterRefIndex}`: The index of the Parameter Reference

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Use a supported type (string, number, date) for the Parameter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1775 REFILLPLAN-533

Message

```
The parameter "{parameterName}" at index {parameterIndex} has a date
type which is incompatible with the refill logic parameter whose type is
{refillLogicParameterType}.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{refillLogicParameterType}`: The type of the Refill Logic Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1776 REFILLPLAN-534

Message

```
The parameter "{parameterName}" at index {parameterIndex} has a number
type which is incompatible with the refill logic parameter whose type is
{refillLogicParameterType}.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{refillLogicParameterType}`: The type of the Refill Logic Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1777 REFILLPLAN-535

Message

```
The parameter "{parameterName}" at index {parameterIndex} has a string
type which is incompatible with the refill logic parameter whose type is
{refillLogicParameterType}.
```

Legend

- `{parameterName}`: The name of the Parameter
- `{parameterIndex}`: The index of the Parameter
- `{refillLogicParameterType}`: The type of the Refill Logic Parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the parameter type to the correct one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP06 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1778 REFILLPLAN-536

Message

```
The parameter "{parameterName}" cannot reference the mapping table
"{mappingTableId}" because this mapping table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a mapping table with an agreement ID
- `{mappingTableId}`: The identifier of the mapping table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a mapping table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1779 REFILLPLAN-537

Message

```
The parameter of the refill plan item cannot reference the mapping table
"{parameterValue}" because this mapping table has an agreement ID.
```

Legend

- `{parameterValue}`: The identifier of the mapping table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a mapping table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1780 REFILLPLAN-538

Message

```
The parameter "{parameterName}" of the refill plan cannot reference the
mapping table "{parameterValue}" because this mapping table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a mapping table with an agreement ID
- `{parameterValue}`: The identifier of the mapping table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a mapping table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1781 REFILLPLAN-539

Message

```
The parameter "{parameterName}" cannot reference the range table
"{rangeTableId}"
because this range table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a range table with an agreement ID

- `{rangeTableId}`: The identifier of the range table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1782 REFILLPLAN-540

Message

```
The parameter of the refill plan item cannot reference the range table
"{parameterValue}" because this range table has an agreement ID.
```

Legend

- `{parameterValue}`: The identifier of the range table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1783 REFILLPLAN-541

Message

```
The parameter "{parameterName}" of the refill plan cannot reference the
range table "{parameterValue}" because this range table has an agreement ID.
```

Legend

- `{parameterName}`: The name of the parameter referencing a range table with an agreement ID
- `{parameterValue}`: The identifier of the range table specified in the parameter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Select a range table without agreement ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1784 REFILLPLAN-542

Message

```
Recurring refill "{recurringRefillName}" is configured for a 4-4-5 calendar.
The only supported frequency type is month.
```

Legend

- `{recurringRefillName}`: The name of the recurring refill

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the frequency type to month.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1785 REFILLPLAN-543

Message

```
Recurring refill "{recurringRefillName}" is configured for a 4-4-5 calendar.
The only supported frequency periods are 1, 3, 6 and 12.
```

Legend

- `{recurringRefillName}`: The name of the recurring refill

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the frequency period to 1, 3, 6 or 12.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1786 REFILLPLAN-544

Message

```
Operations on Refill Item Classes are not available because the Prepaid
Accounts Management feature is disabled.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1787 REFILLPLAN-545

Message

```
Operations on Refill Record Classes are not available because the Prepaid
Accounts Management feature is disabled.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1788 REFILLPLAN-546

Message

```
Operations on Refill Logic objects are not available because the Prepaid
Accounts Management feature is disabled.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1789 REFILLPLAN-547

Message

```
Operations on Refill Plans are not available because the Prepaid Accounts
Management feature is disabled.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1790 REFILLPLAN-548

Message

```
The frequency of the recurring refill "{recurringRefillName}" is invalid.
```

Legend

- `{recurringRefillName}`: The name of the recurring refill

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid frequency in the recurring refill.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1791 RESTCHARGING-1

Message

```
The charging session with the ID "{sessionID}" does not exist in the SAP CC
system.
```

Legend

- `{sessionID}`: The session ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check if the session has not been automatically removed or closed.

Add a valid session ID.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2022 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1792 RESTCHARGING-2

Message

```
The charging session with the ID "{sessionID}" already exists in the SAP CC
system.
```

Legend

- `{sessionID}`: The session ID

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a new session ID and send a new request.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2022 FPS 0 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1793 RFC-1

Message

```
One or more billable items or consumption items could not be loaded into SAP
Convergent Invoicing because they are invalid.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the related error messages and correct the pricing configuration.

Many reasons are possible and can explain the invalid billable item (or invalid consumption item).

Inspect the signaled error messages to locate the issue and solve the situation:

- In the sent billable item and its relating charged item
- In the sent consumption item and its relating charged chargeable item
- In master data (pricing catalog, mapping/range table)
- In customer master data (subscriber account, provider contract and its contract items, subscriber mapping/range tables)
- In system settings

✤ Example

In Cockpit, the app Process a Chargeable Item may display this error when an SAP CC pricing specialist triggered the manual charging of a chargeable item for a service consumption.

Business Context

The error occurred during the processing of the *Billable Items Immediate Loading* feature and its functions. See Billable Items Immediate Loading.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2020 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

See Also

- RFC-2 [page 3070]

Related Information

Immediate Loading of Billable Items

4.1794 RFC-2

Message

```
One or more billable items or consumption items could not be loaded into SAP
Convergent Invoicing because of a communication error.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Execute the operation again later.

Many reasons are possible and can explain the communication error. The failure can be permanent or temporary.

Business Context

The communication error during the processing of the *Billable Items Immediate Loading* feature and its functions. See Billable Items Immediate Loading.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 2020 FPS 2 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

See Also

- RFC-1 [page 3068]

Related Information

Immediate Loading of Billable Items

4.1795 SPENDINGSTATUS-1

Message

```
The label "{label}" is not valid because it does not verify the regular
expression "{regex}".
```

Legend

- `{label}`: The invalid label
- `{regex}`: The regex that labels must verify

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up another value of label verifying the regexp syntax.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1796 SPENDINGSTATUS-2

Message

```
The code ID of the spending status description "{spendingStatusDescriptionId}"
is not valid because it does not verify the regular expression "{regex}".
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description
- `{regex}`: The regex that names of the spending status description must verify

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up another ID of the spending status description verifying the regexp syntax.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1797 SPENDINGSTATUS-3

Message

```
The text description of the spending status description
"{spendingStatusDescriptionDescription}"
is not valid because it does not verify the regular expression "{regex}".
```

Legend

- `{spendingStatusDescriptionDescription}`: The description of the spending status description
- `{regex}`: The regex that descriptions of the spending status description must verify

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set up another text description of the spending status description verifying the regexp syntax.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1798 SPENDINGSTATUS-4

Message

```
The label "{label}" at the index "{index}" is not valid.
```

Legend

- `{label}`: The invalid label
- `{index}`: The index in the list of label positioning the invalid label

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the previous error messages in the error stack.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1799 SPENDINGSTATUS-5

Message

```
The label "{label}" is duplicated at the index "{index1}" and "{index2}".
```

Legend

- `{label}`: The invalid label
- `{index1}`: The first index in the list of labels positioning the duplicated label
- `{index2}`: The second index in the list of labels positioning the duplicated label

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove a label in the spending status description specified in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1800 SPENDINGSTATUS-6

Message

```
The spending status description needs at least a label.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add at least a label in the spending status description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1801 SPENDINGSTATUS-100

Message

```
The spending status description is missing in the create operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a spending status description in the create operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1802 SPENDINGSTATUS-101

Message

```
The spending status description "{spendingStatusDescriptionId}" already exists.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another spending status description in the create operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1803 SPENDINGSTATUS-200

Message

```
The spending status description is missing in the modify operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a spending status description in the modify operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1804 SPENDINGSTATUS-201

Message

```
The spending status description "{spendingStatusDescriptionId}" does not exist.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another spending status description to the modify operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1805 SPENDINGSTATUS-202

Message

```
Cannot modify the spending status description "{spendingStatusDescriptionId}".
Its label "{missingSpendingStatusLabel}" is still used.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description
- `{missingSpendingStatusLabel}`: The spending status label which is missing in the spending status description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add the missing label back in the spending status description to modify or check why the label is still used.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1806 SPENDINGSTATUS-203

Message

```
Cannot modify the spending status description "{spendingStatusDescriptionId}";
Its description "{spendingStatusDescriptionDescription}" cannot be changed.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description
- `{spendingStatusDescriptionDescription}`: The description of the spending status description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create a new spending status description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1807 SPENDINGSTATUS-300

Message

```
The mandatory filter is missing in the search operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify a filter in the search operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1808 SPENDINGSTATUS-301

Message

```
Cannot search for spending status descriptions. The search operation or
the specified filter is invalid. Reason: {reasonInformation}.
```

Legend

- `{reasonInformation}`: The additional information describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check the reason information recorded in your error message; The reason is based on the Java Technology. It details the exception raised in the connected SAP CC system. Typical reasons are: Invalid search filter, Back-end database failure.

Refer to the Java/XML API Reference (Core Library) technical documentation for more information about the `com.highdeal.filter.hci.InvalidSearchException`.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1809 SPENDINGSTATUS-400

Message

```
The ID of the spending status description is missing in the delete operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify the ID of the relevant spending status description in the operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1810 SPENDINGSTATUS-401

Message

```
The spending status description "{spendingStatusDescriptionId}" does not exist.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Specify another ID of spending status description in the delete operation request.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1811 SPENDINGSTATUS-402

Message

```
Error while deleting the spending status description
"{spendingStatusDescriptionId}".
The spending status description is still used in one monitoring plan.
```

Legend

- `{spendingStatusDescriptionId}`: The ID of the spending status description

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

First delete all monitoring plans referencing the spending status description.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1812 SQL-1

Message

```
Incompatible database version ({version}).
```

Legend

- `{version}`: The database version

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Upgrade database to a compatible version.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1813 SQL-2

Message

```
Cannot find JDBC driver ({driverName}).
```

Legend

- `{driverName}`: The name of the driver

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check your classpath.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1814 SQL-3

Message

```
Bad URL syntax : {URL}. Expected format: {URLSample}.
```

Legend

- `{URL}`: The bad URL[17]
- `{URLSample}`: A sample of good URL

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

URL must have the format {1}.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

[17] Uniform Resource Locator

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1815 SQL-4

Message

```
Unable to finish the SQL IResultSet {method} due to {SQLState} SQL state.
```

Legend

- `{method}`: The method called on the ResultSet
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1816 SQL-5

Message

```
The SQLServer database is not in read committed snapshot mode.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set the Microsoft SQL Server database in read committed snapshot mode. As a dba, execute the command script: `ALTER DATABASE <DB_NAME> SET READ_COMMITTED_SNAPSHOT ON`

Verify your changes.

✤ Example

In an SAP Convergent Charging environment, the Core Database requires this mode.

Refer to the database official documentation for more information about this *read committed snapshot* mode (READ_COMMITTED_SNAPSHOT database option).

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

Related Information

Preparing the MS SQL Server Core Database

4.1817 SQL-6

Message

```
The SQL Exception due to {SQLState} SQL state is not fatal and can be retried.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1818 SQL-7

Message

```
Cannot add statement to batch due to {SQLState} SQL State.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1819 SQL-8

Message

```
Cannot set statement batch size due to {SQLState} SQL State.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1820 SQL-9

Message

```
Cannot execute statement batch due to {SQLState} SQL State.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1821 SQL-10

Message

```
Cannot set timestamp on prepareStatement due to {SQLState} SQL State.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1822 SQL-11

Message

```
A failover is required by the SQL Exception due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1823 SQL-12

Message

```
The database is not ready to accept SQL query. SQL state {SQLState}.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1824 SQL-13

Message

```
Unable to change transaction isolation level to {isolationLevel} due to SQL
state {SQLState}.
```

Legend

- `{isolationLevel}`: The transaction isolation level
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1825 SQL-14

Message

```
Unable to reserve ID range for ids generation due to SQL state {SQLState}.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1826 SQL-15

Message

```
Unable to get BigDecimal value from resultSet due to SQL state {SQLState}.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1827 SQL-16

Message

```
The backup JDBC URI ({jdbcBackupUri}) must begin by {jdbcDriverUriSample}
like the primary JDBC URI ({jdbcUri}).
```

Legend

- `{jdbcBackupUri}`: The JDBC Backup URI[18]
- `{jdbcDriverUriSample}`: The JDBC URI sample
- `{jdbcUri}`: The JDBC Primary URI

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your JDBC driver documentation to get information about the URI format.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

[18] Uniform Resource Identifier

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1828 SQL-17

Message

```
Invalid JDBC URI ({jdbcUri}) or related JDBC driver not found.
```

Legend

- `{jdbcUri}`: The JDBC URI[19]

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

[19] Uniform Resource Identifier

Next Actions and Steps (Troubleshooting)

Refer to the documentation of the SQLHELPER_JDBC_URI system parameter to check the syntax of the specified URI.
In case your URI corresponds to an Oracle RDBMS, check that the corresponding JDBC driver is available within your landscape and matches the minimum required version.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging

- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1829 SQL-18

Message

```
There is no SQL transaction opened for the current process.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

An SQL transaction must be opened to use the database, please contact support.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1830 SQL-19

Message

```
The SQL Manager is closed and cannot be used anymore.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify that your process is not shutting down.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1831 SQL-20

Message

```
A shutdown has been called on this SQL connection pool. SQL connection
cannot be delivered.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify that your process is not shutting down.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1832 SQL-21

Message

```
This SQL transaction has been canceled and cannot be used anymore.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Open a new transaction for your process.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1833 SQL-22

Message

```
Unable to execute the SQL operation due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1834 SQL-23

Message

```
Unable to commit the SQL transaction due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1835 SQL-24

Message

```
Unable to rollback the SQL transaction due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1836 SQL-25

Message

```
Unable to close the SQL prepared statement due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1837 SQL-26

Message

```
Unable to close the SQL statement due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1838 SQL-27

Message

```
Unable to close the SQL prepared statement due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1839 SQL-28

Message

```
Unable to close the ResultSet for Big Query statement due to {SQLState} SQL
state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1840 SQL-29

Message

```
Unable to commit the database connection for Big Query statement due to
{SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1841 SQL-30

Message

```
Unable to close the database connection for Big Query statement due to
{SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1842 SQL-31

Message

```
Unable to get the value of Microsoft SQLServer is_read_committed_snapshot_on
parameters due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1843 SQL-32

Message

```
Unable to close the ResultSet used to get the value of Microsoft SQLServer
is_read_committed_snapshot_on parameters due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1844 SQL-33

Message

```
Unable to create the {preparedStatement} prepared statement due to {SQLState}
SQL state.
```

Legend

- `{preparedStatement}`: The prepared statement that cannot be created
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1845 SQL-34

Message

```
Unable to close the prepared statement used by this query {SQLStatement} due to
{SQLState} SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be closed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1846 SQL-35

Message

```
Unable to prepare statement for {SQLStatement} due to {SQLState} SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be created
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1847 SQL-36

Message

```
Unable to execute prepared statement {SQLStatement} due to {SQLState} SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1848 SQL-37

Message

```
The driver and SQLServer database are not in sync regarding date management.
{SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database or your driver documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1849 SQL-38

Message

```
Unable to execute the addBatch() method of the prepared statement using
the Oracle JDBC driver due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database or your driver documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1850 SQL-39

Message

```
Unable to use the SQL Connection pool as it has been shutdown.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify that the server instance is not shutting down.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1851 SQL-40

Message

```
Unable to close prepared statement {SQLStatement} due to {SQLState} SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be closed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1852 SQL-41

Message

```
Unable to execute the prepared statement {SQLStatement} and build a ResultSet
due to {SQLState} SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1853 SQL-42

Message

```
Unable to execute the DML prepared statement {SQLStatement} due to {SQLState}
SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1854 SQL-43

Message

```
Unable to cancel the prepared statement {SQLStatement} due to {SQLState}
SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1855 SQL-44

Message

```
Unable to set object {ObjectAsString} of type {ObjectType} at position
{ObjectPosition} in the prepared statement {SQLStatement} due to {SQLState} SQL
state.
```

Legend

- `{ObjectAsString}`: A string representing the object passed to setObject
- `{ObjectType}`: The type of the object
- `{ObjectPosition}`: The position of the object
- `{SQLStatement}`: The SQL Statement that cannot be executed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {4} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1856 SQL-45

Message

```
Unable to reserve ID range for ids generation because there is no line in
ID_TABLE.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Check your database scripts to see if the original line has been inserted in `ID_TABLE`.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1857 SQL-46

Message

```
Unable to add the current batch to the prepared statement {SQLStatement}
due to {SQLState} SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1858 SQL-47

Message

```
Unable to execute the batch of DML prepared statement {SQLStatement} due
to {SQLState} SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {1} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1859 SQL-48

Message

```
Unable to use the embedded ResultSet due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1860 SQL-49

Message

```
Unable to make a checkpoint on the SQL transaction due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1861 SQL-50

Message

```
Unable to revert the last checkpoint on the SQL transaction due to {SQLState}
SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1862 SQL-51

Message

```
Unable to add batch on the prepared statement {SQLStatement} due to {SQLState}
SQL state.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1863 SQL-52

Message

```
Unable to execute the prepared statement {SQLStatement} on a close SQL
connection.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1864 SQL-53

Message

```
Unable to execute an update to the prepared statement {SQLStatement}
on a close SQL connection.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1865 SQL-54

Message

```
Unable to execute a batch to the prepared statement {SQLStatement} on
a close SQL connection.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be executed in batch mode

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1866 SQL-55

Message

```
Unable to set object to the prepared statement {SQLStatement} on a close
SQL connection.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be set

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1867 SQL-56

Message

```
Unable to add batch on the prepared statement {SQLStatement} on a close
SQL connection.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be added in batch mode

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1868 SQL-57

Message

```
Unable to cancel the prepared statement {SQLStatement} on a close SQL connection.
```

Legend

- `{SQLStatement}`: The SQL Statement that cannot be cancelled

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1869 SQL-58

Message

```
Unable to reconnect ID generation connection due to SQL state {SQLStatement}.
```

Legend

- `{SQLStatement}`: The SQL State reached when reconnecting

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1870 SQL-59

Message

```
This database does not support to store strings which end with a space
character ({invalidString}).
```

Legend

- `{invalidString}`: The value with trailing spaces

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Sanitize the data so that strings do not end with a space character.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1871 SQL-60

Message

```
Unable to retrieve the size of the column {columnName} of the table {tableName}
due to {SQLState} SQL state.
```

Legend

- `{columnName}`: The name of the column
- `{tableName}`: The name of the table
- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {2} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1872 SQL-61

Message

```
The server is not connected to the database using the URL {URL}.
```

Legend

- `{URL}`: The database URL

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

The database with the URL {0} is offline or it is not possible to connect to it.
Check the status of the database and reconnect the server to the database using the adequate Admin+ command.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP09 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging

- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1873 SQL-62

Message

```
Cannot process statement because a Server failure exception occurred.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Contact your SAP Support Team.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP09 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1874 SQL-63

Message

```
Cannot process statement because the database update pool for the database
{URL} is not enabled.
```

Legend

- `{URL}`: The database URL

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Enable the database update pool.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP09 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1875 SQL-64

Message

```
Unable to change the transaction isolation level due to {SQLState} SQL state.
```

Legend

- `{SQLState}`: The SQLState of the SQLException

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Consult your database documentation to get information about the {0} SQL state.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP09 Patch Level 4 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1876 SUBSCRIBERDATA-1

Message

```
The Subscriber Data type is missing or invalid.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fill the Subscriber Data type with a correct value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1877 SUBSCRIBERDATA-2

Message

```
The Subscriber Data id is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fill the Subscriber Data ID.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1878 SUBSCRIBERDATA-3

Message

```
No Subscriber Data found for id ''{id}'' and type ''{type}''.
```

Legend

- `{id}`: The ID of the Subscriber Data
- `{type}`: The type of the Subscriber Data

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fill the Subscriber Data ID and type with a correct value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1879 SUBSCRIBERDATA-4

Message

```
Cannot import Counter Snapshots for Subscription ''{subscriptionCode}''
because it does not exist.
```

Legend

- `{subscriptionCode}`: The code of the Subscription

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Correct the Subscription ID of the Counter Snapshot to import.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1880 SUBSCRIBERDATA-5

Message

```
Cannot import Counter Snapshots for Subscription ''{subscriptionCode}''
because it is not of type offline.
```

Legend

- `{subscriptionCode}`: The code of the Subscription

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

None.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1881 SUBSCRIBERDATA-6

Message

```
Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because
no Subscription is defined in the Snapshot for date ''{snapshotDate}''.
```

Legend

- `{subscriptionCode}`: The code of the Subscription
- `{snapshotDate}`: The date of the invalid Counter Snapshot

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

None.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1882 SUBSCRIBERDATA-7

Message

```
Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because
the Sub-Subscription ''{subSubscriptionCode}'' does not exist.
```

Legend

- `{subscriptionCode}`: The code of the Subscription
- `{subSubscriptionCode}`: The code of the invalid Sub-Subscription

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Correct the ID of the Sub-Subscription with an valid name, or remove the invalid Sub-Subscription.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1883 SUBSCRIBERDATA-8

Message

```
Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because
the Charge ''{chargeCode}'' does not exist.
```

Legend

- `{subscriptionCode}`: The code of the Subscription
- `{chargeCode}`: The code of the invalid Charge

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Correct the ID of the Charge with an valid name, or remove the invalid Charge.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1884 SUBSCRIBERDATA-9

Message

```
Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because
the Counter name ''{counterName}'' is not valid.
```

Legend

- `{subscriptionCode}`: The code of the Subscription
- `{counterName}`: The name of the invalid Counter

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Correct the name of the invalid Counter.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1885 SUBSCRIBERDATA-10

Message

```
Cannot import Access ''{serviceId}''/''{userServideId}'' for Subscription
''{subscriptionCode}'' because there are overlapped periods.
```

Legend

- `{serviceId}`: The service ID of the Access
- `{userServideId}`: The service ID of the Access
- `{subscriptionCode}`: The code of the Subscription

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Correct the Access chronology.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1886 SUBSCRIBERDATA-11

Message

```
Cannot import Access ''{serviceId}''/''{userServideId}'' for Subscription
''{subscriptionCode}'' because a period overlaps the existing Access.
```

Legend

- `{serviceId}`: The service ID of the Access
- `{userServideId}`: The user service ID of the Access
- `{subscriptionCode}`: The code of the Subscription

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Correct the Access chronology.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1887 SUBSCRIBERDATA-12

Message

```
Cannot import Subscription ''{subscriptionCode}'' because the chronology
is invalid.
```

Legend

- `{subscriptionCode}`: The code of the Subscription

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

None.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1888 SUBSCRIBERDATA-13

Message

```
The Subscriber Data owner is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fill the Subscriber Data owner.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1889 SUBSCRIBERDATA-14

Message

```
Cannot import Counter Snapshots for Subscription ''{subscriptionCode}'' because
the dates ''{snapshotDate1}'' and ''{snapshotDate2}'' are not consecutive.
```

Legend

- `{subscriptionCode}`: The code of the Subscription
- `{snapshotDate1}`: The first not consecutive Counter Snapshots date
- `{snapshotDate2}`: The second not consecutive Counter Snapshots date

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Correct the dates of the Counter Snapshots.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 3.0 SP00 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1890 SUBSCRIBERACCOUNT-1

Message

```
The subscriber account "{subscriberAccountId}" (with "{serviceProvider}"
as service provider) is not valid.
```

Legend

- `{subscriberAccountId}`: The identifier of the invalid subscriber account
- `{serviceProvider}`: The identifier of the service provider

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the data model that is provided.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1891 SUBSCRIBERACCOUNT-2

Message

```
The expected type of the additional info "{additionalInfoName}" must be
"{additionalInfoExpectedType}" but not "{additionalInfoInvalidType}".
```

Legend

- `{additionalInfoName}`: The name additional info that has not the awaiting type
- `{additionalInfoExpectedType}`: The expected type of the additional info
- `{additionalInfoInvalidType}`: The invalid type of the additional info

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Change the additional info type to the expected type.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1892 SUBSCRIBERACCOUNT-3

Message

```
The value of the additional info "{additionalInfoName}" must not be empty.
```

Legend

- `{additionalInfoName}`: The name additional info that have an empty value

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Fix the additional info value.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1893 SUBSCRIBERACCOUNT-4

Message

```
The Customer Management Area name "{additionalInfoValue}" provided as a
value of the additional info "{additionalInfoName}" is not defined.
```

Legend

- `{additionalInfoValue}`: The value of the additional info whose value is not a configured name of Customer Management Area
- `{additionalInfoName}`: The name of additional info whose value is not a configured name of Customer Management Area

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Choose a name of Customer Management Area coming from the configured list of Customer Management Areas.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP04 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1894 SUBSCRIBERACCOUNT-5

Message

```
The subscriber account "{subscriberAccountId}" (with "{serviceProvider}" as
service provider) must not contain any prepaid account because the Prepaid
Accounts Management
feature is disabled.
```

Legend

- `{subscriberAccountId}`: The identifier of the invalid subscriber account
- `{serviceProvider}`: The identifier of the service provider

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Remove all prepaid accounts from the subscriber account.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1895 SUBSCRIBERACCOUNT-6

Message

```
The reset frequency of the credit limit balance "{creditLimitBalanceName}"
is invalid.
```

Legend

- `{creditLimitBalanceName}`: The name of the credit limit balance

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Set a valid reset frequency in the credit limit balance.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 5.0 SP 5 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1896 TRANSPORTREQUEST-1

Message

```
The mandatory filter in the Search Transport Request operation is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter in the Search Transport Request operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1897 TRANSPORTREQUEST-2

Message

```
An error occurred during the execution of the search operation: {errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1898 TRANSPORTREQUEST-3

Message

```
The Web services of the updater are not available for receiving responses.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Enable the Web services of the updater.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1899 TRANSPORTREQUEST-4

Message

```
The execution of transport requests is already running.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Wait for the end of current transport requests execution before attempting a new one.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1900 TRANSPORTREQUEST-5

Message

```
The mandatory filter in the Execute Transport Request operation is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter in the Execute Transport Request operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1901 TRANSPORTREQUEST-6

Message

```
An error occurred during the transport request execution: {errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP05 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1902 TRANSPORTREQUEST-7

Message

```
The name of the associated Change List is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a change list name in the Create Transport Request operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**
>
> - Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
> - Texts in error messages may change to improve your user experience. First consider the numerical code for an error
>
> See also Deprecated and Revoked Error Codes [page 58].

4.1903 TRANSPORTREQUEST-8

Message

```
The Transport Request cannot be created because the change list {changeListName}
does not exist.
```

Legend

- `{changeListName}`: The name of the missing change list

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Create first the associated change list with the given name.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

> → Remember
>
> **Error codes can be deprecated or revoked at any time.**

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1904 TRANSPORTREQUEST-9

Message

```
The mandatory filter in the Delete Transport Request operation is missing.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a filter in the Delete Transport Request operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1905 TRANSPORTREQUEST-10

Message

```
An error occurred during the execution of the delete operation: {errorMessage}.
```

Legend

- `{errorMessage}`: The message describing the error that occurred

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

→ Recommendation

SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.

You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

4.1906 TRANSPORTREQUEST-11

Message

```
The Transport Request is missing in the creation operation.
```

The meaning of this error message depends on the software layers and internal functions of the SAP CC system that handles the message. See the note to adapt the terminology [page 57] to the concepts and data models you work with.

Next Actions and Steps (Troubleshooting)

Add a Transport Request to the creation operation.

Verify your changes.

Notes for Troubleshooting

Consider the specifications [page 59] of the appropriate technical interfaces: Web Services, HTTP Communication Interface (HCI), or Message TCP.

SAP User Experience

Enrich your SAP user experience and join our community of professionals:

Questions and Answers for SAP Convergent Charging

> → Recommendation
>
> SAP provides you with the https://community.sap.com/ platform. You can benefit from a wide range of technical and business guidance from a community of experts and share knowledge and your best practices.
>
> You cannot find the answers you are looking for? Contact our community of experts. Share your SAP user experience and feedbacks.

Share your symptoms (error codes) or step-by-step resolutions to a wide range of problems that may occur in your work with SAP Convergent Charging.

Validity

This error code is valid from SAP CC version number 4.0 SP07 to the software version that this documentation refers to. For newer versions, consult the relevant documentation.

→ Remember

Error codes can be deprecated or revoked at any time.

- Before you start the troubleshooting, make sure that you have the latest version of this document. It is available in the Software Development Kit (SDK) of SAP Convergent Charging
- Texts in error messages may change to improve your user experience. First consider the numerical code for an error

See also Deprecated and Revoked Error Codes [page 58].

Important Disclaimers and Legal Information

Hyperlinks

Some links are classified by an icon and/or a mouseover text. These links provide additional information.
About the icons:

- Links with the icon : You are entering a Web site that is not hosted by SAP. By using such links, you agree (unless expressly stated otherwise in your agreements with SAP) to this:
  - The content of the linked-to site is not SAP documentation. You may not infer any product claims against SAP based on this information.
  - SAP does not agree or disagree with the content on the linked-to site, nor does SAP warrant the availability and correctness. SAP shall not be liable for any damages caused by the use of such content unless damages have been caused by SAP's gross negligence or willful misconduct.
- Links with the icon : You are leaving the documentation for that particular SAP product or service and are entering an SAP-hosted Web site. By using such links, you agree that (unless expressly stated otherwise in your agreements with SAP) you may not infer any product claims against SAP based on this information.

Videos Hosted on External Platforms

Some videos may point to third-party video hosting platforms. SAP cannot guarantee the future availability of videos stored on these platforms. Furthermore, any advertisements or other content hosted on these platforms (for example, suggested videos or by navigating to other videos hosted on the same site), are not within the control or responsibility of SAP.

Beta and Other Experimental Features

Experimental features are not part of the officially delivered scope that SAP guarantees for future releases. This means that experimental features may be changed by SAP at any time for any reason without notice. Experimental features are not for productive use. You may not demonstrate, test, examine, evaluate or otherwise use the experimental features in a live operating environment or with data that has not been sufficiently backed up.
The purpose of experimental features is to get feedback early on, allowing customers and partners to influence the future product accordingly. By providing your feedback (e.g. in the SAP Community), you accept that intellectual property rights of the contributions or derivative works shall remain the exclusive property of SAP.

Example Code

Any software coding and/or code snippets are examples. They are not for productive use. The example code is only intended to better explain and visualize the syntax and phrasing rules. SAP does not warrant the correctness and completeness of the example code. SAP shall not be liable for errors or damages caused by the use of example code unless damages have been caused by SAP's gross negligence or willful misconduct.

Bias-Free Language

SAP supports a culture of diversity and inclusion. Whenever possible, we use unbiased language in our documentation to refer to people of all cultures, ethnicities, genders, and abilities.

www.sap.com/contactsap

© 2026 SAP SE or an SAP affiliate company. All rights reserved.

No part of this publication may be reproduced or transmitted in any form or for any purpose without the express permission of SAP SE or an SAP affiliate company. The information contained herein may be changed without prior notice.

Some software products marketed by SAP SE and its distributors contain proprietary software components of other software vendors. National product specifications may vary.

These materials are provided by SAP SE or an SAP affiliate company for informational purposes only, without representation or warranty of any kind, and SAP or its affiliated companies shall not be liable for errors or omissions with respect to the materials. The only warranties for SAP or SAP affiliate company products and services are those that are set forth in the express warranty statements accompanying such products and services, if any. Nothing herein should be construed as constituting an additional warranty.

SAP and other SAP products and services mentioned herein as well as their respective logos are trademarks or registered trademarks of SAP SE (or an SAP affiliate company) in Germany and other countries. All other product and service names mentioned are the trademarks of their respective companies.

Please see https://www.sap.com/about/legal/trademark.html for additional trademark information and notices.