



Front View

Detail: - แสดงผลด้วยตัวเลข 7 SEGMENT สีแดง ขนาด 2.3 นิ้ว

Today Plan : รับข้อมูลการตั้งค่า ผ่านรีโหมด

rget : รับข้อมูลการตั้งค่า ผ่านรีโหมด และมีโหมดการเพิ่มค่าทุกๆรอบ Cycle time

Time : แสดงเวลาปัจจุบัน เมื่อเริ่มต้นการทำงานจะแสดงเป็น นาฬิกานับถอยหลัง ตามค่าเป้าเวลาที่ตั้ง

Actual : แสดงค่าที่รับได้จาก INPUT 1 Channel Diff. : แสดงค่าผลต่าง Actual - Target - Alarm : ทำงานเมื่อ Count Down นับถึง 0 และ Actual ไม่ตรงตามเป้าที่ตั้งไว้

: เลือกได้ เป้า Today Plan หรือ เป้า Target หรือ ค่า Set Point

- สามารถเชื่อมต่อ RS485 ได้ 1 Channel

Address : ตั้งค่า ได้ 1-255

Baud Rate : ตั้งค่า ได้ 4800, 9600, 19200, 38400, 57600

Data Format: Value 32 Bits

Protocol : Modbus RTU read(0x03,0x04) , write(0x10)

Technical Specification

Power Supply	100-240 VAC, 50-60Hz
Display	7 Segment Size 2.3,
Input	Sensor NPN, PNP, Contact 1 Ch
Output	Alarm Relay 1 Ch
Memory	EEPROM with Battery
Setting	Remote IF.
Communication	RS485 Modbus RTU

REMARK		
Frame	Aluminum	
Color	Black	
Model	TGM-61097	

	APPEND
Dimension: 550	0W x 450H x 100D mm.
Character	Arial (Font), White PVC Sticker

F	PRIMUS CO., LTD.
Draft by	Suphot
Date	10.07.2018
Revision	0
Customer	

Approve	

ราคาตั้ง Big Display 2.3" TGM-61097 : 29,200 บาท