Kantech ioSmart Mullion Reader (Multi-Tech)

KT-MUL-MT · 13.56 MHz + 125 kHz + BLE mobile · Wiegand / RS-485

STOCK CODE

39KT-MUL-MT

Slim encrypted reader — ioSmart, MIFARE, ioProx/HID Prox and smartphone keys in one.



3-in-1	AES	8.5–16 V	−40–70 °C
125k + 13.56M + BLE	end-to-end (RS-485)	DC	operating

BEST FOR

- ✔ Kantech KT-1 / KT-400 doors
- ✔ Upgrading from ioProx to smart cards
- ✔ Mobile phone access

NOT FOR

- ✖ Keypad entry (sell KT-MUL-MT-KP)

WHY CUSTOMERS CHOOSE IT

- **Reads ioProx, HID Prox, ioSmart, MIFARE Plus EV1**
- **Bluetooth mobile keys**
- Auto-detects Wiegand or RS-485
- Optical tamper · configurable LED bar
- Panel-less BLE mode with lock output

KEY SPECS

Current	**120 mA peak / 70 mA average @ 12 V**
Read range	**125 kHz up to 5.1 cm · 13.56 MHz up to 3.8 cm**
Size / weight	**115.8 × 44.6 × 24.7 mm · 110 g**
Wiring	**6-pole screwless terminal**

FAMILY — PICK THE RIGHT ONE

KT-MUL-SC	13.56 MHz only
KT-MUL-MT	Multi-tech — **this unit**
KT-MUL-MT-KP	Multi-tech + keypad

COUNTER QUICK ANSWERS

Old Kantech cards? Yes — reads ioProx.

Phone as card? Yes, ioSmart BLE mobile keys.

Encryption? AES-128 end to end in RS-485 mode.

Source: Kantech ioSmart Card Reader installation guide (DN2187-2007).