DSC PowerG Door/Window Contact

PG8945 wireless door/window contact with auxiliary input · 868 MHz

STOCK CODE

22PG8945

Wireless magnetic contact for doors and windows — with a spare input to connect a wired contact too.

⚠ This is the 868 MHz model. Check it matches the customer's PowerG receiver frequency.



8 yrs	2 km	+1	AES
battery life	radio (open air)	aux wired input	128-bit

WHY CUSTOMERS CHOOSE IT

- **Link-quality LED** on the device — find the best spot fast
- **Aux input** — N/O, N/C or EOL wired contact
- Configured from the keypad — no DIP switches
- Fully supervised, frequency hopping, 128-bit AES

BEST FOR

- ✔ Doors and windows on PowerSeries Neo systems
- ✔ Places where cabling is hard
- ✔ Adding a nearby wired contact via the aux input
- ✔ Tight frames where the magnet gap is an issue

KEY SPECS

Battery	**3 V CR123A lithium**
Battery life	**Up to 8 years (typical use)**
Size / weight	**81 × 34 × 25 mm · 53 g**
Operating temp	**−10 to +55 °C**
Compatibility	**PowerSeries Neo**

NOT FOR

- ✖ Non-Neo / non-PowerG panels
- ✖ Outdoor gates (use PG8312 outdoor contact)
- ✖ Metal frames without testing the gap

FAMILY — PICK THE RIGHT ONE

PG4945	433 MHz version
PG8945	868 MHz — **this unit**

COUNTER QUICK ANSWERS

Battery? CR123A 3 V lithium — about 8 years.

Wired contact on the same door? Yes, use the aux input.

Which panel? PowerSeries Neo with a PowerG receiver.