Uniross LFP12-20 Lithium Battery

12.8 V 20 Ah LiFePO4 lithium battery with built-in BMS

STOCK CODE

10LFP12-20

Lead-acid replacement that lasts far longer, weighs less and handles deep discharge — ideal for backup and solar.



20 Ah	2000+	2.8 kg	256 Wh
capacity	cycles	weight	energy

BEST FOR

- ✔ Load-shedding backup for gates, alarms & CCTV
- ✔ Solar systems and small inverters
- ✔ Replacing a 12 V lead-acid battery 1-for-1
- ✔ Frequent deep discharge use
- ✔ Weight-sensitive installs

NOT FOR

- ✖ Charging below 0 °C
- ✖ Chargers without a lithium/14.4 V profile — check charger
- ✖ Very cheap low-use jobs (lead-acid is cheaper)

WHY CUSTOMERS CHOOSE IT

- **LiFePO4** — the safest lithium chemistry
- **Built-in BMS** — protects against over-charge, over-discharge & short circuit
- **2000+ cycles** at 100% discharge
- Light — about half the weight of an equivalent lead-acid
- Can be linked up to 4 in series / 20 in parallel

KEY SPECS

Voltage	**12.8 V nominal**
Max discharge	**40 A continuous · 50 A pulse**
Charge voltage	**14.4 – 14.8 V (float 13.8 V)**
Charge current	**10 A recommended · 20 A max**
Size	**181 × 77 × 167 mm · T3 terminals**
Temperatures	**Discharge −30 to 60 °C · charge 0 to 45 °C**

FAMILY — PICK THE RIGHT ONE

LFP12-12	**12 Ah**
LFP12-20	**20 Ah — this unit**
LFP12-50	**50 Ah**

COUNTER QUICK ANSWERS

Can I swap out my lead-acid? Yes — one-to-one, but check the charger suits lithium.

Self-discharge? Only about 2% per month.

Shipping? Class 9 dangerous goods (UN3480).

Source: Uniross / Landport LFP12-20 datasheet (11/08/2020).

Internal counter reference