Sherlotronics 6 A Lithium Backup PSU

12.8 V 6 A battery-backup PSU for 18–22 Ah lithium batteries

STOCK CODE

14SH6AMP-LITHIUM

Bigger lithium backup supply for CCTV, access control and alarms — charges 18–22 Ah lithium batteries.



6 A	75 W	18–22 Ah	24 mo
output	max power	lithium battery	warranty

WHY CUSTOMERS CHOOSE IT

- **Lithium charging**, current limited 2.4 / 4.8 A
- **Low-battery cut-out** at 10 V
- Over-voltage protection above 15 V
- AC fail output
- Resettable output fuse

BEST FOR

- ✔ CCTV systems with a 20 Ah lithium battery
- ✔ Maglocks and door controllers
- ✔ Load-shedding backup on 12 V systems

NOT FOR

- ✖ Lead-acid batteries
- ✖ Loads above 6 A / 75 W

KEY SPECS

Input	**110 – 230 VAC 50 Hz**
Output	**13 – 14.4 VDC, 6 A**
AC fail output	**140 mA positive switching**
Size / weight	**275 × 225 × 97 mm · 1.3 kg**
Operating temp	**−3 to +60 °C**

FAMILY — PICK THE RIGHT ONE

3A Lithium	For 7 Ah lithium
6A Lithium	For 18–22 Ah lithium — **this unit**

COUNTER QUICK ANSWERS

Battery? Pair with a 20 Ah lithium, e.g. Uniross LFP12-20.

Lead-acid? No — lithium only.

Warranty? 24 months.