Alarm Supplies EAS-400A Strobe Siren

12 V external siren with strobe · 115 dB

STOCK CODE

06EAS-400A

Loud external siren with a flashing strobe — shows the system is armed and draws attention on alarm.



115 dB	12 V	8 Ω	1.4 A
at 1 m	DC	impedance	max current

BEST FOR

- ✔ Outside walls of homes and shops
- ✔ Visible deterrent on alarm installs
- ✔ Most 12 V alarm panels with a bell output

NOT FOR

- ✖ Panels that can't supply 1.4 A on the bell output
- ✖ Self-powered siren needs (no built-in battery)
- ✖ Indoor use — too loud

COUNTER QUICK ANSWERS

Built-in battery? No — it's powered from the panel's bell/siren output.

Will my panel drive it? Check the bell output can deliver 1.4 A.

Tone? Warble, with flashing strobe.

WHY CUSTOMERS CHOOSE IT

- **115 dB warble** tone
- **Strobe light** — about 115 flashes per minute
- White ABS housing, acrylic lens
- Operates from 6 to 15 VDC

KEY SPECS

Input voltage	**12 VDC (6 – 15 VDC)**
Max current	**1,400 mA**
Sound	**115 dB @ 12 V / 1 m · warble**
Impedance	**8 Ω**
Size	**277 × 165 × 103 mm**

Source: Alarm Supplies EAS-400A strobe siren datasheet.

Internal counter reference