Optex BX-80N Perimeter PIR

Outdoor dual-sided curtain PIR · 24 m (12 m each side)

STOCK CODE

07BX80N

Invisible outdoor curtain along the wall of the building — catches intruders before they break a window or door.



24 m	IP55	12–24 V	0.8–1.2 m
12 m each side	weatherproof	10–28 VDC	mount height

BEST FOR

- ✔ Along walls, under windows, past back doors
- ✔ Early warning before entry
- ✔ Long narrow areas beside the house
- ✔ Mounting on the building wall (low)

NOT FOR

- ✖ Open gardens or wide areas (use a wide-angle PIR)
- ✖ Facing roads or moving foliage
- ✖ Battery-only installs — sell the BX-80NR

WHY CUSTOMERS CHOOSE IT

- **Narrow 24 m curtain**, 2 zones each side
- **Size judging** — alarms only when upper and lower beams both see movement
- Double conductive shielding vs. headlights & sunlight
- Adjustable detection range limit
- Temperature compensation

KEY SPECS

Power	**10 – 28 VDC, 38 mA max**
Outputs	**2 relays N.O./N.C., 28 VDC 0.2 A**
Tamper	**N.C., opens when cover removed**
Operating temp	**−20 to +50 °C · 95% RH**
Weight	**400 g · wall mount**

FAMILY — PICK THE RIGHT ONE

BX-80N	**Wired 10–28 VDC — this unit**
BX-80NR	**Battery operated, for wireless transmitters**

COUNTER QUICK ANSWERS

Will cats set it off? Size judging needs both upper & lower zones — small animals usually don't.

How high? 0.8 – 1.2 m on the wall.

Wireless? Use the BX-80NR with a wireless transmitter.

Source: Optex BX-80N/80NR brochure (Elvey).

Internal counter reference